

---

## STEP-UP DC/DC CONVERTER FOR WHITE LED BACK LIGHT

---

NO.EA-271-111123

### OUTLINE

The R1203x Series are PWM control type step-up DC/DC converter ICs with low supply current.

The R1203x is fully dedicated to drive White LEDs with constant current. Each of these ICs consists of an NMOS FET, an oscillator, a PWM comparator, a voltage reference unit, an error amplifier, a current limit circuit, an under voltage lockout circuit (UVLO), and an over-voltage protection circuit (OVP).

The R1203x can drive white LEDs in constant current with high efficiency by using an inductor, a diode, a resistor and capacitors as external components.

The LEDs current can be set by an external resistance value and can adjust the dimming of LEDs by CE pin according to the signal of PWM. Feedback voltage is 0.2V, therefore power loss by current setting resistance is small and efficiency is good. Maximum duty cycle is internally fixed, Typ. 91%. LEDs can be driven from low voltage. Protection circuits are the current limit of Lx peak current, the over voltage limit of output, and the under voltage lockout function.

It is controllable the dimming of LEDs quickly when the PWM signal (between 200Hz to 300kHz) input to CE pin. If the CE pin input is "L" in the fixed time (Typ. 0.5ms), the IC becomes the standby mode and turns OFF LEDs.


### FEATURES

- Supply Current ..... Typ. 500 $\mu$ A
- Standby Current ..... Max. 5 $\mu$ A
- Input Voltage Range ..... 1.8V to 5.5V
- Feedback Voltage ..... 0.2V
- Feedback Voltage Accuracy .....  $\pm 1.0\%$  ( $\pm 10$ mV)
- Temperature-Drift Coefficient of Feedback Voltage ...  $\pm 150$ ppm/ $^{\circ}$ C
- Oscillator Frequency ..... Typ. 1.2MHz
- Maximum Duty Cycle ..... Typ. 91%
- Switch ON Resistance ..... Typ. 1.35 $\Omega$
- UVLO Detector Threshold ..... Typ. 1.6V
- Lx Current Limit Protection ..... Typ. 700mA
- OVP Detector Threshold ..... Typ. 29.5V
- Switching Control ..... PWM
- LED dimming control ..... by external PWM signal (Frequency 200Hz to 300kHz)
- Packages ..... DFN1616-6B, SOT-23-6
- Ceramic capacitors are recommended ..... 0.22 $\mu$ F

### APPLICATION

- White LED Backlight for portable equipment

**BLOCK DIAGRAMS**




**SELECTION GUIDE**

The package for the ICs can be selected at the user's request.

| Product Name     | Package    | Quantity per Reel | Pb Free | Halogen Free |
|------------------|------------|-------------------|---------|--------------|
| R1203L071B-TR    | DFN1616-6B | 5,000 pcs         | Yes     | Yes          |
| R1203N071B-TR-FE | SOT-23-6   | 3,000 pcs         | Yes     | Yes          |

## PIN CONFIGURATIONS



## PIN DESCRIPTIONS

### • DFN1616-6B

| Pin No | Symbol    | Pin Description                   |
|--------|-----------|-----------------------------------|
| 1      | CE        | Chip Enable Pin ("H" Active)      |
| 2      | $V_{FB}$  | Feedback Pin                      |
| 3      | LX        | Switching Pin (Open Drain Output) |
| 4      | GND       | Ground Pin                        |
| 5      | $V_{IN}$  | Input Pin                         |
| 6      | $V_{OUT}$ | Output Pin                        |

\*) Tab is GND level. (They are connected to the reverse side of this IC.)

The tab is better to be connected to the GND, but leaving it open is also acceptable.

### • SOT-23-6

| Pin No | Symbol    | Pin Description                   |
|--------|-----------|-----------------------------------|
| 1      | CE        | Chip Enable Pin ("H" Active)      |
| 2      | $V_{OUT}$ | Output Pin                        |
| 3      | $V_{IN}$  | Input Pin                         |
| 4      | LX        | Switching Pin (Open Drain Output) |
| 5      | GND       | Ground Pin                        |
| 6      | $V_{FB}$  | Feedback Pin                      |

**ABSOLUTE MAXIMUM RATINGS**

(GND=0V)

| Symbol    | Item                            | Rating               | Unit |
|-----------|---------------------------------|----------------------|------|
| $V_{IN}$  | $V_{IN}$ Pin Voltage            | -0.3 to 6.5          | V    |
| $V_{CE}$  | CE Pin Voltage                  | -0.3 to $V_{IN}+0.3$ | V    |
| $V_{FB}$  | $V_{FB}$ Pin Voltage            | -0.3 to $V_{IN}+0.3$ | V    |
| $V_{OUT}$ | $V_{OUT}$ Pin Voltage           | -0.3 to 32           | V    |
| $V_{LX}$  | $L_x$ Pin Voltage               | -0.3 to 32           | V    |
| $I_{LX}$  | $L_x$ Pin Current               | 1000                 | mA   |
| $P_D$     | Power Dissipation (DFN1616-6B)* | 640                  | mW   |
|           | Power Dissipation (SOT-23-6)*   | 420                  |      |
| $T_a$     | Operating Temperature Range     | -40 to 85            | °C   |
| $T_{stg}$ | Storage Temperature Range       | -55 to 125           | °C   |

\*) For Power Dissipation, please refer to PACKAGE INFORMATION.

**ABSOLUTE MAXIMUM RATINGS**

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause the permanent damages and may degrade the life time and safety for both device and system using the device in the field. The functional operation at or over these absolute maximum ratings is not assured.

## ELECTRICAL CHARACTERISTICS

### • R1203x


(Ta=25°C)

| Symbol                               | Item  | Conditions  | Min. | Typ.                       | Max. | Unit   |
|--------------------------------------|---|---|------|----------------------------|------|--------|
| V <sub>IN</sub>                      | Operating Input Voltage                           |   | 1.8  |                            | 5.5  | V      |
| I <sub>DD</sub>                      | Supply Current                                    | V <sub>IN</sub> =5.5V, V <sub>FB</sub> =0V, Lx at no load             |      | 0.5                        | 1.0  | mA     |
| I <sub>standby</sub>                 | Standby Current                                   | V <sub>IN</sub> =5.5V, V <sub>CE</sub> =0V                            |      | 1.0                        | 5.0  | μA     |
| V <sub>UVLO1</sub>                   | UVLO Detector Threshold                           | V <sub>IN</sub> falling   | 1.5  | 1.6                        | 1.7  | V      |
| V <sub>UVLO2</sub>                   | UVLO Released Voltage                             | V <sub>IN</sub> rising  |      | V <sub>UVLO1</sub><br>+0.1 | 1.8  | V      |
| V <sub>CEH</sub>                     | CE Input Voltage "H"                              | V <sub>IN</sub> =5.5V   | 1.5  |                            |      | V      |
| V <sub>CEL</sub>                     | CE Input Voltage "L"                              | V <sub>IN</sub> =1.8V   |      |                            | 0.5  | V      |
| R <sub>CE</sub>                      | CE Pull Down Resistance                           | V <sub>IN</sub> =3.6V   | 600  | 1200                       | 2200 | kΩ     |
| V <sub>FB</sub>                      | V <sub>FB</sub> Voltage Accuracy                  | V <sub>IN</sub> =V <sub>CE</sub> =3.6V                                | 0.19 | 0.20                       | 0.21 | V      |
| $\frac{\Delta V_{FB}}{\Delta T_a}$   | V <sub>FB</sub> Voltage Temperature Coefficient   | V <sub>IN</sub> =V <sub>CE</sub> =3.6V, -40°C ≤ T <sub>a</sub> ≤ 85°C |      | ±150                       |      | ppm/°C |
| I <sub>FB</sub>                      | V <sub>FB</sub> Input Current                     | V <sub>IN</sub> =5.5V, V <sub>FB</sub> =0V or V <sub>IN</sub>         | -0.1 |                            | 0.1  | μA     |
| R <sub>ON</sub>                      | Switch ON Resistance                              | V <sub>IN</sub> =3.6V, I <sub>LX</sub> =100mA                         |      | 1.35                       |      | Ω      |
| I <sub>LXleak</sub>                  | Switch Leakage Current                            | V <sub>LX</sub> =30V  |      | 0                          | 3.0  | μA     |
| I <sub>LXlim</sub>                   | Switch Current Limit                              | V <sub>IN</sub> =3.6V   | 400  | 700                        | 1000 | mA     |
| f <sub>osc</sub>                     | Oscillator Frequency                              | V <sub>IN</sub> =3.6V, V <sub>OUT</sub> =V <sub>FB</sub> =0V          | 1.0  | 1.2                        | 1.4  | MHz    |
| Maxduty                              | Maximum Duty Cycle                                | V <sub>IN</sub> =3.6V, V <sub>OUT</sub> =V <sub>FB</sub> =0V          | 86   | 91                         |      | %      |
| V <sub>OVP1</sub>                    | OVP Detector Threshold                            | V <sub>IN</sub> =3.6V, V <sub>OUT</sub> rising                        | 28.7 | 29.5                       | 30.3 | V      |
| $\frac{\Delta V_{OVP1}}{\Delta T_a}$ | V <sub>OVP1</sub> Voltage Temperature Coefficient | V <sub>IN</sub> =V <sub>CE</sub> =3.6V, -40°C ≤ T <sub>a</sub> ≤ 85°C |      | ±150                       |      | ppm/°C |
| V <sub>OVP2</sub>                    | OVP Released Voltage                              | V <sub>IN</sub> =3.6V, V <sub>OUT</sub> falling                       |      | V <sub>OVP1</sub><br>-1.55 |      | V      |

#### RECOMMENDED OPERATING CONDITIONS (ELECTRICAL CHARACTERISTICS)

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if when they are used over such conditions by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

## TYPICAL APPLICATIONS



|    |               |
|----|---------------|
| C1 | CM105B105K06  |
| C2 | GRM21BR71H224 |
| L1 | LQH32CN220K53 |

### • LED Current setting

When CE pin input is "H" (Duty=100%), LED current can be set with feedback resistor (R1)

$$I_{LED} = V_{FB} / R1$$

### • LED Dimming Control


The LED brightness can be controlled by inputting the PWM signal to the CE pin. If the CE pin input is "L" in the fixed time (Typ.0.5ms), the IC becomes the standby mode and turns OFF LEDs.

The current of LEDs when the CE pin is "H" input (Duty=100%) is shown by the above expression. The current of LEDs can be controlled by Duty of the PWM signal of the input CE pin. The current of LEDs when High-Duty of the CE input is Hduty reaches the value as calculatable following formula.

$$I_{LED} = Hduty \times V_{FB} / R1$$

The frequency of the PWM signal is using the range between 200Hz to 300kHz.

When controlling the LED brightness by the PWM signal of 20kHz or less; The increasing or decreasing of the inductor current might be make a sounds in the hearable sound wave area. In that case, please use the PWM signal in the high frequency area.



Dimming control by CE pin input

- **Soft-Start**

The output of the error amplifier starts from 0V and the inrush current is suppressed when starting by the CE pin "H" input.

Moreover, the inrush current can be suppressed by gradually enlarging Duty of the PWM signal to the CE pin.

- **Selection of Inductors**

The peak current of the inductor at normal mode can be calculated as next formula:

$$I_{Lmax}=1.25 \times I_{LED} \times V_{OUT} / V_{IN} + 0.5 \times V_{IN} \times (V_{OUT} - V_{IN}) / (L \times V_{OUT} \times f_{osc})$$

When the start-up or dimming control by CE pin, transient current flows, the peak current must be equal or less than the current limit of the IC. The peak current should not beyond the rating current of the inductor.

When 4-7LEDs are driven with  $V_{IN}=3.6V$ , the recommended inductance value is 10 $\mu$ H -22 $\mu$ H.


- **Selection of Capacitors**

Set 1 $\mu$ F or more value bypass capacitor C1 between  $V_{IN}$  pin and GND pin as close as possible.

Set 0.22 $\mu$ F or more capacitor C2 between  $V_{OUT}$  pin and GND pin.


**OPERATION OF STEP-UP DC/DC CONVERTER AND OUTPUT CURRENT**

**<Basic Circuit>**




**<Current through L>**

**Discontinuous mode**



**Continuous mode**



There are two operation modes of the step-up PWM control-DC/DC converter. That is the continuous mode and discontinuous mode by the continuousness inductor.

When the transistor turns ON, the voltage of inductor L becomes equal to  $V_{IN}$  voltage. The increase value of inductor current ( $i1$ ) will be

$$\Delta i1 = V_{IN} \times t_{on} / L \dots\dots\dots \text{Formula 1}$$

As the step-up circuit, during the OFF time (when the transistor turns OFF) the voltage is continually supply from the power supply. The decrease value of inductor current ( $i2$ ) will be

$$\Delta i2 = (V_{OUT} - V_{IN}) \times t_{open} / L \dots\dots\dots \text{Formula 2}$$

At the PWM control-method, the inductor current become continuously when  $t_{open}=t_{off}$ , the DC/DC converter operate as the continuous mode.



In the continuous mode, the variation of current of  $i_1$  and  $i_2$  is same at regular condition.

$$V_{IN} \times t_{on} / L = (V_{OUT} - V_{IN}) \times t_{off} / L \dots\dots\dots \text{Formula 3}$$

The duty at continuous mode will be

$$\text{Duty} = t_{on} / (t_{on} + t_{off}) = (V_{OUT} - V_{IN}) / V_{OUT} \dots\dots\dots \text{Formula 4}$$

The average of inductor current at  $t_{open}=t_{off}$  will be

$$I_L(\text{Ave.}) = V_{IN} \times t_{on} / (2 \times L) \dots\dots\dots \text{Formula 5}$$

If the input power is equal to the output power, the  $I_{OUT}$  will be

$$I_{OUT} = V_{IN}^2 \times t_{on} / (2 \times L \times V_{OUT}) \dots\dots\dots \text{Formula 6}$$

If the  $I_{OUT}$  value is large than above the calculated value (Formula 6), it will become the continuous mode, At this status, the peak current ( $I_{Lmax}$ ) of inductor will be

$$I_{Lmax} = I_{OUT} \times V_{OUT} / V_{IN} + V_{IN} \times t_{on} / (2 \times L) \dots\dots\dots \text{Formula 7}$$

$$I_{Lmax} = I_{OUT} \times V_{OUT} / V_{IN} + V_{IN} \times T \times (V_{OUT} - V_{IN}) / (2 \times L \times V_{OUT}) \dots\dots\dots \text{Formula 8}$$



The peak current value is larger than the  $I_{OUT}$  value. In case of this, selecting the condition of the input and the output and the external components by considering of  $I_{Lmax}$  value.

The explanation above is based on the ideal calculation, and the loss caused by  $L_x$  switch and the external components are not included.


The actual maximum output current will be between 50% and 80% by the above calculations. Especially, when the  $I_L$  is large or  $V_{IN}$  is low, the loss of  $V_{IN}$  is generated with on resistance of the switch. Moreover, it is necessary to consider  $V_F$  of the diode (approximately 0.8V) about  $V_{OUT}$ .

## TYPICAL CHARACTERISTICS



### 1) Efficiency vs. Output Current Characteristics




### 2) PWM Dimming Duty Cycle vs. Output Current( $R1=10\Omega$ )




### 3) Output Current Ripple during PWM Dimming




f=300kHz




4) VFB Voltage vs. Temperature




5) Supply Current vs. Temperature




6) Oscillator Frequency vs. Temperature




7) Maxduty vs. Temperature




8) UVLO Output Voltage vs. Temperature




9) OVP Voltage vs. Temperature




10) Switch ON Resistance vs. Temperature



11) Lx Current Limit vs. Temperature



12) OVP Operating Output Voltage Waveform





1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to Ricoh sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of Ricoh.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under Ricoh's or any third party's intellectual property rights or any other rights.
5. The products listed in this document are intended and designed for use as general electronic components in standard applications (office equipment, telecommunication equipment, measuring instruments, consumer electronic products, amusement equipment etc.). Those customers intending to use a product in an application requiring extreme quality and reliability, for example, in a highly specific application where the failure or misoperation of the product could result in human injury or death (aircraft, spacevehicle, nuclear reactor control system, traffic control system, automotive and transportation equipment, combustion equipment, safety devices, life support system etc.) should first contact us.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, fire containment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. Please contact Ricoh sales representatives should you have any questions or comments concerning the products or the technical information.



**Ricoh is committed to reducing the environmental loading materials in electrical devices with a view to contributing to the protection of human health and the environment.**

Ricoh has been providing RoHS compliant products since April 1, 2006 and Halogen-free products since April 1, 2012.

**RICOH** RICOH ELECTRONIC DEVICES CO., LTD.

<http://www.e-devices.ricoh.co.jp/en/>

#### Sales & Support Offices

##### **RICOH ELECTRONIC DEVICES CO., LTD.**

**Higashi-Shinagawa Office (International Sales)**  
3-32-3, Higashi-Shinagawa, Shinagawa-ku, Tokyo 140-8655, Japan  
Phone: +81-3-5479-2857 Fax: +81-3-5479-0502

##### **RICOH EUROPE (NETHERLANDS) B.V.**

**Semiconductor Support Centre**  
Prof. W.H. Keesomlaan 1, 1183 DJ Amstelveen, The Netherlands  
Phone: +31-20-5474-309

##### **RICOH ELECTRONIC DEVICES KOREA CO., LTD.**

3F, Haesung Bldg. 504, Teheran-ro, Gangnam-gu, Seoul, 135-725, Korea  
Phone: +82-2-2135-5700 Fax: +82-2-2051-5713

##### **RICOH ELECTRONIC DEVICES SHANGHAI CO., LTD.**

Room 403, No.2 Building, No.690 Bilbo Road, Pu Dong New District, Shanghai 201203,  
People's Republic of China  
Phone: +86-21-5027-3200 Fax: +86-21-5027-3299

##### **RICOH ELECTRONIC DEVICES CO., LTD.**

**Taipei office**  
Room 109, 10F-1, No.51, Hengyang Rd., Taipei City, Taiwan (R.O.C.)  
Phone: +886-2-2313-1621/1622 Fax: +886-2-2313-1623

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Ricoh Electronics:](#)

[R1203N071B-TR-FE](#)

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9