# Honeywell

# **Current Sensors** Line Guide

**Past, future, and current excellence.** Honeywell Sensing and Control (S&C) offers a wide variety of current sensors to monitor alternating (ac) or direct (dc) current. From digital output detectors sensing a few hundred milliamps to linear sensors monitoring over one thousand amps, our comprehensive line provides superior, often accurate performance at a reduced cost. As well as the advantages you'd expect from an experienced provider offering decades of engineering expertise: thru-hole design, fast response times, output voltage isolation from input, minimum energy dissipation, and enhanced reliability with adjustable performance and built-in temperature compensation.

### FEATURES

#### DIGITAL/INDUCTIVE CURRENT SENSORS CSDA Series.

**Features:** Open collector output • Digital output • ac or dc currents • Thru-hole design • Output voltage isolation from input • Minimum energy dissipation • Maximum current limited only by conductor size • Enhanced accuracy, lowcost sensing • RoHS compliant

**Benefits:** Single digital (TTL logic level, open collector) output that will sink 20 mA of output current. Provides logic level output that changes from Vcc to 0.4 V when sensed current exceeds the operate point. Will not be damaged by overcurrent in the sensed conductor. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, and wattmeters.

#### CLOSED LOOP CURRENT SENSORS CSNB, CSNA, CSNC, CSNE, CSNF, CSNG, CSNJ, CSNK, CSNL, CSNM, CSNP, CSNR, CSNS, CSNT, and CSNX Series.

Features: Current sensing up to 1275 A • ac, dc, and impulse currents • In-line or thru-hole design • Competitive cost/ performance ratio • Rapid response • Reduced overshoot • High overload capability • High level of electrical isolation between primary and secondary circuits • Industrial operating temperature range • Small size and weight • RoHS compliant • CE, UL approvals

**Benefits:** Based on the principles of the magnetoresistive or Hall effects, and the null balance or zero magnetic flux method (feedback system). Magnetic flux in the sensor core is constantly controlled at zero. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

# OPEN LOOP CURRENT SENSORS CSCA-A Series.

Features: ac, dc, and impulse currentsCompetitive cost/performance ratio

• Low power consumption • Compact size

• High level of electrical isolation between primary and secondary circuits • Large primary aperture • RoHS compliant • CE, UL approvals

**Benefits:** Based on the principles of the Hall-effect wherein a Hall-effect device (HED) produces an output voltage linearly related to the amplitude and phase of a magnetic field applied to it. HED output is directly proportional to the amplitude and phase of the primary current. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.



## **Current Sensors Line Guide**

**Digital/Inductive** 

**Current Sensors** 



# Common sense. Global leadership.

Honeywell S&C offers linear (analog) open loop, digital, or closed-loop current sensors. When any of these sensors detect predetermined signals, the system then performs the designated task. For instance, the digital signal's logic level output may sound an alarm, start a motor, or open a valve. The linear signal duplicates the waveform — often ideal for feedback elements to control a motor, or regulate machine function. And Honeywell's new closed-loop current sensor with magnetoresistive (MR) technology offers amazing offset drift performance over a wide temperature range ---with almost no thermal drift, for enhanced accuracy.

For proven engineering expertise, component dependability, and global support, trust Honeywell S&C.

#### **CSDA Series**

Operate current	0.5 A.t. nom., 3.5 A.t. nom.
Sensed current type	ac or dc
Output	voltage
Response time	100 µs
Accuracy	better than 0.5 %
Mounting	PCB mounting pins or screw mount
Pinout style	3-pin PCB or 3-pin AMP connector
Operating temperature	-25 °C to 85 °C [-13 °F to 185 °F]
Supply voltage	6 Vdc to 16 Vdc

Closed Loop Current Sensors		CSNA111 eeeo on rts	Honeywell SSNF151 Water Star (Spin 44)
	CSNX Series	CSNA Series	CSNF Series
Sensed current range	±56 A	±70 A, ±90 A, ±100 A	±150 A, ±180 A, ±200 A
Sensed current type	ac, dc, impulse	ac, dc, impulse	ac, dc, impulse
Output	current	current	current
Coil turns	2000 (50 Ohm coil)	1000 (90 or 50 Ohm coil) 2000 (160 or 130 Ohm coil)	1000 (30 Ohm coil) 2000 (100 Ohm coil)
Response time	< 0.2 µs	< 1 µs	< 0.5 µs
Accuracy	±0.24 %	±0.5 %	±0.5 %
Mounting	PCB on 11-pins	PCB on 3-pins	PCB on 3-pins
Pinout style	unipolar	offset	center
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	0 °C to 70 °C [32 °F to 158 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	4.75 Vdc to 5.25 Vdc	±13 Vdc, ±15 Vdc	±12 Vdc to ±15 Vdc

# Honeywell

-

Closed Loop Current Sensors	CSNB131-002 9031 OP -11		CSNE151-100 9814 + 0
	CSNB Series	CSNC Series	CSNE Series
Sensed current range	±100 A	±90 A	±36 A, ±90 A
Sensed current type	ac, dc	ac, dc	ac, dc, impulse
Output	current	current	current
Coil turns	2000	1000 (50 Ohm coil)	1000 (110 Ohm or 66 Ohm coil)
Response time	< 1 µs	< 1 µs	< 1 µs
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	PCB on 3 pins	PCB on 3 pins	PCB on 13 pins
Pinout style	Offset	Offset	5-pin
Operating temperature	0 °C to 70 °C [32 °F to 158 °F]	-25 °C to 85 °C [-13 °F to 185 °F]	0 °C to 70 °C [32 °F to 158 °F]
Supply voltage	±15.0 Vdc	±13.0 Vdc	±12 Vdc to ±15 Vdc



### **Current Sensors Line Guide**



**Closed Loop Current Sensors** 







	CSNI Sorios	CSNM Sorios	CSNP Sories
	CSNL Series	CSINM Series	CSNF Series
Sensed current range	±600 A	±1000 A	±90 A
Sensed current type	ac, dc	ac, dc	ac, dc
Output	current	current	current
Coil turns	2000	3000	1000
Response time	< 0.5 µs	< 1 µs	< 0.5 µs
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	panel	panel	PCB on 3 pins
Pinout style	Molex (3-way)	Molex (3-way)	offset
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	±12.0 Vdc to ±18.0 Vdc	±12.0 Vdc to ±18.0 Vdc	±12.0 Vdc to ±15.0 Vdc



nesponse unie	< 0.5 μδ	< 0.0 µ3	< 0.0 µ3
Accuracy	±0.5 %	±0.5 %	±0.5 %
Mounting	panel	PCB on 3 pins	PCB on 3 pins
Pinout style	Molex (3-way)	center, offset	offset
Operating temperature	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]	-40 °C to 85 °C [-40 °F to 185 °F]
Supply voltage	±12 Vdc to ±18 Vdc	±12.0 Vdc to ±15.0 Vdc	±12.0 Vdc to ±15.0 Vdc

## Honeywell



N = Number of turns

Open Loop Current Sensors			
	CSLS Series	CSLT Series	CSLW Series
Sensed current range	±60 A	±100 A	±1 A, ±5 A, ±40 mA, ±200 mA
Sensed current type	ac, dc	ac, dc	ac, dc
Output	sink/source	sink/source	sink/source
Coil turns	-	-	12, 60, 300, 1500
Response time	3 µs	3 µs	3 µs
Sensitivity	15 mV/AT ±2 mV/AT @ 5 Vdc	15 mV/AT ±2 mV/AT @ 5 Vdc	various
Mounting	PCB	PCB	PCB
Pinout style	3-pin	3-pin	5-pin
Operating temperature	-25 °C to 100 °C [-13 °F to 212 °F]	-25 °C to 100 °C [-13 °F to 212 °F]	-25 °C to 100 °C [-13 °F to 212 °F]
Supply voltage	4.5 Vdc to 10.5 Vdc	4.5 Vdc to 10.5 Vdc	4.5 Vdc to 10.5 Vdc

#### **CSLA Series.**

**Features:** Linear output • ac or dc currents • Thru-hole design • Enhanced response time • Output voltage isolation from input • Minimum energy dissipation • Maximum current limited only by conductor size • Adjustable performance and built-in temperature compensation assures reliable operation • Enhanced accuracy, low-cost sensing • RoHS compliant

Benefits: Incorporates Honeywell's 91SS12-2 and SS94A1 linear output Halleffect transducter (LOHET<sup>™</sup>). Sensing element is assembled in a printed circuit board mountable housing, available in four configurations. Potential applications include variable speed drives, overcurrent protection, ground fault detectors, current feedback control systems, robotics, UPS and telecommunication power supplies, welding power supplies, battery management systems, and wattmeters.

#### **CSLH Series.**

**Features:** ac or dc currents • Miniature • Linear ratiometric output • Current sinking or sourcing output for interfacing flexibility • No insertion loss • Enhanced response time • Low-cost sensing

Minimum energy dissipation
Maximum current limited only by conductor size
Built-in temperature compensation

promotes reliable operation • RoHs compliant

**Benefits:** Open-loop sensor incorporates Honeywell's SS490 Series miniature ratiometric linear Hall-effect sensor. Element is encapsulated in a PCBmountable plastic package. Combination of sensor, flux collector, and housing comprises the current sensor assembly. Potential applications include motor control, HVAC and consumer tools, current monitoring of electronic circuits, overcurrent protection, ground fault

Sensing and Control Automation and Control Solutions Honeywell 1985 Douglas Drive North Golden Valley, MN 55422 USA +1-815-235-6847 www.honeywell.com/sensing detectors, robotics, industrial process control, UPS and telecommunication power supplies, welding current monitoring, battery management systems in mobile equipment, watt meters, and variable speed drives.

#### CSLS, CSLT, CSLW Series.

Features: ac or dc currents • Linear ratiometric output • Current sinking or sourcing output for interfacing flexibility • No insertion loss • Enhanced response time • Compact size for applications with limited space • Enhanced accuracy, low-cost sensing • Minimum energy dissipation • Maximum current limited only by conductor size • Built-in temperature compensation promotes reliable operation • RoHs compliant

**Benefits:** Incorporate Honeywell's SS490 Series miniature ratiometric linear Halleffect sensor. Element is encapsulated in a printed circuit board-mountable plastic package. Sensors are ratiometric. Potential applications include motor control in HVAC and consumer tools, current monitoring of electronic circuits, overcurrent protection, ground fault detectors, robotics, industrial process control, UPS and telecommunication power supplies, welding current monitoring, battery management systems in mobile equipment, watt meters, and variable speed drives.

**Warranty.** Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds defective. The foregoing is buyer's sole remedy and is in lieu of all warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

For more information about Sensing and Control products, visit www.honeywell. com/sensing or call +1-815-235-6847 Email inquiries to info.sc@honeywell.com

### WARNING PERSONAL INJURY

• DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury.

Failure to comply with these instructions could result in death or serious injury.

### WARNING MISUSE OF DOCUMENTATION

- The information presented in this catalogue is for reference only. DO NOT USE this document as product installation information.
- Complete installation, operation and maintenance information is provided in the instructions supplied with each product.

Failure to comply with these instructions could result in death or serious injury.

# Honeywell

005895-1-EN IL50 GLO June 2008 Copyright © 2008 Honeywell International Inc. All rights reserved.





Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.З, офис 1107

### Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

#### http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

#### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.З, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж: moschip.ru moschip.ru\_4

moschip.ru\_6 moschip.ru\_9