

DEMO MANUAL DC2302A

LTC4123EDC Low Power Wireless Charger Demonstration Kit

DESCRIPTION

Demonstration Circuit DC2302A is a kit of the DC2300A demonstration board, featuring the LTC®4123EDC, and the DC2301A Single Switch Transmitter demonstration board. The DC2300A can charge a single NiMH battery at up to 25mA, with an air gap of 0.8mm to 4.0mm. The DC2300A detects Zinc-Air primary cells and will not charge them.

Design files for this circuit board are available at http://www.linear.com/demo/DC2302A

(T, LTC, LTM, Linear Technology, the Linear logo and TimerBlox are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.

PERFORMANCE SUMMARY Sue

Specifications are at T_A = 25°C

| SYMBOL | PARAMETER | CONDITIONS | MIN | TYP | MAX | UNITS |
|------------------|---------------------------------|--|-----|-----|-----|-------|
| V_{IN} | DC2301A Voltage Input | I _{VIN} ≤ 0.5A | 4.5 | | 5.5 | V |
| I _{BAT} | DC2300A Battery Charger Current | V _{CC} = 3V ~ 5V, DC2300A.R1 = 953Ω | 24 | | 26 | mA |



Figure 1. Demonstration Kit with Battery




Figure 2. Typical Application Circuit



DEMO BOARD PROCEDURE

Refer to Figure 5 for the proper measurement equipment setup and follow the procedure below:

NOTE: When measuring the input or output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. Measure the input or output voltage ripple by touching the probe tip directly across the signal and GND terminals. See Figure 6 for proper scope probe technique.

- 1. Set PS1 to 1.3V and turn on.
- 2. Plug a Micro-USB cable into DC2301.J1, the other end of the cable should go to a computer USB port or a 5V wall charger.
- 3. Verify that DC2301A.D1 is lit. DC2301A.D1 is between the boards, near the front face.

4. The LTC4123EDC spends the first 90s after power up testing for either a reverse battery or a Zinc-Air primary battery. DC2300A.D1 should be blinking slowly. AM1should read 25mA, VM1 should read between 3V and 5V.

The LTC4123EDC tests for a Zinc-Air battery by applying the programmed charge current, and checking to see if V(BAT) rises above ≈ 1.65 V.

- If the battery is absent, reversed or Zinc-Air, DC2300A. D1 will start blinking rapidly.
- 5. Turn off and disconnect PS1, AM1 and VM1. Install the P675 NiMH battery in the DC2300A.BH1 battery holder. See Figure 4 for proper insertion. Warning: improper insertion may short battery.



(a) DC2300A Top



(b) DC2301A Top



(c) DC2300A Bottom




(d) DC2301A Bottom

Figure 3. DC2300A and DC2301A Demo Boards



dc2302afa

DEMO BOARD PROCEDURE





(b)



Figure 4. Proper Insertion of Battery in Demo Kit



DEMO BOARD PROCEDURE




Figure 5. DC2300A Mounted on Top of DC2301A



Figure 6. Measuring Input or Output Ripple

Note: All connections from equipment should be Kelvin connected directly to the board pins which they are connected on this diagram and any input or output leads should be twisted pair.

LINEAR TECHNOLOGY

THEORY OF OPERATION

The DC2302A kit demonstrates operation of the LTC4123EDC Low Power Wireless Charger. The kit is composed of the DC2300A Wireless Power Transfer (WPT) receiver and the DC2301A WPT transmitter.

DC2300A – Low Power Battery Charger Board Featuring the LTC4123EDC

The LTC4123EDC integrates a low power CC-CV linear charger optimized for NiMH cells. The LTC4123EDC also contains a low leakage diode for rectifying the output of the WPT resonant tank. The DC2300A WPT resonant tank is set to 244kHz. Tested receive coils are listed in Table 1.

The CC-CV charger will operate with a V_{CC} as low as 2.2V, and charge a NiMH battery to 1.61V ($T_A = -10^{\circ}$ C). The Charge Voltage is temperature dependent, a temperature coefficient of -2.5mV/°C, and a typical charge voltage of 1.5075, at room (see Figure 7).

The LTC4123EDC has a fault state machine that checks for battery reversal and presence of a Zinc-Air primary cell in the first 90s after V_{CC} is applied.

The LTC4123EDC has an on-die temperature sensing that will shut down the charger if the sensed temperature is too high or low.




Figure 7. Charge Voltage vs Temperature (Placeholder)

The WPT for the LTC4123EDC is implemented as resonant power transfer, with the LTC4123EDC rectifying the resonant tank voltage to generate V_{CC} (see Figure 9).

DC2301A – Wireless Power Transmitter Board Featuring the LTC6990IDCB

The DC2301A is a wireless power transmitter board using an LTC6990IDCB TimerBlox®, followed by a zero voltage switching Class C amplifier.

The LTC6990IDCB is programmed to generate a 244kHz square wave, but the Class C amplifier tank is resonant at 315kHz, resulting in zero voltage switching (see Figure 8). Tested transmit coils are listed in Table 2.




Figure 8. DC2301A $V_{IN} = 5V$, Air Gap = 4mm




Figure 9. DC2300A $V_{IN} = 5V$, Air Gap = 4mm



THEORY OF OPERATION

Operating the DC2302A WPT Kit from a USB Port

The DC2302A WPT Demo Kit to can comply with the requirements for a USB peripheral. One requirement is the $50\mu C$ inrush charge specification, which drives the maximum input capacitance. Another requirement is that a USB peripheral must draw less than 100mA, until negotiating for more. The DC2302A WPT kit does not contain a microcontroller to negotiate for more than 100mA, so, it must operate at less than 100mA.

DC2301A.C2 can be changed to $4.7\mu F$, which in parallel with DC2301A.C1 = $4.7\mu F$, will be less than the $10\mu F$. The DC2302A will then meet the $50\mu C$ inrush charge specification.

All air gaps mentioned below are the coil face to coil face distances:

| 0.8mm gap: | USB.V _{CC} current = $102mA$ @ USB.V _{CC} = $4.5 \sim 5.5V$ 300mV of $255kHz$ ripple on USB.V _{CC} DC2300A.V(BAT) = $1 \sim 1.4V$ |
|---------------|--|
| 2.4mm gap: | USB.V _{CC} current = 84mA @ USB.V _{CC} = $4.5 \sim 5.5$ V 280mV of 255kHz ripple on USB.Vcc DC2300A.V(BAT) = $1 \sim 1.4$ V |
| 4.0mm gap: | USB.V _{CC} current = 73mA @ USB.V _{CC} = $4.5 \sim 5.5$ V 240mV of 255kHz ripple on USB.Vcc DC2300A.V(BAT) = $1 \sim 1.4$ V |

So, if the gap is kept greater than \approx 1.5mm and DC2301A.C2 \leq 4.7µF, the DC2302A should meet the compliance requirements for a USB peripheral. The DC2302A will not support suspend mode operation.

PARTS LIST

Table 1. Tested LRx Coils

| THE STATE OF THE S | | |
|--|-----------------|---|
| Vendor | Part number | URL |
| Wurth | 760308101208 | http://www.we-online.com |
| Inter-Technical | L4120R19 | http://www.inter-technical.com/index.php?page=products# |
| Sunlord | SWA12R10H17C01B | http://www.sunlordinc.com/ |

Table 2. Tested LTx Coils


| Vendor | Part number | URL |
|---|-----------------|---|
| Wurth | 760308103206 | http://www.we-online.com |
| Inter-Technical L41200T23 http://www.inter-technical.com/index.php?page=products# | | http://www.inter-technical.com/index.php?page=products# |
| Sunlord | SWA28R15H08C01B | http://www.sunlordinc.com/ |

PARTS LIST


| ITEM | QTY | REFERENCE | PART DESCRIPTION | MANUFACTURER/PART NUMBER | |
|---------------|-----------|----------------------------|--|-----------------------------------|--|
| | • | • | DC2300A | • | |
| Required | Circuit | Components | | | |
| 1 | 1 | C1 | CAP, CHIP, X5R, 4.7μF, ±10%, 10V, 0402 | SAMSUNG, CL05A475KP5NRNC | |
| 2 | 1 | CRx | CAP, CHIP, COG, 33nF, ±5%, 50V, 1206/0805 | TDK, C2012C0G1H333J125AA | |
| 4 | 1 | LRx | RECEIVE ANTENNA, 13µH, ±10%, 10mm | WURTH, 760308101208 | |
| 5 | 1 | R1 | RES, CHIP, 953Ω, ±1%, 1/16W, 0402 | VISHAY, CRCW0402953RFKED | |
| 6 | 1 | U1 | LOW POWER WIRELESS CHARGER, 2mm × 2mm DFN6 | LINEAR TECH., LTC4123EDC | |
| Additiona | l Demo | Board Circuit Components | | | |
| 1 | 0 | C2-OPT | CAP, CHIP, X5R, 1µF, ±10%, 16V, 0402 | TDK, C1005X5R1C105K | |
| 2 | 1 | D1 | LED, RED, SMT, 0603 | ROHM, SML-311UTT86 | |
| 3 | 1 | R2 | RES, CHIP, 4.7kΩ, ±5%, 1/16W, 0402 | VISHAY, CRCW04024K70JNED | |
| lardware | e: For De | emo Board Only | | | |
| 1 | 1 | BH1 | COIN CELL BATTERY RETAINER, 11.6mm | KEYSTONE, 2996 | |
| 2 | 7 | E1, E2, E3, E4, E5, E6, E7 | TURRET, 0.061" | MILL-MAX, 2308-2-00-80-00-00-07-0 | |
| | | | DC2301A | | |
| Required | Circuit | Components | | | |
| 1 | 1 | C2 | CAP, CHIP, X5R,100μF, ±20%,6.3V,1206 | MURATA, GRM31CR60J107ME39L | |
| 2 | 1 | CTx1 | CAP, CHIP, COG, 33nF, ±1%, 25V, 1206/0805 | KEMET, C0805C333F3GACTU | |
| 3 | 1 | CTx2 | CAP, CHIP, COG, 1nF, ±5%, 50V, 0603 | TDK, C1608C0G1H102J080AA | |
| 4 | 1 | LTx | TRANSMIT ANTENNA, 7.5µH, ±10%, 28mm × 15mm | WURTH, 760308103206 | |
| 5 | 1 | M1 | MOSFET, N-CH 20V, 6A, SOT23-3 | VISHAY, SI2312CDS-T1-GE3 | |
| 6 | 1 | R1 | RES, CHIP, 205kΩ, ±1%, 1/16W, 0402 | VISHAY, CRCW0402357KFKED | |
| 7 | 1 | U1 | TimerBlox: VOLTAGE CONTROLLED SILICON OSCILLATOR, 2mm × 3mm DFN6 | LINEAR TECH., LTC6990IDCB | |
| Additiona | l Demo | Board Circuit Components | | | |
| 1 | 1 | C1 | CAP, CHIP, X5R, 4.7μF, ±20%, 6.3V, 0402 | TDK, C1005X5R0J475M | |
| 2 | 1 | D1 | LED, RED, SMT, 0603 | LITEON, LTST-C193KRKT-5A | |
| 3 | 1 | J1 | USB2.0 MICRO-B RECEPTACLE, RT, REVERSED, 1932788-1 | TE, 1932788-1 | |
| 4 | 1 | R2 | RES, CHIP, 2.2kΩ, ±5%, 1/16W, 0402 | VISHAY, CRCW04022K20JNED | |
| - Hardware | e: For De | emo Board Only | | | |
| 1 | 2 | E1, E2 | TURRET, 0.061" | MILL-MAX, 2308-2-00-80-00-00-07-0 | |



SCHEMATIC DIAGRAM



SCHEMATIC DIAGRAM



DEMO MANUAL DC2302A

DEMONSTRATION BOARD IMPORTANT NOTICE

Linear Technology Corporation (LTC) provides the enclosed product(s) under the following AS IS conditions:

This demonstration board (DEMO BOARD) kit being sold or provided by Linear Technology is intended for use for **ENGINEERING DEVELOPMENT OR EVALUATION PURPOSES ONLY** and is not provided by LTC for commercial use. As such, the DEMO BOARD herein may not be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including but not limited to product safety measures typically found in finished commercial goods. As a prototype, this product does not fall within the scope of the European Union directive on electromagnetic compatibility and therefore may or may not meet the technical requirements of the directive, or other regulations.

If this evaluation kit does not meet the specifications recited in the DEMO BOARD manual the kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY THE SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THIS INDEMNITY, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user releases LTC from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge. Also be aware that the products herein may not be regulatory compliant or agency certified (FCC, UL, CE, etc.).

No License is granted under any patent right or other intellectual property whatsoever. LTC assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or any other intellectual property rights of any kind.

LTC currently services a variety of customers for products around the world, and therefore this transaction is not exclusive.

Please read the DEMO BOARD manual prior to handling the product. Persons handling this product must have electronics training and observe good laboratory practice standards. **Common sense is encouraged**.

This notice contains important safety information about temperatures and voltages. For further safety concerns, please contact a LTC application engineer.

Mailing Address:

Linear Technology 1630 McCarthy Blvd. Milpitas, CA 95035

Copyright © 2004, Linear Technology Corporation



ПОСТАВКА ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

многоканальный

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru_6 moschip.ru_4 moschip.ru_9