



Quality Products. Service Excellence.

Tube Guitar Amplifier - Power Transformers 290 Series

REPLACEMENT & UPGRADES

Features



- Designed for drop in replacement of original units.
- Physically, parts were designed to look similar to original factory units (where possible).
- Material used & design specs. were kept as close as possible to the original part to preserve the stock "tone".



Fender (Power Transformers)

Hammond P/N	Amp Model	Similar Amp P/N's*	Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
290EX	BANDMASTER*	67233, 125P7D, 125P7DX, 022814	Blond, 6G7-A, Blackface, AA763, AB763, Silverface, AC568, AD1269	120V	660Vct @ 275 mA	53V Bias	6.3Vct @ 4A		
290EEX	BANDMASTER*		Blond, 6G7-A, Blackface, AA763, AB763, Silverface, AC568, AD1269	120/210/230/240 @ 50/60 Hz	660Vct @ 275 mA	53V Bias	6.3Vct @ 4A		
290D2X	BANDMASTER*		Tweed	120V @ 60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	BANDMASTER*		Tweed	120/210/220/230/240V @ 50/60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290DHX	BANDMASTER DELUXE*	76041000		120V @ 60 Hz	315V @ 250 mA		26V @ 100 mA	6V @ 1A	6.3Vct @ 5A
290D2X	BANDMASTER REVERB*	8087, 125P5D, 125P5DX, 022798, 022806	Blackface, Silverface, AA1069, AA270, AA763,	120V @ 60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	BANDMASTER REVERB*		Blackface, Silverface, AA1069, AA270, AA763,	120/210/220/230/240V @ 50/60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2X	BASSMAN*	8087, 125P5D, 125P5DX, 022798, 022806	Tweed, 5F6, 5F6A, 10	120V @ 60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	BASSMAN*		Tweed, 5F6, 5F6A, 10	120/210/220/240V @ 50/60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	

Hammond P/N	Amp Model	Similar Amp P/N's*		Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
290EX	BASSMAN*	67233, 125P7D, 125P7DX, 022814		Blackface, AA864, AA165, AB165, Silverface, AA270	120V @ 60 Hz	660Vct @ 275 mA	53V Bias	6.3Vct @ 4A		
290EEX	BASSMAN*			Blackface, AA864, AA165, AB165, Silverface, AA270	120/210/230/240V @ 50/60 Hz	660Vct @ 275 mA	53V Bias	6.3Vct @ 4A		
290DX	BASSMAN* (Lower Plate Volts)	8087		Tweed, 5F6, 5F6A	120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DEX	BASSMAN* (Lower Plate Volts)			Tweed, 5F6, 5F6A	240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DX	BASSMAN* (Lower Plate Volts)	8087		Combos	120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DEX	BASSMAN* (Lower Plate Volts)			Combos	240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290FX	BASSMAN 100*	125P34A, 022756		Silverface	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	BASSMAN 100*			Silverface	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
291ZZ	BASSMAN 135*	13692		Silverface	120V @ 60 Hz	364Vct @ 1A	53V Bias	6.3Vct @ 7A	6.3Vct @ 7A	
291ZEZ	BASSMAN 135			SAME	120/240V @ 50/60 Hz	364Vct @ 1A	53V Bias	6.3Vct @ 7A	6.3Vct @ 7A	
290TX	BASSMAN 59* (REISSUE)	36483		217-1000-010	120V @ 60 Hz	696Vct @ 500 mA	52V Bias	6.5V @ 2A	5V @ 2A	
290YX	BASSMAN 70*	13895		Silverface	120V @ 60 Hz	372Vct @ 400 mA	56V Bias	6.3Vct @ 4A		
290YEX	BASSMAN 70*			Silverface	240V @ 50/60 Hz	372Vct @ 400 mA	56V Bias	6.3Vct @ 4A		
290UX	BLUES DELUXE*	36958			117V @ 60 Hz	308.5V @ 250 mA	39V Bias	6.6V @ 3.75A		
290UEX	BLUES DELUXE*				240V @ 50/60 Hz	308.5V @ 250 mA	39V Bias	6.6V @ 3.75A		
290UX	BLUES DELUXE* (REISSUE)	36958			117V @ 60 Hz	308.5V @ 250 mA	39V Bias	6.6V @ 3.75A		
290UEX	BLUES DELUXE* (REISSUE)				240V @ 50/60 Hz	308.5V @ 250 mA	39V Bias	6.6V @ 3.75A		
290XX	BLUES JR.*	49967			117V @ 60 Hz	260V @ 170 mA		20V @ 100 mA	6.3V @ 3A	
290XEX	BLUES JR.*				240V @ 50/60 Hz	260V @ 170 mA		20V @ 100 mA	6.3V @ 3A	
290AX	BRONCO*	125P1B, 022772, 66079B		AA764, AB764, Blackface, Silverface	120V, 60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AEX	BRONCO*			AA764, AB764, Blackface, Silverface	120/220/230/240V 50/60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AX	CHAMP*	125P1B, 022772, 66079B		5C1, 5E1, 5F1, Tweed, Blackface, Silverface, AA764	120V, 60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
291AEX	CHAMP*			5C1, 5E1, 5F1, Tweed, Blackface, Silverface, AA764	120/220/230/240V 50/60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290BAX	CHORUS*	31668			120V @ 60 Hz	60Vct @ 2.85A				

Hammond P/N	Amp Model	Similar Amp P/N's*		Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
290EX	CONCERT*	67233, 125P7D, 125P7DX, 022814		Brownface, 6G12A, Blackface, AA763	120V @ 60 Hz	660Vct @ 275 mA	53V Bias	6.4Vct @ 4A		
290EEX	CONCERT*			Brownface, 6G12A, Blackface, AA763	120/210/230/240 @ 50/60 Hz	660Vct @ 275 mA	53V Bias	6.4Vct @ 4A		
290BX	DELUEX*	125P2A, 125P23B, 022749, 025130		5A3, 5B3, 5C3, 5D3, 6G3, AB763	120V @ 60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290BEX	DELUEX*			5A3, 5B3, 5C3, 5D3, 6G3, AB763	240V @ 50/60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290BBX	DELUEX*	6452		Tweed	120V @ 50/60 Hz	710Vct @ 115 mA	-	6.3Vct @ 1.65A	5V @ 2A	
290BBEX	DELUEX*			Tweed	120/220/230/240 @ 50/60 Hz	710Vct @ 115 mA	-	6.3Vct @ 1.65A	5V @ 2A	
290CX	DELUXE 65 REVERB* (REISSUE)	041316, 022723, 125P26A		021-7400-000	120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	DELUXE 65 REVERB* (REISSUE)			021-7400-000	240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CX	DELUXE 68 CUSTOM REVERB*	041316, 022723, 125P26A			120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	DELUXE 68 CUSTOM REVERB*				240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290BX	DELUXE REVERB*	125P33A, 022749, 125P23B, 025130		Blackface, Silverface, AA763, AB763, AB868, A1172, A1270, Volume Boost	120V @ 60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290BEX	DELUXE REVERB*			Blackface, Silverface, AA763, AB763, AB868, A1172, A1270, Volume Boost	240V @ 50/60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290CX	FENDER 30*	041316, 022723, 125P26A			120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	FENDER 30*				240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290HAX	HARVARD*	5F10		Tweed Push Pull	120V @ 60 Hz	550Vct @ 100 mA	50V Bias	6.3Vct @ 2.5A	5V @ 3A	
290HAEX	HARVARD*			Tweed Push Pull	120V/210/230V/240V @ 50/60 Hz	550Vct @ 100 mA	50V Bias	6.3Vct @ 2.5A	5V @ 3A	
290UX	HOT ROD DELUXE*	36958		021-3202-000	117V @ 60 Hz	308.5V @ 250 mA		39V @ 250 mA	6.6V @ 3.75A	
290UEX	HOT ROD DELUXE*			021-3202-000	240V @ 50/60 Hz	308.5V @ 250 mA		39V @ 250 mA	6.6V @ 3.75A	
290VX	HOT ROD DEVILLE*	41752			117V @ 60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290VEX	HOT ROD DEVILLE*				240V @ 50/60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290CX	MODEL 30*	041316, 022723, 125P26A			120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	MODEL 30*				240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290AAX	MUSICMASTER BASE*	026821			120V, 60 Hz	490Vct @ 90 mA		6.3V @ 1.25A		
290BAX	POWER CHORUS*	31668			120V @ 60 Hz	60Vct @ 2.85A				

Hammond P/N	Amp Model	Similar Amp P/N's*		Chassis No.*	Primary Volts	Secondary 1	2	3	4	5
290AX	PRINCETON*	125P1B, 022772, 66079B		Tweed, Brown, Blackface, Silverface, AA964	120V, 60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AEX	PRINCETON*			Tweed, Brown, Blackface, Silverface, AA964	120/220/230/240V 50/60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AX	PRINCETON REVERB*	125P1B, 022772, 66079B		AA1164, AA764, B1270, Blackface, Silverface	120V, 60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AEX	PRINCETON REVERB*			AA1164, AA764, B1270, Blackface, Silverface	120/220/230/240V 50/60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290D2X	PRO*	8087, 125P5D, 125P5DX, 022798, 022806		Tweed, Blackface, AB763	120V @ 60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	PRO*			Tweed, Blackface, AB763	120/210/220/240V @ 50/60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2X	PRO REVERB*	8087, 125P5D, 125P5DX, 022798, 022806		Silverface, AB668, AA1069, AA270	120V @ 60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	PRO REVERB*			Silverface, AB668, AA1069, AA270	120/210/220/240V @ 50/60 Hz	710/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290XXA	PRO JR.*	41782			117V @ 60 Hz	260V @ 170 mA		6.3V @ 3A		
290XXB	PRO JR.*				117V @ 60 Hz	260V @ 170 mA		6.3Vct @ 3A		
290FX	QUAD WITH REVERB*	125P34A, 022756			120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	QUAD WITH REVERB*				240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FX	SHOWMAN*	125P34A, 022756		Silverface, Blackface, AB763, AC568, AA763	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	SHOWMAN*			Silverface, Blackface, AB763, AC568, AA763	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FX	SHOWMAN REVERB*	125P34A, 022756		AA768	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	SHOWMAN REVERB*			AA768	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FX	SHOWMAN DUAL*	125P34A, 022756		AB763, AC568	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	SHOWMAN DUAL*			AB763, AC568	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FX	SHOWMAN DUAL REVERB*	125P34A, 022756		100, AA769	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	SHOWMAN DUAL REVERB*			100, AA769	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290S2Z	SUNN 2000*	3-12 PT			117V @ 60 Hz	780Vct @ 400 mA	55V Bias	6.3Vct @ 8A	5V @ 4A	
290DX	SUPER*	8087		Brownface, 5F4, 6G4, 6G4-A	120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DEX	SUPER*			Brownface, 5F4, 6G4, 6G4-A	240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290D2X	SUPER*	8087, 125P5D, 125P5DX, 022798, 022806		Tweed	120V @ 60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	SUPER*			Tweed	120/210/220/230/240V @ 50/60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290DX	SUPER* (lower plate voltage)	8087		Tweed, 5F4, Brownface, 6G4, 6G4-A	120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DEX	SUPER* (lower plate voltage)			Tweed, 5F4, Brownface, 6G4, 6G4-A	240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290ACX	SUPER CHAMP X2*	91234000			120V @ 60 Hz	300V @ 100 mA	34Vct @ 100 mA	9V @ 1.5A	6.6V @ 1.5A	

Hammond P/N	Amp Model	Similar Amp P/N's*		Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
291ACX	SUPER CHAMP X2*				120/240V @ 50/60 Hz	300V @ 100 mA	34Vct @ 100 mA	9V @ 1.5A	6.6V @ 1.5A	
290D2X	SUPER REVERB*	8087, 125P5D, 125P5DX, 022798, 022806		Brownface, Blackface, AA763, AB763, Silverface, AB568, AA270	120V @ 60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290D2EX	SUPER REVERB*			Brownface, Blackface, AA763, AB763, Silverface, AB568, AA270	120/210/220/230/240V @ 50/60 Hz	710Vct/610Vct @ 300 mA	50V Bias	6.3Vct @ 5A	5V @ 3A	
290FX	SUPER SIX REVERB 100*	125P34A, 022756			120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	SUPER SIX REVERB 100*				240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
291ZZ	SUPER SIX REVERB 135*	13692			120V @ 60 Hz	364Vct @ 1A	53V @ 1A	6.3Vct @ 7A		
291ZEZ	SUPER SIX REVERB 135*				120/240V @ 50/60 Hz	364Vct @ 1A	53V @ 1A	6.3Vct @ 7A		
290VX	SUPER SONIC 60 COMBO*	41752		021-3201-000	117V @ 60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290VEX	SUPER SONIC 60 COMBO*			021-3201-000	240V @ 50/60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290SX	TONEMASTER*	26554			120/230/240V @ 50/60 Hz	337Vct @ 1.1A		54V @ 250 mA	6.4V @ 3A	
290CX	TREMOLUX*	041316, 022723, 125P26A		AA763, AB763	120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	TREMOLUX*			AA763, AB763	240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290BX	TREMOLUX* TWEED	041316, 022723, 125P26A		5E9, 5E9-A, 5G9	120V @ 60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290BEX	TREMOLUX* TWEED			5E9, 5E9-A, 5G9	240V @ 50/60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
290RX	TWIN RED KNOB*	26477			120V @ 60 Hz	337Vct @ 1.1A		54V @ 250 mA	6.4V @ 3A	
290REX	TWIN RED KNOB*				100/120/220/240V @ 50/60 Hz	337Vct @ 1.1A		54V @ 250 mA	6.4V @ 3A	
290FX	TWIN REVERB*	125P34A, 022756		AA769, AA270, Silverface, AB763, Blackface, 100	120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	TWIN REVERB*			AA769, AA270, Silverface, AB763, Blackface, 100	240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290BAX	ULTIMATE CHORUS*	31668			120V @ 60 Hz	60Vct @ 2.85A				
290BAX	ULTIMATE CHORUS*	31668			120V @ 60 Hz	60Vct @ 2.85A				
290BAX	ULTRA CHORUS*	31668			120V @ 60 Hz	60Vct @ 2.85A				
290AX	VIBRO CHAMP*	125P1B, 022772, 66079B		AA764, Blackface, Silverface	120V, 60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290AEX	VIBRO CHAMP*			AA764, Blackface, Silverface	120/220/230/240V 50/60 Hz	650/550Vct @ 100 mA		6.3Vct @ 2.25A	5V @3A	
290ABX	VIBRO CHAMP XD*	74596000F			120/240V, 50/60 Hz	293.5V @ 100 mA	34Vct @ 95 mA	9V @ 1.25A	6.3V @ 5A	
290SX	VIBRO KING*	26554			120/230/240V @ 50/60 Hz	337Vct @ 1.1A		54V @ 250 mA	6.4V @ 3A	
290ABX	VIBRO CHAMP XD*	74596000F			120/240V, 50/60 Hz	293.5V @ 100 mA	34Vct @ 95 mA	9V @ 1.25A	6.3V @ 5A	
290SX	VIBRO KING*	26554			120/230/240V @ 50/60 Hz	337Vct @ 1.1A		54V @ 250 mA	6.4V @ 3A	

Hammond P/N	Amp Model	Similar Amp P/N's*		Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
290CX	VIBROLUX*	041316, 022723, 125P26A	AB763		120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	VIBROLUX*				240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CX	VIBROLUX REVERB*	041316, 022723, 125P26A	AA964, AB568, AA270		120V @ 60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290CEX	VIBROLUX REVERB*				240V @ 50/60 Hz	650Vct @ 180 mA	50V Bias	6.3V @ 4.5A	5V @ 3A	
290FX	VIBROSONIC*	125P34A, 022756			120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290FEX	VIBROSONIC*				240V @ 50/60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A		
290EZ	57 TWIN REISSUE*	64419000			120V @ 60 Hz	640Vct @ 250 mA	50V Bias	6.3V @ 4A	5V @ 4A	
290EEZ	57 TWIN REISSUE*				240V @ 50/60 Hz	660Vct @ 250 mA	50V Bias	6.3V @ 4A	5V @ 4A	
290DX	59 BASSMAN*	8087			120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290DEX	59 BASSMAN*				240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
290WX	63 REVERB*	68319A	6G15		120V @ 60 Hz	237V @ 50 mA		6.6V @ 1.05A		
290WEX	63 REVERB*				240V @ 50/60 Hz	237V @ 50 mA		6.6V @ 1.05A		
290UX	63 VIBROVERB REISSUE*				117V @ 60 Hz	308.5V @ 250 mA		39V @ 250 mA	6.6V @ 3.75A	
290UEX	63 VIBROVERB REISSUE*				240V @ 50/60 Hz	308.5V @ 250 mA		39V @ 250 mA	6.6V @ 3.75A	
290EBZ	65 TWIN REVERB REISSUE*				120V @ 60 Hz	340V @ 500 mA		50V @ 100 mA	6.3V @ 6A	
290VX	93 SUPER CONCERT*				117V @ 60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290VEX	93 SUPER CONCERT*				240V @ 50/60 Hz	342V @ 500 mA		52Vct @ 250 mA	6.3V @ 3.75A	
290EAX	94 TWIN REISSUE*				120V @ 60 Hz	365Vct @ 850 mA		27.5V @ 100 mA	6.3V @ 7A	
291AX	GENERIC	41776			120V @ 60 Hz	650Vct @ 81 mA		6.3V @ 2A	5V @ 2A	
291BX	GENERIC				120V @ 60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
291BEX	GENERIC				240V @ 50/60 Hz	660Vct @ 138 mA	50V Bias	6.3V @ 3A	5V @ 3A	
291CX	GENERIC				120V @ 60 Hz	650Vct @ 207 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
291CEX	GENERIC				240V @ 50/60 Hz	650Vct @ 207 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
291DX	GENERIC				120V @ 60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
291DEX	GENERIC				240V @ 50/60 Hz	650Vct @ 230 mA	50V Bias	6.3Vct @ 4A	5V @ 3A	
291EEX	GENERIC				240V @ 50/60 Hz	660Vct @ 276 mA	53V Bias	6.5V @ 3.15A		
291FX	GENERIC				120V @ 60 Hz	640Vct @ 518 mA	60V Bias	6.5V @ 5.5A	6.5V @ 5.5A	
290CAX	GENERIC				120/240V @ 50/60 Hz	630/550Vct @ 115 mA		6.3V @ 2A	5V @ 2A	
290CBZ	GENERIC				120V @ 60 Hz	650Vct @ 120 mA		6.3V @ 2A	5V @ 3A	

Hammond P/N	Similar Amp Amp Model	P/N's*	Chassis No.*	Primary Volts	Secondary 1	Secondary 2	Secondary 3	Secondary 4	Secondary 5
290DAX	GENERIC			120/240V @ 50/60 Hz	710/610Vct @ 230 mA		6.3Vct @ 5A		5V @ 3A

Marshall (Power Transformers)

Part No.	Primary	Marshall Model Names	Equivalent To Marshall Part No.	Bobbin/Paper Wound
290MAZ	117/234VAC 50/60 Hz.	Studio 15 "Little Fatty"	294-285/6	BOBBIN
290PAZ	120/240 VAC 50/60 Hz.	18 Watt Combo	-	BOBBIN
290GX	120/220/240 VAC 50/60 Hz.	JCM 800, JMP - 50 watt	-	BOBBIN
290HX	120/220/240 VAC 50/60 Hz.	JCM 800 & JMP - 100 watt	-	PAPER
290KX	120/240 VAC 50/60 Hz.	JCM 900 - 50 watt	-	BOBBIN
290JX	120/240 VAC 50/60 Hz.	JCM 900 - 100 watt	-	BOBBIN
290LEX	100/120/220/230/240 VAC 50/60 Hz.	JMT 45	-	BOBBIN
290LX	120/240 VAC 50/60 Hz.	General	-	BOBBIN
290QX	120/240 VAC 50/60 Hz.	JTM30	-	BOBBIN

VOX (Power Transformers)

Part No.	Primary	VOX Model Names	Equivalent To VOX Part No.	Bobbin/Paper Wound
290PX	120/240 VAC 50/60 Hz.	AC15	-	BOBBIN
290CZ	120 VAC 60 Hz.	AC15C1	-	BOBBIN
290CEZ	120/240 VAC 50/60 Hz.	AC15C1	-	BOBBIN
290NX	100/120/220/230/240 VAC 50/60 Hz.	AC30 60's Vintage Vertical	-	PAPER
290MX	120/240 VAC 50/60 Hz.	AC30 60's Vintage Flat	-	BOBBIN
290MAX	120/240 VAC 50/60 HZ.	TB35C2 TONY BRUNO	-	BOBBIN

Yorkville/ Traynor (Power Transformers)

Part No.	Old Part No.	Traynor Amp	Yorkville / Traynor Part No.	Primary	Secondary 1	Secondary 2	Secondary 3	Secondary 4
291TC	99145	Mono Block 2 Bass Amp	A-1305	115VAC / 60Hz.	76.5Vct @ 4.3A			
290TRA	98965	100 Watt Bass	A-1380	120VAC 60 Hz.	320V @ 600 mA	60V @ 50 mA	6.3Vct @ 9A	
290TRB	79465	YBA2-B	A-1314	120VAC 60 Hz.	620Vct @ 115 mA	6.3Vct @ 3A		
291YX	79691	YBA-3	A-1315	120V 60 Hz	800Vct @ 530 mA	6.3Vct @ 6A		
291JX	81384	BaseMaster YBA-1	A-1310	120V 60 Hz	320V @ 500 mA	60V @ 20 mA	6.65Vct @ 2.5A	-
291JEX	---	BaseMaster YBA-1	A-1310	120/240V 50/60 Hz	320V @ 500 mA	60V @ 20 mA	6.65Vct @ 2.5A	-

¹ Special order only. Please contact Hammond's sales team for more information.

AMPEG (Power Transformers)

Part No.	Primary	AMPEG Model Names	Equivalent To AMPEG Part No.	Bobbin/Paper Wound
290CAZ	117 VAC 60 Hz.	GEMINI VI 25W	PT 113	BOBBIN
290ETX	120 VAC 60 Hz.	SUPER ECHO TWIN	PT-109	BOBBIN

***DISCLAIMER:** Hammond Mfg. is not affiliated with Fender Musical Instruments Corp., Marshall Amplification, Yorkville/Traynor, AMPEG or VOX Amplification companies. Amplifier model names are trademarks of the Amplifier companies and are just listed here for reference purpose only.

Data subject to change without notice

© 2020. Hammond Manufacturing Ltd. All rights reserved.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9