

SPC56B-Discovery

SPC560B-DIS Discovery evaluation board

Data brief - production data



Features

- SPC560B54L5 32-bit 48 MHz e200z0h CPU, 32-bit Power Architecture[®] Technology CPU, 768 kB Code Flash in an LQFP144 package.
- On-board USB-JTAG PLS debugger and HW selection mode to use stand-alone JTAG debuggers.
- Board power supply: through external +12 V
 PSU or from the USB bus (5 V supply voltage).
- Seven LEDs: D6 for 5 V power on,D2 for Reset, D101, D102, D103 for PLS debugger section, D7 and D8 for PC3 and PC2 outputs
- Two push buttons (reset and user)
- A potentiometers for ADC input (user)
- Two extension headers (2 x 36 pin 100 mil) for all LQFP144 pins and for quick connection to prototyping boards, additional modules and easy probing.
- JTAG interface (2 x 7 male 100mil connector)
- USB port (mini -B)
- 16 MHz crystal
- · Specification:
 - Board size 100 x 55 mm
 - MCU: SPC560B54L5 LQFP144
 - 2 extension headers 2 x 36 pin 100 mil
 - DC connector (+12 V input)
 - Mini USB B
 - JTAG 2 x 7 100 mil connector

Description

The SPC560B-DIS Discovery is a low cost and quick way to discover SPC56 B line.

Based on SPC560B54L5, the discovery board includes a JTAG debugger from PLS, LEDs, push buttons and extension headers to connect prototyping boards or additional modules.

PLS UDE software is available for free download and includes a perpetual 256 kByte debugging/programming license.

Free ready-to-run application firmware examples are available on SPC5Studio to support quick evaluation and development.

SPC5Studio includes visual configurable code generation engine, board support package (BSP), startup routines, interrupt services, free RTOS (optional) and a full set of low level drivers. SPC5Studio includes HighTec GNU "C" compiler, with a 30-days full free trial support. SPC5Studio is available for free download.

The SPC56 B line is designed to address the specific need of car body applications but as well many other markets where high temperature operation, high reliability, low power stand-by operation with quick wake up and real-time loads diagnostic are required.

An E2E Community is available on ST WEB to get ST experts support in getting started quickly with SPC56 microcontrollers.

Table 1. Device summary

Order code	Reference
1 25C200B-1312	SPC56B-Discovery with SPC560B54L5

1 System requirements, HW and SW resources

1.1 System requirements

- Windows PC (XP, Vista, 7 or 8)
- USB type A to mini-B cable

1.2 Development toolchain

• SPC5Studio (includes Hightec GNU "C" compiler, with a 30-days full free trial support)

1.3 Demonstration software

Demonstration software is preloaded in the MCU flash memory for easy demonstration of the SPC560B54L5 in stand-alone mode. For more information and to download the latest version available, please refer to ST web.

577

SPC560B-Discovery Revision history

2 Revision history

Table 2. Revision history

Date	Revision	Changes
04-Oct-2013	1	Initial release.
19-Mar-2014	2	Updated Description.
14-Jul-2015	3	Updated value of Code Flash from 256 to 768 kB in <i>Features</i> . Updated value from 128 kByte to 256 for debugging/programming PLS UDE software in <i>Description</i> . Updated <i>Section 1: System requirements, HW and SW resources</i> .

IMPORTANT NOTICE - PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2015 STMicroelectronics - All rights reserved

ПОСТАВКА ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

многоканальный

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru_6 moschip.ru 4 moschip.ru 9