

### DEMO MANUAL DC2011A

## LT8613: 42V, 6A Micropower Synchronous Step-Down Regulator with Current Sense

#### DESCRIPTION

Demonstration Circuit 2011A is a 42V, 6A micropower synchronous step-down regulator with current sense featuring the LT®8613. The demo board is designed for 5V output from a 5.8V to 42V input. The wide input range allows a variety of input sources, such as automotive batteries and industrial supplies. The LT8613 is a compact, high efficiency, and high speed synchronous monolithic step-down switching regulator. The integrated power switches and inclusion of all necessary circuitry reduce the components count and solution size. Ultralow  $3\mu A$  quiescent current in Burst Mode® operation achieves high efficiency at very light loads. Fast minimum on-time of 40ns enables high  $V_{IN}$  to low  $V_{OUT}$  conversion at high frequency.

The LT8613 switching frequency can be programmed either via oscillator resistor or external clock over a 200kHz to 2.2MHz range. The SYNC pin on the demo board is grounded by default for low ripple Burst Mode operation. To synchronize to an external clock, move JP1 to SYNC and apply the external clock to the SYNC turret. Once JP1 is on SYNC position, a DC voltage of 3V or higher can be applied to the SYNC turret for pulse skipping operation.

The DC2011A has output current limit set at 6A by default. The current limit can be moved to the input side for

application where input supply current is limited.  $I_{CTRL}$  and  $I_{MON}$  on the board set and monitor the regulated current, respectively.

Figure 1 shows the efficiency of DC2011A circuit. Figure 2 shows the LT8613 temperature rising on DC2011A demo board under different load conditions. The rated maximum load current is 6A, while derating is necessary for certain  $V_{IN}$  and thermal conditions. The demo board has an EMI filter installed. To use the EMI filter, the input should be tied to  $V_{FMI}$  terminal, not  $V_{IN}$  terminal.

The LT8613 data sheet gives a complete description of the part, operation and application information. The data sheet must be read in conjunction with this demo manual for DC2011A. The LT8613 is assembled in a 3mm × 6mm plastic QFN package with exposed pads for low thermal resistance. Proper board layout is essential for minimum EMI and maximum thermal performance. See the data sheet section "PCB Layout" and "High Temperature Considerations".

Design files for this circuit board are available at http://www.linear.com/demo/DC2011A

T, LT, LTC, LTM, Linear Technology, the Linear logo and Burst Mode are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners

#### **PERFORMANCE SUMMARY** Specifications are at T<sub>A</sub> = 25°C

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
V <sub>IN</sub>	Input Supply Range		5.8		42	V
V <sub>OUT</sub>	Output Voltage		4.875	.875 5	5.125	V
I <sub>OUT</sub>	Maximum Output Current	Derating Is Necessary for Certain V <sub>IN</sub> and Thermal Conditions	6			А
f <sub>SW</sub>	Switching Frequency		665	700	735	kHz
EFE	Efficiency at DC	V <sub>IN</sub> = 12V , I <sub>OUT</sub> = 3A	94		%	



#### **QUICK START PROCEDURE**

Demonstration Circuit 2011A is easy to set up to evaluate the performance of the LT8613. Refer to Figure 3 for proper measurement equipment setup and follow the procedure below:

NOTE. When measuring the input or output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. Measure the input or output voltage ripple by touching the probe tip directly across the  $V_{\mbox{\scriptsize IN}}$  or  $V_{\mbox{\scriptsize OUT}}$  and GND terminals. See Figure 4 for the proper scope technique.

- 1. Place JP1 on GND position.
- 2. With power off, connect the input power supply to  $V_{\text{IN}}$  and GND.
- 3. With power off, connect the load from  $V_{OUT}$  to GND.

5. Check for the proper output voltage ( $V_{OUT} = 5V$ ). NOTE. If there is no output, temporarily disconnect the load to make sure that the load is not set too high or is shorted.

4. Turn on the power at the input.

other parameters.

6. Once the proper output voltage is established, adjust the load within the operating ranges and observe the output voltage regulation, ripple voltage, efficiency and

NOTE. Make sure that the input voltage does not exceed 42V.

7. An external clock can be added to the SYNC terminal when SYNC function is used (JP1 on the SYNC position). Please make sure that RT should be chosen to set the LT8613 switching frequency equal to or below the lowest SYNC frequency. See the data sheet section "Synchronization".




Figure 1. Efficiency vs. Load Current (Using V<sub>IN</sub> Terminal)




Figure 2. Temperature Rising vs. Input Voltage

### **QUICK START PROCEDURE**




Figure 3. Proper Measurement Equipment Setup





Figure 4. Measuring Output Ripple

# DEMO MANUAL DC2011A

## **PARTS LIST**

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER	
Required C	ircuit Comp	onents			
1	1	C2	CAP., X5R, 10µF, 50V, 10% 1210	MURATA, GRM32ER61H106KA12L	
2	2	C4, C12	CAP., X5R, 0.1µF, 50V, 10% 0402	TDK, C1005X5R1H104K	
3	1	C6	CAP., X5R, 100µF, 10V, 20% 1210	MURATA, GRM32ER61A107ME20L	
4	2	C7, C11	CAP., X7R, 1.0μF, 25V, 10% 0603	MURATA, GRM188R71E105KA12D	
5	1	C8	CAP., X7R, 0.1µF, 50V, 10% 0603	MURATA, GRM188R71H104KA93D	
6	1	C9	CAP., COG, 10pF, 50V, 5% 0603	MURATA, GRM1885C1H100JA01D	
7	1	L1	IND, 3.3µH, IHLP2525EZ-01	VISHAY, IHLP2525EZER3R3M01	
8	1	R1	RES., CHIP., 0Ω, 1/2W, 1% 1210	VISHAY, CRCW12100000Z0EA	
9	1	R5	RES., CHIP., 0.008Ω, 1/2W, 1%, 2010	VISHAY, WSL20108L000FEA	
10	2	R6, R7	RES., CHIP., 0Ω, 1/10W, 0603	VISHAY, CRCW06030000Z0EA	
11	1	R8	RES., CHIP., 60.4k,1/10W, 1%, 0603	VISHAY, CRCW060360K4FKE	
12	2	R9, R12	RES., CHIP., 100k,1/10W, 1%, 0603	VISHAY, CRCW0603100KFKEA	
13	1	R10	RES., CHIP., 1M, 1/10W, 1%, 0603	VISHAY, CRCW06031M00FKEA	
14	1	R11	RES., CHIP., 243k, 1/10W, 1%, 0603	VISHAY, CRCW0603243KFKEA	
15	1	U1	IC, REGULATOR, 28-QFN, UDE	LINEAR TECH., LT8613EUDE#PBF	
Additional I	Demo Board	l Circuit Components			
1	1	C1	CAP., ALUM 22µF 63V	SUNCON, 63CE22BS	
2	2	C3, C10	CAP., X5R, 10µF, 50V, 10% 1210	MURATA, GRM32ER61H106KA12L	
3	0	C5 (OPT)	CAP., 0603		
4	1	C15	CAP., X5R, 0.1µF, 50V, 10% 0402	TDK, C1005X5R1H104K	
5	1	FB1	FERRITE BEAD 100Ω 8A SMD 1812	WÜRTH ELEKTRONIK, 74279226101	
6	1	L2	IND., 6.8μH, IHLP3232DZ-01	VISHAY, IHLP3232DZER6R8M01	
7	0	R2, R3, R4 (0PT)	RES., 0603		
8	1	R7	RES., CHIP., 0Ω, 1/10W, 1%, 0603	VISHAY, CRCW06030000Z0EA	
Hardware/C	omponents	(For Demo Board Only)			
1	12	E1-E12	TESTPOINT, TURRET, 0.094"	MILL-MAX, 2501-2-00-80-00-00-07-0	
2	1	JP1	HEADER, 3-PIN 0.079" SINGLE ROW	SULLINS, NRPN031PAEN-RC	
3	1	XJP1	SHUNT, 0.079" CENTER	SAMTEC, 2SN-BK-G	
4	4	MH1-MH4	STAND-OFF, NYLON 0.50" TALL	KEYSTONE, 8833 (SNAP ON)	

## SCHEMATIC DIAGRAM





#### DEMO MANUAL DC2011A

#### DEMONSTRATION BOARD IMPORTANT NOTICE

Linear Technology Corporation (LTC) provides the enclosed product(s) under the following AS IS conditions:

This demonstration board (DEMO BOARD) kit being sold or provided by Linear Technology is intended for use for **ENGINEERING DEVELOPMENT OR EVALUATION PURPOSES ONLY** and is not provided by LTC for commercial use. As such, the DEMO BOARD herein may not be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including but not limited to product safety measures typically found in finished commercial goods. As a prototype, this product does not fall within the scope of the European Union directive on electromagnetic compatibility and therefore may or may not meet the technical requirements of the directive, or other regulations.

If this evaluation kit does not meet the specifications recited in the DEMO BOARD manual the kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY THE SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THIS INDEMNITY, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user releases LTC from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge. Also be aware that the products herein may not be regulatory compliant or agency certified (FCC, UL, CE, etc.).

No License is granted under any patent right or other intellectual property whatsoever. LTC assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or any other intellectual property rights of any kind.

LTC currently services a variety of customers for products around the world, and therefore this transaction is not exclusive.

Please read the DEMO BOARD manual prior to handling the product. Persons handling this product must have electronics training and observe good laboratory practice standards. Common sense is encouraged.

This notice contains important safety information about temperatures and voltages. For further safety concerns, please contact a LTC application engineer.

Mailing Address:

Linear Technology 1630 McCarthy Blvd. Milpitas, CA 95035

Copyright © 2004, Linear Technology Corporation



#### **ПОСТАВКА** ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

многоканальный

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

### Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

#### http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

#### Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru\_6 moschip.ru 4 moschip.ru 9