

Low Noise Amplifier DC - 28 GHz

Rev. V3

Features

- Ultra Wideband Performance
- Noise Figure: 1.4 dB @ 8 GHz
- High Gain: 17 dB @ 8 GHz
- Output IP3: 28 dBm @ 8 GHz
- Bias Voltage: V_{DD} = 5 6 V
- Bias Current: I_{DSQ} = 60 100 mA
- 50 Ω Matched Input / Output
- · Positive Voltage Only
- Die Size: 2.99 x 1.5 x 0.1 mm
- RoHS* Compliant

Description

The MAAL-011141-DIE is an easy to use, wideband low noise distributed amplifier die. It operates from DC to 28 GHz and provides 17 dB of linear gain, 16 dBm of P1dB and 1.4 dB of noise figure at 8 GHz. The input and output are fully matched to 50 Ω with typical return loss >15 dB.

This amplifier employs an active termination circuit to achieve a lower noise figure at the lower end of the frequency range than is possible using traditional resistive termination techniques.


This product is fabricated using a GaAs pHEMT process which features full passivation for enhanced reliability.

The MAAL-011141-DIE can be used as a low noise amplifier stage or as a driver stage in higher power applications. This device is ideally suited for Test and Measurement, EW, ECM, and Radar applications.

Ordering Information

Part Number	Package
MAAL-011141-DIE	gel pack
MAAL-011141-DIESMB	wafer evaluation module

Functional Schematic¹



1. Image not to scale.

Pin Configuration²

Pin#	Pin Name	Description
1	RF _{IN}	RF Input
2	RF _{OUT} / V _{DD}	RF Output / Drain Voltage
3	V _G	Gate Voltage
4	V _{AT}	Active Termination Voltage
5	AUX1	Auxiliary Drain Voltage 1
6	AUX2	Auxiliary Drain Voltage 2
7-13	GND	DC + RF Ground to Backside Via

2. Backside of die must be connected to RF, DC and thermal ground.

^{*} Restrictions on Hazardous Substances, compliant to current RoHS EU directive.



Low Noise Amplifier DC - 28 GHz

Rev. V3

Electrical Specifications: T_A = +25°C, V_{DD} = 6 V, I_{DSQ} = 75 mA, V_{AT} = 5 V, Z_0 = 50 Ω

Parameter	Test Conditions	Units	Min.	Тур.	Max.
Gain	P _{IN} = -20 dBm 2.0 GHz 8.0 GHz 12.0 GHz 18.0 GHz 26.5 GHz	dB	16.5 — 15.0 —	18.5 17.0 17.0 17.0 17.0	_
Output P1dB	2.0 GHz 8.0 GHz 12.0 GHz 18.0 GHz 26.5 GHz	dBm	_	17.0 16.0 16.0 15.0 12.5	
OIP3	P _{IN} = -20 dBm / tone, 10 MHz Tone Spacing 2.0 GHz 8.0 GHz 12.0 GHz 18.0 GHz 26.5 GHz	dBm	_	29.5 28.0 26.5 26.0 22.5	_
Input Return Loss	P _{IN} = -20 dBm	dB	_	15	_
Output Return Loss	P _{IN} = -20 dBm	dB	_	15	_
Noise Figure	2.0 GHz 8.0 GHz 12.0 GHz 18.0 GHz 26.5 GHz	dB	_	2.5 1.4 1.6 2.4 4.0	3.0 — 2.2 —
Isolation	P _{IN} = -20 dBm 2.0 GHz 8.0 GHz 12.0 GHz 18.0 GHz 26.5 GHz	dB	_	60 40 37 33 32	_
V _G	Adjusted to set I _{DSQ} = 75 mA	V	_	0.7	_
I _{AT}	V _{AT} = 5 V	mA	_	10	_



Low Noise Amplifier DC - 28 GHz

Rev. V3

Operating Conditions

Recommended biasing conditions are V_{DD} = 6 V, I_{DSQ} = 75 mA. Bias of 5 V must be applied to V_{AT} pin. I_{DSQ} is set by adjusting V_{G} after setting V_{DD} and V_{AT} . The drain bias voltage range, V_{DD} , is 5 to 6 V, and the quiescent drain current biasing is 60 to 100 mA. To maintain the best performance MACOM recommends using an active bias circuit for constant I_{DD} .

There are three possible bias methods:

- 1. The use of an external bias tee where the required V_{DD} is applied at RFout/VDD and V_{G} is set to provide a current bias (I_{DSQ}) of 60 to 100 mA. This provides wide band performance of DC 28 GHz (depending on the bandwidth of the bias tee).
- 2. The direct application of V_{DD} to AUX1. Using this method provides for an operational frequency of 2 28 GHz. However, a voltage drop across an internal 17 Ω resistance must be accounted for. For example, with I_{DSQ} = 75 mA, 7.3 V must be applied at AUX1 for a V_{DD} of 6 V.
- 3. The direct application of V_{DD} to AUX2. Using this method provides for an operational frequency of DC 28 GHz. However, a voltage drop across series 17 Ω and 32 Ω resistors must be accounted for. For example, with I_{DSQ} = 75 mA, 9.67 V must be applied at AUX2 for a V_{DD} of 6 V.

In all cases DC blocking is required on the RF input. Additionally options 2 or 3 require DC blocking on the RF output line. It should also be noted that when using the internal bias circuit (option 2 or 3) $I_{\rm DSQ}$ is limited to a maximum of 80 mA.

Regardless of bias method used, 2 bypass capacitors of 100 pF and 0.1 μ F should be connected to AUX2. This provides for increased device stability margins and improved gain flatness below 2 GHz when required. The 100 pF cap is a single layer chip capacitor and should be positioned as close to the device as possible. The 0.1 μ F SMT cap can be placed further away on the PCB.

The available evaluation board is configured for bias option 3 using AUX2 for the supply of V_{DD} .

Maximum Operating Conditions

Parameter	Operating Maximum	
Input Power ³	P _{IN} ≤1 dB compression level	
Junction Temperature ⁴	+150°C	
Operating Temperature	-40°C to +85°C	

- MACOM does not recommend sustained operation at power levels above 1 dB gain compression.
- Operating at nominal conditions with junction temperature ≤ +150°C will ensure MTTF > 1 x 10⁶ hours.

Absolute Maximum Ratings^{5,6}

Parameter	Absolute Maximum	
Input Power	18 dBm	
Drain Voltage	7 V	
Gate Voltage	0.9 V	
Active Termination Voltage	6 V	
AUX1 Current	80 mA	
AUX2 Current	80 mA	
Junction Temperature ⁷	+175°C	
Storage Temperature	-65°C to +125°C	

- Exceeding any one or combination of these limits may cause permanent damage to this device.
- MACOM does not recommend sustained operation near these survivability limits.
- 7. Junction temperature directly effects device MTTF, and should be kept as low as possible to maximize product lifetime.

Handling Procedures

Please observe the following precautions to avoid damage:

Static Sensitivity


These electronic devices are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these HBM Class 1A devices.



Low Noise Amplifier DC - 28 GHz

Rev. V3

Application Schematic






Low Noise Amplifier DC - 28 GHz

Rev. V3

Applications Section: Sample Board Layout



Parts List

Part	Value	Case Style
C1 - C3	0.1 μF	0402
C4 - C6	100 pF	Single Layer

Evaluation PCB Specifications

Top Layer: 1/2 oz Copper Cladding, 0.017 mm thickness Dielectric Layer: Rogers RO4350B 0.101 mm thickness Bottom Layer: 1/2 oz Copper Cladding, 0.017 mm thickness Finished overall thickness: 0.135 mm




Low Noise Amplifier DC - 28 GHz

Rev. V3

Recommended Bonding Diagram & PCB Layout

RF input and output port matching circuit patterns are designed to compensate for bonding wires. Input and output matching are identical.



Evaluation PCB Specifications


Top Layer: 1/2 oz Copper Cladding, 0.017 mm thickness Dielectric Layer: Rogers RO4350B 0.101 mm thickness Bottom Layer: 1/2 oz Copper Cladding, 0.017 mm thickness Finished overall thickness: 0.135 mm




Low Noise Amplifier DC - 28 GHz


Rev. V3

Typical Performance Curves: V_{DD} = 6 V, I_{DSQ} = 75 mA, V_{AT} = 5 V







Input Return loss




Output Return Loss



Low Frequency S-Parameters



Reverse Isolation



7

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Visit www.macom.com for additional data sheets and product information.




Low Noise Amplifier DC - 28 GHz


Rev. V3

Typical Performance Curves: V_{DD} = 6 V, I_{DSQ} = 75 mA, V_{AT} = 5 V

Output P1dB



Output IP3 (10 MHz tone spacing)






Low Noise Amplifier DC - 28 GHz

Rev. V3

MMIC Die Outline



Bond Pad Detail^{8,9}

Pin#	Size (x)	Size (y)
1 - 2	70	140
9 -12	70	90
3 - 8, 13	70	70

All dimensions shown as microns (μm) with a tolerance of +/-5 μm, unless otherwise noted.

^{9.} Die thickness is 100 μ m +/- 10 μ m.



Low Noise Amplifier DC - 28 GHz

Rev. V3

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

ПОСТАВКА ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

многоканальный

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru_6 moschip.ru_4 moschip.ru_9