

## **Product Specification**

## 32GFC RoHS Compliant Short Wavelength SFP+ Transceiver FTLF8532P4BNV

## PRODUCT FEATURES

- Up to 28.05 Gb/s bi-directional data links
- Hot-pluggable SFP+ footprint
- Built-in digital diagnostic functions
- 850nm Oxide VCSEL laser transmitter
- Duplex LC connector
- RoHS compliant
- 100m over M5F MMF (50/125 um OM4)
- 70m over M5E MMF (50/125um OM3)
- 20m on 50µm (OM2) MMF
- Metal enclosure, for lower EMI
- Single 3.3V power supply
- Operating temperature range:

0°C to 85°C



#### **APPLICATIONS**

■ Tri-Rate 8.5/14.025/28.05 Gb/s Fibre Channel

Finisar's FTLF8532P4BNV SFP+ transceivers are designed for use in Fibre Channel links up to 28.05 Gb/s data rate over multimode fiber. They are compliant with FC-PI-6<sup>a</sup>, SFF-8472 Rev 12.2<sup>c</sup>, and compatible with SFF-8432<sup>b</sup> and applicable portions of SFF-8431 Rev. 4.1<sup>d</sup>. The transceiver is RoHS compliant and per Directive 2011/65/EU<sup>e</sup>. See Finisar Application Note AN-2038 for more details.

## PRODUCT SELECTION

## FTLF8532P4BNV



## I. Pin Descriptions

Pin	Symbol	Name/Description	Ref.
1	$V_{\mathrm{EET}}$	Transmitter Ground (Common with Receiver Ground)	1
2	$T_{FAULT}$	Transmitter Fault.	2
3	$T_{ m DIS}$	Transmitter Disable. Laser output disabled on high or open.	3
4	SDA	2-wire Serial Interface Data Line (MOD-DEF2)	4
5	SCA	2-wire Serial Interface Clock (MOD-DEF1)	4
6	MOD_ABS	Module Absent, connected to $V_{\text{EET}}$ or $V_{\text{EER}}$	4
7	RS0	Rx Rate Select:	5
		Open or Low = 8.5 or 14.025 Gb/s Fibre Channel (Low Bandwidth)	
		High = 28.05 Gb/s Fibre Channel (High Bandwidth)	
8	LOS	Loss of Signal indication. Logic 0 indicates normal operation.	6
9	RS1	Tx Rate Select:	5
		Open or Low = 8.5 or 14.025 Gb/s Fibre Channel (Low Bandwidth)	
		High = 28.05 Gb/s Fibre Channel (High Bandwidth)	
10	$V_{\rm EER}$	Receiver Ground (Common with Transmitter Ground)	1
11	$V_{\rm EER}$	Receiver Ground (Common with Transmitter Ground)	1
12	RD-	Receiver Inverted DATA out. AC Coupled	
13	RD+	Receiver Non-inverted DATA out. AC Coupled	
14	$ m V_{EER}$	Receiver Ground (Common with Transmitter Ground)	1
15	$V_{CCR}$	Receiver Power Supply	
16	$V_{CCT}$	Transmitter Power Supply	
17	$V_{\mathrm{EET}}$	Transmitter Ground (Common with Receiver Ground)	1
18	TD+	Transmitter Non-Inverted DATA in. AC Coupled.	
19	TD-	Transmitter Inverted DATA in. AC Coupled.	
20	$V_{\mathrm{EET}}$	Transmitter Ground (Common with Receiver Ground)	1

- 1. Circuit ground is internally isolated from chassis ground.
- 2.  $T_{FAULT}$  is an open collector/drain output, which should be pulled up with a 4.7k-10k Ohms resistor on the host board if intended for use. Pull up voltage should be between 2.0V to Vcc+0.3V. A high output indicates a transmitter fault caused by either the TX bias current or the TX output power exceeding the preset alarm thresholds. A low output indicates normal operation. In the low state, the output is pulled to <0.8V.
- 3. Laser output disabled on  $T_{DIS} > 2.0V$  or open, enabled on  $T_{DIS} < 0.8V$ .
- 4. Should be pulled up with 4.7k 10kohms on host board to a voltage between 2.0V and 3.6V. MOD\_ABS pulls line low to indicate module is plugged in.
- 5. Rate select can also be set through the 2-wire bus in accordance with SFF-8472 v. 12.1°. Rx Rate Select is set at Bit 3, Byte 110, Address A2h. Tx Rate Select is set at Bit 3, Byte 118, Address A2h. Note: writing a "1" selects maximum bandwidth operation. Rate select is the logic OR of the input state of Rate Select Pin and 2-wire bus.
- 6. LOS is open collector output. Should be pulled up with 4.7k 10kohms on host board to a voltage between 2.0V and 3.6V. Logic 0 indicates normal operation; logic 1 indicates loss of signal.






Diagram of Host Board Connector Block Pin Numbers and Names



## II. Absolute Maximum Ratings

Parameter	Symbol	Min	Typ	Max	Unit	Ref.
Maximum Supply Voltage	Vcc	-0.5		4.0	V	
Storage Temperature	$T_{S}$	-40		85	°C	
Case Operating Temperature	$T_{\rm C}$	0		85	°C	
Relative Humidity (Non-condensing)	RH	0		85	%	1

#### Notes:

1. Non Condensing

## III. Electrical Characteristics ( $T_A$ , $V_{CC} = 3.15$ to 3.46 Volts)

Parameter	Symbol	Min	Тур	Max	Unit	Ref.
Supply Voltage	Vcc	3.15		3.46	V	
Supply Current	Icc			290	mA	1
Transmitter						
Input differential impedance	Rin		100		Ω	2
Differential data input eye height	Vin,pp				mV	2
28.05Gb/s		50		900		
14.025Gb/s & 8.5Gb/s		180		700		
Transmit Disable Voltage	$V_{\mathrm{D}}$	2		Vcc	V	3
Transmit Enable Voltage	$V_{\mathrm{EN}}$	Vee		Vee+0.8	V	
Receiver						
Single ended data output swing	Vout,pp	185		425	mV	4
LOS Fault	V <sub>LOS</sub> fault	2		Vcchost	V	5
LOS Normal	V <sub>LOS norm</sub>	Vee		Vee+0.8	V	5
Power Supply Rejection	PSR	100			mVpp	6

- 1. With established link. The total power dissipation could exceed 1W when the module is trying to establish link at operating case temperature below  $25^{\circ}\mathrm{C}$
- 2. Connected directly to TX data input pins. AC coupling from pins into CDR, Inner eye height (EH6) for high loss case, BER contour 10<sup>-6</sup>, per FC-PI 6 and FC-MSQS-2.
- 3. Or open circuit.
- 4. Into 100 ohms differential termination.
- 5. LOS is an open collector output. Should be pulled up with 4.7k 10kohms on the host board. Normal operation is logic 0; loss of signal is logic 1. Maximum pull-up voltage is 5.5V.
- 6. Receiver sensitivity is compliant with power supply sinusoidal modulation of 20 Hz to 1.5 MHz up to specified value applied through the recommended power supply filtering network.



## IV. Optical Characteristics ( $T_A$ , $V_{CC} = 3.15$ to 3.46 Volts)

Parameter	Symbol	Min	Тур	Max	Unit	Ref.
Transmitter						
Average Output Power: 50 or 62.5 MMF	P <sub>OUT</sub>				dBm	1
8.5Gb/s		-8.2				
14.025Gb/s		-7.8				
28.05Gb/s		-6.7				
Optical Wavelength	λ	840		860	nm	
Spectral Width (RMS), 28.05Gb/s	σ			0.57	nm	
Optical Modulation Amplitude	OMA				μW(dBm)	
8.5 Gb/s		302 (-5.2)				
14.025Gb/s		331 (-4.8)				
28.05Gb/s		479 (-3.2)				
Transmitter Waveform and Dispersion Penalty, 8.5	TWDP			4.3	dB	2
Gb/s						
Vertical Eye Closure Penalty	CEVPQ			2.5.	dB	
14.025 Gb/s				2.56		3,4
28.05 Gb/s Relative Intensity Noise	RIN			3.13	dB/Hz	
28.05Gb/s	KIIN			-129	UD/ FIZ	
14.025Gb/s & 8.5Gb/s				-129		
Receiver				-120		
Unstressed Receiver OMA Sensitivity	RxSENS	I	1		μW(dBm)	5,6
8.5 Gb/s	KASLINS			76(-11.2)	μν(αΒιιι)	3,0
14.025Gb/s				89(-10.5)		
28.05Gb/s				95(-10.2)		
Average Receiver Power	Rx <sub>MAX</sub>			2	dBm	
Optical Center Wavelength	$\lambda_{\mathrm{C}}$	770		860	nm	
Optical Return Loss		12			dB	
LOS De-Assert	LOS <sub>D</sub>			-13	dBm	
LOS Assert	LOSA	-30			dBm	
LOS Hysteresis		0.5			dB	

- 1. Class 1 Laser Safety limit per FDA/CDRH, and EN (IEC) 60825 laser safety standards.
- 2. TWDP is calculated with a 1,0 equalizer and a 9.84 GHz Gaussian filter for the fiber simulation. Jitter values at  $\gamma_T$  and  $\gamma_R$  are controlled by TWDP and stress receiver sensitivity.
- 3. For 16GFC, VECPQ is calculated with a 16.6 GHz Gaussian filter for fiber simulation
- 4. For 32GC, VECPQ is calculated with a 24.7GHz Gaussian filter for fiber simulation
- 5. Unstressed Rx sensitivity
- 6. For 32GFC with FEC, receiver sensitivity is defined at  $10^{-6}$  BER level, not  $10^{-12}$  BER level.



## **IV.** General Specifications

Parameter	Symbol	Min	Тур	Max	Units	Ref.
Data Rate	BR		8.5		Gb/sec	1
			14.025			
			28.05			
Bit Error Rate	BER			10 <sup>-12</sup>		2
				10 <sup>-6</sup>		3
Fiber Length on 50/125µm	L			50	m	4
(OM2/M5) MMF				35		5
				20		6
Fiber Length on 50/125µm high-	L			150	m	4
bandwidth (OM3/M5E) MMF				100		5
·				70		6
Fiber Length on 50/125µm high-	L			190	m	4
bandwidth (OM4/M5F) MMF				125		5
·				100		6

#### Notes:

- 1. 8x Fibre Channel compatible, per FC-PI-4<sup>1</sup>.
- 2. PRBS 2<sup>7</sup>-1 for 8GFC. PRBS 2<sup>31</sup>-1 for 16GFC
- 3. FEC for 32GFC
- 4. At 8.5 Gb/s Fibre Channel data rate.
- 5. At 14.025 Gb/s Fibre Channel data rate.
- 6. At 28.05Gb/s Fibre Channel data rate

## VI. Environmental Specifications

Parameter	Symbol	Min	Тур	Max	Units	Ref.
Case Operating Temperature	$T_{op}$	0		70	°C	
Storage Temperature	$T_{sto}$	-40		85	°C	

## VII. Regulatory Compliance

Finisar transceivers are Class 1 Laser Products and comply with US FDA regulations. These products are certified by TÜV and CSA to meet the Class 1 eye safety requirements of EN (IEC) 60825 and the electrical safety requirements of EN (IEC) 60950. Copies of certificates are available at Finisar Corporation upon request.

.



## VIII. Digital Diagnostic Functions

Finisar FTLF8532P4BNV SFP+ transceivers support the 2-wire serial communication protocol as defined in the SFP MSA<sup>f</sup>. It is very closely related to the E<sup>2</sup>PROM defined in the GBIC standard, with the same electrical specifications.

The standard SFP serial ID provides access to identification information that describes the transceiver's capabilities, standard interfaces, manufacturer, and other information.

Additionally, Finisar SFP transceivers provide a enhanced digital diagnostic monitoring interface, which allows real-time access to device operating parameters such as transceiver temperature, laser bias current, transmitted optical power, received optical power and transceiver supply voltage. It also defines a sophisticated system of alarm and warning flags, which alerts end-users when particular operating parameters are outside of a factory set normal range.

The SFP MSA defines a 256-byte memory map in E<sup>2</sup>PROM that is accessible over a 2-wire serial interface at the 8 bit address 1010000X (A0h). The digital diagnostic monitoring interface makes use of the 8 bit address 1010001X (A2h), so the originally defined serial ID memory map remains unchanged. The interface is identical to, and is thus fully backward compatible with both the GBIC Specification and the SFP Multi Source Agreement. The complete interface is described in Finisar Application Note AN-2030: "Digital Diagnostics Monitoring Interface for SFP Optical Transceivers".

The operating and diagnostics information is monitored and reported by a Digital Diagnostics Transceiver Controller (DDTC) inside the transceiver, which is accessed through a 2-wire serial interface. When the serial protocol is activated, the serial clock signal (SCL, Mod Def 1) is generated by the host. The positive edge clocks data into the SFP transceiver into those segments of the E<sup>2</sup>PROM that are not write-protected. The negative edge clocks data from the SFP transceiver. The serial data signal (SDA, Mod Def 2) is bi-directional for serial data transfer. The host uses SDA in conjunction with SCL to mark the start and end of serial protocol activation. The memories are organized as a series of 8-bit data words that can be addressed individually or sequentially.

For more information, please see the SFP MSA documentation<sup>c,f</sup> and Finisar Application Note AN-2030.



## IX. Digital Diagnostic Specifications

FTLF8532P4BNV transceivers can be used in host systems that require either internally or externally calibrated digital diagnostics.


Parameter	Symbol	Units	Min	Max	Accuracy	Ref.
Transceiver temperature	D <sub>DDTemp</sub>	$^{\circ}\mathrm{C}$	0	+70	±5°C	
Transceiver supply voltage	DDDVoltage	V	3.14	3.45	±3%	
Transmitter bias current	D <sub>DDBias</sub>	mA	0	50	±10%	1
Transmitter output power	DDDTx-Power	dBm	-9	+2	±3dB	
Receiver average optical input power	D <sub>DDRx-Power</sub>	dBm	-12	2	±3dB	

<sup>1.</sup> Accuracy of Measured Tx Bias Current is 10% of the actual Bias Current from the laser driver to the laser.



## X. Mechanical Specifications

Finisar's FTLF8532P4BNV SFP+ transceivers are compatible with the SFF-8432<sup>b</sup> specification for improved pluggable form factor.



FTLF8532P4BNV




## XI. PCB Layout and Bezel Recommendations


<u>Ma</u>tum and Basic Dimension Established by Customer


<u>A</u>Rads and Vias are Chassis Ground, 11 Places

<u>A</u>Through Holes are Unplated









#### NOTES:

⚠ MINIMUM PITCH ILLUSTRATED, ENGLISH DIMENSIONS ARE FOR REFERENCE ONLY

2. NOT RECOMMENDED FOR PCI EXPANSION CARD APPLICATIONS



## XII. References

- a. "Fibre Channel Physical Interfaces -5, INCITS 479-2011 (Defines 8GFC and 16GFC)
   Fibre Channel Physical Interfaces -6, INCITS 512-2014 (Defines 32GFC)"
- b. "Improved Pluggable Form Factor", SFF Document Number SFF-8432, Revision 5.0, July 16, 2007.
- c. "Digital Monitoring Interface for Optical Transceivers", SFF Document Number SFF-8472, Revision 12.2.
- d. "Enhanced Small Form Factor Pluggable Module 'SFP+ '", SFF Document Number SFF-8431, Revision 4.1, July 6, 2009; Addendum Jun 21, 2013.
- e. Directive 2011/65/EU of the European Council Parliament and of the Council, "on the restriction of the use of certain hazardous substances in electrical and electronic equipment". 08-June 2011, which supercedes the previous ROHS Directive 2002/95/EC.
- f. Small Form Factor Pluggable (SFP) Transceiver Multi-source Agreement (MSA), September 14, 2000 which is available as SFF Document Number INF-8074, Revision 1.0 May 12, 2001
- g. "0.8mm Card Edge Connector for 16Gb/s Applications", SFF Document Number SFF-8081, Revision 0.2, December 21, 2009.
- h. SFF-8402, Revision 0.2

## **XIII.** For More Information

Finisar Corporation 1308 Moffett Park Drive Sunnyvale, CA 94089-1133 Tel. 1-408-548-1000 Fax 1-408-541-6138 sales@finisar.com www.finisar.com

## **ПОСТАВКА** ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

# Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

## http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

## Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru\_6 moschip.ru\_4 moschip.ru\_9