MIC5219

500mA-Peak Output LDO Regulator

General Description

The MIC5219 is an efficient linear voltage regulator with high peak output current capability, very low dropout voltage, and better than 1% output voltage accuracy. Dropout is typically 10mV at light loads and less than 500mV at full load.

The MIC5219 is designed to provide a peak output current for startup conditions where higher inrush current is demanded. It features a 500mA peak output rating. Continuous output current is limited only by package and layout.

The MIC5219 can be enabled or shut down by a CMOS or TTL compatible signal. When disabled, power consumption drops nearly to zero. Dropout ground current is minimized to help prolong battery life. Other key features include reversed-battery protection, current limiting, overtemperature shutdown, and low noise performance with an ultra-low-noise option.

The MIC5219 is available in adjustable or fixed output voltages in space-saving SOT-23-5 and MM8™ 8-lead power MSOP packages. For higher power requirements see the MIC5209 or MIC5237.


Features

- 500mA Output current capability
  - **SOT-23-5 package - 500mA peak**
  - **MSOP-8 package - 500mA continuous**
- Low 500mV maximum dropout voltage at full load
- Extremely tight load and line regulation
- Tiny SOT-23-5 and MM8™ power MSOP-8 package
- Ultra-low-noise output
- Low temperature coefficient
- Current and thermal limiting
- Reversed-battery protection
- CMOS/TTL-compatible enable/shutdown control
- Near-zero shutdown current


Applications

- Laptop, notebook, and palmtop computers
- Cellular telephones and battery-powered equipment
- Consumer and personal electronics
- PC Card V_{CC} and V_{PP} regulation and switching
- SMPS post-regulator/dc-to-dc modules
- High-efficiency linear power supplies

Typical Applications



5V Ultra-Low-Noise Regulator




3.3V Ultra-Low-Noise Regulator

Ordering Information


Part Number	Marking	Volts	Junction Temp. Range	Package
MIC5219-3.0BMM	—	3.0V	–40°C to +125°C	MSOP-8
MIC5219-3.3BMM	—	3.3V	–40°C to +125°C	MSOP-8
MIC5219-3.6BMM	—	3.6V	–40°C to +125°C	MSOP-8
MIC5219-5.0BMM	—	5.0V	–40°C to +125°C	MSOP-8
MIC5219BMM	—	Adj.	–40°C to +125°C	MSOP-8
MIC5219-2.5BM5	LG25	2.5V	–40°C to +125°C	SOT-23-5
MIC5219-2.6BM5	LG26	2.6V	–40°C to +125°C	SOT-23-5
MIC5219-2.7BM5	LG27	2.7V	–40°C to +125°C	SOT-23-5
MIC5219-2.8BM5	LG28	2.8V	–40°C to +125°C	SOT-23-5
MIC5219-2.9BM5	LG29	2.9V	–40°C to +125°C	SOT-23-5
MIC5219-3.0BM5	LG30	3.0V	–40°C to +125°C	SOT-23-5
MIC5219-3.1BM5	LG31	3.1V	–40°C to +125°C	SOT-23-5
MIC5219-3.3BM5	LG33	3.3V	–40°C to +125°C	SOT-23-5
MIC5219-3.6BM5	LG36	3.6V	–40°C to +125°C	SOT-23-5
MIC5219-5.0BM5	LG50	5.0V	–40°C to +125°C	SOT-23-5
MIC5219BM5	LGAA	Adj.	–40°C to +125°C	SOT-23-5

Other voltages available. Consult Micrel for details.


Pin Configuration




MIC5219-x.xBMM
MM8™ MSOP-8
Fixed Voltages



MIC5219-x.xBM5
SOT-23-5
Fixed Voltages



MIC5219BMM
MM8™ MSOP-8
Adjustable Voltage



MIC5219BM5
SOT-23-5
Adjustable Voltage

Pin Description

Pin No. MSOP-8	Pin No. SOT-23-5	Pin Name	Pin Function
2	1	IN	Supply Input
5–8	2	GND	Ground: MSOP-8 pins 5 through 8 are internally connected.
3	5	OUT	Regulator Output
1	3	EN	Enable (Input): CMOS compatible control input. Logic high = enable; logic low or open = shutdown.
4 (fixed)	4 (fixed)	BYP	Reference Bypass: Connect external 470pF capacitor to GND to reduce output noise. May be left open.
4 (adj.)	4 (adj.)	ADJ	Adjust (Input): Feedback input. Connect to resistive voltage-divider network.

Absolute Maximum Ratings

Supply Input Voltage (V_{IN}) ..... –20V to +20V
Power Dissipation (P_D) ..... Internally Limited
Junction Temperature (T_J) ..... –40°C to +125°C
Lead Temperature (Soldering, 5 sec.) ..... 260°C

Operating Ratings

Supply Input Voltage (V_{IN}) ..... +2.5V to +12V
Enable Input Voltage (V_{EN}) ..... 0V to V_{IN}
Junction Temperature (T_J) ..... –40°C to +125°C
Package Thermal Resistance ..... see Table 1

Electrical Characteristics

$V_{IN} = V_{OUT} + 1.0V$; $C_{OUT} = 4.7\mu F$, $I_{OUT} = 100\mu A$; $T_J = 25°C$, **bold** values indicate $–40°C \le T_J \le +125°C$; unless noted.

Symbol	Parameter	Conditions	Min	Typical	Max	Units
V_{OUT}	Output Voltage Accuracy	variation from nominal V_{OUT}	–1 **–2**		1 **2**	% **%**
$\Delta V_{OUT}/\Delta T$	Output Voltage Temperature Coefficient	**Note 2**		**40**		ppm/°C
$\Delta V_{OUT}/V_{OUT}$	Line Regulation	$V_{IN} = V_{OUT} + 1V$ to 12V		0.009	0.05 **0.1**	%/V
$\Delta V_{OUT}/V_{OUT}$	Load Regulation	I_{OUT} = 100µA to 500mA **Note 3**		0.05	0.5 **0.7**	%
$V_{IN} – V_{OUT}$	Dropout Voltage, **Note 4**	I_{OUT} = 100µA		10	60 **80**	mV
		I_{OUT} = 50mA		115	175 **250**	mV
		I_{OUT} = 150mA		175	300 **400**	mV
		I_{OUT} = 500mA		350	500 **600**	mV
I_{GND}	Ground Pin Current, **Notes 5, 6**	$V_{EN} \ge 3.0V$, I_{OUT} = 100µA		80	130 **170**	µA
		$V_{EN} \ge 3.0V$, I_{OUT} = 50mA		350	650 **900**	µA
		$V_{EN} \ge 3.0V$, I_{OUT} = 150mA		1.8	2.5 **3.0**	mA
		$V_{EN} \ge 3.0V$, I_{OUT} = 500mA		12	20 **25**	mA
	Ground Pin Quiescent Current, **Note 6**	$V_{EN} \le 0.4V$		0.05	**3**	µA
		$V_{EN} \le 0.18V$		0.10	**8**	µA
PSRR	Ripple Rejection	f = 120Hz		75		dB
I_{LIMIT}	Current Limit	V_{OUT} = 0V		700	**1000**	mA
$\Delta V_{OUT}/\Delta P_D$	Thermal Regulation	**Note 7**		0.05		%/W
e_{no}	Output Noise	I_{OUT} = 50mA, C_{OUT} = 2.2µF, C_{BYP} = 0		500		nV/√Hz
		I_{OUT} = 50mA, C_{OUT} = 2.2µF, C_{BYP} = 470pF		300		nV/√Hz
ENABLE Input						
V_{ENL}	Enable Input Logic-Low Voltage	V_{EN} = logic low (regulator shutdown)			0.4 **0.18**	V
		V_{EN} = logic high (regulator enabled)	2.0			V
I_{ENL}	Enable Input Current	$V_{ENL} \le 0.4V$		0.01	–1	µA
		$V_{ENL} \le 0.18V$		**0.01**	**–2**	µA
I_{ENH}		$V_{ENH} \ge 2.0V$	2	5	20 **25**	µA

Note 1: Absolute maximum ratings indicate limits beyond which damage to the component may occur. Electrical specifications do not apply when operating the device outside of its operating ratings. The maximum allowable power dissipation is a function of the maximum junction temperature, $T_{J(max)}$, the junction-to-ambient thermal resistance, θ_{JA}, and the ambient temperature, T_A. The maximum allowable power dissipation at any ambient temperature is calculated using: $P_{D(max)} = (T_{J(max)} - T_A) \div \theta_{JA}$. Exceeding the maximum allowable power dissipation will result in excessive die temperature, and the regulator will go into thermal shutdown. See Table 1 and the "Thermal Considerations" section for details.

Note 2: Output voltage temperature coefficient is defined as the worst case voltage change divided by the total temperature range.

Note 3: Regulation is measured at constant junction temperature using low duty cycle pulse testing. Parts are tested for load regulation in the load range from 100µA to 500mA. Changes in output voltage due to heating effects are covered by the thermal regulation specification.

Note 4: Dropout voltage is defined as the input to output differential at which the output voltage drops 2% below its nominal value measured at 1V differential.

Note 5: Ground pin current is the regulator quiescent current plus pass transistor base current. The total current drawn from the supply is the sum of the load current plus the ground pin current.


Note 6: V_{EN} is the voltage externally applied to devices with the EN (enable) input pin.

Note 7: Thermal regulation is defined as the change in output voltage at a time "t" after a change in power dissipation is applied, excluding load or line regulation effects. Specifications are for a 500mA load pulse at V_{IN} = 12V for t = 10ms.


Note 8: C_{BYP} is an optional, external bypass capacitor connected to devices with a BYP (bypass) or ADJ (adjust) pin.

Typical Characteristics


Power Supply Rejection Ratio




Power Supply Rejection Ratio




Power Supply Rejection Ratio




Power Supply Rejection Ratio




Power Supply Rejection Ratio




Power Supply Rejection Ratio




Power Supply Ripple Rejection vs. Voltage Drop




Power Supply Ripple Rejection vs. Voltage Drop




Noise Performance




Noise Performance




Noise Performance




Dropout Voltage vs. Output Current




Dropout Characteristics




Ground Current vs. Output Current




Ground Current vs. Supply Voltage




Ground Current vs. Supply Voltage



Block Diagrams



Ultra-Low-Noise Fixed Regulator



Ultra-Low-Noise Adjustable Regulator

Applications Information

The MIC5219 is designed for 150mA to 200mA output current applications where a high current spike (500mA) is needed for short, startup conditions. Basic application of the device will be discussed initially followed by a more detailed discussion of higher current applications.

Enable/Shutdown

Forcing EN (enable/shutdown) high (> 2V) enables the regulator. EN is compatible with CMOS logic. If the enable/shutdown feature is not required, connect EN to IN (supply input). See Figure 5.

Input Capacitor

A 1µF capacitor should be placed from IN to GND if there is more than 10 inches of wire between the input and the ac filter capacitor or if a battery is used as the input.

Output Capacitor

An output capacitor is required between OUT and GND to prevent oscillation. The minimum size of the output capacitor is dependent upon whether a reference bypass capacitor is used. 1µF minimum is recommended when C_{BYP} is not used (see Figure 5). 2.2µF minimum is recommended when C_{BYP} is 470pF (see Figure 6). For applications <3V, the output capacitor should be increased to 22µF minimum to reduce start-up overshoot. Larger values improve the regulator's transient response. The output capacitor value may be increased without limit.

The output capacitor should have an ESR (equivalent series resistance) of about 5Ω or less and a resonant frequency above 1MHz. Ultra-low-ESR capacitors could cause oscillation and/or underdamped transient response. Most tantalum or aluminum electrolytic capacitors are adequate; film types will work, but are more expensive. Many aluminum electrolytics have electrolytes that freeze at about –30°C, so solid tantalums are recommended for operation below –25°C.

At lower values of output current, less output capacitance is needed for stability. The capacitor can be reduced to 0.47µF for current below 10mA or 0.33µF for currents below 1mA.

No-Load Stability

The MIC5219 will remain stable and in regulation with no load (other than the internal voltage divider) unlike many other voltage regulators. This is especially important in CMOS RAM keep-alive applications.

Reference Bypass Capacitor

BYP is connected to the internal voltage reference. A 470pF capacitor (C_{BYP}) connected from BYP to GND quiets this reference, providing a significant reduction in output noise (ultra-low-noise performance). C_{BYP} reduces the regulator phase margin; when using C_{BYP}, output capacitors of 2.2µF or greater are generally required to maintain stability.

The start-up speed of the MIC5219 is inversely proportional to the size of the reference bypass capacitor. Applications requiring a slow ramp-up of output voltage should consider larger values of C_{BYP}. Likewise, if rapid turn-on is necessary, consider omitting C_{BYP}.

Thermal Considerations

The MIC5219 is designed to provide 200mA of continuous current in two very small profile packages. Maximum power dissipation can be calculated based on the output current and the voltage drop across the part. To determine the maximum power dissipation of the package, use the thermal resistance, junction-to-ambient, of the device and the following basic equation.

$$P_{D(max)} = \frac{\left(T_{J(max)} - T_A\right)}{\theta_{JA}}$$

$T_{J(MAX)}$ is the maximum junction temperature of the die, 125°C, and T_A is the ambient operating temperature. θ_{JA} is layout dependent; table 1 shows examples of thermal resistance, junction-to-ambient, for the MIC5219.

Package	θ_{JA} Recommended Minimum Footprint	θ_{JA} 1" Square 2 oz. Copper	θ_{JC}
MM8™ (MM)	160°C/W	70°C/W	30°C/W
SOT-23-5 (M5)	220°C/W	170°C/W	130°C/W

Table 1. MIC5219 Thermal Resistance

The actual power dissipation of the regulator circuit can be determined using one simple equation.

$$P_D = (V_{IN} - V_{OUT})\, I_{OUT} + V_{IN}\, I_{GND}$$

Substituting $P_{D(MAX)}$ for P_D and solving for the operating conditions that are critical to the application will give the maximum operating conditions for the regulator circuit. For example, if we are operating the MIC5219-3.3BM5 at room temperature, with a minimum footprint layout, we can determine the maximum input voltage for a set output current.

$$P_{D(max)} = \frac{(125°C - 25°C)}{220°C/W}$$

$$P_{D(max)} = 455mW$$

The thermal resistance, junction-to-ambient, for the minimum footprint is 220°C/W, taken from table 1. The maximum power dissipation number cannot be exceeded for proper operation of the device. Using the output voltage of 3.3V, and an output current of 150mA, we can determine the maximum input voltage. Ground current, maximum of 3mA for 150mA of output current, can be taken from the Electrical Characteristics section of the data sheet.

$$455mW = (V_{IN} - 3.3V) \times 150mA + V_{IN} \times 3mA$$

$$455mW = (150mA) \times V_{IN} + 3mA \times V_{IN} - 495mW$$

$$950mW = 153mA \times V_{IN}$$

$$V_{IN} = 6.2V_{MAX}$$

Therefore, a 3.3V application at 150mA of output current can accept a maximum input voltage of 6.2V in a SOT-23-5 package. For a full discussion of heat sinking and thermal effects on voltage regulators, refer to the Regulator Thermals section of Micrel's *Designing with Low-Dropout Voltage Regulators* handbook.

Peak Current Applications

The MIC5219 is designed for applications where high start-up currents are demanded from space constrained regulators. This device will deliver 500mA start-up current from a SOT-23-5 or MM8 package, allowing high power from a very low profile device. The MIC5219 can subsequently provide output current that is only limited by the thermal characteristics of the device. You can obtain higher continuous currents from the device with the proper design. This is easily proved with some thermal calculations.

If we look at a specific example, it may be easier to follow. The MIC5219 can be used to provide up to 500mA continuous output current. First, calculate the maximum power dissipation of the device, as was done in the thermal considerations section. Worst case thermal resistance (θ_{JA} = 220°C/W for the MIC5219-x.xBM5), will be used for this example.

$$P_{D(max)} = \frac{\left(T_{J(max)} - T_A\right)}{\theta_{JA}}$$

Assuming a 25°C room temperature, we have a maximum power dissipation number of

$$P_{D(max)} = \frac{(125°C - 25°C)}{220°C/W}$$

$$P_{D(max)} = 455mW$$

Then we can determine the maximum input voltage for a five-volt regulator operating at 500mA, using worst case ground current.

$P_{D(max)} = 455mW = (V_{IN} - V_{OUT})\ I_{OUT} + V_{IN}\ I_{GND}$

$I_{OUT} = 500mA$

$V_{OUT} = 5V$

$I_{GND} = 20mA$

$455mW = (V_{IN} - 5V)\ 500mA + V_{IN} \times 20mA$

$2.995W = 520mA \times V_{IN}$

$$V_{IN(max)} = \frac{2.955W}{520mA} = 5.683V$$

Therefore, to be able to obtain a constant 500mA output current from the 5219-5.0BM5 at room temperature, you need extremely tight input-output voltage differential, barely above the maximum dropout voltage for that current rating.

You can run the part from larger supply voltages if the proper precautions are taken. Varying the duty cycle using the enable pin can increase the power dissipation of the device by maintaining a lower average power figure. This is ideal for applications where high current is only needed in short bursts. Figure 1 shows the safe operating regions for the MIC5219-x.xBM5 at three different ambient temperatures and at different output currents. The data used to determine this figure assumed a minimum footprint PCB design for minimum heat sinking. Figure 2 incorporates the same factors as the first figure, but assumes a much better heat sink. A 1" square copper trace on the PC board reduces the thermal resistance of the device. This improved thermal resistance improves power dissipation and allows for a larger safe operating region.

Figures 3 and 4 show safe operating regions for the MIC5219-x.xBMM, the power MSOP package part. These graphs show three typical operating regions at different temperatures. The lower the temperature, the larger the operating region. The graphs were obtained in a similar way to the graphs for the MIC5219-x.xBM5, taking all factors into consideration and using two different board layouts, minimum footprint and 1" square copper PC board heat sink. (For further discussion of PC board heat sink characteristics, refer to Application Hint 17, “Designing PC Board Heat Sinks”.)

The information used to determine the safe operating regions can be obtained in a similar manner to that used in determining typical power dissipation, already discussed. Determining the maximum power dissipation based on the layout is the first step, this is done in the same manner as in the previous two sections. Then, a larger power dissipation number multiplied by a set maximum duty cycle would give that maximum power dissipation number for the layout. This is best shown through an example. If the application calls for 5V at 500mA for short pulses, but the only supply voltage available is 8V, then the duty cycle has to be adjusted to determine an average power that does not exceed the maximum power dissipation for the layout.

$$Avg.P_D = \left(\frac{\%\ DC}{100}\right)\left(V_{IN} - V_{OUT}\right) I_{OUT} + V_{IN}\ I_{GND}$$

$$455mW = \left(\frac{\%\ DC}{100}\right)(8V - 5V)\ 500mA + 8V \times 20mA$$

$$455mW = \left(\frac{\%\ Duty\ Cycle}{100}\right) 1.66W$$

$$0.274 = \frac{\%\ Duty\ Cycle}{100}$$

$$\%\ Duty\ Cycle\ Max = 27.4\%$$


With an output current of 500mA and a three-volt drop across the MIC5219-xxBMM, the maximum duty cycle is 27.4%.

Applications also call for a set nominal current output with a greater amount of current needed for short durations. This is a tricky situation, but it is easily remedied. Calculate the average power dissipation for each current section, then add the two numbers giving the total power dissipation for the regulator. For example, if the regulator is operating normally at 50mA, but for 12.5% of the time it operates at 500mA output, the total power dissipation of the part can be easily determined. First, calculate the power dissipation of the device at 50mA. We will use the MIC5219-3.3BM5 with 5V input voltage as our example.

$P_D \times 50mA = (5V - 3.3V) \times 50mA + 5V \times 650\mu A$


$P_D \times 50mA = 173mW$

However, this is continuous power dissipation, the actual on-time for the device at 50mA is (100%-12.5%) or 87.5% of the time, or 87.5% duty cycle. Therefore, P_D must be multiplied by the duty cycle to obtain the actual average power dissipation at 50mA.




a. 25°C Ambient **b. 50°C Ambient** **c. 85°C Ambient**

Figure 1. MIC5219-x.xBM5 (SOT-23-5) on Minimum Recommended Footprint




a. 25°C Ambient **b. 50°C Ambient** **c. 85°C Ambient**

Figure 2. MIC5219-x.xBM5 (SOT-23-5) on 1-inch^2 Copper Cladding



a. 25°C Ambient **b. 50°C Ambient** **c. 85°C Ambient**

Figure 3. MIC5219-x.xBMM (MSOP-8) on Minimum Recommended Footprint



a. 25°C Ambient **b. 50°C Ambient** **c. 85°C Ambient**

Figure 4. MIC5219-x.xBMM (MSOP-8) on 1-inch^2 Copper Cladding

$P_D \times 50mA = 0.875 \times 173mW$

$P_D \times 50mA = 151mW$

The power dissipation at 500mA must also be calculated.

$P_D \times 500mA = (5V – 3.3V)\ 500mA + 5V \times 20mA$

$P_D \times 500mA = 950mW$

This number must be multiplied by the duty cycle at which it would be operating, 12.5%.

$P_D \times = 0.125 \times 950mW$

$P_D \times = 119mW$

The total power dissipation of the device under these conditions is the sum of the two power dissipation figures.

$P_{D(total)} = P_D \times 50mA + P_D \times 500mA$

$P_{D(total)} = 151mW + 119mW$

$P_{D(total)} = 270mW$

The total power dissipation of the regulator is less than the maximum power dissipation of the SOT-23-5 package at room temperature, on a minimum footprint board and therefore would operate properly.

Multilayer boards with a ground plane, wide traces near the pads, and large supply-bus lines will have better thermal conductivity.

For additional heat sink characteristics, please refer to Micrel Application Hint 17, “Designing P.C. Board Heat Sinks”, included in Micrel’s *Databook*. For a full discussion of heat sinking and thermal effects on voltage regulators, refer to Regulator Thermals section of Micrel’s *Designing with Low-Dropout Voltage Regulators* handbook.

Fixed Regulator Circuits




Figure 5. Low-Noise Fixed Voltage Regulator

Figure 5 shows a basic MIC5219-x.xBMX fixed-voltage regulator circuit. A 1µF minimum output capacitor is required for basic fixed-voltage applications.




Figure 6. Ultra-Low-Noise Fixed Voltage Regulator

Figure 6 includes the optional 470pF noise bypass capacitor between BYP and GND to reduce output noise. Note that the minimum value of C_{OUT} must be increased when the bypass capacitor is used.

Adjustable Regulator Circuits




Figure 7. Low-Noise Adjustable Voltage Regulator

Figure 7 shows the basic circuit for the MIC5219 adjustable regulator. The output voltage is configured by selecting values for R1 and R2 using the following formula:

$$V_{OUT} = 1.242V\left(\frac{R2}{R1} + 1\right)$$

Although ADJ is a high-impedance input, for best performance, R2 should not exceed 470kΩ.






Figure 8. Ultra-Low-Noise Adjustable Application.

Figure 8 includes the optional 470pF bypass capacitor from ADJ to GND to reduce output noise.

Package Information



8-Pin MSOP (MM)



SOT-23-5 (M5)

MICREL INC. 1849 FORTUNE DRIVE SAN JOSE, CA 95131 USA

TEL + 1 (408) 944-0800 FAX + 1 (408) 944-0970 WEB http://www.micrel.com

This information is believed to be accurate and reliable, however no responsibility is assumed by Micrel for its use nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent right of Micrel Inc.

© 2000 Micrel Incorporated

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001
Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:
moschip.ru
moschip.ru_4
moschip.ru_6
moschip.ru_9