

## PowerVerter APS X 3000W 24VDC 230V Inverter/Charger with Pure Sine Wave Output, Hardwired

MODEL NUMBER: **APSX3024SW**



### Highlights

- 24V DC or 230V (selectable) AC input & output; 230V, 50/60 Hz, pure sine wave output (hardwired)
- 3000 watts continuous, 4500 watts OverPower and 6000 watts DoubleBoost inverter output
- 3-stage, 23/90 amp selectable wet/dry cell battery charger; Auto Transfer Switching
- Automatic Voltage Regulation corrects brownouts and overvoltages without using battery power

### Package Includes

- APSX3024SW Inverter/Charger
- Instruction manual with warranty information

### Description

Tripp Lite's APSX3024SW DC-to-AC inverter with automatic line-to-battery transfer and integrated charging system serves as an extended run UPS, a standalone power source or an automotive inverter. Supplies up to 3000 watts of continuous 230V sine wave AC power from any 24V battery or automotive DC source. When hardwire AC input is energized, commercial power passes through to connected equipment and the battery set is recharged via 3 stage, 23/90 amp charging system. In UPS mode, the APS system responds to blackouts and severe voltage fluctuations with a near instantaneous automatic transfer to battery-derived AC output. Includes a set of high current DC input terminals for simple installation (user supplies batteries and cabling - see owner's manual for recommendations). Passes sine wave utility or generator power during battery charging and UPS line power operation, and sine wave AC output in inverter and UPS backup modes. Built-in Automatic Voltage Regulation (AVR) corrects line power AC brownouts and overvoltages without using battery power during battery charging and UPS standby modes. Reliable large transformer design, with frequency control powers resistive electronic loads or large inductive motors, compressors and other items with high current needs on startup. Optional [APSRM4](#) wired remote power switch with full status LEDs provides remote power inverter on/off switching and continuous status information (part# [APSRM4](#) sold separately). Supports an unlimited amount of runtime with any number of user-supplied batteries connected. Highly adaptable to a variety of applications and site conditions with adjustable charger settings for wet/gel battery types and selectable line to battery power transfer voltages.

NOTE: To protect against high current draw that may occur during inverter failure, a fuse link rated at 250a should be positioned no more than 18" from the APSX3024SW's battery in the positive line.

### Features

- Supports 230V AC output from a 230V AC line power source or 24V DC battery source
- 3000W continuous sinewave AC output in inverter mode
- Double Boost output supports momentary start-up loads up to 200% of the continuous rating for up to 10 seconds (see specification chart) - OverPower output supports longer duration overloads to 150% for up to 60 seconds
- 3-stage, selectable 23/90 amp battery charger with adjustable settings for wet/gel battery types
- 3-position operating mode switch supports "AUTO" mode to enable automatic transfer between DC and AC modes, CHARGE-ONLY to maintain a full battery charge when AC is present without auto transfer and SYSTEM OFF settings

- Set of 6 front panel LEDs display continuous status information
- Set of 4 dip switches support AC input selection of 230V, selectable 50 /60Hz frequency, and selectable full or half cycle transfer times
- Set of 4 dip switches support wet/gel battery charging profiles, adjustable 260/270V(230V) high voltage auto transfer during overvoltages and selectable 150/60V / 170/180V(230V) AC low voltage auto transfer during brownouts
- Set of 4 additional dip switches support battery equalization program and battery charger low / high settings
- Automatic overload and thermal(overheating) shutoff
- Front panel remote control connector enables remote off/on switching([APSRM4](#) sold separately)
- Load sensing control dial enables adjustable load threshold required to automatically turn the inverter on and off in DC mode as load conditions change
- Automatic Generator Starter jack enables user configuration of automatic generator start-up as inverter batteries drop to 23.0 VDC and generator shutoff as inverter batteries are recharged to 28.2 VDC.
- Remote battery temperature sensing connection function prolongs battery life by adjusting the charge float voltage level based on battery temperature

## Specifications

OUTPUT	
Frequency Compatibility	50 / 60 Hz
Output Receptacles	Hardwire
Output (Watts)	3000
Continuous Output Capacity (Watts)	3000
Peak Output Capacity (Watts)	6000
Output Nominal Voltage	230V
Output Voltage Regulation	LINE POWER (AC): Maintains 230V nominal sine wave output from line power source. INVERTER POWER (AC): Maintains sine wave output voltage of 230 VAC (+/-5%).
Output Frequency Regulation	50/60 Hz (+/- 0.3 Hz)
Pure Sine Wave Output	Yes
INPUT	
Nominal Input Voltage(s) Supported	230V AC
Recommended Electrical Service	DC INPUT: Requires 24VDC input source capable of delivering 145A for the required duration (when used at full continuous capacity - DC requirements increase during OverPower and DoubleBoost operation).
Maximum Input Amps	28
Input Connection Type	DC INPUT: Set of DC bolt-down terminals. AC INPUT: Hardwire via built in terminal strip with cover plate
Voltage Compatibility (VAC)	230
Voltage Compatibility (VDC)	24
BATTERY	
Expandable Battery Runtime	Runtime is expandable with any number of user supplied wet or gel type batteries
DC System Voltage (VDC)	24
Battery Pack Accessory (Optional)	<a href="#">98-121</a> sealed lead acid battery(optional)



Battery Charge	Selectable 23 / 90 amp
Expandable Runtime	Yes
<b>VOLTAGE REGULATION</b>	
Voltage Regulation Description	Includes automatic voltage regulation to correct brownouts and overvoltages back to usable levels
Overvoltage Correction	Overvoltages are automatically reduced by 10%
Brownout Correction	Brownouts are automatically boosted by 10% and 20%
<b>USER INTERFACE, ALERTS &amp; CONTROLS</b>	
Front Panel LEDs	Set of 6 LEDs offer continuous status information on load percentage (6 levels reported) and battery charge level (7 levels reported). See manual for sequences.
Switches	3 position on/off/remote switch enables simple on/off power control plus "auto/remote" setting that enables distant on/off control of the inverter system when used in conjunction with optional <a href="#">APSRM4</a> accessory when used in inverter mode. In AC uninterrupt
<b>PHYSICAL</b>	
Shipping Dimensions (hwd / in.)	20.080 x 18.430 x 22.520
Shipping Dimensions (hwd / cm)	51.00x46.81 x 57.20
Shipping Weight (lbs.)	87
Shipping Weight (kg)	39.46
Unit Dimensions (hwd / in.)	10.08 x 8.90 x 12.40
Unit Dimensions (hwd / cm)	25.60 x22.606 x 31.496
Unit Weight (lbs.)	64.8
Unit Weight (kg)	29.39
Material of Construction	Metal
<b>ENVIRONMENTAL</b>	
Relative Humidity	0-95% non-condensing
Operating Temperature	32-104 Fahrenheit / 0-40 Celcius
<b>LINE / BATTERY TRANSFER</b>	
Transfer Time (Line Power to Battery Mode)	Dip-switch selectable 20 millisecond (full cycle) / 10 millisecond (half-cycle) transfer times which are compatible with many computers, servers and networking equipment - verify transfer time compatibility of loads for UPS applications
Low Voltage Transfer to Battery Power	In 230V AC "auto" mode, inverter/charger switches to battery mode as line voltage drops to 170V AC (user adjustable to 180V).
High Voltage Transfer to Battery Power	In 230V AC "auto" mode, inverter/charger switches to battery mode as line voltage increases to 260V (user adjustable to 270 - see manual).
<b>SPECIAL FEATURES</b>	
Remote Control Capability	Yes



**Tripp Lite**  
1111 W. 35th Street  
Chicago, IL 60609 USA  
Telephone: 773.869.1234  
www.tripplite.com

TVSS Grounding	Main grounding lug connects inverter/charger to earth or vehicle chassis ground
<b>WARRANTY</b>	
Product Warranty Period (U.S. & Canada)	2-year limited warranty
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	2-year limited warranty
Product Warranty Period (Puerto Rico)	2-year limited warranty

© 2015 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<http://www.tripplite.com/products/product-certification-agencies>

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9