




## FSS-SMT Series

---

### Low Profile Force Sensor

#### DESCRIPTION

Honeywell's FSS-SMT Series force sensors are designed to be one of the most reliable force sensors available as illustrated by 20 million Mean Cycles to Failure (MCTF) at 25 °C [77 °F] rating. This low profile Surface Mount Technology (SMT) sensor allows for automated assembly on a printed circuit board, often helping the customer to reduce assembly costs.

The FSS-SMT Series force sensor is designed to provide precise and reliable force sensing performance in a compact commercial-grade package. The sensor incorporates Honeywell sensing technology that uses a specialized piezoresistive micromachined silicon sensing element. The low power, unamplified, uncompensated Wheatstone bridge circuit design provides inherently stable mV output over the force range.

#### FEATURES AND BENEFITS

---

- Surface Mount Technology allows for automated assembly and may eliminate hand soldering
- RoHS-compliant materials meet Directive 2002/95/EC
- Low deflection (approx. 30 µm typical at full scale) helps reduce measurement error
- Direct mechanical coupling of the actuation ball to the sense element reduces coupling errors and keeps mechanical hysteresis to a minimum
- Product rating of 20 million MCTF at 25 °C [77 °F], subject to application variation, provides for consistent output over time and reduces repairs or replacements
- Small size minimizes space on the printed circuit board (PCB)
- Provides enhanced sensitivity without compromising signal integrity, resulting in low system noise and reducing measurement errors
- Electrically ratiometric output accommodates supply voltage variations, leading to low ratiometricity error
- Low voltage supply allows for use in many battery powered applications
- High resistance to electrostatic discharge (ESD) meets ESD Sensitivity Classification Level 3B (8 KV), reducing special handling during assembly
- Sensor output has low sensitivity to many mounting stresses

Force sensors operate on the principle that the resistance of silicon-implanted piezoresistors will change when the resistors flex under applied force. The sensor concentrates force from the applications, through the stainless steel ball, directly to the silicon-sensing element. The amount of resistance changes in proportion to the amount of force being applied. This change in circuit resistance results in a corresponding mV output level change.

The sensor package design incorporates patented modular construction. The use of innovative elastomeric technology and engineered molded plastics results in load excitation capacities up to 60 N (range dependent). The stainless steel ball provides excellent mechanical stability, and is suitable for a variety of potential medical and commercial applications.

#### POTENTIAL APPLICATIONS

---

##### Medical

- Infusion pumps
- Ambulatory non-invasive pumps
- Occlusion detection
- Kidney dialysis machines
- Enteral pumps

##### Industrial

- Load and compression sensing
- Variable tension control
- Robotic end-effectors
- Wire bonding equipment

# FSS-SMT Series

**Table 1. Performance Characteristics (At 10 ±0.01 Vdc, 25 °C [77 °F].)<sup>1</sup>**

| Characteristic                                                  | Unit   | FSS005WNGX |      |      | FSS010WNGX |      |      | FSS015WNGX |      |      | FSS020WNGX |      |      |
|-----------------------------------------------------------------|--------|------------|------|------|------------|------|------|------------|------|------|------------|------|------|
|                                                                 |        | Min.       | Typ. | Max. | Min.       | Typ. | Max. | Min.       | Typ. | Max. | Min.       | Typ. | Max. |
| Force sensing range                                             | N      | 0 to 5     |      |      | 0 to 10    |      |      | 0 to 15    |      |      | 0 to 20    |      |      |
| Excitation <sup>2</sup>                                         | Vdc    | 3.3        | 10   | 12.5 | 3.3        | 10   | 12.5 | 3.3        | 10   | 12.5 | 3.3        | 10   | 12.5 |
| Null offset <sup>3</sup>                                        | mV     | -30        | 0    | +30  | -30        | 0    | +30  | -30        | 0    | +30  | -30        | 0    | +30  |
| Null shift <sup>4</sup><br>(25 to 0°, 25 to 50° C)              | mV     | –          | ±0.5 | –    | –          | ±0.5 | –    | –          | ±0.5 | –    | –          | ±0.5 | –    |
| Span <sup>5</sup>                                               | mV     | 330        | 360  | 390  | 330        | 360  | 390  | 330        | 360  | 390  | 330        | 360  | 390  |
| Linearity (BFSL) <sup>6</sup>                                   | % span | –          | ±0.5 | –    | –          | ±0.5 | –    | –          | ±0.5 | –    | –          | ±0.5 | –    |
| Sensitivity <sup>7</sup>                                        | mV/V/N | 6.6        | 7.2  | 7.8  | 3.3        | 3.6  | 3.9  | 2.2        | 2.4  | 2.6  | 1.65       | 1.8  | 1.95 |
| Sensitivity shift <sup>8</sup><br>(25 °C to 0°, 25 °C to 50 °C) | % span | –          | ±5.0 | –    | –          | ±5.0 | –    | –          | ±5.0 | –    | –          | ±5.0 | –    |
| Repeatability <sup>9</sup>                                      | % span | –          | ±0.2 | –    | –          | ±0.2 | –    | –          | ±0.2 | –    | –          | ±0.2 | –    |
| Response time<br>(10 %FS to 90 %FS)                             | ms     | –          | 0.1  | 0.5  | –          | 0.1  | 0.5  | –          | 0.1  | 0.5  | –          | 0.1  | 0.5  |
| Input resistance                                                | kΩ     | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  |
| Output resistance                                               | kΩ     | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  | 4.0        | 5.0  | 6.0  |
| Plunger deflection                                              | μm     | –          | 26   | –    | –          | 28   | –    | –          | 33   | –    | –          | 30   | –    |
| Overforce <sup>10</sup>                                         | N      | –          | –    | 15   | –          | –    | 30   | –          | –    | 45   | –          | –    | 60   |

**Notes:**

- All force-related specifications are established using dead weight or compliant force.
- The range of voltage excitation which can be supplied to the product to produce an output which is proportional to force but due to ratiometricity errors may not remain within the specified performance limits. Non-compensated force sensors, excited by constant current (1.5 mA) instead of voltage, exhibit partial temperature compensation of span.
- The output signal obtained when the zero force is applied to the sensor. Also known as "null" or "zero".
- The change in the null resulting from a change in temperature. It is not a predictable error as it can shift up and down from unit to unit. Change in temperature causes the entire output curve to shift up or down along the voltage axis.
- The algebraic difference between output signals measured at the upper and lower limits of the operating force range. Also known as "full scale output" or simply "span".
- The maximum deviation of product output from a straight line fitted to output measured over the operating force range. It is also the straight line through a set of points which minimizes the sum of the square of the deviations of each of the points from the straight line.
- The ratio of output signal change to the corresponding input force change. Sensitivity is determined by computing the ratio of span to the specified operating force range multiplied by the supply voltage being used.
- The maximum deviation in sensitivity due to changes in temperature over the operating temperature range, relative to sensitivity measured at 25 °C.
- The maximum difference between output readings when the same force is applied consecutively, under the same operating conditions, with force approaching from the same direction within the operating force range.
- The maximum force which may safely be applied to the product for it to remain in specification once force is returned to the operating force range. Exposure to higher forces may cause permanent damage to the product. Unless otherwise specified, this applies to all temperatures within the operating temperature range.

## CAUTION

### EXCEEDING PRODUCT OVERFORCE RATING

- Ensure the overforce ratings given in Table 1 are not exceeded during any phase of sensor assembly to the board, as well as during the use of the sensor in the application.

**Failure to comply with these instructions may result in product damage.**

**Table 2. Environmental Specifications**

| Characteristic                             | Parameter                                     |
|--------------------------------------------|-----------------------------------------------|
| Operating temperature <sup>1</sup>         | -40 °C to 85 °C [-40 °F to 185 °F]            |
| Shock                                      | qualification tested to 150 g                 |
| Vibration                                  | qualification tested to 0 to 2 kHz, 20 g sine |
| MCTF <sup>2</sup> (Mean Cycles To Failure) | 20 million at 25 °C [77 °F]                   |
| Output ratiometric                         | within supply range                           |

**Notes:**

- The temperature range over which the product may safely be exposed without excitation or force applied. Under these conditions the product will remain in specification after excursion to any temperatures in this range. Exposure to temperatures beyond this range may cause permanent damage to the product.
- MCTF is a basic measure of reliability for a non-repairable device. It is the mean number of cycles to maximum operating force over which a sensor can be expected to operate until failure. The mean value is determined statistically from a probability distribution for failures based upon test data. MCTF may vary depending on the specific application in which a sensor is utilized.




# Low Profile Force Sensor

**Table 3. Absolute Maximum Ratings<sup>1</sup>**

| Characteristic                   | Parameter                                     |
|----------------------------------|-----------------------------------------------|
| Storage temperature <sup>2</sup> | -40 °C to 100 °C [-40 °F to 212 °F]           |
| Solderability <sup>3</sup>       | 10 s at 260 °C [500 °F]                       |
| ESD                              | Meets ESD Sensitivity Classification Level 3B |

**Notes:**

1. The extreme limits that the product can withstand without damage to the product.
2. The temperature range over which the product may safely be exposed without excitation or force applied. Under these conditions, the product will remain in the specification after excursions to any temperature in this range. Exposure to temperatures beyond this range may cause permanent damage to the product.
3. The maximum temperature and time to which the product may be exposed for processing the solder electrical connections.

**Figure 1. Excitation Schematic (Excitation 5 Vdc Typ., 6 Vdc max.)**

**Figure 2. Sensor Mounting Diagram (For reference only: mm/[in].)**

**Figure 3. Packaging Dimensions (For reference only.)**


## Order Guide

| Catalog Listing | Description                                                                                       |
|-----------------|---------------------------------------------------------------------------------------------------|
| FSS005WNGB      | FSS-SMT Series Low Profile Force Sensor, 0 N to 5 N force sensing range, short tube packaging     |
| FSS005WNGR      | FSS-SMT Series Low Profile Force Sensor, 0 N to 5 N force sensing range, tape and reel packaging  |
| FSS005WNGT      | FSS-SMT Series Low Profile Force Sensor, 0 N to 5 N force sensing range, standard tube packaging  |
| FSS010WNGB      | FSS-SMT Series Low Profile Force Sensor, 0 N to 10 N force sensing range, short tube packaging    |
| FSS010WNGR      | FSS-SMT Series Low Profile Force Sensor, 0 N to 10 N force sensing range, tape and reel packaging |
| FSS010WNGT      | FSS-SMT Series Low Profile Force Sensor, 0 N to 10 N force sensing range, standard tube packaging |
| FSS015WNGB      | FSS-SMT Series Low Profile Force Sensor, 0 N to 15 N force sensing range, short tube packaging    |
| FSS015WNGR      | FSS-SMT Series Low Profile Force Sensor, 0 N to 15 N force sensing range, tape and reel packaging |
| FSS015WNGT      | FSS-SMT Series Low Profile Force Sensor, 0 N to 15 N force sensing range, standard tube packaging |
| FSS020WNGB      | FSS-SMT Series Low Profile Force Sensor, 0 N to 20 N force sensing range, short tube packaging    |
| FSS020WNGR      | FSS-SMT Series Low Profile Force Sensor, 0 N to 20 N force sensing range, tape and reel packaging |
| FSS020WNGT      | FSS-SMT Series Low Profile Force Sensor, 0 N to 20 N force sensing range, standard tube packaging |

### WARNING

#### MISUSE OF DOCUMENTATION

- The information presented in this product sheet is for reference only. Do not use this document as a product installation guide.
- Complete installation, operation, and maintenance information is provided in the instructions supplied with each product.

**Failure to comply with these instructions could result in death or serious injury.**

### WARNING

#### PERSONAL INJURY

DO NOT USE these products as safety or emergency stop devices or in any other application where failure of the product could result in personal injury.

**Failure to comply with these instructions could result in death or serious injury.**

#### WARRANTY/REMEDY

Honeywell warrants goods of its manufacture as being free of defective materials and faulty workmanship. Honeywell's standard product warranty applies unless agreed to otherwise by Honeywell in writing; please refer to your order acknowledgement or consult your local sales office for specific warranty details. If warranted goods are returned to Honeywell during the period of coverage, Honeywell will repair or replace, at its option, without charge those items it finds defective. **The foregoing is buyer's sole remedy and is in lieu of all other warranties, expressed or implied, including those of merchantability and fitness for a particular purpose. In no event shall Honeywell be liable for consequential, special, or indirect damages.**

While we provide application assistance personally, through our literature and the Honeywell web site, it is up to the customer to determine the suitability of the product in the application.

Specifications may change without notice. The information we supply is believed to be accurate and reliable as of this printing. However, we assume no responsibility for its use.

#### SALES AND SERVICE

Honeywell serves its customers through a worldwide network of sales offices, representatives and distributors. For application assistance, current specifications, pricing or name of the nearest Authorized Distributor, contact your local sales office or:

**E-mail:** [info.sc@honeywell.com](mailto:info.sc@honeywell.com)

**Internet:** [sensing.honeywell.com](http://sensing.honeywell.com)

#### Phone and Fax:

|               |                                                           |
|---------------|-----------------------------------------------------------|
| Asia Pacific  | +65 6355-2828<br>+65 6445-3033 Fax                        |
| Europe        | +44 (0) 1698 481481<br>+44 (0) 1698 481676 Fax            |
| Latin America | +1-305-805-8188<br>+1-305-883-8257 Fax                    |
| USA/Canada    | +1-800-537-6945<br>+1-815-235-6847<br>+1-815-235-6545 Fax |

Sensing and Control

Honeywell

1985 Douglas Drive North

Golden Valley, MN 55422

[sensing.honeywell.com](http://sensing.honeywell.com)

080281-3-EN  
April 2014

© 2014 Honeywell International Inc. All rights reserved.

# Honeywell

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9