

Part Number: WP3A10SF4C


### Features

- Mechanically and spectrally matched to the phototransistor.
- RoHS compliant.

### Description

SF4 Made with Gallium Aluminum Arsenide Infrared Emitting diodes.

### Package Dimensions



#### Notes:

1. All dimensions are in millimeters (inches).
2. Tolerance is  $\pm 0.25(0.01)$  unless otherwise noted.
3. Lead spacing is measured where the leads emerge from the package.
4. The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.



## Selection Guide

| Part No.   | Dice         | Lens Type   | Po (mW/sr) [2]<br>@ 20mA *50mA |      | Viewing Angle [1] |
|------------|--------------|-------------|--------------------------------|------|-------------------|
|            |              |             | Min.                           | Typ. | 2θ1/2             |
| WP3A10SF4C | SF4 (GaAlAs) | Water Clear | 7                              | 40   | 50°               |
|            |              |             | *18                            | *55  |                   |

Notes:

1. θ1/2 is the angle from optical centerline where the luminous intensity is 1/2 of the optical peak value.
2. \* Luminous intensity with asterisk is measured at 50mA; Radiant Intensity/ luminous flux: +/-15%.

## Electrical / Optical Characteristics at TA=25°C

| Parameter                | P/N | Symbol         | Typ. | Max. | Units | Test Conditions           |
|--------------------------|-----|----------------|------|------|-------|---------------------------|
| Forward Voltage [1]      | SF4 | V <sub>F</sub> | 1.3  | 1.6  | V     | I <sub>F</sub> =20mA      |
| Reverse Current          | SF4 | I <sub>R</sub> |      | 10   | uA    | V <sub>R</sub> = 5V       |
| Capacitance              | SF4 | C              | 90   |      | pF    | V <sub>F</sub> =0V;f=1MHz |
| Peak Spectral Wavelength | SF4 | λ <sub>P</sub> | 880  |      | nm    | I <sub>F</sub> =20mA      |
| Spectral Bandwidth       | SF4 | Δλ1/2          | 50   |      | nm    | I <sub>F</sub> =20mA      |

Note:


1. Forward Voltage: +/-0.1V.

## Absolute Maximum Ratings at TA=25°C





| Parameter                   | Symbol           | SF4                 | Units |
|-----------------------------|------------------|---------------------|-------|
| Power dissipation           | P <sub>D</sub>   | 80                  | mW    |
| DC Forward Current          | I <sub>F</sub>   | 50                  | mA    |
| Peak Forward Current [1]    | i <sub>FS</sub>  | 1.2                 | A     |
| Reverse Voltage             | V <sub>R</sub>   | 5                   | V     |
| Operating Temperature       | T <sub>A</sub>   | -40 To +85          | °C    |
| Storage Temperature         | T <sub>STG</sub> | -40 To +85          | °C    |
| Lead Solder Temperature [2] |                  | 260°C For 3 Seconds |       |
| Lead Solder Temperature [3] |                  | 260°C For 5 Seconds |       |

Notes:

1. 1/100 Duty Cycle, 10μs Pulse Width.
2. 2mm below package base.
3. 5mm below package base.





## WP3A10SF4C



# Kingbright

## PACKING & LABEL SPECIFICATIONS

WP3A10SF4C




1,000PCS / BAG



56K / 9# BOX

OUTSIDE LABEL



OUTSIDE LABEL


28K / 5# BOX

# Kingbright

P/NO: WP3A10XXX

QTY: 1,000 pcs

Q.C.



S/N: XXXX

CODE: XXX

LOT NO:



RoHS Compliant

## LED MOUNTING METHOD

1. The lead pitch of the LED must match the pitch of the mounting holes on the PCB during component placement. Lead-forming may be required to insure the lead pitch matches the hole pitch. Refer to the figure below for proper lead forming procedures.

(Fig. 1)




Fig.1

”○” Correct mounting method ”×” Incorrect mounting method

Note 1-2 : Do not route PCB trace in the contact area between the leadframe and the PCB to prevent short-circuits.

2. When soldering wire to the LED, use individual heat-shrink tubing to insulate the exposed leads to prevent accidental contact short-circuit.

(Fig. 2)



Fig. 2

3. Use stand-offs (Fig. 3) or spacers (Fig. 4) to securely position the LED above the PCB.



Fig. 3




Fig. 4

## LEAD FORMING PROCEDURES

1. Maintain a minimum of 2mm clearance between the base of the LED lens and the first lead bend. (Fig. 5 and 6)




Fig. 5




Fig. 6

2. Lead forming or bending must be performed before soldering, never during or after Soldering.
3. Do not stress the LED lens during lead-forming in order to fractures in the lens epoxy and damage the internal structures.
4. During lead forming, use tools or jigs to hold the leads securely so that the bending force will not be transmitted to the LED lens and its internal structures. Do not perform lead forming once the component has been mounted onto the PCB. (Fig. 7)
5. Do not bend the leads more than twice. (Fig. 8)




Fig. 7




Fig. 8

6. After soldering or other high-temperature assembly, allow the LED to cool down to 50°C before applying outside force (Fig. 9). In general, avoid placing excess force on the LED to avoid damage. For any questions please consult with Kingbright representative for proper handling procedures.




Fig. 9

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9