



## DR22 Series

### AC Output DIN Rail Mount SSRs

- Output ratings up to 35 Amps at 600 VAC
- Built-in overvoltage protection
- Relay or Contactor configuration
- Integral heat sink eliminates the need for complex thermal calculations
- DBC substrate for superior thermal performance
- "Elevator" screw option to allow the use of ring or lug type terminals
- IP20 touch-safe housing
- AC or DC control
- C-UL-US and TUV approved

**NOVA22**

## PRODUCT SELECTION

| Control Voltage | 20A        | 30A        | 35A        |
|-----------------|------------|------------|------------|
| 90-280 VAC/VDC  | DR2260A20x | DR2260A30x | DR2260A35x |
| 4-32 VDC        | DR2260D20x | DR2260D30x | DR2260D35x |

## AVAILABLE OPTIONS



- Required for valid part number
- For options only and not required for valid part number

## OUTPUT SPECIFICATIONS (2)

| Description                                                                     | 20A        | 30A       | 35A       |
|---------------------------------------------------------------------------------|------------|-----------|-----------|
| Operating Voltage (47-440Hz) [V <sub>RMS</sub> ]                                | 48-600     | 48-600    | 48-600    |
| Transient Overvoltage [V <sub>pk</sub> ] (3)                                    | 1200       | 1200      | 1200      |
| Maximum Off-State Leakage Current @ Rated Voltage [mA <sub>RMS</sub> ]          | 1          | 1         | 1         |
| Minimum Off-State dV/dt @ Maximum Rated Voltage [V/μsec]                        | 500        | 500       | 500       |
| Load Current, General Use UL508/LC A IEC62314 @ 40°C [A <sub>RMS</sub> ]        | 20         | 30        | 35        |
| Load Current, Motor Starting UL508 FLA/LC B IEC62314 @ 40°C [A <sub>RMS</sub> ] | 8.5/4.8    | 14/7.6    | 26/14     |
| Minimum Load Current [mA <sub>RMS</sub> ]                                       | 100        | 100       | 150       |
| Maximum 1 Cycle Surge Current (50/60Hz) [A <sub>pk</sub> ]                      | 286/300    | 716/750   | 1290/1350 |
| Maximum On-State Voltage Drop @ Rated Current [V <sub>pk</sub> ]                | 1.35       | 1.35      | 1.3       |
| Maximum 1/2 Cycle I <sup>2</sup> t for Fusing (50/60Hz) [A <sup>2</sup> sec]    | 409/375    | 2563/2343 | 8320/7593 |
| Minimum Power Factor (at Maximum Load) (4)                                      | 0.5        | 0.5       | 0.5       |
| Motor Rating UL 508/IEC62314 [HP (kW)]: 120 VAC                                 | 0.5 (0.37) | 1 (0.74)  | 2 (1.5)   |
| Motor Rating UL 508/IEC62314 [HP (kW)]: 240 VAC                                 | 1.5 (1.1)  | 3 (2.2)   | 5 (3.73)  |
| Motor Rating UL 508/IEC62314 [HP (kW)]: 480 VAC                                 | 3 (2.24)   | 5 (3.7)   | 10 (7.4)  |

## INPUT SPECIFICATIONS (2)

| Description                          | DR2260Dxxx      | DR2260Axxx         |
|--------------------------------------|-----------------|--------------------|
| Control Voltage Range                | 4-32 VDC (5)    | 90-280 VAC/VDC (6) |
| Maximum Reverse Voltage              | -32 VDC         | -                  |
| Minimum Turn-On Voltage              | 4 VDC           | 90 VAC/VDC         |
| Must Turn-Off Voltage                | 1 VDC           | 5 VAC/VDC          |
| Minimum Input Current (for on-state) | 7 mA            | 6 mA               |
| Maximum Input Current                | 15 mA           | 10 mA              |
| Nominal Input Impedance              | Current Limited | Current Limited    |
| Maximum Turn-On Time [msec]          | 1/2 Cycle (7)   | 20                 |
| Maximum Turn-Off Time [msec]         | 1/2 Cycle       | 30                 |

## GENERAL SPECIFICATIONS <sup>(2)</sup>

| Description                                         | Parameters                                                      |
|-----------------------------------------------------|-----------------------------------------------------------------|
| Dielectric Strength, Input to Output (50/60Hz)      | 4000 V <sub>RMS</sub>                                           |
| Dielectric Strength, Input/Output to Case (50/60Hz) | 4000 V <sub>RMS</sub>                                           |
| Minimum Insulation Resistance (@ 500 VDC)           | 10 <sup>9</sup> Ohms                                            |
| Maximum Capacitance, Input/Output                   | 8 pF                                                            |
| Ambient Operating Temperature Range <sup>(8)</sup>  | -40 to 80 °C                                                    |
| Ambient Storage Temperature Range                   | -40 to 100 °C                                                   |
| Short Circuit Current Rating <sup>(9)</sup>         | 100kA                                                           |
| Weight (typical)                                    | Option "U" 10.5 oz (298 g), Option "V", "W" 10.6 oz (301 g)     |
| Housing Material                                    | UL94 V-0                                                        |
| Heat Sink Material                                  | Aluminum                                                        |
| Din Rail Clip Material                              | Zink Plated Steel                                               |
| Hardware Finish                                     | Nickel Plating                                                  |
| Input Terminal Screw Torque Range (lb-in/Nm)        | Option "U" 13-15/1.5-1.7, Option "V", "W" 5/0.5 <sup>(10)</sup> |
| Load Terminal Screw Torque Range (lb-in/Nm)         | Option "U" 13-15/1.5-1.7, Option "V", "W" 18-20/2-2.2           |
| Humidity                                            | 95% non-condensing                                              |
| LED Input Status Indicator                          | Green                                                           |

## INPUT CURRENT INFORMATION

4-32 VDC Input



90-280 VAC/VDC Input



## SURGE CURRENT INFORMATION

DR2260x20x



DR2260x30x



DR2260x35x



--- Single Pulse <sup>(11)</sup>

## THERMAL DERATE INFORMATION <sup>(8)</sup>




## EQUIVALENT CIRCUIT BLOCK DIAGRAMS/WIRING DIAGRAM

### DC Control



### AC/DC Control



### Recommended Wire Sizes

| Terminal Configuration                       | Wire Size (Solid / Stranded)    | Wire Pull-Out Strength (lb)[N] |
|----------------------------------------------|---------------------------------|--------------------------------|
| Output (13)<br>Relay "U" suffix              | 2 x 18 AWG (1 mm²) Stranded     | 20 [88]                        |
|                                              | 2 x 10 AWG (6 mm²) Stranded     | 60 [266]                       |
| Input<br>Relay "U" suffix                    | 2 x 18 AWG (1 mm²) Stranded     | 20 [88]                        |
|                                              | 2 x 12 AWG (4 mm²) Stranded     | 40 [177]                       |
| Output<br>Contactor<br>"V" & "W"<br>suffixes | 2 x 20 AWG (0.75 mm²) [minimum] | 25 [111]                       |
|                                              | 2 x 10 AWG (6 mm²)              | 80 [355]                       |
|                                              | 2 x 8 AWG (10 mm²) [maximum]    | 90 [400]                       |
| Input<br>Contactor<br>"V" & "W"<br>suffixes  | 30 AWG (0.05 mm²) [minimum]     | 4.5 [20]                       |
|                                              | 12 AWG (3.3 mm²) [maximum]      | 30 [133]                       |
|                                              | 26 AWG (0.13 mm²) [minimum]     | 4 [18]                         |
|                                              | 12 AWG (3.3 mm²) [maximum]      | 30 [133]                       |


## MECHANICAL SPECIFICATIONS

Tolerances:  $\pm 0.02$  in / 0.5 mm  
All dimensions are in: inches [millimeters]


### Contactor Configuration



### Relay Configuration



### Input Connector



### Protective Earth Connection




Protective Earth (PE) screw type recommended is 10-32 UNC standard not provided with SSR. Through the use of a DIN rail ground (protective conductor) terminal block, the DIN rail itself can be used as the grounding bus bar. In this case, the zinc plated steel material used for the DIN rail clip of DR22 models, permits a secure path to ground and avoid the need of a further PE connection.

**TABLE 1. Compatible Terminals**

| Terminals                     |  |  |  |  |
|-------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------|
| <b>Crydom Part No.</b>        | <b>Fork Lug</b>                                                                     | <b>Ring Lug</b>                                                                     | <b>Copper Lug</b>                                                                   | <b>Copper Lug</b>                                                                    |
| <b>Width [W] in (mm)</b>      | 0.45 (11.4)                                                                         | 0.45 (11.4)                                                                         | TRM0                                                                                | TRM6                                                                                 |
| <b>Stud Size Dia [D] (in)</b> | #8 (0.168)                                                                          | #8 (0.168)                                                                          |                                                                                     |                                                                                      |
| <b>Wire Size AWG</b>          |                                                                                     |                                                                                     | 6-0                                                                                 | 14-6                                                                                 |

### Elevator Screw (Suffix 'W')



The Elevator Screw option allows the screw and clamp to be raised out of the mating threads completely. This provides for the insertion and use of a ring or lug type wire terminal. Refer to TABLE 1 for Compatible Terminals.

## ACCESSORIES

| Recommended Accessories                                                           |                                                                                   |                                                                                   |
|-----------------------------------------------------------------------------------|-----------------------------------------------------------------------------------|-----------------------------------------------------------------------------------|
|  |  |  |
| <b>Connectors</b>                                                                 | <b>ID Marker</b>                                                                  | <b>Lug Terminal</b>                                                               |
| CP201                                                                             | CNLB                                                                              | TRM0                                                                              |
| CP202                                                                             | CNLN                                                                              | TRM6                                                                              |
|                                                                                   | CNL2                                                                              |                                                                                   |

## New Accessories!

### Connectors

Part number: CP201, CP202



Pluggable input connectors, 2 position, with screw terminals (CP201) or spring type terminals (CP202). Compatible with Contactor Configuration NOVA22 SSRs.

### Lug Terminal

Part number: TRM0



Copper wire lug for AWG 6 (13.3 mm<sup>2</sup>) to AWG 0 (53.5 mm<sup>2</sup>) wire size. For use with "Elevator" screw option ("W" suffix) NOVA22 SSRs.

## AGENCY APPROVALS, CONFORMANCES AND EMC



### Certification in accordance with:

United States Standard for Industrial Control Equipment - UL 508 and Canadian Standard Association for Industrial Control Equipment – C22.2 No. 14.

TUV Certified in accordance to EN62314

Vibration Resistance: (15)

IEC 60068-2-6: Amplitude Range 10-500 Hz, Displacement 0.75mm

Shock Resistance: (15)

IEC 60068-2-27: Peak Acceleration 50g, Duration 11ms.

### Electromagnetic Compatibility

| Generic Standard                                      | Immunity Tests          | Test Specification Level |                          | Performance |
|-------------------------------------------------------|-------------------------|--------------------------|--------------------------|-------------|
| IEC 61000-6-2<br>Immunity for Industrial Environments | Electrostatic Discharge | 8kV air discharge        |                          | Criterion B |
|                                                       | IEC 61000-4-2           | 6kV contact discharge    |                          | Criterion A |
|                                                       | Fast transients (burst) | Output                   | 2kV, 5kHz, 100kHz        | Criterion B |
|                                                       |                         | Input                    | 1kV, 5kHz, 100kHz        | Criterion B |
|                                                       | Surge                   | Output                   | 1kV Line to Line         | Criterion B |
|                                                       |                         |                          | 2kV Line to Earth        | Criterion B |
|                                                       |                         | AC Input                 | 1kV Line to Line         | Criterion B |
|                                                       |                         |                          | Option 2kV Line to Earth | Criterion B |

## GENERAL NOTES

- (1) Control voltage 18-52 VAC/VDC is available upon request.
- (2) All parameters at 25°C unless otherwise specified.
- (3) Output will self trigger between 900-1200 Vpk, not suitable for capacitive loads.
- (4) High inductive loads requires nominal control voltage; AC input models only.
- (5) Increase minimum voltage by 1 V for operations from -20 to -40°C.
- (6) For ambient temperatures above 40°C the maximum control voltage must not exceed 250 VAC/VDC.
- (7) Turn-on time for Instantaneous turn-on versions is 0.1 msec.
- (8) AC input models operating range is -20 to 60 °C.
- (9) When protected with the appropriate class and rated fuse. For detailed info please contact Crydom Technical Support.
- (10) Input torque only for contactor (V,W) with screw terminals Connector.
- (11) For single surge pulse  $T_c=25^{\circ}\text{C}$ ;  $T_j=125^{\circ}\text{C}$ . For AC Output SSRs, AC RMS value of surge current equals the peak value divided by  $\sqrt{2}$  (1.414).
- (12) Minimum spacing to obtain max. current is 22.5mm between adjacent units.
- (13) For 35 Amp Relay ("U") layout models, use Pin Terminals (L 0.410 in x Ø 0.102 in) to install 8 AWG wire.
- (14) Applicable to Relay ("U") option.
- (15) Test made with a unit fixed between DIN RAIL Stoppers. Multiple devices mounted close each other, results may vary.

**⚠ DANGER / PELIGRO / DANGER /GEFAHR / PERICOLO / 危險**

|                                                                                                                                                                                                                                                                                                                                                               |                                                                                                                                                                                                                                                                                                                                                                                                     |                                                                                                                                                                                                                                                                                                                                                                                              |                                                                                                                                                                                                                                                                                                                                                                                                                             |                                                                                                                                                                                                                                                                                                                                                                                                       |                                                                                                                                         |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| <b>HAZARD OF ELECTRIC SHOCK, EXPLOSION, OR ARC FLASH.</b> <ul style="list-style-type: none"> <li>Disconnect all power before installing or working with this equipment.</li> <li>Verify all connections and replace all covers before turning on power.</li> </ul> <p><b>Failure to follow these instructions will result in death or serious injury.</b></p> | <b>RIESGO DE DESCARGA ELECTRICA O EXPLOSION.</b> <ul style="list-style-type: none"> <li>Desconectar todos los suministros de energia a este equipo antes de trabajar con este equipo.</li> <li>Verificar todas las conexiones y colocar todas las tapas antes de energizar el equipo.</li> </ul> <p><b>El incumplimiento de estas instrucciones puede provocar la muerte o lesiones serias.</b></p> | <b>RISQUE DE DESCARGE ELECTRIQUE OU EXPLOSION</b> <ul style="list-style-type: none"> <li>Eteindre toutes les sources d'énergie de cet appareil avant de travailler dessus de cet appareil</li> <li>Vérifier tous connections, et remettre tous couverts en place avant de mettre sous</li> </ul> <p><b>De non-suivi de ces instructions provoquera la mort ou des lésions sérieuses.</b></p> | <b>GEFAHR EINES ELEKTRISCHE N SCHLAGES ODER EINER EXPLOSION.</b> <ul style="list-style-type: none"> <li>Stellen Sie jeglichen Strom ab, der dieses Gerät versorgt, bevor Sie an dem Gerät Arbeiten durchführen</li> <li>Vor dem Drehen auf Energie alle Anschlüsse überprüfen und alle Abdeckungen ersetzen.</li> </ul> <p><b>Unterlassung dieser Anweisungen können zum Tode oder zu schweren Verletzungen führen.</b></p> | <b>RISCHIO DI SCOSSA ELETTRICA O DELL'ESPLOSIONE.</b> <ul style="list-style-type: none"> <li>Spenda tutta l'alimentazione che fornisce questa apparecchiatura prima di lavorare a questa apparecchiatura</li> <li>Verificare tutti i collegamenti e sostituire tutte le coperture prima dell'accensione</li> </ul> <p><b>L'omissione di queste istruzioni provocherà la morte o lesioni serie</b></p> | <p><b>存在电击、爆炸或电弧闪烁危险</b></p> <ul style="list-style-type: none"> <li>在操作此设备之前请先关闭电源。</li> </ul> <p><b>若不遵守这些说明，可能会导致严重的人身伤害甚至死亡。</b></p> |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|

**⚠ WARNING / AVERTISSEMENT / WARNUNG /ADVERTENCIA / AVVERTENZA / 警告**

|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |                                                                                                                                                                                                                                                                                                                                                                                                                                             |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>RISK OF MATERIAL DAMAGE AND HOT ENCLOSURE</b> <ul style="list-style-type: none"> <li>The product's side panels may be hot, allow the product to cool before touching.</li> <li>Follow proper mounting instructions including torque values.</li> <li>Do not allow liquids or foreign objects to enter this product.</li> </ul> <p><b>Failure to follow these instructions can result in serious injury, or equipment damage.</b></p>                                                                           | <b>RISQUE DE DOMMAGE MATERIEL ET DE SURCHAUFFE DU BOITIER</b> <ul style="list-style-type: none"> <li>Les panneaux latéraux du produit peuvent être chauds. Laisser le produit refroidir avant de le toucher.</li> <li>Respecter les consignes de montage, et notamment les couples de serrage.</li> <li>Ne pas laisser pénétrer de liquide ni de corps étrangers à l'intérieur du produit.</li> </ul> <p><b>Le non-respect de cette directive peut entraîner, des lésions corporelles graves ou des dommages matériels.</b></p> | <b>GEFAHR VON MATERIALSCHÄDEN UND GEHÄUSEERHITZUNG</b> <ul style="list-style-type: none"> <li>Die Seitenwände können heiß sein. Lassen Sie das Produkt abkühlen, bevor Sie es berühren.</li> <li>Beachten Sie die Montageanweisungen,</li> <li>Führen Sie keine Flüssigkeiten oder Fremdkörper in das Produkt ein.</li> </ul> <p><b>Die Nichtbeachtung dieser Anweisung kann Körperverletzung oder Materialschäden zur Folge haben.</b></p> |
| <b>RIESGO DE DAÑOS MATERIALES Y DE SOBRECALENTAMIENTO DE LA UNIDAD</b> <ul style="list-style-type: none"> <li>Los paneles laterales del producto pueden estar calientes. Esperar que el producto se enfríe antes de tocarlo.</li> <li>Respetar las instrucciones de montaje, y en particular los pares de apretado.</li> <li>No dejar que penetren líquidos o cuerpos extraños en el producto.</li> </ul> <p><b>Si no se respetan estas precauciones pueden producirse graves lesiones, daños materiales.</b></p> | <b>RISCHIO DI DANNI MATERIALI E D'INVOLUCRO CALDO</b> <ul style="list-style-type: none"> <li>I pannelli laterali dell'apparecchio possono scottare; lasciar quindi raffreddare il prodotto prima di toccarlo.</li> <li>Seguire le istruzioni di montaggio corrette.</li> <li>Non far entrare liquidi o oggetti estranei in questo apparecchio.</li> </ul> <p><b>La mancata osservanza di questa precauzione può causare gravi rischi per l'incolumità personale o danni alle apparecchiature.</b></p>                           | <p><b>材料损坏和高温外壳的危险性</b></p> <ul style="list-style-type: none"> <li>产品的一侧面板可能很热，在其冷却前请不要触碰。</li> <li>遵照正确的安装说明，包括扭矩值。</li> <li>请勿让液体及其他异物进入本产品。</li> </ul> <p><b>如不能正确执行这些操作说明，极有可能造成严重人体伤害或者设备的损坏。</b></p>                                                                                                                                                                                                                                  |

**ANNEX - ENVIRONMENTAL INFORMATION**

The environmental information disclosed in this annex including the EIP Pollution logo are in compliance with People's Republic of China Electronic Industry Standard SJ/T11364 – 2006, Marking for Control of Pollution Caused by Electronic Information Products.

| Part Name         | Toxic or hazardous Substance and Elements |              |              |                               |                                |                                       |
|-------------------|-------------------------------------------|--------------|--------------|-------------------------------|--------------------------------|---------------------------------------|
|                   | Lead (Pb)                                 | Mercury (Hg) | Cadmium (Cd) | Hexavalent Chromium (Cr (VI)) | Polybrominated biphenyls (PBB) | Polybrominated diphenyl ethers (PBDE) |
| Semiconductor die | X                                         | O            | O            | O                             | O                              | O                                     |
| Solder            | X                                         | O            | O            | O                             | O                              | O                                     |

**附件 - 环保信息**

此附件所标示的包括电子信息产品污染图标的环保信息符合中华人民共和国电子行业标准 SJ/T11364 - 2006, 电子信息产品污染控制标识要求。

| 部件名称  | 有毒有害物质或元素 |        |        |               |            |              |
|-------|-----------|--------|--------|---------------|------------|--------------|
|       | 铅 (Pb)    | 汞 (Hg) | 镉 (Cd) | 六价铬 (Cr (VI)) | 多溴联苯 (PBB) | 多溴二苯醚 (PBDE) |
| 半导体芯片 | X         | O      | O      | O             | O          | O            |
| 焊接点   | X         | O      | O      | O             | O          | O            |



## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9