

LTC3452EUF
SYNCHRONOUS BUCK-BOOST
MAIN/CAMERA WHITE LED DRIVER

DESCRIPTION

WARNING!**Do not look directly at operating LED.**

This circuit produces light that can damage eyes.

Demonstration circuit 928 is a SYNCHRONOUS BUCK-BOOST MAIN/CAMERA WHITE LED DRIVER featuring the LTC3452EUF.

The circuit drives two banks of LEDs: one 250mA flash device, and a bank of 5 LEDs at 20mA each for backlighting. The backlight LED currents are typically matched within 2%. The input voltage range of 2.7V to 5.5V is suitable for a single Lithium-Ion battery or three AAA batteries in series. Some of the many features include: Lithium-Ion battery input voltage range, flash LED output, separate, dimmable backlight outputs, internal synchronous power switches, minimal and low-profile external components, and simple design; therefore the LTC3452 is the top solution for highly efficient, space-constrained, cellular telephone camera flash solutions.

The flash output (LED_H) is activated by depressing The 'FLASH' momentary switch, or connecting the 'ENH' terminal to 'V_{IN}' with a jumper wire.

WARNING- The LED_H LED can be permanently damaged if the flash mode is engaged for more than a few seconds.

The backlight outputs (LED_{L1-5}) are activated by depressing The 'DISPLAY' momentary switch, or connecting the 'ENL' terminal to 'V_{IN}' with a jumper wire. The backlight intensity can be modulated by applying a 10kHz pwm signal to the 'ENL' terminal, as indicated in the table.

Figure 2 shows efficiency at 200mA flash output with various 4.7uH inductors.

The LTC3452 datasheet gives a complete description of the part along with operation and applications information. The datasheet must be read in conjunction with this Quick Start Guide for demonstration circuit 928. In addition, the Nichia NSCW100 datasheet (www.nichia.com) and the AOT2015 datasheet (www.aot.com) must be read to understand thermal and LED current constraints for varying flash current pulse-widths and intensity. The LTC3452 is offered in a small low profile QFN package. Proper board layout is essential for maximum thermal performance. See the datasheet section 'Layout Considerations'.

**Design files for this circuit board are available.
Call the LTC factory.**

LT, LTC, LTM, LT, Burst Mode, OPTI-LOOP, Over-The-Top and PolyPhase are registered trademarks of Linear Technology Corporation. Adaptive Power, C-Load, DirectSense, Easy Drive, FilterCAD, Hot Swap, LinearView, µModule, Micropower SwitcherCAD, Multimode Dimming, No Latency ΔΣ, No Latency Delta-Sigma, No R_{SENSE}, Operational Filter, PanelProtect, PowerPath, PowerSOT, SmartStart, SoftSpan, Stage Shedding, SwitcherCAD, ThinSOT, UltraFast and VLDO are trademarks of Linear Technology Corporation. Other product names may be trademarks of the companies that manufacture the products.

PERFORMANCE SUMMARY Specifications are at TA = 25°C

SYMBOL	PARAMETER	CONDITIONS	MIN	TYP	MAX	UNITS
V _{IN}	Input Supply Range		2.7		5.5	V
V _{OUT}	Output Voltage Range				4.4	V
I _{OUT}	Output Current – LED _H	V _{IN} = 2.7V to 5.5V		250		mA
I _{OUT}	Output Current – LED _{L1} through LED _{L5}	V _{IN} = 2.7V to 5.5V		20		mA each
V _{OUT P-P}	Output Ripple	V _{IN} = 4.2V, I _{OUT} = 20mA (20MHz BW)		10		mV _{P-P}
I _{REG}	Output Regulation	Line, V _{IN} = 2.7V to 5.5V		±1.0		%
F _{SW}	Switching Frequency			1.0		MHz
P _{OUT} /P _{IN}	Efficiency	V _{IN} = 4.2V, I _{OUT} = 200mA		85		%

QUICK START PROCEDURE

Demonstration circuit 928 is easy to set up to evaluate the performance of the LTC3452EUF. Refer to Figure 1 for proper measurement equipment setup and follow the procedure below:

NOTE. When measuring output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. Measure the output voltage ripple by touching the probe tip directly across the output capacitor. See Figure 2 for proper scope probe technique.

1. Preset a dc source capable of 5.5V at 1A to 4V.
2. With power off, connect the input power supply to 'VIN' and 'GND' of the circuit.
3. Turn on the power at the input. The input voltage may be varied between 2.7V and 5.5VDC.

NOTE. Make sure that the input voltage does not exceed 5.5V.

4. Press 'DISPLAY' to observe a constant 20mA x 5 LED backlight for displays.
5. Press 'FLASH' to observe a 250mA camera flash.

WARNING- The LED_H LED can be permanently damaged if the flash mode is engaged for more than a few seconds.

6. Alternatively, the backlight and flash modes can be enabled by connecting 'ENL' (backlight), or 'ENH' (flash) to 'VIN'.
7. The backlight intensity can be modulated by applying a 10kHz, 2V pwm signal to the 'ENL' terminal. Output current will vary with duty cycle, as indicated in the table on the board.




Figure 1. Proper Measurement Equipment Setup




Figure 2. Measuring Input or Output Ripple





Figure 3. Efficiency



Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9