

# HA1630S01/02/03 Series

## Ultra-Small Low Voltage Operation CMOS Single Operational Amplifier

R03DS0081EJ0200

Rev.2.00

Jan 10, 2014

### Description

The HA1630S01/02/03 are single CMOS Operational Amplifiers realizing low voltage operation, low input offset voltage and low supply current. In addition to a low operating voltage from 1.8V, these device output can achieve full swing output voltage capability extending to either supply. Available in an ultra-small CMPAK-5 package that occupies only 1/8 the area of the SOP-8 package.


### Features

- Low power and single supply operation  $V_{DD} = 1.8$  to  $5.5$  V
- Low input offset voltage  $V_{IO} = 4.0$  mV Max
- Low supply current  $I_{DD} = 15$   $\mu$ A Typ (HA1630S01)  
 $I_{DD} = 50$   $\mu$ A Typ (HA1630S02)  
 $I_{DD} = 100$   $\mu$ A Typ (HA1630S03)
- Maximum output voltage  $V_{OH} = 2.9$  V Min (at  $V_{DD} = 3.0$  V)
- Low input bias current  $I_{IB} = 1$  pA Typ


### Ordering Information

| Type No.    | Package Name | Package Code |
|-------------|--------------|--------------|
| HA1630S01CM | CMPAK-5      | PTSP0005ZC-A |
| HA1630S01LP | MPAK-5       | PLSP0005ZB-A |
| HA1630S02CM | CMPAK-5      | PTSP0005ZC-A |
| HA1630S02LP | MPAK-5       | PLSP0005ZB-A |
| HA1630S03CM | CMPAK-5      | PTSP0005ZC-A |
| HA1630S03LP | MPAK-5       | PLSP0005ZB-A |

## Pin Arrangement



## Equivalent Circuit



## Absolute Maximum Ratings

(Ta = 25°C)

| Items                      | Symbol                | Ratings                              | Unit | Note |
|----------------------------|-----------------------|--------------------------------------|------|------|
| Supply voltage             | V <sub>DD</sub>       | 7                                    | V    |      |
| Differential input voltage | V <sub>IN(diff)</sub> | -V <sub>DD</sub> to +V <sub>DD</sub> | V    |      |
| Input voltage              | V <sub>IN</sub>       | -0.3 to +V <sub>DD</sub>             | V    | 1    |
| Power dissipation          | P <sub>T</sub>        | 200                                  | mW   |      |
| Operating temp. Range      | Topr                  | -40 to +85                           | °C   |      |
| Storage temp. Range        | Tstg                  | -55 to +125                          | °C   |      |

Note: 1. Do not apply Input Voltage exceeding V<sub>DD</sub> or 7 V.

## Electrical Characteristics

(V<sub>DD</sub> = 3.0 V, Ta = 25°C)

| Items                           | Symbol                | Min         | Typ     | Max | Unit | Test Condition                      |
|---------------------------------|-----------------------|-------------|---------|-----|------|-------------------------------------|
| Input offset voltage            | V <sub>IO</sub>       | —           | —       | 4.0 | mV   | V <sub>in</sub> = 1.5 V             |
| Input offset current            | I <sub>IO</sub>       | —           | (1.0)   | —   | pA   | V <sub>in</sub> = 1.5 V             |
| Input bias current              | I <sub>IB</sub>       | —           | (1.0)   | —   | pA   | V <sub>in</sub> = 1.5 V             |
| Output high voltage             | V <sub>OH</sub>       | 2.9         | —       | —   | V    | R <sub>L</sub> = 1 MΩ               |
| Output source current           | I <sub>O SOURCE</sub> | 6           | 12      | —   | μA   | V <sub>OH</sub> = 2.5 V (HA1630S01) |
|                                 |                       | 25          | 50      | —   |      | V <sub>OH</sub> = 2.5 V (HA1630S02) |
|                                 |                       | 50          | 100     | —   |      | V <sub>OH</sub> = 2.5 V (HA1630S03) |
| Output low voltage              | V <sub>OL</sub>       | —           | —       | 0.1 | V    | R <sub>L</sub> = 1 MΩ               |
| Output sink current             | I <sub>O SINK</sub>   | —           | (0.8)   | —   | mA   | V <sub>OL</sub> = 0.5 V (HA1630S01) |
|                                 |                       | —           | (1.0)   | —   |      | V <sub>OL</sub> = 0.5 V (HA1630S02) |
|                                 |                       | —           | (1.2)   | —   |      | V <sub>OL</sub> = 0.5 V (HA1630S03) |
| Common mode input voltage range | V <sub>CM</sub>       | -0.1 to 2.1 | —       | —   | V    |                                     |
| Slew rate                       | SR                    | —           | (0.125) | —   | V/μs | C <sub>L</sub> = 20 pF (HA1630S01)  |
|                                 |                       | —           | (0.50)  | —   |      | C <sub>L</sub> = 20 pF (HA1630S02)  |
|                                 |                       | —           | (1.00)  | —   |      | C <sub>L</sub> = 20 pF (HA1630S03)  |
| Voltage gain                    | A <sub>V</sub>        | 60          | 100     | —   | dB   |                                     |
| Gain bandwidth product          | BW                    | —           | (200)   | —   | kHz  | C <sub>L</sub> = 20 pF (HA1630S01)  |
|                                 |                       | —           | (680)   | —   |      | C <sub>L</sub> = 20 pF (HA1630S02)  |
|                                 |                       | —           | (1200)  | —   |      | C <sub>L</sub> = 20 pF (HA1630S03)  |
| Power supply rejection ratio    | PSRR                  | 60          | 80      | —   | dB   |                                     |
| Common mode rejection ratio     | CMRR                  | 60          | 80      | —   | dB   |                                     |
| Supply current                  | I <sub>DD</sub>       | —           | 15      | 30  | μA   | R <sub>L</sub> = ∞ (HA1630S01)      |
|                                 |                       | —           | 50      | 100 |      | R <sub>L</sub> = ∞ (HA1630S02)      |
|                                 |                       | —           | 100     | 200 |      | R <sub>L</sub> = ∞ (HA1630S03)      |

Note: 1. ( ) : Design specification

Table of Graphs

| Electrical Characteristics        |                 |                                 | HA1630S01<br>Figure | HA1630S02<br>Figure | HA1630S03<br>Figure | Test<br>Circuit |
|-----------------------------------|-----------------|---------------------------------|---------------------|---------------------|---------------------|-----------------|
| Supply current                    | $I_{DD}$        | vs Supply voltage               | 1-1                 | 2-1                 | 3-1                 | 2               |
|                                   |                 | vs Ambient temperature          | 1-2                 | 2-2                 | 3-2                 |                 |
| Output high voltage               | $V_{OH}$        | vs Output source current        | 1-3                 | 2-3                 | 3-3                 | 4               |
|                                   |                 | vs Supply voltage               | 1-4                 | 2-4                 | 3-4                 |                 |
| Output source current             | $I_{O\ SOURCE}$ | vs Ambient temperature          | 1-5                 | 2-5                 | 3-5                 | 6               |
| Output low voltage                | $V_{OL}$        | vs Output sink current          | 1-6                 | 2-6                 | 3-6                 | 5               |
| Output sink current               | $I_{O\ SINK}$   | vs Ambient temperature          | 1-7                 | 2-7                 | 3-7                 | 6               |
| Input offset voltage              | $V_{IO}$        | Distribution                    | 1-8                 | 2-8                 | 3-8                 | 1               |
|                                   |                 | vs Supply voltage               | 1-9                 | 2-9                 | 3-9                 |                 |
|                                   |                 | vs Ambient temperature          | 1-10                | 2-10                | 3-10                |                 |
| Common mode input voltage range   | $V_{CM}$        | vs Ambient temperature          | 1-11                | 2-11                | 3-11                | 7               |
| Power supply rejection ratio      | PSRR            | vs Frequency                    | 1-12                | 2-12                | 3-12                | 1               |
| Common mode rejection ratio       | CMRR            | vs Frequency                    | 1-13                | 2-13                | 3-13                | 7               |
| Voltage gain & phase angle        | $A_v$           | vs Frequency                    | 1-14                | 2-14                | 3-14                | 10              |
| Input bias current                | $I_{IB}$        | vs Ambient temperature          | 1-15                | 2-15                | 3-15                | 3               |
|                                   |                 | vs Input voltage                | 1-16                | 2-16                | 3-16                |                 |
| Slew Rate (rising)                | SRr             | vs Ambient temperature          | 1-17                | 2-17                | 3-17                | 9               |
| Slew Rate (falling)               | SRf             | vs Ambient temperature          | 1-18                | 2-18                | 3-18                |                 |
| Slew rate                         |                 | Large signal transient response | 1-19                | 2-19                | 3-19                |                 |
|                                   |                 | Small signal transient response | 1-20                | 2-20                | 3-20                |                 |
| Total harmonic distortion + noise | (0 dB)          | vs. Output voltage p-p          | —                   | 2-21                | 3-21                | 8               |
|                                   | (40 dB)         | vs. Output voltage p-p          | —                   | 2-22                | 3-22                |                 |
| Maximum p-p output voltage        |                 | vs Frequency                    | 1-21                | 2-23                | 3-23                |                 |
| Voltage noise density             |                 | vs Frequency                    | 1-22                | 2-24                | 3-24                |                 |

## Main Characteristics (HA1630S01)

Figure 1-1. HA1630S01  
Supply Current vs. Supply Voltage




Figure 1-2. HA1630S01  
Supply Current vs. Ambient Temperature




Figure 1-3. HA1630S01  
Output High Voltage vs. Output Source Current




Figure 1-4. HA1630S01  
Output High Voltage vs. Supply Voltage





Figure 1-5. HA1630S01  
Output Source Current vs. Ambient Temperature











Figure 1-12. HA1630S01  
Power Supply Rejection Ratio vs. Frequency




Figure 1-13. HA1630S01  
Common Mode Rejection Ratio vs. Frequency




Figure 1-14. HA1630S01  
Open Loop Voltage Gain and Phase Angle vs. Frequency




Figure 1-15. HA1630S01  
Input Bias Current vs. Ambient Temperature




Figure 1-16. HA1630S01  
Input Bias Current vs. Input Voltage




Figure 1-17. HA1630S01  
Slew Rate (rising) vs. Ambient Temperature




Figure 1-18. HA1630S01  
Slew Rate (falling) vs. Ambient Temperature




Figure 1-19. HA1630S01  
Large Signal Transient Response




Figure 1-20. HA1630S01  
Small Signal Transient Response




Figure 1-21. HA1630S01  
Voltage Output p-p vs. Frequency










Figure 1-22. HA1630S01  
Voltage Noise Density vs. Frequency



## Main Characteristics (HA1630S02)

Figure 2-1. HA1630S02  
Supply Current vs. Supply VoltageFigure 2-2. HA1630S02  
Supply Current vs. Ambient TemperatureFigure 2-3. HA1630S02  
Output High Voltage vs. Output Source CurrentFigure 2-4. HA1630S02  
Output High Voltage vs. Supply VoltageFigure 2-5. HA1630S02  
Output Source Current vs. Ambient Temperature









Figure 2-12. HA1630S02  
Power Supply Rejection Ratio vs. Frequency




Figure 2-13. HA1630S02  
Common Mode Rejection Ratio vs. Frequency




Figure 2-14. HA1630S02  
Open Loop Voltage Gain and Phase Angle vs. Frequency




Figure 2-15. HA1630S02  
Input Bias Current vs. Ambient Temperature




Figure 2-16. HA1630S02  
Input Bias Current vs. Input Voltage




Figure 2-17. HA1630S02  
Slew Rate (rising) vs. Ambient Temperature




Figure 2-18. HA1630S02  
Slew Rate (falling) vs. Ambient Temperature




Figure 2-19. HA1630S02  
Large Signal Transient Response




Figure 2-20. HA1630S02  
Small Signal Transient Response




Figure 2-21. HA1630S02  
Total Harmonic Distortion + Noise vs.  
Output Voltage p-p




Figure 2-22. HA1630S02  
Total Harmonic Distortion + Noise vs.  
Output Voltage p-p




Figure 2-23. HA1630S02  
Voltage Output p-p vs. Frequency










Figure 2-24. HA1630S02  
Voltage Noise Density vs. Frequency



## Main Characteristics (HA1630S03)

Figure 3-1. HA1630S03  
Supply Current vs. Supply VoltageFigure 3-2. HA1630S03  
Supply Current vs. Ambient TemperatureFigure 3-3. HA1630S03  
Output High Voltage vs. Output Source CurrentFigure 3-4. HA1630S03  
Output High Voltage vs. Supply VoltageFigure 3-5. HA1630S03  
Output Source Current vs. Ambient Temperature









Figure 3-12. HA1630S03  
Power Supply Rejection Ratio vs. Frequency




Figure 3-13. HA1630S03  
Common Mode Rejection Ratio vs. Frequency





Figure 3-14. HA1630S03  
Open Loop Voltage Gain and Phase Angle vs. Frequency











Figure 3-21. HA1630S03  
Total Harmonic Distortion + Noise vs.  
Output Voltage p-p




Figure 3-22. HA1630S03  
Total Harmonic Distortion + Noise vs.  
Output Voltage p-p




Figure 3-23. HA1630S03  
Voltage Output p-p vs. Frequency






Figure 3-24. HA1630S03  
Voltage Noise Density vs. Frequency



## Test Circuits

### 1. Power Supply Rejection Ratio, PSRR & Voltage Offset, $V_{IO}$



$$\frac{V_{IO}}{V_{DD}}$$


$$V_{IO} = \left( V_O - \frac{V_{DD}}{2} \right) \times \frac{R_S}{R_S + R_F}$$

$$\frac{PSRR}{V_{DD}}$$


$$PSRR = -20 \log \left( \left| \frac{V_{O1} - V_{O2}}{V_{DD1} - V_{DD2}} \right| \times \frac{R_S}{R_S + R_F} \right)$$

Measure  $V_O$  corresponding to  $V_{DD1} = 1.8 \text{ V}$  and  $V_{DD2} = 5.5 \text{ V}$


### 2. Supply Current, $I_{DD}$



### 3. Input Bias Current, $I_{IB}$



### 4. Output High Voltage, $V_{OH}$




$$\frac{V_{OH}}{V_{DD}}$$

$$R_L = 1 \text{ M}\Omega$$

$$V_{IN1} = V_{DD} / 2 - 0.05 \text{ V}$$

$$V_{IN2} = V_{DD} / 2 + 0.05 \text{ V}$$

### 5. Output Low Voltage, $V_{OL}$




$$\frac{V_{OL}}{V_{DD}}$$

$$R_L = 1 \text{ M}\Omega$$

$$V_{IN1} = V_{DD} / 2 + 0.05 \text{ V}$$

$$V_{IN2} = V_{DD} / 2 - 0.05 \text{ V}$$

6. Output Source Current,  $I_{OSOURCE}$  & Output Sink Current,  $I_{OSINK}$  $I_{OSOURCE}$ 

$$V_O = V_{DD} - 0.5 \text{ V}$$

$$V_{IN1} = V_{DD} / 2 - 0.05 \text{ V}$$


$$V_{IN2} = V_{DD} / 2 + 0.05 \text{ V}$$

 $I_{OSINK}$ 

$$V_O = +0.5 \text{ V}$$

$$V_{IN1} = V_{DD} / 2 + 0.05 \text{ V}$$



$$V_{IN2} = V_{DD} / 2 - 0.05 \text{ V}$$

7. Common Mode Input Voltage,  $V_{CM}$  & Common Mode Rejection Ratio, CMRRCMRR

$$CMRR = -20 \log \left( \left| \frac{V_{O1} - V_{O2}}{V_{IN1} - V_{IN2}} \right| \times \frac{R_S}{R_S + R_F} \right)$$

Measure  $V_O$  corresponding to  $V_{IN1} = 0 \text{ V}$  and  $V_{IN2} = 2.1 \text{ V}$

## 8. Total Harmonic Distortion, THD



THD

Gain Variable

$$1 + R_F / R_S = 100$$





freq = 100 Hz, 1 kHz, 10 kHz

## 9. Slew Rate, SR

10. Gain,  $A_V$  & Phase, GBW

Package Dimensions


| JEITA Package Code | RENESAS Code | Previous Code    | MASS (Typ) [g] |
|--------------------|--------------|------------------|----------------|
| SC-74A             | PLSP0005ZB-A | MPAK-5 / MPAK-5V | 0.015          |



| Reference<br>Symbol | Dimensions in millimeters |      |      |
|---------------------|---------------------------|------|------|
|                     | Min                       | Nom  | Max  |
| A                   | 1.0                       | —    | 1.4  |
| A <sub>1</sub>      | 0                         | —    | 0.1  |
| A <sub>2</sub>      | 1.0                       | 1.1  | 1.3  |
| A <sub>3</sub>      | —                         | 0.25 | —    |
| b                   | 0.35                      | 0.4  | 0.5  |
| c                   | 0.11                      | 0.16 | 0.26 |
| D                   | 2.8                       | 2.95 | 3.1  |
| E                   | 1.5                       | 1.6  | 1.8  |
| e                   | —                         | 0.95 | —    |
| H <sub>E</sub>      | 2.5                       | 2.8  | 3.0  |
| L                   | 0.3                       | —    | 0.7  |
| L <sub>1</sub>      | 0.1                       | —    | 0.5  |
| L <sub>P</sub>      | 0.2                       | —    | 0.6  |
| x                   | —                         | —    | 0.05 |
| y                   | —                         | —    | 0.05 |
| Q                   | —                         | 0.3  | —    |

© 2013 Renesas Electronics Corporation. All rights reserved.

| JEITA Package Code | RENESAS Code | Previous Code      | MASS (Typ) [g] |
|--------------------|--------------|--------------------|----------------|
| SC-88A             | PTSP0005ZC-A | CMPAK-5 / CMPAK-5V | 0.006          |




| Reference Symbol | Dimensions in millimeters |      |      |
|------------------|---------------------------|------|------|
|                  | Min                       | Nom  | Max  |
| A                | 0.8                       | —    | 1.1  |
| A <sub>1</sub>   | 0                         | —    | 0.1  |
| A <sub>2</sub>   | 0.8                       | 0.9  | 1.0  |
| A <sub>3</sub>   | —                         | 0.25 | —    |
| b                | 0.15                      | 0.22 | 0.3  |
| c                | 0.1                       | 0.13 | 0.15 |
| D                | 1.8                       | 2.0  | 2.2  |
| E                | 1.15                      | 1.25 | 1.35 |
| e                | —                         | 0.65 | —    |
| H <sub>E</sub>   | 1.8                       | 2.1  | 2.4  |
| L                | 0.3                       | —    | 0.7  |
| L <sub>1</sub>   | 0.1                       | —    | 0.5  |
| L <sub>P</sub>   | 0.2                       | —    | 0.6  |
| x                | —                         | —    | 0.05 |
| y                | —                         | —    | 0.05 |
| Q                | —                         | 0.25 | —    |

© 2013 Renesas Electronics Corporation. All rights reserved.

## Taping & Reel Specification

### [Taping]

| Package Code | W | P | Ao   | Bo   | Ko  | E    | F   | D1   | Maximum Storage No. |
|--------------|---|---|------|------|-----|------|-----|------|---------------------|
| MPAK-5       | 8 | 4 | 3.3  | 3.3  | 1.5 | 1.75 | 3.5 | 1.05 | 3,000 pcs/reel      |
| CMPAK-5      | 8 | 4 | 2.25 | 2.45 | 1.1 | 1.75 | 3.5 | 1.05 | 3,000 pcs/reel      |




### [Reel]


| Package | Tape width | W1   | W2 |
|---------|------------|------|----|
| MPAK-5  | 8          | 11.4 | 9  |
| CMPAK-5 | 8          | 11.4 | 9  |

### [Ordering Information]

| Ordering Unit |
|---------------|
| 3,000 pcs     |



## Mark Indication



1 A □ : HA1630S01

1 B □ : HA1630S02

1 C □ : HA1630S03

□ = Control code  
(— or blank)

## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
  2. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
  3. Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of Renesas Electronics products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
  4. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from such alteration, modification, copy or otherwise misappropriation of Renesas Electronics product.
  5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; and safety equipment etc.

Renesas Electronics products are neither intended nor authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems, surgical implantations etc.), or may cause serious property damages (nuclear reactor control systems, military equipment etc.). You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application for which it is not intended. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for which the product is not intended by Renesas Electronics.
  6. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
  7. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or systems manufactured by you.
  8. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
  9. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You should not use Renesas Electronics products or technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. When exporting the Renesas Electronics products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations.
  10. It is the responsibility of the buyer or distributor of Renesas Electronics products, who distributes, disposes of, or otherwise places the product with a third party, to notify such third party in advance of the contents and conditions set forth in this document, Renesas Electronics assumes no responsibility for any losses incurred by you or third parties as a result of unauthorized use of Renesas Electronics products.
  11. This document may not be reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
  12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
- (Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.



### SALES OFFICES

### Renesas Electronics Corporation

<http://www.renesas.com>

Refer to "<http://www.renesas.com/>" for the latest and detailed information.

**Renesas Electronics America Inc.**  
2880 Scott Boulevard Santa Clara, CA 95050-2554, U.S.A.  
Tel: +1-408-588-6000, Fax: +1-408-588-6130

**Renesas Electronics Canada Limited**  
1101 Nicholson Road, Newmarket, Ontario L3Y 9C3, Canada  
Tel: +1-905-898-5441, Fax: +1-905-898-3220

**Renesas Electronics Europe Limited**  
Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, U.K  
Tel: +44-1628-651-700, Fax: +44-1628-651-804

**Renesas Electronics Europe GmbH**  
Arcadiastrasse 10, 40472 Düsseldorf, Germany  
Tel: +49-211-65030, Fax: +49-211-6503-1327

**Renesas Electronics (China) Co., Ltd.**  
7th Floor, Quantum Plaza, No.27 ZhiChunLu Haidian District, Beijing 100083, P.R.China  
Tel: +86-10-8235-1155, Fax: +86-10-8235-7679

**Renesas Electronics (Shanghai) Co., Ltd.**  
Unit 301, Tower A, Central Towers, 555 LanGao Rd., Putuo District, Shanghai, China  
Tel: +86-21-2226-0888, Fax: +86-21-2226-0999

**Renesas Electronics Hong Kong Limited**  
Unit 1601-1613, 16/F., Tower 2, Grand Century Place, 193 Prince Edward Road West, Mongkok, Kowloon, Hong Kong  
Tel: +852-2886-9318, Fax: +852 2886-9022/9044

**Renesas Electronics Taiwan Co., Ltd.**  
13F, No. 363, Fu Shing North Road, Taipei, Taiwan  
Tel: +886-2-8175-9600, Fax: +886 2-8175-9670

**Renesas Electronics Singapore Pte. Ltd.**  
80 Bendemeer Road, Unit #06-02 Hyflux Innovation Centre Singapore 339949  
Tel: +65-6213-0200, Fax: +65-6213-0300

**Renesas Electronics Malaysia Sdn.Bhd.**  
Unit 906, Block B, Menara Amcorp, Amcorp Trade Centre, No. 18, Jln Persiaran Barat, 46050 Petaling Jaya, Selangor Darul Ehsan, Malaysia  
Tel: +60-3-7955-9390, Fax: +60-3-7955-9510

**Renesas Electronics Korea Co., Ltd.**  
12F., 234 Teheran-ro, Gangnam-Gu, Seoul, 135-080, Korea  
Tel: +82-2-558-3737, Fax: +82-2-558-5141

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9