

#### PROPER USE GUIDELINES

Cumulative Trauma Disorders can result from the prolonged use of manually powered hand tools. AMP hand tools are intended for occasional use and low volume applications. AMP offers a wide selection of powered application equipment for extended—use, production operations.




Figure 1

#### 1. INTRODUCTION

AMP Crimping Die Assembly 58537-1 is designed to crimp AMP 50-Ohm RF Series BNC Dual-Crimp Connectors when used in AMP PRO-CRIMPER II Frame Assembly 354940-1.

NOTE

This tool is designed primarily for field installation, repair, maintenance work, or prototyping in industrial, commercial, or institutional applications. AMP offers a variety of tools to satisfy your performance requirements. For additional information, contact the Technical Assistance Center at 1–800–722–1111.

AMP Catalog 82074 provides a guide for cable—to—connector selection. For connectors not referenced in the catalog, contact AMP Product Engineering for recommendations.

#### 2. DESCRIPTION

\*Trademark

The die assembly consists of an indenter die and an anvil die, which when closed form three crimping

chambers. The two larger crimping chambers crimp the ferrule of the connector onto the coaxial cable, and the smaller crimping chamber crimps the center contact onto the center conductor of the coaxial cable. Each die is held in the tool jaws by a single screw. See Figure 1.

#### 3. DIE INSTALLATION (Figure 1)

- 1. Close the tool handles until the ratchet releases, then allow the tool handles to open fully.
- Install anvil die in the movable jaw of the tool frame. Align the die with the retaining screw hole, then secure die with the die-retaining screw. Do NOT fully tighten.
- 3. Install indenter die in the stationary jaw of the tool frame. Slowly close the tool handles, allowing the dies to align themselves.

NOTE

Once the anvil has entered the indenter, place a copper bus bar (1.57-mm ±0.05 mm [.062-in. ±.002 in.] diameter) into the center contact crimping chamber of the die assembly.



- 4. Close the tool handles completely.
- 5. Securely tighten both screws with the appropriate screwdriver.

#### 4. CRIMPING PROCEDURE

Select the appropriate cable size and connector. The wire size and insulation diameter must be within the specified range for the connector.

NOTE

This tool is provided with a crimp height adjustment feature. Initially, the crimp height should be verified. Refer to Section 5, CRIMP HEIGHT ADJUSTMENT, to verify crimp height before using the tool.

For detailed information on cable strip lengths and proper assembly of the connector, refer to the instructions packaged with the connector. Make sure that the connector's ferrule has been placed onto the cable, and that the cable's braided shield is flared away from the cable. Then proceed as follows:

## 4.1. Crimping the Center Contact (Figure 2)

- Close the tool handles until the dies are partially closed.
- Assemble the center contact onto the cable center conductor and place the center contact in the smallest crimping chamber of the anvil die.
   Make sure the flange on the end of the center contact butts against the die.

- 3. Holding the cable in place, close the tool handles until the ratchet releases.
- 4. Allow the tool handles to open fully and remove the crimped center contact from the dies.

## 4.2. Crimping the Ferrule (Figure 3)

- 1. Insert the crimped center contact into the connector body until the cable dielectric butts against the dielectric inside the connector body or until the center contact is securely positioned within the connector. Make sure that the braided shield is over the support sleeve of the connector body and that no strands from the shield enter the connector body.
- 2. Slide the ferrule up over the braided shield and onto the connector until the ferrule butts against the shoulder on the connector body.
- 3. Place the ferrule in the appropriate crimping chamber of the anvil die so that the shoulder on the connector body butts against the edge of the die.


NOTE

Refer to the instruction sheet packaged with the connector to determine the appropriate crimping chamber for the ferrule.

4. While holding the assembly together, begin to close the tool handles. Keep holding the assembly until the dies have closed enough to clamp the assembly in place.

CAUTION

Make sure that both sides of the ferrule are started evenly into the crimping chamber. Do NOT attempt to crimp an improperly positioned ferrule.








Figure 3

- 5. Carefully close the tool handles until the ratchet releases.
- 6. Allow the tool handles to open fully and remove the crimped connector from the dies.

## 5. CRIMP HEIGHT ADJUSTMENT (Figure 4)

The tool frame assembly ratchet mechanism features an adjustment wheel with numbered settings. If the crimp height is not acceptable, adjust the ratchet as follows:

- 1. Remove the lockscrew from the ratchet adjustment wheel.
- 2. With a screwdriver, adjust the ratchet wheel from the opposite side of the tool.
- 3. Observe the ratchet adjustment wheel. If a tighter crimp is required, rotate the adjustment wheel COUNTERCLOCKWISE to a higher-numbered setting. If a looser crimp is required, rotate the adjustment wheel CLOCKWISE to a lower-numbered setting.
- 4. Replace the lockscrew.
- Make a sample crimp and measure the crimp height. If the crimp height is acceptable, secure the lockscrew. If the dimension is unacceptable,

remove lockscrew and continue to adjust the ratchet, and again measure a sample crimp.

#### 6. MAINTENANCE AND INSPECTION

#### 6.1. Maintenance

- 1. Remove dust, moisture, and other contaminants with a clean, soft brush, or a clean, soft, lint–free cloth. Do NOT use any objects that could damage the dies or tool.
- 2. Make sure that the proper die-retaining screws are properly secured.
- 3. When the dies are not in use, store them in a clean, dry area.
- 4. Store the tool with the tool handles closed to prevent objects from becoming lodged within the jaws.

#### 6.2. Inspection

- 1. Remove all lubrication and accumulated film from the dies by immersing the dies in a suitable commercial degreaser.
- Make certain that all die-retaining screws and die components are properly secured.
- 3. Inspect the crimping surfaces for flattened, chipped, worn, or cracked areas. If damage is evident, the dies must be replaced. Refer to Section 7, REPLACEMENT.




Figure 4



## 6.3. Measuring Die Opening


The die assembly will perform correctly as long as:
(1) the product specified is correct for the application,
(2) the specific die assembly is used, (3) the die
assembly has been measured to ensure that the
openings are correct, and (4) the tool has been
adjusted correctly. Figure 5 provides information on
die opening sizes.

### 7. REPLACEMENT

AMP Crimping Die Assembly 58537–1 is inspected before shipment. AMP recommends that the dies be inspected immediately upon arrival at your facility to ensure that the dies have not been damaged during shipment.

Order replacements through your local AMP representative, or call 1~800–526–5142, or send a facsimile of your purchase order to 1–717–986–7605, or write to:

CUSTOMER SERVICE (38–35) AMP INCORPORATED P.O. BOX 3608 HARRISBURG, PA 17105–3608



DIE CLOSURE DIMENSIONS (mm [IN.])		
A	В	С
1.27±0.05 [.050±.002]	6.10±0.10 [.240±.004]	6.50±0.10 [.256±.004]

Figure 5

# **ПОСТАВКА** ЭЛЕКТРОННЫХ КОМПОНЕНТОВ

многоканальный

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

# Данный компонент на территории Российской Федерации Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

## http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

## Офис по работе с юридическими лицами:

105318, г. Москва, ул. Щербаковская д. 3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru moschip.ru\_6 moschip.ru 4 moschip.ru 9