

HDMI INTERFACE CONTROLLER FOR TFT PANEL

Model: DD-1920-HDMI

Part number: 41730010X-3

INSTRUCTIONS

CONTENTS

- Page: 2. Introduction, How to Proceed, Usage Note, Disclaimer
 - 3. System design Diagram of a suggested system
 - 4. Assembly notes Important information about system elements
 - 5. Connection & Operation How to use the controller
 - 9. Connectors, pinouts & jumpers Essential connection information
 - 16. Controller dimensions
 - **17. Application notes**
 - 19. Troubleshooting
 - 20Specifications
 - 21. Appendix I Mode Support Table
 - 22. Appendix II RS-232 control protocols
 - 26. Appendix III Appendix III DDC/CI support at HDMI port
 - 27. Appendix IV Mapping definition
 - 28. Appendix V DV remote control unit work for DD-1920-HDMI
 - 30. Warranty, Caution & Limitation of Liability, Trademarks
 - 31. Contact details

It is essential that these instructions are read and understood before connecting or powering up this controller.

Introduction

Designed for LCD monitor and other flat panel display applications, the DD-1920-HDMI controller provides easy to use HDMI interface controller for:

TFT (active matrix) LCDs with LVDS interface of 1920x1200, 1920x1080, 1920x480, 1680x1050, 1600x1200, 1400x1050, 1366x768, 1280x1024, 1280x800, 1280x768, 1024x768, 800x600, 800x480, 640x480, 480x640 resolution

> Support HDMI 1.3 input up to 1080p/WUXGA input resolution

Ordering information :

Controller	Part number	Ordering part number
DD-1920-HDMI	P/N 41730010X-3	P/N 4173001XX-3

HOW TO PROCEED

- Ensure you have all parts & that they are correct, refer to:
 - Connection diagram (separate document for each panel)
- Connector reference (in following section)
- Assembly notes
- Check controller switch & jumper settings (errors may damage the panel)
- Prepare the PC
- Connect the parts
- > Understand the operation and functions (in following section)

IMPORTANT USAGE NOTE

This product is for use by system developers and integrators, the manufacturer accepts no liability for damage or injury caused by the use of this product. It is the responsibility of the developer, integrators or other user of this product to:

- > Ensure that all necessary and appropriate safety measures are taken.
- > Obtain suitable regulatory approvals as may be required.
- Check power settings to all component parts before connection.
- Understand the operation and connectivity requirements of this controller.

DISCLAIMER

There is no implied or expressed warranty regarding this material.

SYSTEM DESIGN

A typical LCD based display system utilising this controller is likely to comprise the following:



Summary:

- 1. LCD panel
- 2. LCD controller card, DD-1920-HDMI
- 3. LVDS cable (for connection with LVDS panel)
- 4. Inverter for LCD backlight (if not built into LCD)
- 5. Inverter cable
- 6. Function controls
- 7. Function controls cable
- 8. IR sensor (Optional)
- 9. RS-232 control interface
 10. HDMI signal source
- 11. Audio output (Stereo)
- 12. Power input (12VDC)

Digital View offers a range of accessories such as listed above, to make up complete display solution.

ASSEMBLY NOTES

This controller is designed for monitor and custom display projects using 1920 x 1200, 1920 x 1080, 1920 x 480, 1680x1050, 1600x1200, 1400x1050, 1440x900, 1366x768, 1280x1024, 1280x800, 1280x768, 1024x768, 1024x600, 800x600, 800x480, 640x480, 480x640 resolution TFT panels with a VGA, SVGA, XGA, SXGA, UXGA, WUXGA signal input. The following provides some guidelines for installation and preparation of a finished display solution.

Preparation: Before proceeding it is important to familiarize yourself with the parts making up the system and the various connectors, mounting holes and general layout of the controller. As much as possible connectors have been labeled. Guides to connectors and mounting holes are shown in the following relevant sections.

- 1. LCD Panel: This controller is designed for typical LVDS interface TFT panels with panel voltage 3.3V or 5V or 12V LVDS interface. Due to the variation between manufacturers of signal timing and other panel characteristics factory setup and confirmation should be obtained before connecting to a panel. (NOTE: Check panel power jumper settings before connection)
- 2. Controller card: Handle the controller card with care as static charge may damage electronic components.
- 3. LVDS signal cable : In order to provide a clean signal it is recommended that LVDS signal cables are no longer than 46cm (18 inches). If loose wire cabling is utilized these can be made into a harness with cable ties. Care should be taken when placing the cables to avoid signal interference. Additionally it may be necessary in some systems to add ferrite cores to the cables to minimize signal noise.
- 4. Inverter: This will be required for the backlight of an LCD, some LCD panels have an inverter built in. As panels may have 1 or more backlight tubes and the power requirements for different panel models backlights may vary it is important to match the inverter in order to obtain optimum performance. See page 15 for the Application notes "Inverter connection section for more informations.
- 5. Inverter Cables: Different inverter models require different cables and different pin assignment. Make sure correct cable pin out to match the inverter. Using wrong cable pin out may damage the inverter.
- 6. OSD switch mount controls: The following section discusses the controls required and the section on connectors provides the detail. The controls are minimal: On/Off, Backlight Brightness (depends on inverter), OSD (5 momentary buttons) analog VR type or (8 momentary buttons) digital type.
- 7. OSD switch mount controls cable: The cables to the function switches should be of suitable quality and length so that impedance does not affect performance. Generally lengths up to 1 metre (3 feet) should be acceptable.
- 8. IR sensor: It is an optional part only, can be unconnected if not using IR remote control. See Appendix V for button definition.
- 9. RS-232 control interface : Firmware upgrade and serial control via this interface port.
- 10. HDMI input: Support HDMI 1.3 input up to 1080p/WUXGA resolution. Plug the HDMI cable to the connector P3 on the controller board.

11. Audio output (Stereo) from HDMI : This port support Stereo audio output (no amplification) from the HDMI audio source inputted. It requires to select the audio port "Speakers" via OSD menu under "Sound" > "Output" OSD menu page.

12. Power Input: 12VDC is required, this should be a regulated supply. Although the controller provides power regulation for the LCD power this does not relate to the power supplied to the backlight inverter. If an unregulated power supply is provided to an inverter any fluctuations in power may affect operation, performance and lifetime of the inverter and or backlight tubes.

- **Power Safety**: Note that although only 12VDC is supplied as 'power-in' a backlight inverter for panel backlighting produces significantly higher voltages (the inverter does not connect to the ground plane). We strongly advise appropriate insulation for all circuitry.
- EMI: Shielding will be required for passing certain regulatory emissions tests. Also the choice of external Controller to PC signal cable can affect the result.
- Ground: The various PCB mounting holes are connected to the ground plane.
- Servicing: The board is not user serviceable or repairable. Warranty does not cover user error in connecting up to the controller and is invalidated by unauthorized modification or repairs.
- **Controller Mounting**: It is recommended that a clearance of at least 10mm is provided above and 5mm below the controller when mounted. Additionally consideration should be given to:
 - Electrical insulation.
 - Grounding.
 - EMI shielding.
 - Cable management. Note: It is important to keep panel signal cables apart from the inverter & backlight cables to prevent signal interference.
 - Heat & Ventilation: Heat generated from other sources, for example the backlight of a very high brightness panel may generate significant heat which could adversely affect the controller.
 - Other issues that may affect safety or performance.

IMPORTANT: Please read the Application Notes section for more information

CONNECTION & OPERATION

CAUTION: Never connect or disconnect parts of the display system when the system is powered up as this may cause serious damage.

CONNECTION

Connection and usage is quite straight forward (it is useful to have the relevant connection diagram available at this time):

LCD panel & Inverter: Connect the inverter (if it is not built-in the panel) to the CCFT lead connector of the LCD panel.

LVDS type panels: Plug the LVDS signal cable direct to J3. Insert the panel end of the cable to the LCD panel connector.

Inverter & Controller: Plug the inverter cable to CNB1 and CNA1 (if necessary). Plug another end to the connector on the inverter.

Function switch & Controller: Plug the OSD switch mount cable to CNC1 on the controller board and another end to the OSD switch mount.

LED 1: Plug in a 3-way with dual colour LED to connector LED1 on the controller board for indicating the controller status.

IR & Controller: Plug in a 3-way with IR sensor to connector IR1 on the controller board.

Jumpers : Check all jumpers are set correctly. Details referring the connection diagram.

Jumpers & Inverter & Panel voltage: Particularly pay attention to the settings of JA3, JB1, JB2, JB3. JB2 & JB3 are used for inverter control (read inverter specification and information on the jumper table to define the correct settings). JA3 is used for panel voltage input (read panel specification and information on the jumper table to define the correct settings).

HDMI cable : Plug the HDMI cable to the connector P3 on the controller board.

SPDIF audio connector : audio output ports CN11 supports audio SPDIF audio output from HDMI audio source inputted. It requires to select the audio port "SPDIF" via OSD menu under "Sound" > "Output" OSD menu page.

Audio output (Stereo) from HDMI : audio output port CN1 supports Stereo audio output (no amplification) from the HDMI audio source inputted. It requires to select the audio port "Speakers" via OSD menu under "Sound" > "Output" OSD menu page.

Power supply & Controller: Plug the DC 12V power in to the connector PP2. You can consider to use DigitalView mating power cable P/N 426013800-3, 160mm.

Power on: Switch on the controller board and panel by using the OSD switch mount.

CAUTION: Never connect or disconnect parts of the display system when the system is powered up as this may cause serious damage.

Controller LED status (LED1) :

State	LED color
No signal & backlight off	RED
No signal & backlight on	ORANGE
With signal & backlight on	GREEN

General:

- If you are using supplied cables & accessories, ensure they are correct for the model of panel and controller.
- If you are making your own cables & connectors refer carefully to both the panel & inverter specifications and the section in this manual, "Connectors, Pinouts & Jumpers" to ensure the correct pin to pin wiring.

OPERATION

Once the system has been connected and switched on there are a number of functions available to adjust the display image as summarized in the following sections. The settings chosen will be saved for each mode independently.

LCD DISPLAY SYSTEM SETTINGS

NOTE: By way of explanation the following refers to a set of sample buttons that may be obtained as an option. In addition to power on/off and connection for backlight brightness the controller provides an On Screen Display of certain functions which are controlled by 5 momentary type buttons (analog VR type) or 8 momentary type buttons (digital type):

Controls	Analog VR type	Digital type
On/Off – turns controller board power on	VR toggle switch	On/Off button
Brightness – controls backlight brightness	Rotary VR	Brightness +/- buttons
Menu – turns OSD menu On or Off (it will auto time	Menu button	Menu button
off) (Function with signal input		
only)		
Select – Select function / Confirm	SEL DN	SEL DN
(under OSD menu on state)		
Move up to select individual RGB color level OSD	SEL UP	SEL UP
page		
(under OSD menu on state)		
+ – increase the setting / moves the selector to the	+	+
next function		
(under OSD menu on state)		
decrease the setting / moves the selector to the	-	-
previous function		
(under OSD menu on state)		
Reset to Factory Defaults	Press and hold SEL DN	Press and hold SEL DN button,
	button, then power on the	then power on the controller
	controller	
Switch to next input source	+	+
(under OSD menu off state)		







Digital type

Image				
 濛	Brightness	Increase/decrease brightness level. Press – or + (-		
0	Contrast	Increase/decrease contrast level. Press – or + (- +) Total : 100 steps		
	Sharpness	Increase/decrease sharpness level. Press – or + (-		
	Color	Color temp (Adjust the warmness of the image displayed. The higher temperature the coolest image looks like. The lower temperature the warmest image looks like.) 4200k 5000k 6500k 7500k 9300k User R Press - or + (- R Press - or + (- H) Total : 100 steps B Press - or + (- H) Total : 100 steps B Press - or + (- H) Total : 100 steps Reset Gamma (0.4/0.6/1.0/1.6/2.2)		
Display				
濛	Backlight**			
	Invert	B/L Invert : Invert for the backlight brightness		
	Control	D/A / PWM : Selection for voltage level dimming control / PWM dimming control		
	Frequency	Backlight frequency 100 ~ 440Hz in a step of 20		
	B/L	Backlight brightness adjustment		
1280 1366	Widescreen n	node >		
	DDC program	ming Video timing CVT timing [Please refer to application note for this function details]		

Ő	Sound				
	₽	Mute	Mute		
	چ	Output	Select audio output port Speakers : via CN1 & J1 connector SPDIF : via CN11 connector		
	System				
A.C.	Û	Timer : OSD Timeout in seconds 3 sec 6 sec 12 sec Always On			
		Rotation : OSD menu rotation in degree 0 90 180 270			
	↔ menu	Position : Adjust OSD menu position			
	MENU Menu	Transparency : Set OSD transparency Press – or + (- +) Total : 100 steps			
	CEFI+ AIL+ III	Reset : Load factory default settings. Press down on OSD keypad to factory reset			

[Firmware version : V1.07.00 or up]

Remark : Items marked I have sub menus. Exit the OSD menu to save the setting chosen



CONNECTORS, PINOUTS & JUMPERS

The various connectors are:



Summary: Connectors

Ref	Purpose	Description
CN1	Audio output (Stereo) from HDMI	JST 4-way, S4B-ZR-SM4A (Mating type : ZHR-4)
		(Matching connection cable P/N 426685400-3)
CN8	Serial control	Molex 53261-0671, 6 ways 1.25mm pitch
		(Mating type : Molex 51021-0600)
		(Matching connection cable P/N 426171800-3)
CNA1	Auxiliary power output	JST 4-way, S4B-XH-A (Mating type : XHP-4)
		(Matching cable P/N 426040200-3)
CNB1	Backlight inverter	JST 5-way, S5B-XH-A (Mating type : XHP-5)
		(Matching cable P/N 426058300-3)
CNC1	OSD controls	Hirose DF13A-12P-1.25H (Mating type : DF13-12S-1.25C)
		(Matching OSD switch mount cable P/N 426122200-3 (150mm) or P/N
		426122210-3 (250mm)
IR1	Infra-Red sensor connector	Molex 53261-0371, 3 way 1.25mm pitch (Mating type : 51021-0300)
		(Matching connection cable P/N 426031500-3)
P3	HDMI signal input	HDMI connector (Type A)
J3	LVDS panel signal	JAE FI-RE51S-HF (Mating type : JAE FI-RE51HL)
PP2	Power input	Molex 43650-0200 compatible (Mating type : Molex 43645-0200
		compatible)
		(Matching power cable : P/N 426013800-3, 160mm)

Summary: Jumpers setting

Ref	Purpose	Note
JA1	On board +5V logic power enable	1-3 & 2-4 closed, factory set, do not remove
JA3	Panel power voltage select	See panel voltage setting table 1 CAUTION: Incorrect setting will cause panel damage
JB1	Backlight brightness voltage range	1-2 closed = 3.3V max 2-3 closed = 5V max
JB2	Backlight inverter on/off control – signal level	1-2 = On/Off control signal 'High' = +12V 2-3 = On/Off control signal 'High' = +5V Open = On/Off control signal 'High' = Open collector CAUTION : Incorrect setting can damage inverter.
JB3	Backlight inverter on/off control – polarity	1-2 = control signal 'high' = CCFT ON 2-3 = control signal 'low' = CCFT ON
JB5	Backlight control type selection	 1-2 = VR/Digital switch mount control 3-4 = Analog backlight brightness control via RS-232 command (0xe0) – voltage range 0~5V 5-6 = PWM (Pulse Width Modulation) brightness
JP1	Reserved	Reserved for internal programming use (Always 1-2 closed)
JP6	Input power control	Short = External switch control Open = Switch mount control
SW1	Panel selection	See table below
SW2	Panel selection	See table below

Table 1 : Panel voltage setting table :

Input voltage via PP2	Panel Voltage	JA3	Jumper on board
	3.3V	3-4 closed	JA3
12VDC	5V	1-2 closed	
	12V	OPEN	

CAUTION: Incorrect setting can damage panel & controller



Pos #1	Pos #2	Pos #3	Pos #1	Description	Panel resolution
1 03 #1	103 #2	103 #5	1 03. 1	For WUXGA papel	
OFF	OFF	OFF	OFF	Samsung LTM220CS01	1920x1200
011	011	011	011	AU Optronics B170UW02 V0	1920x1200
ON	OFF	OFF	OFF	AU Optronics M215HW01	1920x1080
				Samsung LTM230HT01	1920x1080
OFF	ON	OFF	OFF	Samsung LTI400HA01	1920x1080
		•		For UXGA panel	
ON	OFF	OFF	OFF	NEC NL160120BC27-14	1600x1200
				For WXGA panel	
ON	OFF	OFF	OFF	Samsung LTA260W2-L01	1366x768
ON	ON	OFF	OFF	Samsung LTA460WS-L03	1366x768
OFF	OFF	ON	OFF	Sharp LQ315T3LZ24 /	1366x768
	011	011	011	AU Optronics M156XW01 V0	10000100
ON	OFF	ON	OFF	LG LC420W02-A4	1366x768
OFF	ON	ON	OFF	NEC NL12880BC20-02D	1280x800
OFF	ON	OFF	OFF	NEC NL12876BC26-21	1280x768
ON	ON	ON	OFF		1680x1050
		055			4000-4004
					1280x1024
				Fujitsu FLC485XC8V	1280x1024
			ON	Sharp LQ181E1LW31	1280x1024
				ALL Optropics M100EC01	1200x1024
UFF	UFF	UN	UN	For XCA papel	128081024
	OFF	ON	ON		1024×768
				LG LM151X2	1024x700
			ON	Sharp O150X1LGB1	1024x768
		011		Sharp LQ150X1LOD1	1024x768
ON	OFF	ON	ON	NEC NI 10276BC12-02	1024x768
OFF	ON	ON	ON	NEC NI 10276BC13-01C	1024x768
ON	ON	ON	ON	NEC NL10276BC30-18/ 30-18C	1024x768
				NEC NL10276BC20-08	1024x768
For SVGA panel					
OFF	OFF	ON	OFF	PrimeView PD104SL5H2	800x600
				Sharp LQ121S1DG11	800x600
				Sharp LQ104S1DG21	800x600
				Sharp LQ121S1DG41	800x600
ON	OFF	ON	OFF	Toshiba LTM12C289	800x600
OFF	ON	ON	OFF	Sharp LQ084S3DG01	800x600
ON	ON	OFF	OFF	Sharp LQ121S1LG41	800x600
				NEC NLOUDUBCZ1-UZ	800v600
				Sharp LQ104S1DG21	800x600
					000X000
			UN		000000
ON	OFF	ON			800~180
	OFF	OFF	ON	Sharp I 0070V3I G44	800x480
	UFF			Others	0000400
ON	OFF	OFF	ON		1920×480
ON	ON	ON	OFF	AU Optronics M200RW/01 V/1	1600x900
ON	OFF	OFF	OFF	Sharp I Q150F1LH22	1400x1050
ON	ON	OFF	OFF	Samsung LTM190M2-L31	1440x900
ON	OFF	ON	OFF	IGIM171WX3-TLA1	1440x900
OFF	ON	ON	OFF	LGLM171WX3	1440x900
OFF	OFF	ON	OFF	CPT CLAA102NA0ACW	1024x600
					102-70000

For additional and recent added panels, please contact us to support.

Pos #5	Pos #6	Pos #7	Description
OFF	OFF	OFF	WUXGA
ON	OFF	OFF	UXGA
OFF	ON	OFF	SXGA
ON	ON	OFF	WXGA
OFF	OFF	ON	XGA
ON	OFF	ON	SVGA
OFF	ON	ON	VGA / WVGA
ON	ON	ON	Others

SW1 Pos 8 = Reserved.

DIP switch selection – SW1

Pos. #	Function	Description
1	Panel pixel format	OFF : Double Pixel
		ON : Single Pixel
2	LVDS data mapping select	ON : Mapping A (LVDS panel)
		OFF : Mapping B (LVDS panel)
		Please adjust to get the correct picture. See as Appendix III for details of
		mapping A and B.
3	Reserved	Reserved
4	Operating mode selection	OFF : General application
		ON : Work with RM-DN5 (firmware version E1.12.10a) from HDMI port [#]

Remark :

Assign SW1 position 4 to ON for connection to RM-DN5 (Firmware version : E1.12.10a) from HDMI port with the following changes :
Add "Loading..." message on screen while startup and stay until the valid signal.
Changed the default Auto Source Seek to Off
Changed the IR key from "Display" key to "OSD Next" key for menu function
Extend longer delay time approx. (4 secs) to detect signal for "No Signal" state
Only HDMI input and disabled all other "Source" selections in OSD, IR hotkeys & RS-232 for RM-DN5 mode

CN1 – Audio output (Stereo) from HDMI : JST 4-way, S4B-ZR-SM4A

		(Mating type : ZHR-4)
PIN	SYMBOL	DESCRIPTION
1	AMP L-	Audio Left channel (Negative)
2	AMP L+	Audio Left channel (Positive)
3	AMP R-	Audio Right channel (Negative)
4	AMP R+	Audio Right (Positive)

CN8 – RS-232 serial control: Molex 53261-0671, 6 ways 1.25mm pitch (Matching type : Molex 51021-0600)

PIN	SYMBOL	DESCRIPTION
1	SDATA	Reserved
2	SCLK	Reserved
3	VCC	+5V
4	TXD	RS-232 Tx data
5	GND	Ground
6	RXD	RS-232 Rx data

CNA1 - Auxiliary power output: JST S4B-XH-A		(Matching type : XHP-4)
PIN	SYMBOL	DESCRIPTION
1	AUX POWER	+12V DC, 500mA max
2	GND	Ground
3	GND	Ground
4	AUX 5V	+5V DC, 500mA max

CNB1 – Backlight inverter connector: JST S5B-XH-A		er connector: JST S5B-XH	-A (Matching type : XHP-5)
PIN		SYMBOL	DESCRIPTION
1		GND	Ground
2		VBKL	Backlight power supply, +12VDC, 3A max
3		BLCTRL	Backlight On/Off control signal (refer to JB2 & JB3)
4		BVR_WIP	Backlight brightness VR pin WIP
5		BVR_A	Backlight brightness VR pin A

NC1 – OSD switch mount control, Hirose DF13A-12P-1.25H (Mating type : DF13-12S-1.25C)		
PIN	SYMBOL	DESCRIPTION
1	PSWIN	Power button A
2	SW_ON	Power button B
3	BVR_A	Backlight Brightness VR pin A
4	BVR_WIP	Backlight Brightness R pin WIP
5	BVR_B	Backlight Brightness VR pin B (470 ohm resistor to +5V Vcc)
6	GND	Ground
7	MENU	OSD menu
8	-/LEFT	OSD -/Left
9	+/RIGHT	OSD +/Right
10	SEL_DN	OSD Select down
11	SEL_UP	OSD Select up
12	NC	No connection

IR1 – Infra-Red sensor connector: Molex 53261-0371, 3 way 1.25mm pitch (Matching type : Molex 51021-0300)

PIN	SYMBOL	DESCRIPTION
1	GND	Ground
2	STDBY_Vcc	Stand by voltage
3	IR Data	IR data

J1 – HDMI connector: JST SM20B-SRDS (Matching type : JST SHDR-20V-S-B)

PIN	SYMBOL	DESCRIPTION
1	GND	Ground
2	GND	Ground
3	RXC+	TMDS Data C+
4	RXC-	TMDS Data C-
5	RX0+	TMDS Data 0+
6	RX0-	TMDS Data 0-
7	RX1+	TMDS Data 1+
8	RX1-	TMDS Data 1-
9	RX2+	TMDS Data 2+
10	RX2-	TMDS Data 2-
11	GND	Ground
12	GND	Ground
13	MSTR2_SCL	Reserved
14	MSTR2_SDA	Reserved
15	DDC_5V	+5V power supply for DDC (optional)
16	HPD	Hot plug detection
17	DDC_SCL	DDC serial clock
18	DDC_SDA	DDC Data
19	VCC1	VCC 5V output
20	VCC2	VCC 5V output

J3 – LVDS output connector: JAE FI-RE51S-HF (Matching type : JAE FI-RE51HL)

PIN	SYMBOL	DESCRIPTION	
1	VDD (+12V)	Panel power supply (+12V) (selected by JA3)	
2	VDD (+12V)	Panel power supply (+12V) (selected by JA3)	
3	VDD (+12V)	VDD (+12V) Panel power supply (+12V) (selected by JA3)	
4	VDD (+12V)	Panel power supply (+12V) (selected by JA3)	
5	VDD (+12V)	Panel power supply (+12V) (selected by JA3)	
6	VDD (3,3V/5V)	Panel power supply (3,3V/5V) (selected by JA3)	
7	VDD (3,3V/5V)	Panel power supply (3,3V/5V) (selected by JA3)	
8	VDD (3,3V/5V)	Panel power supply (3,3V/5V) (selected by JA3)	
9	VDD (3,3V/5V)	Panel power supply (3,3V/5V) (selected by JA3)	
10	VDD (3,3V/5V)	Panel power supply (3,3V/5V) (selected by JA3)	
11	GND	Ground	
12	GND	Ground	
13	GND	Ground	
14	GND	Ground	
15	GND	Ground	
16	NC	No connection	
17	NC	No connection	
18	NC	No connection	
19	NC	No connection	
20	GND	Ground	
21	GND	Ground	
22	NC	No connection	
23	NC	No connection	
24	TXA3+	Positive differential LVDS data bit A3	
25	TXA3-	Negative differential LVDS data bit A3	
26	GND	Ground	
27	TXAC+	Positive LVDS clock for A channel	
28	TXAC-	Negative LVDS clock for A channel	
29	GND	Ground	
30	TXA2+	Positive differential LVDS data bit A2	
31	TXA2-	Negative differential LVDS data bit A2	
32	TXA1+	Positive differential LVDS data bit A1	
33	TXA1-	Negative differential LVDS data bit A1	
.34	TXA0+	Positive differential LVDS data bit A0	
35	TXA0-	Negative differential LVDS data bit A0	
36	GND	Ground	
37	NC	No connection	
38	NC	No connection	
30	TXB3+	Positive differential LVDS data bit B3	
40	TYB3-	Negative differential LVDS data bit B3	
40	GND	Ground	
41		Positive LVDS clock for R channel	
42			
43			
44	GND	Ground	
45	I XB2+	Positive differential LVDS data bit B2	
46	TXB2-	Negative differential LVDS data bit B2	

47	TXB1+	Positive differential LVDS data bit B1
48	TXB1-	Negative differential LVDS data bit B1
49	TXB0+	Positive differential LVDS data bit B0
50	TXB0-	Negative differential LVDS data bit B0
51	GND	Ground

LED1 – Dual color LED o	onnector for controller status, JST 3-way, S3B-ZR-SM4A	(Mating type : JST ZHR-3)
PIN	DESCRIPTION	
1	Green LED pin (anode)	
2	LED pin common (cathode)	
3	Red LED pin (anode)	

P	P2 - Power supply	(Mating type : Molex 43645-0200 compatible)
	PIN	DESCRIPTION
	1	+12VDC 5A max
	2	Ground

P3 – HDMI connector

• • • • • • • • • • • • • • • • • • • •		
PIN	SYMBOL	DESCRIPTION
1	DATA2+	TMDS Data2+
2	DATA2S	TMDS Data2 Shield
3	DATA2-	TMDS Data2–
4	DATA1+	TMDS Data1+
5	DATA1S	TMDS Data1 Shield
6	DATA1-	TMDS Data1–
7	DATA0+	TMDS Data0+
8	DATA0S	TMDS Data0 Shield
9	DATA0-	TMDS Data0–
10	CLK+	TMDS Clock+
11	CLK@	TMDS Clock Shield
12	CLK-	TMDS Clock–
13	CEC	CEC
14	NC	No connection
15	SCL	SCL (<u>I²C</u> Serial Clock for <u>DDC</u>)
16	SDA	SDA (<u>I²C</u> Serial Data Line for <u>DDC</u>)
17	CEC/GND	Ground
18	+5V	+5 V Power (max 50 mA)
19	HPDET	Hot Plug Detect

CONTROLLER DIMENSIONS



The maximum thickness of the controller is 13.95mm (measured from bottom of PCB to top of components, including any underside components & leads). We recommend clearances of:

- 5mm from bottom of PCB if mounting on a metal plate we also recommend a layer of suitable insulation material is added to the mounting plate surface.
- 10mm above the components
- 3~5mm around the edges

Any of the holes shown above can be used for mounting the PCB, they are 3.2mm in diameter.

CAUTION: Ensure adequate insulation is provided for all areas of the PCB with special attention to high voltage parts such as the inverter.

APPLICATION NOTES

USING THE CONTROLLER WITHOUT BUTTONS ATTACHED

This is very straightforward by following the steps below :

- Firstly setup the controller/display system with the buttons. With controls attached and display system active make any settings for colour and image position as required then switch everything off.
- Use a jumper to close JP6 jumper, this will fix the board On.
- Refer to inverter specifications for details as to fixing brightness to a desired level, this may require a resistor, an open circuit or closed circuit depending on inverter.

INVERTER CONNECTION

There are potentially 3 issues to consider with inverter connection:

- Power
- Enable
- Brightness

Please read the following sections for a guide to these issues.

Inverter Power: As per the table for CNB1 pin 1 is ground and pin 2 provides 12VDC. This should be matched with the inverter specification: see table.

CNB1

PIN	DESCRIPTION	
1	Ground	
2	+12VDC	

Remark: For higher power inverter, more current for 12V can be taken from CNA1 pin 1. Maximum current drawn on CNA1 pin 1 and CNB1 pin 2 is 3A(12V)

Enable: This is a pin provided on some inverters for On/Off function and is used by this panel controller for VESA DPMS compliance. If the inverter does not have an enable pin or the enable pin is not used then DPMS will not be operational. Pin 3 should be matched to the inverters specification for the 'enable' or 'disable' pin.

CNB1

PIN	DESCRIPTION
3	Enable

Further, jumpers JB2 & JB3 should be set to match the inverters specification for the enable pin power and High or Low setting: see table.

Ref	Purpose	Note
JB2	Inverter enable voltage	1-2 H = 12V, 2-3 H = 5V (Vcc), OPEN H = open collector
JB3	Inverter control	1-2 H = On, 2-3 L = On

Brightness: There are various methods for brightness control and it is important to consider the specifications for the inverter to be used. Generally the situation is:

Brightness can controlled by using a resistor or VR (Variable Resistor).

- Brightness controlled by adding a circuit such as PWM (Pulse Width Modulation).
- No adjustment of brightness is possible.

CNB1 pins 4 & 5 are available for connecting to an inverter or circuit where VR control is supported.

CNB1

INB1	
PIN	DESCRIPTION
4	VR WIP
5	VR A

This can then be matched with function controls (OSD switch mount) pins 3 & 4: see cable design below .

DIGITALVIEW[®] Design Guideline for making VR circuitry :



Signal description / Notes :

available at CNC1 pin 6).

 R1 : 470ohm on board
 RPOT is an external potentiometer (in-line dip style) that can be plugged directly into CNC1 pins 3,4,5. RPOT must be supplied / installed by user.
 BVR_B : Voltage tapped from "top" of potentiometer, the node of R1 and RPOT.
 BVR_WIP : Voltage tapped from wiper arm of RPOT.
 BVR_A : Voltage tapped from "bottom" of RPOT.
 BVR_A : Voltage tapped from "bottom" of RPOT.
 BVR_A : Voltage is left floating on the controller board. To use this circuit, you need to tie this point to a potential (usually GND,

CNB1 – Backlight inverter connector: JST B5B-XH-A (Matching type : XHP-5)

PIN	SYMBOL	DESCRIPTION	
1	GND	Ground	
2	VBKL	+12VDC, backlight power supply (selected by JA3 & JA6)	
3	BLCTRL	On/Off control (enable) – see JB2 & JB3	
4	BVR_WIP	Brightness VR - WIP	
5	BVR_A	Brightness VR A	

CNC1 – Control switch, JST B12B-XH-A (Matching type : XHP-12)

PIN	SYMBOL	DESCRIPTION	
1	PSWIN	Power button A	
2	SW_ON	Power button B	
3	BVR_A	Backlight Brightness VR pin A	
4	BVR_WIP	Backlight Brightness R pin WIP	
5	BVR_B	Backlight Brightness VR pin B (470 ohm resistor to +5V Vcc)	
6	GND	Ground	
7	MENU	OSD menu	
8	-/LEFT	OSD -/Left	
9	+/RIGHT	OSD +/Right	
10	SEL_DN	OSD Select down	
11	SEL_UP	OSD Select up	
12	NC	No connection	

The VR for brightness depends on the inverter. The main power load for On/Off is handled by a relay on the controller. **Example for circuit design :**

1.) Choose RPOT = 10K

2.) Tie BVR_A to GND

3.) Circuit analysis gives BVR_WIP as the following (see Figure 1)

 $BVR_WIP = 5 x (Rbc/10.47)$

where BVR_WIP is in Volts. And Rbc is the resistance from the wiper arm to bottom of pot in Kohms.

To evaluate, plug in different values of Rbc :

Rbc	BVR_WIP
0	0 V
2.5 K	1.2 V
5 K	2.4 V
7.5 K	3.6 V
10 K	4.8 V

So this circuit could provide Brightness adjust voltage ranging from 0V to 5V.



rage 18 01 32

TROUBLESHOOTING

General

- A general guide to troubleshooting a flat panel display system it is worth considering the system as separate elements, such as:
- Controller (jumpers, PC settings)
- Panel (controller, cabling, connection, panel, PC settings)
- Backlight (inverter, cabling, backlight tubes)
- Cabling
- Computer system (display settings, operating system)

Through step by step cross checking with instruction manuals and a process of elimination to isolate the problem it is usually possible to clearly identify the problem area.

No image:

- > If the panel backlight is not working it may still be possible to just see some image on the display.
- > A lack of image is most likely to be caused by incorrect connection, lack of power, failure to provide a signal or incorrect graphic card settings.

Image appearance:

- > A faulty panel can have blank lines, failed sections, flickering or flashing display
- Incorrect graphics card refresh rate, resolution or interlaced mode will probably cause the image to be the wrong size, to scroll, flicker badly or possibly even no image.
- Incorrect jumper settings on the controller may cause everything from total failure to incorrect image. CAUTION: Do not set the panel power input incorrectly.
- > Sparkling on the display: faulty panel signal cable.

Backlight:

Items to check include: Power input, Controls, Inverter and Tubes generally in this order.

- If half the screen is dimmer than the other half:
- Check cabling for the inverter.
- > For a specific backlight tube check the AC pins orientation (CAUTION: Never reverse any DC power pins).

Also:

- If adjusting brightness control has no effect the chances are that the VR rating or method of adjusting brightness is not compatible or correctly connected to the inverter.
- > If system does not power down when there is a loss of signal

Continued failure:

If unit after unit keeps failing consider and investigate whether you are short circuiting the equipment or doing something else seriously wrong.

Generally after common sense issues have been resolved we recommend step by step substitution of known working parts to isolate the problem.

SPECIFICATIONS

Panel compatibility	1920x1200, 1920x1080, 1680x1050, 1600x1200, 1400x1050, 1440x900,
	1366x768, 1280x1024, 1280x800, 1280x768, 1024x768, 1024x600,
	800x600, 800x480, 640x480, 480x640 resolution TFT LVDS LCD's support.
No. of colours	Up to 3 x 8 bit providing 16.7 million colours.
Vertical refresh rate	WUXGA, UXGA, WXGA, SXGA, XGA, SVGA, VGA resolution up to 60Hz.
Dot clock (pixel clock) maximum	165 MHz
Graphics formats	Standard WUXGA, UXGA, SXGA, XGA, SVGA, VGA
Standard input at source	- HDMI
Controls available	- On/Off
	- Brightness (inverter)
	- OSD menu
	- OSD select
	- OSD setting +
	- OSD setting -
Control interface	- Buttons, RS-232, IR remote control
Settings memory	Settings are stored in non volatile memory
Language OSD support	Graphics OSD icons
Voltage output for LCD	+3.3V, +5V, +12V
	The current drawn for 3.3V, 5V or 12V panel from 12VDC power input is
	limited to 3A.
Input voltage	12VDC , 5A max +/- 5%
Controller power consumption	Approx 4W (controller logic only, no panel and inverter are involved)
Controller dimensions	62.7mm x 91.4mm x 13.8mm
Storage temperature limits	-40°C to +70°C
Operating temperature limits	0°C to +60°C

NOTES

Please note the following:

• For specific panel setup a sample of an LCD may be required (this will be returned) and a copy of the full technical specifications for the panel from the manufacturer.

• Re-layout and custom development services are available.

Appendix I – Mode Support Table

HDMI (P3) port :

Mode	Resolution	Clk	Horizontal	Vertical
		[MHz]	freq	freq [Hz]
			[KHz]	
V_60	640x480 60Hz	25.175	31.469	59.940
SV_60	800x600 60Hz	40.000	37.879	60.317
X_60	1024x768 60Hz	65.000	48.363	60.004
SX_60	1280x1024 60Hz	108	63.81	60.020
UX_60	1600x1200 60Hz	162	75.000	60
WUX_60	1920x1080 60Hz	172.8	67.5	60
WUX_60	1920x1200 60Hz	193.2	74.5	60
1080p60	1920x1080p 60Hz	135	67.5	60
1080i60	1920x1080i 60Hz	74.14	33.7	60
1080i50	1920x1080i 50Hz	74.184	28.1	50
720p60	1280x720P 60Hz	74.25	45	60
576p50	720x576P 50Hz	26.9568	31.2	50
480p60	720x480P 60Hz	26.9568	31.4	60

Appendix II - RS-232 control protocols

RS-232 Serial control (Baud rate 2400, 8 bits, 1 stop bit and no parity) *Physical connection :*

Controller side Connector interface : CN8 Mating connector : Molex 51021-0600

654321 Mating face of CN8

PIN#	Description	
4	RS-232 Tx Data	
5	Ground	
6	RS-232 Rx Data	

Computer side Connector interface : Serial port Mating connector : DB9 Female $\overbrace{\left(\begin{array}{c}1&2&3&4\\6&7&8&9\end{array}\right)}^{\left(1&2&3&4\\6&7&8&9\end{array}}$ Matin

> Description RS-232 Rx Data

RS-232 Tx Data

Ground

PIN#

2

5

Mating face of RS-232 DB9 Male

Software connection :

The OSD function can be controlled through sending the RS-232 protocol. The RS-232 program can be custom-made to fit for application or it can be used the program provided by Digitalview on request. Please contact your local sales for informations.

1. Commands to implement switch mount control buttons

Function	Command	Description	Acknowledge (if enabled)
Menu	0xf7	Menu button pressed	Button equivalent
Select-down	0xfa	Select down button	Button equivalent
button		pressed	
Select-up	0xfb	Select up button pressed	Button equivalent
button			
Right/+ button	Oxfc	Right/+button pressed	Button equivalent
Left/- button	0xfd	Left/- button pressed	Button equivalent

2. Parameter setting - immediate, relative, reset and query

Function	Command	Description	Acknowledge (if enabled)
Brightness	0x81,	Set brightness =	Brightness.
control	nn "+" "-"	value/increment/decrement	
	"r" "R"	Reset	Range: "0""0"-"6""4"
	"?"	Query	Default: "3""2"
Contrast	0x82, "a" "A",	Set all contrast =	Contrast.
control	nn "+" "-"	value/increment/decrement	
	"r" "R"	Reset	Range: "4""0"-"6""4"
	"?"	Query	Default: "3""2"
Sharpness	0x8a,	Set sharpness=	Sharpness
	nn "+" "-" "r"	value/increment/decrement	
	"R"	Reset	Range: "F""C"-"0""4"
	"?"	Query	Default: "0""0"
OSD H position	0x90,	Set osd_hpos =	OSD horizontal position
	nnn "+" "-"	value/increment/decrement	
	"r" "R" "?"	Reset	Range: "0""0""0"-"3""E""8"
		Query	Default: "1""F""4"
OSD V position	0x91,	Set osd_vpos =	OSD vertical position
	nnn "+" "-"	value/increment/decrement	
	"r" "R" "?"	Reset	Range: "0""0""0"-"3""E""8"
		Query	Default: "1""F""4"
Select menu	0x93,	Select menu timeout =	OSD menu timeout value.

timeout	nn "+" "-" "r" "R" "?"	value/increment/decrement Reset Query	"00" – Continuous. Value – Round up to nearest available step. If value > max available step, set it to the max available step. "0" "0" – Always On. "0" "C" – 12 seconds (Default) "0" "6" – 6 seconds "0" "3" – 3 seconds
GAMMA value select	0x9d, n "r" "R" "?"	Select GAMMA value = Value Reset Query	GAMMA value: "0" – 0.4, "1" – 0.6 "2" – 1.0 (Default), "3" – 1.6 "4" – 2.2
Colour temperature select	0xb3, n "r" "R" "?"	Select colour temperature = value Reset Query	Main selected. "0" – user defined RGB values. "1" – 4200K. "2" – 5000K. "3" – 6500K. "4" – 7500K. (Default) "5" – 9300K.
Red level for selected colour temperature	0xb4, nn "+" "-" "r" "R" "?"	Set the level of the red channel for the selected colour temp. = value/increment/decrement Reset Query	Red level for selected colour temperature. Range: "0""0"-"6""4" Default: "6""4"
Green level for selected colour temperature	0xb5, nn "+" "-" "r" "R" "?"	Set the level of the green channel for the selected colour temp. = value/increment/decrement Reset Query	Green level for selected colour temperature. Range: "0""0"-"6""4" Default: "6""4"
Blue level for selected colour temperature	0xb6, nn "+" "-" "r" "R" "?"	Set the level of the blue channel for the selected colour temp. = value/increment/decrement Reset Query	Blue level for selected colour temperature. Range: "0""0"-"6""4" Default: "6""4"
Backlight brightness control	0xe0, nn "+" "-" "?"	Set backlight brightness = value/increment/decrement Query	Backlight brightness. Range: "0""0"-"6""4"

			function when JB5 sets 3-4 closed
			* Apply for inverter control voltage in range of 0~5V. Each step interval is in 1
Backlight on/off control	0xe1, "0" I	Set backlight brightness = Disable backlight	Backlight on "1" / off "0".
"1" Enable backlight "r" "R" Reset			Default "1" = On
Backlight PWM**	0xe5, "0" "1" "?"	Set backlight type D/A or PWM Query	"1" – PWM "0" – D/A
Backlight PWM	0xe6,	Set Backlight PWM	+/- 20Hz
Frequency**	nnn "+" "-" "2"	Frequency =	Value
	:	decrement	120Hz : "0", "7", "8"
		Query	140Hz : "0", "8", "C"
			160Hz : "0", "A", "0"
			180Hz : "0", "B", "4"
			200Hz : "0", "C", "8"
			220HZ: U, D, C 240Hz: "O" "E" "O"
			240172 . 0 , 1 , 0 260Hz · "1" "0" "4"
			280Hz : "1", "1", "8"
			300Hz : "1", "2", "C"
			320Hz : "1", "4", "0"
			340Hz : "1", "5", "4"
			360Hz : "1", "6", "8"
			380Hz : "1", "7", "C"
			400HZ: 1, 9, 0
			420112 . 1 , A , 4 440Hz · "1" "B" "8"
Backlight	0xe7,	Set backlight invert	"1" – Invert
Invert**	0" "1" "?"	Normal or Invert Query	"0" – Normal
OSD menu	0xf6,	OSD menu lock Off/ On	"0" – OSD menu lock Off
IUCK	II U I "r" "R"		
	"?"	Query	Default "0" = off

** - Only effective on V1.07.00 or up version.

3. Other control

	Description	Acknowledge (if enabled)
Dxc1, "0" "1"	Disable/enable command	"0" – acknowledge
	acknowledge.	disabled.
		"1" – acknowledge
		enabled.
Dxc4, n	Check whether a command	"0" – not available.
	is available.	"1" – available.
Dxc8,	Soft power	"0" – soft power off.
0" "1"	On/off	"1" –soft power on.
?"	query	
Dxcb, "0"	Read BIOS version	"nnnn" = BIOS ver. "nn.nn"
Dxcb, "1"	Read PCBA number	"nnnn" = PCBA number
		DD-1920="41730"
Dxce	Reset all parameters to	"1" – successful.
	factory default value	
	xc1, "0" "1" xc4, n xc8,)" "1" ?" xcb, "0" xcb, "1" xce	xc1, "0" "1"Disable/enable command acknowledge.xc4, nCheck whether a command is available.xc8,Soft power0" "1" On/off queryxcb, "0"Read BIOS versionxcb, "1"Read PCBA numberxceReset all parameters to factory default value

** - Only effective on V1.07.00 or up version.

Hex to ASCII conversion table

Hex	ASCII	Hex	ASCII	Hex	ASCII	Hex	ASCII
0x30	0	0x41	А	0x61	а	0x2B	+
0x31	1	0x42	В	0x62	b	0x2D	-
0x32	2	0x43	С	0x63	С	0x3F	?
0x33	3	0x44	D	0x64	d		
0x34	4	0x45	E	0x65	е		
0x35	5	0x46	F	0x66	f		
0x36	6	0x47	G	0x67	g		
0x37	7	0x48	Н	0x68	h		
0x38	8	0x49	1	0x69	i		
0x39	9	0x4A	J	0x6A	j		
		0x4B	K	0x6B	k		
		0x4C	L	0x6C	—		
		0x4D	М	0x6D	m		
		0x4E	Ν	0x6E	n		
		0x4F	0	0x6F	0		
		0x50	Р	0x70	р		
		0x51	Q	0x71	q		
		0x52	R	0x72	r		
		0x53	S	0x73	S		
		0x54	Т	0x74	t		
		0x55	U	0x75	u		
		0x56	V	0x76	V		
		0x57	W	0x77	W		
		0x58	Х	0x78	Х		
		0x59	Y	0x79	у		
		0x5A	Z	0x7A	Z		



Appendix III – DDC/CI support at HDMI port

This controller (start from V1.07.00 or later firmware revision) supports the following DDC/CI commands at HDMI port :

Brightness Contrast

-

_

- RGB Color -
- Input Source (HDMI)
- Power States (On, Standby, Sleep)
 - On mode: Always on. Display No sync message and never goes off when no signal •
 - Standby mode: Off backlight & Off panel power when no signal •
 - Reduced power off / Sleep mode: Screen saver on = Always On; Screen saver off = Backlight off. Display "No sync" message for 10sec, then off backlight

Appendix IV – Mapping definition

• Definition of Mapping A :



• Definition of Mapping B :



Appendix V – DV remote control unit work for DD-1920-HDMI

P/N 559000106-3 :

DigitalView remote control unit (without DV logo silk screen printing)

P/N 559000105-3 :

DigitalView remote control unit (with DigitalView logo silk screen printing)



BUTTON	FUNCTION
POWER BUTTON	Soft power ON/OFF button.
ATTENTION BUTTON	Use combined with digit keys to enable/disable the IR function. DD-1920-HDMI : "Attention" + "1"
MUTE BUTTON (Switch to mute on/off mode.
SEL UP (Λ) / SEL DN (\vee)	Press this button to select the items in the OSD menu.
+ / - BUTTON	Use "+" button to direct control the hotkey function for switching to next input source. In OSD menu, pressing this button to adjust the settings.
DISPLAY BUTTON	Activate the OSD menu display on screen.
HDMI BUTTON	Press this button in the non OSD menu display mode to select DVI source.

WARRANTY

The products are warranted against defects in workmanship and material for a period of three (3) year from the date of purchase provided no modifications are made to it and it is operated under normal conditions and in compliance with the instruction manual.

The warranty does not apply to:

- Product that has been installed incorrectly, this specifically includes but is not limited to cases where electrical short circuit is caused.
- Product that has been altered or repaired except by the manufacturer (or with the manufacturer's consent).
- · Product that has subjected to misuse, accidents, abuse, negligence or unusual stress whether physical or electrical.
- Ordinary wear and tear.

Except for the above express warranties, the manufacturer disclaims all warranties on products furnished hereunder, including all implied warranties of merchantability and fitness for a particular application or purpose. The stated express warranties are in lieu of all obligations or liabilities on the part of the manufacturer for damages, including but not limited to special, indirect consequential damages arising out of or in connection with the use of or performance of the products.

CAUTION

Whilst care has been taken to provide as much detail as possible for use of this product it cannot be relied upon as an exhaustive source of information. This product is for use by suitably qualified persons who understand the nature of the work they are doing and are able to take suitable precautions and design and produce a product that is safe and meets regulatory requirements.

LIMITATION OF LIABILITY

The manufacturer's liability for damages to customer or others resulting from the use of any product supplied hereunder shall in no event exceed the purchase price of said product.

TRADEMARKS

The following are trademarks of Digital View Ltd:

- Digital View
- DD-1920-HDMI

CONTACT DETAILS

USA

Digital View Inc. 18440 Technology Drive Building 130 Morgan Hill, California, 95037 USA Tel: (1) 408-782 7773 Fax: (1) 408-782 7883 Sales: ussales@digitalview.com

EUROPE

Digital View Ltd. The Lake House Knebworth Park Herts, SG3 6PY UK Tel: +44-(0)20-7631-2150 Fax: Fax: +44-(0)20-7631-2156 Sales: uksales@digitalview.com

ASIA

Digital View Ltd 2nd Floor Bamboos Center 52 Hung To Road Kwun Tong Hong Kong **Tel:** (852) 2861 3615 **Fax:** (852) 2520 2987 **Sales:** hksales@digitalview.com

WEBSITE

www.digitalview.com

Brand names belong to their respective owners. Specification subjects to change without notice.

2nd issue: May 2015 (DD-1920 -HDMI-1x manual.doc)

© Digital View Ltd 2015





Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.З, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж: moschip.ru moschip.ru_4

moschip.ru_6 moschip.ru_9