



SAW Filters for Mobile Communications

Series/Type: B9012

The following products presented in this data sheet are being withdrawn.

Ordering Code	Substitute Product	Date of Withdrawal	Deadline Last Orders	Last Shipments
B39901B9012K210	B39901B9431M410	2009-12-18	2010-06-30	2010-09-30


For further information please contact your nearest EPCOS sales office, which will also support you in selecting a suitable substitute. The addresses of our worldwide sales network are presented at www.epcos.com/sales.

Features

- Low-loss RF filter for mobile telephone EGSM system, transmit path
- Low amplitude ripple
- Usable passband 35 MHz
- Unbalanced to balanced operation
- Impedance transformation from 100 Ω to 50 Ω
- Suitable for GPRS class 1 to 12
- Ceramic package for Surface Mounted Technology (SMT)
- Pb-free

Terminals


- Ni, gold-plated

Chip sized SAW package DCS6S


Dimensions in mm, approx. weight 0,010 g

Pin configuration

- 4, 6 Balanced inputs
- 2 Unbalanced output
- 1, 3 Output ground
- 1, 3, 5 To be grounded



Type	Ordering code	Marking and Package according to	Packing according to
B9012	B39901-B9012-K210	C61157-A7-A115	F61074-V8152-Z000

Electrostatic Sensitive Device (ESD)
Maximum ratings

Operable temperature range	T	- 30 / + 85	$^{\circ}\text{C}$	Machine Model, 10 pulses peak power of GSM signal, duty cycle 4:8
Storage temperature range	T_{stg}	- 40 / + 85	$^{\circ}\text{C}$	
DC voltage	V_{DC}	5	V	
ESD voltage	V_{ESD}^*	100*	V	
Input power at	P_{IN}	13	dBm	
GSM850, GSM900 GSM1800 and GSM1900 Tx bands				

* - acc. to JESD22-A115A (Machine Model), 10 negative & 10 positive pulses

SAW Components
B9012
Low-Loss Filter for Mobile Communication
897,5 MHz
Data Sheet

Characteristics

Operating temperature range: $T = 25 \pm 2 \text{ }^{\circ}\text{C}$
 Terminating source impedance: $Z_S = 100 \text{ } \Omega$ (balanced) || 82 nH
 Terminating load impedance: $Z_L = 50 \text{ } \Omega$

			min.	typ.	max.	
Center frequency	f_C		—	897,5	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
880,0 ... 915,0 MHz			—	2,4	2,9	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
880,0 ... 915,0 MHz			—	0,8	1,5	dB
Input VSWR						
880,0 ... 915,0 MHz			—	1,8	2,0	
Output VSWR						
880,0 ... 915,0 MHz			—	1,8	2,0	
Output phase balance ($\phi(S_{31}) - \phi(S_{21}) + 180^{\circ}$)						
880,0 ... 915,0 MHz			-10	—	10	degree
Output amplitude balance ($ S_{31}/S_{21} $)						
880,0 ... 915,0 MHz			-1,0	—	1,0	dB
Diff. to common mode suppression	S_{sc12}					
880,0 ... 915,0 MHz			18	26	—	dB
1760,0 ... 1830,0 MHz			18	41	—	dB
2640,0 ... 2745,0 MHz			18	32	—	dB
Attenuation	α					
0,0 ... 800,0 MHz			45	56	—	dB
800,0 ... 860,0 MHz			25	42	—	dB
860,0 ... 870,0 MHz			13	26	—	dB
925,0 ... 935,0 MHz			9	15	—	dB
935,0 ... 1805,0 MHz			25	31	—	dB
1805,0 ... 3660,0 MHz			30	36	—	dB
3660,0 ... 6000,0 MHz			15	30	—	dB

SAW Components
B9012
Low-Loss Filter for Mobile Communication
897,5 MHz
Data Sheet

Characteristics

Operating temperature range: $T = -10 \dots +80 \text{ }^{\circ}\text{C}$
 Terminating source impedance: $Z_S = 100 \text{ } \Omega$ (balanced) || 82 nH
 Terminating load impedance: $Z_L = 50 \text{ } \Omega$



		min.	typ.	max.	
Center frequency	f_C	—	897,5	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$	—	2,6	3,0	dB
880,0 ... 915,0 MHz					
Amplitude ripple (p-p)	$\Delta\alpha$	—	1,0	1,5	dB
880,0 ... 915,0 MHz					
Input VSWR		—	1,8	2,0	
880,0 ... 915,0 MHz					
Output VSWR		—	1,8	2,0	
880,0 ... 915,0 MHz					
Output phase balance ($\phi(S_{31}) - \phi(S_{21}) + 180^{\circ}$)		-10	—	10	degree
880,0 ... 915,0 MHz					
Output amplitude balance ($ S_{31}/S_{21} $)		-1,0	—	1,0	dB
880,0 ... 915,0 MHz					
Diff. to common mode suppression	S_{sc12}				
880,0 ... 915,0 MHz		18	26	—	dB
1760,0 ... 1830,0 MHz		18	41	—	dB
2640,0 ... 2745,0 MHz		18	32	—	dB
Attenuation	α				
0,0 ... 800,0 MHz		45	56	—	dB
800,0 ... 860,0 MHz		25	42	—	dB
860,0 ... 870,0 MHz		12	26	—	dB
925,0 ... 935,0 MHz		8	15	—	dB
935,0 ... 1805,0 MHz		25	31	—	dB
1805,0 ... 3660,0 MHz		30	36	—	dB
3660,0 ... 6000,0 MHz		15	30	—	dB

SAW Components
B9012
Low-Loss Filter for Mobile Communication
897,5 MHz
Data Sheet

Characteristics

Operating temperature range: $T = -30 \dots +85 \text{ }^{\circ}\text{C}$
 Terminating source impedance: $Z_S = 100 \text{ } \Omega$ (balanced) || 82 nH
 Terminating load impedance: $Z_L = 50 \text{ } \Omega$

			min.	typ.	max.	
Center frequency	f_C		—	897,5	—	MHz
Maximum insertion attenuation	$\alpha_{\max}$					
	880,0 ... 915,0 MHz		—	2,7	3,7	dB
Amplitude ripple (p-p)	$\Delta\alpha$					
	880,0 ... 915,0 MHz		—	1,2	2,2	dB
Input VSWR						
	880,0 ... 915,0 MHz		—	1,8	2,0	
Output VSWR						
	880,0 ... 915,0 MHz		—	1,8	2,0	
Output phase balance ($\phi(S_{31}) - \phi(S_{21}) + 180^{\circ}$)						
	880,0 ... 915,0 MHz		-10	—	10	degree
Output amplitude balance ($ S_{31}/S_{21} $)						
	880,0 ... 915,0 MHz		-1,0	—	1,0	dB
Diff. to common mode suppression	S_{sc12}					
	880,0 ... 915,0 MHz		18	26	—	dB
	1760,0 ... 1830,0 MHz		18	41	—	dB
	2640,0 ... 2745,0 MHz		18	32	—	dB
Attenuation	α					
	0,0 ... 800,0 MHz		45	56	—	dB
	800,0 ... 860,0 MHz		25	42	—	dB
	860,0 ... 870,0 MHz		12	26	—	dB
	925,0 ... 935,0 MHz		8	13	—	dB
	935,0 ... 1805,0 MHz		25	30	—	dB
	1805,0 ... 3660,0 MHz		30	36	—	dB
	3660,0 ... 6000,0 MHz		15	30	—	dB

Transfer function (measurement)

Transfer function (wideband measurement)


**Published by EPCOS AG****Surface Acoustic Wave Components Division, SAW MC WT****P.O. Box 80 17 09, 81617 Munich, GERMANY**

© EPCOS AG 2004. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[EPCOS:](#)

[B39901B9012K210](#)

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9