


Figure 1

1. INTRODUCTION

SMA Hermetically-Sealed Panel Feedthrough Jack Receptacles 1053159-1, 1053181-1, 1053182-1, 1053226-1, 1053227-1, 1053254-1, 1061372-1, and 1089139-1 are designed to be mounted onto a panel using the following tools:

TOOL DESCRIPTION	PART NUMBER CROSS-REFERENCE	
	TE CONNECTIVITY	M/A-COM
Step Reamer	1055284-1	2098-0442-54
.250-36, UNS-2B Bottoming Tap†	--	2098-5618-54
Torque Tool	1055251-1	2098-0248-54
3/8-in. Open Wrench†	--	--

† Commercially available



Unless otherwise specified, dimensions in this instruction sheet are in metric units [with U.S. customary units in brackets].

Reasons for reissue of this instruction sheet are provided in Section 5, REVISION SUMMARY.

2. DESCRIPTION

The jack receptacle consists of a jack and metal gasket. See Figure 1.

3. ASSEMBLY PROCEDURE



Follow safety precautions included with the tools used for assembly.

1. Refer to Figure 2, and drill a hole in the panel to the diameter shown. Using the step reamer, ream the hole to the depth shown. Using the bottoming tap, tap the thread to the depth shown.

2. While holding the collet of the torque tool, turn the handle clockwise until it stops. Thread the jack into the tool until it bottoms inside the tool. Hand-tighten the jack. Refer to Figure 3.



The torque tool is preset between 2.60 and 3.05 Nm [23 and 27 in.-lb].

Recommended Panel Cutout
Note: Dimensions are in inches over millimeters.




Figure 2




Figure 3

3. Install the metal gasket onto the jack. See Figure 4.




Figure 4

4. Thread the jack into the connector housing by turning the handle of the torque tool clockwise until the handle releases. See Figure 5, Detail A.

5. While holding the collet of the torque tool with the open wrench, turn the handle counter-clockwise, and remove the jack assembly from the torque tool. See Figure 5, Detail B.

6. Install the jack assembly onto the panel.

4. REPLACEMENT AND REPAIR

Discard and replace any defective or damaged jack receptacles or metal gaskets.

5. REVISION SUMMARY

Since the previous version of this document, the following changes were made:

- Updated document to corporate requirements.




Figure 5

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9