

## Description

The model ESX10-Sxxx extends our product group of electronic overcurrent protection devices for DC 24 V applications. At a width of only 12.5mm it provides selective protection for all DC 24 V load circuits. This is achieved by a combination of active electronic current limitation in the event of a short circuit and overload disconnection typically from 1.2 times rated current. The ESX10-S is a plug-in type and thus allows quick and easy installation for groups of devices with several circuits on the power distribution systems Module 17plus and SVSxx.

DC 24 V switch-mode power supplies are widely used in automation today. In the event of an overload, however, they turn down the output voltage which is intended to power all connected loads. So if there is a failure in a single load of the system, the supply voltage will break down also in all other load circuits. Not only does this frequently cause undefined fault conditions, but it can even lead to machine stoppages or system downtimes.

This is exactly where the ESX10-S comes in by responding to the overload conditions faster than the switch-mode power supply. The max. possible overcurrent is limited to typically 1.4 times rated current (see table 1). This allows switching on capacitive loads of up to 20,000  $\mu$ F, but a disconnection will only be effected in the event of an overload or short circuit. For adjustment to the load conditions the current rating can be selected by means of a rotary switch from 1A to 10A. Status and failure indication is by means of a multi-coloured LED, an integral short circuit proof status output (single or group alarms) or via a potential-free relay contact (change-over contact). Remote actuation is possible via a remote reset signal. The manual ON/OFF switch on the device itself allows start-up of certain individual load circuits. As soon as the ESX10-S detects overload or short circuit in its load circuit, it blocks the load output transistor and disconnects the current flow in the faulty circuit. After remedy of the failure, the load output of the ESX10-S is re-activated by an electronic reset signal or manually by actuating the ON/OFF switch on the device.

**US patent number:** US 6,490,141 B2

## Features and Benefits

- Selective load protection, electronic trip curve
- All types of loads can be connected (DC 24 V motors upon request)
- Active current limitation when switching on capacitive loads up to min. 20,000  $\mu$ F and in case of overload/short circuit
- Whole-number adjustable current ratings from 1A to 10 A by means of rotary switch
- Reliable overload disconnection typically from  $1.2 \times I_N$  even with long load lines or small cable cross sections
- Manual ON/OFF switch (S1)
- Clear status indication by means of LED, electronic status output SF or signal output F (potential-free auxiliary contact)
- Electronic reset input RE, control input IN
- Integral fail-safe-element
- Width per channel only 12.5 mm
- Plug-in type mounting on power distribution system Module 17plus and SVSxx.

## Approvals

Authority	Standard	Rated voltage	Current ratings
UL	UL 2367	DC 24 V	1...10 A
UL	UL 508 C22.2 No 14	DC 24 V	1...10 A



**ESX10-S**

## Technical data ( $T_{amb} = 25^\circ\text{C}$ , $U_B = \text{DC } 24\text{ V}$ )

### Operating data


Operating voltage $U_B$	DC 24 V (18...32 V)
Current ratings $I_N$	<b>adjustable ratings:</b> 1 A through 10 A in 1 A steps
Standby current $I_0$	in ON condition: typically 25 mA with version -103/-115/-125 typically 20 mA with version -114/-117/-124/-127
Visual status indication	multicoloured LED: <b>green:</b> - load circuit connected <b>flashing (green/yellow):</b> - load current warning limit reached 80% <b>yellow:</b> - overload or short circuit until disconnection <b>red:</b> - after disconnection due to overload, short circuit or temperature - after undervoltage disconnection in ON condition of operating voltage with automatic reset <b>flashing (red/OFF):</b> - upon changed rating adjustment <b>OFF:</b> - devices switched off via ON/OFF switch - no operating voltage with ON/OFF switch in ON condition
Load circuit	
Load output	power MOSFET switching output (plus switching)
Load current warning limit ( $I_{Limit}$ )	typically $0.8 \times I_N$
hysteresis	typically 5%
Overload disconnection ( $I_{OL}$ )	typically $1.2 \times I_N$ (1.05...1.35 $\times I_N$ ) (see time/current characteristic)
Short circuit current ( $I_{SC}$ )	active current limitation with $I_{SC} =$ typically $2.5 \times I_N$ , 1 A typically $1.4 \times I_N$ , 2 A -10 A (see time/current characteristic)
Trip times	at overload disconnection ( $I_{OL}$ ) = typ. 3 s at short circuit current ( $I_{SC}$ ) = typically 0.1 s (see time/current characteristic)
Temperature	internal temperature monitoring with monitoring electronic disconnection disconnection hysteresis typically $+100^\circ\text{C}$ typically 10 °C
Operating voltage monitoring with regard to low voltage	OFF at typically $U_B < 16.0\text{ V}$ ON at typically $U_B > 17.5\text{ V}$ with automatic ON and OFF switching

Technical data ( $T_{amb} = 25^\circ\text{C}$ , $U_B = \text{DC } 24\text{ V}$ )		Technical data ( $T_{amb} = 25^\circ\text{C}$ , $U_B = \text{DC } 24\text{ V}$ )	
Switch-on delay $t_{\text{start}}$	typically 0.1 s - after each ON operation, reset and after applying of $U_B$ - during switch-on delay the load circuit is disconnected.	Reset input RE	<b>ESX10-124/-125-S127</b> Electrical data voltage max. + DC 32 V high > DC 8 V ≤ DC 32 V low ≤ DC 3 V > 0 V current consumption typically 2.6 mA (+ DC 24 V) RESET – pulse / edge from low > 100 ms on high > 100 ms
Disconnection of load circuit	- manually on the device with the ON/OFF switch (OFF) - after disconnection due to overload or short circuit - temporarily at undervoltage - at excess temperature of the device - upon changed rating adjustment - at no operating voltage	Reset signal RE	By means of the reset signal the electronically locked ESX10-S124/-S125-S127 can be remotely reset via an external momentary switch or via the PLC. A joint reset signal can also be applied to more than one device at a time. Devices in ON condition will remain unaffected.
Leakage current in load circuit in the OFF condition	typically < 1 mA	Signal output F	<b>ESX10-S103</b> Electrical data potential-free auxiliary change-over contact max. DC 30 V / 0.5 A min. 10 V / 10 mA
Capacitive loads	min. 20,000 $\mu\text{F}$	Standard condition:	SC/SO (13/14) closed SC-SI (13/12) open load output connected through
Free-wheeling diode	external free-wheeling diode recommended for inductive load	Fault condition:	SC/SO (13/14) open SC-SI (13/12) closed load output locked
Parallel connection of several load outputs	not allowed	Signal output F	<b>ESX10-S115 / -S125</b> Electrical data potential-free auxiliary make contact max. DC 30 V / 0.5 A min. 10 V / 10 mA
<b>Status output SF</b>	<b>ESX10-S114 / -S124</b> Electrical data plus switching signal output, connects $U_B$ to terminal SF Rated data: DC 24 V / max. 0.2 A (short circuit proof) The status output is connected internally with a 10 kOhm resistor against 0 V	Normal condition:	SC/SO (13/14) closed load output connected
Status OUT (-S114/-S124)	ESX10-S114/-S124 (Signal Status OUT), at $U_B = + 24\text{ V}$	Fault condition:	SC/SO (13/14) open load output locked
Normal condition:	+ 24 V	S1 is ON, load output connected	
Fault condition:	0 V	S1 is ON, load output blocked or in the event of manual disconnection (S1 is OFF) red LED lighted	
	0 V	no operating voltage $U_B$	
<b>Status output SF</b>	<b>ESX10-S117-S127</b> Electrical data plus switching signal output, connects $U_B$ to terminal SF Rated data: DC 24 V / max. 0.2 A (short circuit proof) The status output is locked internally with a 10 kOhm resistor against 0 V.	General Characteristics	
Status OUT (-S117/-S127)	ESX10-S117-S127 (Signal Status OUT inverted), at $U_B = + 24\text{ V}$	Fail-safe-element	integral fail-safe-element 15 A Max. rupture capacity of the element is 300 A at 24 V DC
Standard condition:	0 V	ON/OFF switch is ON, load output connected through	
Fault condition:	+ 24 V	ON/OFF switch is ON, load output locked or with manual disconnection ON/OFF switch is OFF	
	0 V	no operating voltage $U_B$	
<b>Control input IN+</b>	<b>ESX10-S114 / -S115 / -S117</b> Electrical data voltage max. DC 32 V High > DC 8 V < DC 32 V Low < DC 3 V > 0 V Current consumption typically 2.6 mA (DC 24 V)	Terminals	<b>LINE+ / LOAD+ / 0V / (RE / IN+ / SF) or (SC / SO / SI)</b>
Control input IN+	+24 V level (HIGH): device is switched on by a remote ON/OFF signal. 0 V level (LOW) device is switched off by a remote ON/OFF signal.	Blade terminals	6.3 mm to EN60934-6.3-0.8
Switch S1 ON/OFF	device can only be switched on when a HIGH level is applied to IN+	Housing material	moulded
Reset function	a blocked load output (blocked by overload/ short circuit) can externally be reset by the control input For this purpose the control input has to be switched off for at least 100 ms and switched on again afterwards.	Mounting method	plug-in type onto Module 17plus and SVSxx
		Ambient temperature	0...+50 °C (without condensation, cf. EN 60204-1)
		Storage temperature	-40...+70 °C
		Humidity	96 hrs / 95% RH 40°C to IEC 60068-2-78-Cab climate class 3K3 to EN 60721
		Vibration	3g test to IEC 60068-2-6, test Fc ,
		Degree of protection	IEC 60529, DIN VDE 0470) operating area IP30 terminal area IP00
		EMC requirements (EMC directive, CE logo)	emission: EN 61000-6-3 susceptibility: EN 61000-6-2
		Insulation co-ordination (IEC 60934)	0.5 kV / pollution degree 2 reinforced insulation in operating area
		Dielectric strength	max. DC 30 V (load circuit)
		Insulation resistance (OFF condition)	n/a, only electronic disconnection
		Approvals	CE logo UL 2367, File # E306740, Solid State Overcurrent Protectors UL 508, File # E322549
		Dimensions (w x h x d)	12.5 x 70 x 60 mm (tolerances to DIN ISO 286 part 1 IT13)
		Mass	approx. 40 g


**Table 1: typical voltage drop, current limitation, max. load current**

Current rating $I_N$	Typical voltage drop $U_{ON}$ at $I_N$	active current limitation $I_{Limit}$ typically	Max. load current at 100 % ON duty	
			$T_{AMB} = 40^\circ\text{C}$	$T_{AMB} = 50^\circ\text{C}$
1 A	15 mV	$2,5 \times I_N$	1 A	1 A
2 A	30 mV	$1,4 \times I_N$	2 A	2 A
3 A	45 mV	$1,4 \times I_N$	3 A	3 A
4 A	60 mV	$1,4 \times I_N$	4 A	4 A
5 A	75 mV	$1,4 \times I_N$	5 A	5 A
6 A	90 mV	$1,4 \times I_N$	6 A	5 A
7 A	105 mV	$1,4 \times I_N$	7 A	6 A
8 A	120 mV	$1,4 \times I_N$	8 A	7 A
9 A	135 mV	$1,4 \times I_N$	9 A	8 A
10 A	150 mV	$1,4 \times I_N$	10 A	9 A

Note: When mounted side-by-side without convection, the devices should carry max 80% of their rated load continuously (100 % ON duty).

**Time/current characteristic curve ( $T_{amb} = 25^\circ\text{C}$ ,  $U_B = \text{DC } 24\text{ V}$ )**


- Without the current limitation there would be a much higher overcurrent in the event of an overload or short circuit.

**Schematic diagram ESX10-S127 (example)**


### Order numbering code

**Type No.**
**ESX10** Electronic Circuit Protector, with current limitation

**Mounting**
**S** plug-in, with rotary switch for 10-step current rating adjustment from 1 A to 10 A

**Version**
**1** without physical isolation

**Signal input**

- 0** without signal input (only version -S103)
- 1** control input  $I_N$  (only version -S114/-S115/-S117)
- 2** with reset input RE (only version -S124/-125/-127)

**Signal output:**

- 3** signal change-over contact (only version -S103)
- 4** status output SF (only version -S114/-124)
- 5** signal contact (only version -S115/-125)
- 7** status output SF, inverted (only version -S117/-S127)

**Operating voltage**
**DC 24 V** voltage rating DC 24 V

**Current ratings**
**1 A - 10 A adjustable**
**ESX10 - S 1 0 3 - DC 24 V - 1 A-10 A** ordering example

Standard types:

**ESX10-S103-DC24V-1A...10A**
**ESX10-S127-DC24V-1A...10A**

### Please note

- The user has to ensure that the cable cross section of the load circuit in question complies with the current rating of the ESX10-S used.
- In addition special precautions must be taken in the system or machine (e.g. use of a safety PLC) which reliably prevent an automatic re-start of parts of the system (cf. Machinery Directive 2006/42/EG and EN 60204-1, Safety of Machinery). In the event of a failure (short circuit/overload) the load circuit will be disconnected electronically by the ESX10-S.


**Wiring diagrams**

The auxiliary contacts are shown in the OFF or fault condition

**ESX10-S103**

without signal input

with signal output F (group signal, change-over)




Standard condition: SC/SO closed, SC-SI open  
 Fault condition: SC/SO open, SC-SI closed

**ESX10-S114**

with signal input IN+

with status indication SF




Standard condition: SF+24V = OK  
 Fault condition: SF 0V

**ESX10-S115**

with signal input IN+

with signal output F (group signal, N/O)




Standard condition: SC/SO closed  
 Fault condition: SC/SO open

**ESX10-S117**

with signal input IN+

with status indication SF inverted




Standard condition: SF 0V = OK  
 Fault condition: SF +24V

**ESX10-S124**

with reset input RE

with status indication SF




Standard condition: SF +24V = OK  
 Fault condition: SF 0V

**ESX10-S125**

with reset input RE

with signal output F (group signal, N/O)




Standard condition: SC/SO closed  
 Fault condition: SC/SO open

**ESX10-S127**


with reset input RE

with status indication SF inverted




Standard condition: SF 0V = OK  
 Fault condition: SF +24V

**Dimensions ESX10-S**



**Accessories**

**Module 17plus**  
For technical data see section Power Distribution Systems



All dimensions without tolerances are for reference only. In the interest of improved design, performance and cost effectiveness, the right to make changes in these specifications without notice is reserved. Product markings may not be exactly as the ordering codes. Errors and omissions excepted.



**Данный компонент на территории Российской Федерации****Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

**<http://moschip.ru/get-element>**

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибуторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ Р В 0015-002 и ЭС РД 009

**Офис по работе с юридическими лицами:**

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9