



# 260-8Xi<sup>®</sup> & 260-8XPi<sup>®</sup> Analog VOM

## 260-8Xi has all of the circuit protection features and advantages for which the 260 Series is famous...

And even more features than its predecessors. The yellow case color for enhanced visibility and user safety awareness is the trademark of the 260-8Xi. The durable ABS plastic case also provides high-impact resistance and increased drop protection in the toughest environments.

- Instant Trend Information for Quick Positive "Yes/No" Checks
- Zero RFI Emission
- Audible Continuity Check
- Resettable Overload Circuit Protection Relay
- 1.5 V and 9 V Batteries and Probe Test Leads With Alligator Clips
- Mirrored Scale for Parallax Reduction



## Specifications

### DC VOLTAGE

Ranges	Accuracy	Sensitivity
250mV, 1V, 2.5V, 10V, 25V, 50V, 250V, 500V, 1000V	2% of full scale	20K $\Omega$ per volt

### AC VOLTAGE

Ranges	Accuracy	Sensitivity
2.5V, 10V, 25V, 50V, 250V, 500V, 1000V	3% of full scale	5K $\Omega$ per volt

### DECIBEL

5 Ranges: -20 to +50dB  
Reference: 0dB= 1mW into 600 $\Omega$

### AC CURRENT

Up to 250 AC amperes with AC Amp-Clamp Adapter Accessory 00541.

### DC CURRENT

Ranges	Accuracy	Voltage Drop: (Nominal)
50 $\mu$ A, 1mA, 10mA, 100mA, 500mA, 10A	1.5% full scale 50 $\mu$ A 2.0% of full scale, all others	250mV on 50 $\mu$ A/1mA; 255mV on 10mA/10A; 300mV on 100mA; 500mV on 500mA

## Ordering Information

VOM	Catalog No.	ACCESSORIES	Catalog No.	ACCESSORIES	Catalog No.
260-8Xi, Yellow	12395	Probe Leads w/Screw-on Alligator Clip	00125	Case, Yellow Padded Polyester	00832
260-8XPi, Protected, Yellow	12396	Probe Set, Replaceable Tip, Banana Lead Set, Alligator, Banana Clip Set, Alligator, Screw-On 150-2 Amp Clamp Adapter, AC	07538 07500 00425 00541	Case, Black Padded Polyester Case, Hard Leatherette Front Load Case, Molded Plastic	00834 00805 45028

Additional accessories are on pages 22-24.

## Specifications (Continued)

### RESISTANCE

Ranges	Accuracy	Maximum Indication
Rx1 Rx100 Rx10K	2.5° of arc on Rx1 2.0° of arc on all others	0-2K $\Omega$ 0-200K $\Omega$ 0-20M $\Omega$

**BATTERIES:** 1.5 V D, 9V (NEDA No. 13F, 1604A)

**FUSE:** F1 1A, 250V, type 3AG, quick acting Littelfuse<sup>®</sup> Type 312001; F2 2A, 600V

Littelfuse<sup>®</sup> Type BLS or 2A 600V, Bussman<sup>®</sup> Type BBS.

**SIZE:** 5 1/4" x 7" x 3 1/8" (13.34 x 17.78 x 7.94 cm)

**WEIGHT:** 2 1/4 lbs. (1.02 Kg)

**RATED CIRCUIT-TO-GROUND VOLTAGE:** 1000V AC/DC Max

Specifications subject to change without notice.

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9