

# RJ45 10/100 Base-T Jack with Magnetic Module

ARJ11D

RoHS  
Compliant



16.26 x 13.84 x 21.59mm

## FEATURES:

- Available with or without LED
- Suitable CAT 5 & 6 cable and UTP
- Comply IEEE 802.3ab
- LAN Magnetic with RJ4
- Suitable for RoHS compliant reflow

## APPLICATIONS:

- 10/100 Base-T LAN
- NIC, LoM and PC

## STANDARD SPECIFICATIONS at 25°C

Operating temperature range: 0°C to +70°C Storage temperature range: -40°C to +85°C


| Part Number           | Turns Ratio |         | EMI Fingers | LEDs L/R | Insertion Loss (dB TYP) 1-65 MHz | Return Loss (dB TYP @100Ω±15Ω) |           |           |             |
|-----------------------|-------------|---------|-------------|----------|----------------------------------|--------------------------------|-----------|-----------|-------------|
|                       | TX          | RX      |             |          |                                  | 1- 10 MHz                      | 10-30 MHz | 30-60 MHz | 60 – 80 MHz |
| ARJ11D-MCSA-LU2       | 1CT:1       | 1CT:1CT | Yes         | NONE     | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MASB-B-A-□MU2  | 1CT:1CT     | 1CT:1CT | Yes         | Y/G      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MCSC-LU2       | 1CT:1       | 1CT:1CT | Yes         | NONE     | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MDSD-A-B-□LT2  | 1CT:1       | 1CT:1   | No          | G/Y      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MCSD-LT2       | 1CT:1       | 1CT:1   | Yes         | NONE     | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MDSE-A-B-□MU2  | 1CT:1CT     | 1CT:1CT | No          | G/Y      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MASE-A-B-□MU2  | 1CT:1CT     | 1CT:1CT | Yes         | G/Y      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MDSG-B-A-□MU2  | 1CT:1CT     | 1CT:1CT | No          | Y/G      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MASG-B-A-□MU2  | 1CT:1CT     | 1CT:1CT | Yes         | Y/G      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MASG-A-A-□MU2  | 1CT:1CT     | 1CT:1CT | Yes         | G/G      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MESH-LU2       | 1CT:1       | 1CT:1CT | Yes         | NONE     | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MDSH-A-B-□LU2  | 1CT:1       | 1CT:1CT | No          | G/Y      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MASH-B-A-□LU2  | 1CT:1       | 1CT:1CT | Yes         | Y/G      | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MBSJ-A-DA-HLT2 | 1CT:1       | 1CT:1   | Yes         | G/O G    | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MBSK-A-DA-HMU2 | 1CT:1CT     | 1CT:1CT | Yes         | G/O G    | -1                               | -20                            | -16       | -12       | -10         |
| ARJ11D-MBSL-A-DA-HLU2 | 1CT:1       | 1CT:1CT | Yes         | G/O G    | -1                               | -20                            | -16       | -12       | -10         |

| Part Number           | Crosstalk (dB TYP) |           |            | Common Mode Rejection (dB TYP) |            | Hipot (Vrms) @60Hz |
|-----------------------|--------------------|-----------|------------|--------------------------------|------------|--------------------|
|                       | 1-30 MHz           | 30-60 MHz | 60-100 MHz | 1-50 MHz                       | 50-150 MHz |                    |
| ARJ11D-MCSA-LU2       | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MASB-B-A-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MCSC-LU2       | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MDSD-A-B-□LT2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MCSD-LT2       | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MDSE-A-B-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MASE-A-B-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MDSG-B-A-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MASG-B-A-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MASG-A-A-□MU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MESH-LU2       | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MDSH-A-B-□LU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MASH-B-A-□LU2  | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MBSJ-A-DA-HLT2 | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MBSK-A-DA-HMU2 | -40                | -35       | -30        | -30                            | -20        | 1500               |
| ARJ11D-MBSL-A-DA-HLU2 | -40                | -35       | -30        | -30                            | -20        | 1500               |

### □: LED Polarity Option

ARJ11D-MA: E, F or G  
ARJ11D-MD: E, F or G

Contact Abracon for more custom configurations. See options to build a custom configuration.



# RJ45 10/100 Base-T Jack with Magnetic Module

ARJ11D

RoHS  
Compliant




16.26 x 13.84 x 21.59mm

## OPTIONS AND PART IDENTIFICATION

ARJ11D -  -  -  -  -  -  -


| Mechanical                                | Schematic                                 | Left LED color<br>(e.g. B for Yellow,<br>AB for Green-Yellow)   | Right LED color<br>(e.g. B for Yellow,<br>AB for Green-Yellow)  | LED polarity                                                    | Turns Ratio (Tx)                                                                                                 | Turns Ratio (Rx)                                                                                                 | Gold plating                                           |
|-------------------------------------------|-------------------------------------------|-----------------------------------------------------------------|-----------------------------------------------------------------|-----------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------|
| MA, MB<br>(Please see mechanical section) | SA ~ SR<br>(Please see schematic section) | Blank: No LED<br>A: Green<br>B: Yellow<br>C: Amber<br>D: Orange | Blank: No LED<br>A: Green<br>B: Yellow<br>C: Amber<br>D: Orange | Blank: No LED<br>E ~ I<br>(Please see 7.0 LED polarity section) | K: 1CT:1.41<br>L: 1CT:1<br>M: 1CT:1CT<br>N: 1.414:1CT<br>O: 1CT:1.41CT<br>P: 1:2CT<br>Q: 1:1.414CT<br>R: 1CT:2.5 | S: 1CT:1.41<br>T: 1CT:1<br>U: 1CT:1CT<br>V: 1.414:1CT<br>W: 1CT:1.41CT<br>X: 1:2CT<br>Y: 1:1.414CT<br>Z: 1CT:2.5 | 1: 3u "<br>2: 6u "<br>3: 15u "<br>4: 30u "<br>5: 50u " |

## MECHANICAL DIMENSIONS



Dimension: mm. All tolerances are  $\pm 0.25$

ABRACON IS  
ISO 9001:2008  
CERTIFIED



**ABRACON**  
CORPORATION

Visit [www.abracon.com](http://www.abracon.com) for Terms & Conditions of Sale  
30332 Esperanza, Rancho Santa Margarita, California 92688  
tel 949-546-8000 | fax 949-546-8001 | [www.abracon.com](http://www.abracon.com)

Revised: 05.03.11

# RJ45 10/100 Base-T Jack with Magnetic Module



ARJ11D

RoHS  
Compliant



16.26 x 13.84 x 21.59mm

## SCHEMATICS



# RJ45 10/100 Base-T Jack with Magnetic Module



ARJ11D

RoHS  
Compliant



16.26 x 13.84 x 21.59mm

## SCHEMATICS - continued



# RJ45 10/100 Base-T Jack with Magnetic Module


ARJ11D

RoHS  
Compliant



16.26 x 13.84 x 21.59mm



## LED POLARITY




## PACKING: 60pcs/tray

Packing 60pcs/tray  
Packaging material: PET

Outer carton unit 1320 pcs/ 22 Trays/box




## REFLOW PROFILE:



**ATTENTION:** Abracon Corporation's products are COTS – Commercial-Off-The-Shelf products; suitable for Commercial, Industrial and, where designated, Automotive Applications. Abracon's products are not specifically designed for Military, Aviation, Aerospace, Life-dependant Medical applications or any application requiring high reliability where component failure could result in loss of life and/or property. For applications requiring high reliability and/or presenting an extreme operating environment, written consent and authorization from Abracon Corporation is required. Please contact Abracon Corporation for more information.

ABRACON IS  
ISO 9001:2008  
CERTIFIED



**ABRACON**  
CORPORATION

Visit [www.abracon.com](http://www.abracon.com) for Terms & Conditions of Sale  
30332 Esperanza, Rancho Santa Margarita, California 92688  
tel 949-546-8000 | fax 949-546-8001 | [www.abracon.com](http://www.abracon.com)

Revised: 05.03.11

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9