

Voltage Variable Attenuator 5 - 45 GHz

Rev. V1

Features

- 5 - 45 GHz Frequency Range
- 1.5 dB Insertion Loss @ 20 GHz
- >30 dB Attenuation Range
- High Linearity, 30 dBm IIP3
- Lead-Free 3 mm, 16-Lead QFN Package
- RoHS* Compliant

Description

The MAAV-011013 is a voltage variable attenuator with analog control and greater than 30 dB of attenuation. Excellent linearity is maintained over the full attenuation range. The attenuation level is set by two control voltages of 0 to -2 V. This device is assembled in a lead free 3 mm 16 lead PQFN plastic package.


Applications include transceivers for cellular infrastructure.

Ordering Information^{1,2}

| Part Number | Package |
|--------------------|----------------|
| MAAV-011013-TR0500 | 500 Part Reel |
| MAAV-011013-TR1000 | 1000 Part Reel |
| MAAV-011013-001SMB | Sample Board |

1. Reference Application Note M513 for reel size information.
2. All sample boards include 5 loose parts.

Functional Block Diagram



Pin Configuration^{3,4}

| Pin No. | Function |
|---------|-----------------|
| 1 | No Connection |
| 2 | Ground |
| 3 | RF Input |
| 4 | Ground |
| 5 | No Connection |
| 6 | V _{C1} |
| 7 | V _{C2} |
| 8 | No Connection |
| 9 | Ground |
| 10 | RF Output |
| 11 | Ground |
| 12 - 16 | No Connection |

3. It is recommended to connect unused pins to ground.
4. The exposed pad centered on the package bottom must be connected to RF, DC and thermal ground.

* Restrictions on Hazardous Substances, European Union Directive 2011/65/EU.

Voltage Variable Attenuator 5 - 45 GHz

Rev. V1

Electrical Specifications: $T_A = +25^\circ\text{C}$, $Z_0 = 50 \Omega$, $P_{IN} = -10 \text{ dBm}$

| Parameter | Test Conditions | Units | Min. | Typ. | Max. |
|---|--|-------|----------------------|----------------------|------|
| Insertion Loss (V_{C1} and $V_{C2} = -2 \text{ V}$) | 5.9 - 15.5 GHz | dB | — | 1.5 | 4.0 |
| | 17.6 - 20 GHz | | | 1.5 | 4.0 |
| | 20 - 30 GHz | | | 2.5 | 6.0 |
| | 30 - 34 GHz | | | 2.5 | 6.5 |
| | 37 - 40 GHz | | | 3.0 | 7.0 |
| Attenuation (V_{C1} and $V_{C2} = 0 \text{ V}$) ⁵ | 5.9 - 8.5 GHz | dB | 22.5 | 25.0 | — |
| | 10 - 11.7 GHz | | 27.5 | 32.0 | |
| | 12.75-15.35 GHz | | 29.5 | 35.0 | |
| | 17.6 - 20 GHz | | 31.0 | 35.0 | |
| | 20 - 30 GHz | | 33.5 | 39.0 | |
| | 30 - 34 GHz | | 31.0 | 37.0 | |
| | 37 - 40 GHz | | 30.0 | 36.0 | |
| Input P1dB ⁶ | 5 - 25 GHz | dBm | 24 | 25 | — |
| | 25 - 40 GHz | | 20 | 22 | |
| IIP3 (any attenuation) | $P_{IN} = 12 \text{ dBm/tone @ } 5.0 - 15.0 \text{ GHz}$ $P_{IN} = 12 \text{ dBm/tone @ } 15.0 - 26.5 \text{ GHz}$ $P_{IN} = 12 \text{ dBm/tone @ } 26.5 - 40.0 \text{ GHz}$ | dBm | 29.0 27.5 27.0 | 31.0 30.0 31.0 | — |
| IIP3 ($V_{C1}=V_{C2}=-2 \text{ V}$) | $P_{IN} = 12 \text{ dBm/tone @ } 5 - 40 \text{ GHz}$ | dBm | — | 42 | — |
| Input Return Loss (any attenuation) | — | dB | — | 10 | — |
| Output Return Loss (any attenuation) | — | dB | — | 10 | — |

5. To increase attenuation from minimum attenuation state ($V_{C1} = -2 \text{ V}$ and $V_{C2} = -2 \text{ V}$) to max attenuation state ($V_{C1} = 0 \text{ V}$ and $V_{C2} = 0 \text{ V}$), V_{C1} increases to full range prior to adjusting V_{C2} .

6. Guaranteed on MACOM Sample Board only

Absolute Maximum Ratings^{7,8}

| Parameter | Absolute Maximum |
|------------------------|------------------|
| Input Power | 30 dBm |
| Voltage (RF pins) | 30 V |
| Voltage (control pins) | +1 V to -6 V |
| Storage Temperature | -55°C to +150°C |
| Case Temperature | -40°C to +85°C |

- Exceeding any one or combination of these limits may cause permanent damage to this device.
- MACOM does not recommend sustained operation near these survivability limits.

Handling Procedures

The following precautions should be observed to avoid damage:

Static Sensitivity


Gallium Arsenide Integrated Circuits are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these HBM Class 1A devices.

Voltage Variable Attenuator 5 - 45 GHz


Rev. V1

Typical Performance Curves: @ +25°C



Gain



Input Return Loss




Output Return Loss




Typical Performance Curves: S-Parameters @ +25°C


S-Parameters $V_{C1} = -2.0 V, V_{C2} = -2.0 V$




S-Parameters $V_{C1} = -0.6 V, V_{C2} = -2.0 V$




S-Parameters $V_{C1} = -0.4 V, V_{C2} = -2.0 V$



S-Parameters $V_{C1} = -0.1 V, V_{C2} = -2.0 V$




S-Parameters $V_{C1} = 0 V, V_{C2} = -0.6 V$




Typical Performance Curves: Power Gain, Freq. 16 GHz


Power Gain @ $V_{C1} = -2.0\text{ V}$, $V_{C2} = -2.0\text{ V}$



Power Gain @ $V_{C1} = -0.4\text{ V}$, $V_{C2} = -2.0\text{ V}$



Power Gain @ $V_{C1} = 0\text{ V}$, $V_{C2} = -2.0\text{ V}$




Voltage Variable Attenuator 5 - 45 GHz


Rev. V1

Typical Performance Curves: Power Gain @ +25°C


Power Gain @ $V_{C1} = -2.0$ V, $V_{C2} = -2.0$ V




Power Gain @ $V_{C1} = 0$ V, $V_{C2} = -2.0$ V




Power Gain @ $V_{C1} = -0.4$ V, $V_{C2} = -2.0$ V



Power Gain @ $V_{C1} = 0$ V, $V_{C2} = -0.6$ V



Power Gain @ $V_{C1} = 0$ V, $V_{C2} = 0$ V




Voltage Variable Attenuator 5 - 45 GHz


Rev. V1

Typical Performance Curves: Input IP3


Input IP3 vs. Frequency
@ $V_{C1} = -2.0\text{ V}$, $V_{C2} = -2.0\text{ V}$




Input IP3 vs. SCL Input Power
@ $V_{C1} = -2.0\text{ V}$, $V_{C2} = -2.0\text{ V}$




Input IP3 vs. Attenuation, SCL $P_{IN} = 6\text{ dBm}$



Input IP3 vs. Attenuation, SCL $P_{IN} = 12\text{ dBm}$



Lead-Free 3 mm 16-Lead PQFN[†]



[†] Reference Application Note S2083 for lead-free solder reflow recommendations.
Meets JEDEC moisture sensitivity level 1 requirements.
Plating is NiPdAuAg.

MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9