

# Small Signal Transistors

## TO-39 Case



TYPE NO.	DESCRIPTION	V <sub>CB0</sub>	V <sub>CE0</sub>	V <sub>EBO</sub>	I <sub>CBO</sub> @ I <sub>CEO</sub> I <sub>ICES</sub> I <sub>CEV</sub> I <sub>CER</sub>	V <sub>CB</sub>	h <sub>FE</sub>		@ I <sub>C</sub>	@ V <sub>CE</sub>	V <sub>CE(SAT)</sub>	@ I <sub>C</sub>	f <sub>T</sub>	C <sub>ob</sub>	t <sub>on</sub>	t <sub>off</sub>	NF	
		(V)	(V)	(V)			(V)	(V)	(mA)	(V)	(V)	(mV)	(mV)	(MHz)	(pF)	(ns)	(ns)	(dB)
		MIN	*V <sub>CER</sub> MIN	MIN			MIN	MIN	MIN	MAX			MAX		MIN	MAX	MAX	MAX
2N656A	NPN AMPL/SWITCH	60	60	6.0	10	30	30	90	200	10	2.00	200	50	20	--	--	--	
2N657A	NPN AMPL/SWITCH	100	100	6.0	10	30	30	90	200	10	2.00	200	50	20	--	--	--	
2N696	NPN AMPL/SWITCH	60	40	5.0	1.00	30	20	60	150	10	1.50	150	80	35	--	--	--	
2N697A	NPN AMPL/SWITCH	60	35	5.0	1.00	30	40	120	150	10	1.50	150	50	35	--	--	--	
2N698	NPN AMPL/SWITCH	120	60	7.0	0.05	75	20	60	150	10	1.50	150	50	15	--	--	--	
2N699B	NPN AMPL/SWITCH	120	80	7.0	0.01	90	40	120	150	10	1.30	150	60	15	--	--	--	
2N1052	NPN HIGH VOLTAGE	200	155	6.0	10	200	20	80	200	6.0	5.00	200	8.0	50	--	--	--	
2N1053	NPN AMPL/SWITCH	180	135	6.0	10	180	20	80	200	6.0	5.00	200	8.0	50	--	--	--	
2N1054	NPN AMPL/SWITCH	125	115	6.0	5.00	125	20	--	200	6.0	4.00	200	8.0	50	--	--	--	
2N1055	NPN AMPL/SWITCH	100	100	6.0	15	100	20	80	50	6.0	2.00	50	3.0	--	--	--	--	
2N1116	NPN AMPL/SWITCH	60	60	6.0	15	60	40	150	500	6.0	5.00	500	6.0	80	--	--	--	
2N1117	NPN AMPL/SWITCH	60	60	6.0	15	60	40	150	200	6.0	4.00	200	4.0	--	--	--	--	
2N1118	PNP AMPL/SWITCH	25	25	6.0	1.00	25	15	--	1.0	6.0	--	--	--	12	--	--	--	
2N1119	PNP AMPL/SWITCH	10	10	6.0	0.10	10	15	--	15	0.5	0.15	5.0	--	12	--	--	--	
2N1131	PNP AMPL/SWITCH	50	35	5.0	100	50	20	45	150	10	1.50	150	50	45	--	--	--	
2N1131A	PNP AMPL/SWITCH	60	40	5.0	0.50	45	20	45	150	10	1.50	150	90	45	--	--	--	
2N1132B	PNP AMPL/SWITCH	70	50	6.0	0.10	50	30	75	150	10	1.50	150	90	30	--	--	--	
2N1258	PNP AMPL/SWITCH	30	30	5.0	0.20	20	75	150	10	1.0	0.60	10	--	10	--	--	--	
2N1259	PNP AMPL/SWITCH	50	50	5.0	0.20	30	25	100	10	1.0	0.30	10	--	10	--	--	--	
2N1420	NPN AMPL/SWITCH	60	30	5.0	1.00	30	100	300	150	10	1.50	150	50	35	--	--	--	
2N1445	NPN AMPL/SWITCH	120	120	6.0	10	120	20	80	200	10	4.00	200	--	--	--	--	--	
2N1479	NPN AMPL/SWITCH	60	40	6.0	10	30	20	60	200	4.0	1.40	200	1.5	--	--	--	--	
2N1480	NPN AMPL/SWITCH	100	55	6.0	10	30	20	60	200	4.0	1.40	200	1.5	--	--	--	--	
2N1481	NPN AMPL/SWITCH	60	40	6.0	10	30	35	100	200	4.0	1.40	200	1.5	--	--	--	--	
2N1482	NPN AMPL/SWITCH	100	55	6.0	10	30	35	100	200	4.0	1.40	200	1.5	--	--	--	--	
2N1507	NPN AMPL/SWITCH	60	25	5.0	1.00	30	100	300	150	10	1.50	150	50	35	--	--	--	
2N1573	NPN AMPL/SWITCH	125	80	5.0	1.00	40	30	100	5.0	5.0	1.00	10	60	10	--	--	--	
2N1574	NPN AMPL/SWITCH	125	80	5.0	1.00	40	60	200	5.0	5.0	1.00	10	60	10	--	--	--	
2N1613B	NPN AMPL/SWITCH	120	50	7.0	0.10	60	40	120	150	10	0.20	150	60	10	--	--	--	
2N1615	NPN AMPL/SWITCH	100	100	6.0	2.00	60	25	--	5.0	10	5.00	50	5.0	20	--	--	--	
2N1676	PNP AMPL/SWITCH	4.5	4.5	4.5	0.10	4.5	25	--	2.0	0.2	1.50	10	40	7.0	--	--	--	
2N1700	NPN AMPL/SWITCH	60	40	6.0	75	40	20	80	100	4.0	1.00	100	--	--	--	--	--	
2N1711	NPN AMPL/SWITCH	75	50	7.0	0.10	60	100	300	150	10	1.00	150	70	25	--	--	--	
2N1711B	NPN AMPL/SWITCH	120	50	7.0	0.10	60	100	300	150	10	0.20	150	70	10	--	--	--	
2N1716	NPN AMPL/SWITCH	60	60	6.0	2.00	60	40	120	200	5.0	2.00	200	16	50	--	--	--	
2N1717	NPN AMPL/SWITCH	100	100	6.0	1.00	75	40	120	200	5.0	2.00	200	16	50	--	--	--	
2N1889	NPN AMPL/SWITCH	100	60	7.0	0.10	75	40	120	150	10	5.00	150	50	15	--	--	--	
2N1890	NPN AMPL/SWITCH	100	60	7.0	0.10	75	100	300	150	10	1.20	50	60	15	--	--	--	
2N1893A	NPN AMPL/SWITCH	140	80	7.0	0.10	90	40	120	150	10	2.00	150	100	8.0	--	--	--	
2N1973	NPN AMPL/SWITCH	100	60	7.0	0.025	75	75	--	10	10	1.20	50	60	15	--	--	--	
2N1974	NPN AMPL/SWITCH	100	60	7.0	0.025	75	35	--	10	10	1.20	50	50	15	--	--	--	

(5-April 2013)

## OUTSTANDING SUPPORT AND SUPERIOR SERVICES



---

### PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

---

### DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2<sup>nd</sup> day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

---

### REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

---

### CONTACT US

#### Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.  
145 Adams Avenue  
Hauppauge, NY 11788 USA  
Main Tel: (631) 435-1110  
Main Fax: (631) 435-1824  
Support Team Fax: (631) 435-3388  
[www.centrasemi.com](http://www.centrasemi.com)

**Worldwide Field Representatives:**  
[www.centrasemi.com/wwreps](http://www.centrasemi.com/wwreps)

**Worldwide Distributors:**  
[www.centrasemi.com/wwdistributors](http://www.centrasemi.com/wwdistributors)

---

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: [www.centrasemi.com/terms](http://www.centrasemi.com/terms)

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9