


4 - 18 GHz VPIN SP3T Switch

TGS2313



Key Features



- 4-18 GHz High Isolation SP3T
- 1.0 dB Typical Insertion Loss
- 35 dB Nominal Isolation
- 12 dB Typical Return Loss
- On-Chip Bias Network
- DC blocked at RF ports
- Chip dimensions: 2.16 x 2.16 x 0.10 mm
(0.085 x 0.085 x 0.004 in)

Primary Applications

- EW Receivers
- Radar
- Communications Systems

Measured Fixtured Data

$I_{control} = \pm 20mA$



Product Description

The TriQuint TGS2313 is a 4-18 GHz Single Pole Triple Throw (SP3T) Switch. This part is designed using TriQuint's proven standard VPIN production process.

The TGS2313 provides a nominal 1.0 dB insertion loss, 12 dB return loss, and 35 dB isolation.

The TGS2313 integrates DC blocking capacitors on all ports and includes decoupled DC bias pads to reduce the number of off-chip components.

The part is ideally suited for EW receivers, radar, and communication systems.

Evaluation Boards are available upon request.

Lead-free and RoHS compliant.

Datasheet subject to change without notice.

**TABLE I
MAXIMUM RATINGS**

Symbol	Parameter 1/	Value	Notes
V^+	Positive Supply Voltage	+3 V	2/, 3/
V^-	Negative Supply Voltage	-3 V	
I^+	Positive Supply Current (Quiescent)	22 mA	2/ 3/
P_{IN}	Input Continuous Wave Power	24 dBm	3/
P_D	Power Dissipated	0.45 W	3/4/
T_M	Mounting Temperature (30 Seconds)	320 °C	
T_{STG}	Storage Temperature	-65 to 150 °C	

- 1/ These ratings represent the maximum operable values for this device.
- 2/ V^+_{max} and I^+_{max} are both per bias pad.
- 3/ Combinations of supply voltage, supply current, input power, and output power shall not exceed P_D .
- 4/ When operated at this bias condition with a base plate temperature of 70 °C, the median life is reduced to TBD hours.

**TABLE II
FUNCTION TABLE**

STATE	RF-A	RF-B	RF-C	Icontrol-A	Icontrol-B	Icontrol-C
1	Low-Loss	Isolated	Isolated	+20 mA	-20mA	-20mA
2	Isolated	Low-Loss	Isolated	-20mA	+20 mA	-20mA
3	Isolated	Isolated	Low-Loss	-20mA	-20mA	+20 mA



TABLE III
RF CHARACTERIZATION TABLE

(T_A = 25 °C, Nominal)

I_{control} = ± 20mA



PARAMETER	THROUGH PATH IDENTIFICATION	TEST CONDITION	NOMINAL	UNITS
Insertion Loss	RF Input to RF Output A	f = 4 – 18 GHz	1.0	dB
Isolation	RF Input to RF Output B RF Input to RF Output C	f = 4 – 18 GHz	35	dB
Input Return Loss	RF Input to RF Output A RF Input to RF Output B RF Input to RF Output C	f = 4 – 18 GHz	12	dB
Output Return Loss	RF Input to RF Output A RF Input to RF Output B RF Input to RF Output C	f = 4 – 18 GHz	12	dB

Measured Fixtured Data
Bias Conditions: $I_{control} = \pm 20$ mA




Measured Fixtured Data


Bias Conditions: $I_{control} = \pm 20$ mA



Equivalent Schematic



Mechanical Drawing



Units: millimeters (inches)

Thickness: 0.100 (0.004)


Chip edge to bond pad dimensions are shown to center of bond pad

Chip size tolerance: +/- 0.051 (0.002)

GND IS BACKSIDE OF MMIC

Bond pad #1	(Vc)	0.114 x 0.142 (0.004 x 0.006)
Bond pad #2	(Vb)	0.114 x 0.142 (0.004 x 0.006)
Bond pad #3	(Va)	0.114 x 0.142 (0.004 x 0.006)
Bond pad #4	(RF Output A)	0.152 x 0.218 (0.006 x 0.009)
Bond pad #5	(RF Output B)	0.218 x 0.152 (0.009 x 0.006)
Bond pad #6	(RF Output C)	0.152 x 0.218 (0.006 x 0.009)
Bond pad #7	(RF Input)	0.218 x 0.152 (0.009 x 0.006)

Assembly Drawing



Note:

± 20mA control lines (IControl_A, IControl_B, IControl_C) use on-chip resistors for diode current control.

GaAs MMIC devices are susceptible to damage from Electrostatic Discharge. Proper precautions should be observed during handling, assembly and test.

Assembly Process Notes

Reflow process assembly notes:

- Use AuSn (80/20) solder with limited exposure to temperatures at or above 300 °C for 30 sec.
- An alloy station or conveyor furnace with reducing atmosphere should be used.
- No fluxes should be utilized.
- Coefficient of thermal expansion matching is critical for long-term reliability.
- Devices must be stored in a dry nitrogen atmosphere.

Component placement and adhesive attachment assembly notes:

- Vacuum pencils and/or vacuum collets are the preferred method of pick up.
- Air bridges must be avoided during placement.
- The force impact is critical during auto placement.
- Organic attachment can be used in low-power applications.
- Curing should be done in a convection oven; proper exhaust is a safety concern.
- Microwave or radiant curing should not be used because of differential heating.
- Coefficient of thermal expansion matching is critical.

Interconnect process assembly notes:

- Thermosonic ball bonding is the preferred interconnect technique.
- Force, time, and ultrasonics are critical parameters.
- Aluminum wire should not be used.
- Discrete FET devices with small pad sizes should be bonded with 0.0007-inch wire.
- Maximum stage temperature is 200 °C.

GaAs MMIC devices are susceptible to damage from Electrostatic Discharge. Proper precautions should be observed during handling, assembly and test.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9