74AVCH20T245

20-bit dual supply translating transceiver with configurable voltage translation; 3-state

Rev. 6 — 14 January 2019

Product data sheet

1. General description

The 74AVCH20T245 is a 20-bit, dual supply transceiver that enables bi-directional voltage level translation. The device can be used as two 10-bit transceivers or as a single 20-bit transceiver. It features four 10-bit input-output ports (1An, 1Bn and 2An, 2Bn), two output enable inputs ($n\overline{OE}$), two direction inputs (nDIR) and dual supplies ($V_{CC(A)}$ and $V_{CC(B)}$). $V_{CC(A)}$ and $V_{CC(B)}$ can be independently supplied at any voltage between 0.8 V and 3.6 V making the device suitable for bi-directional voltage level translation between any of the low voltage nodes: 0.8 V, 1.2 V, 1.5 V, 1.8 V, 2.5 V and 3.3 V. The 1An and 2An ports, $n\overline{OE}$ and nDIR are referenced to $V_{CC(A)}$, the 1Bn and 2Bn ports are referenced to $V_{CC(B)}$. A HIGH on a 1DIR allows transmission from 1An to 1Bn and a LOW on 1DIR allows transmission from 1Bn to 1An. A HIGH on $n\overline{OE}$ causes the outputs to assume a HIGH impedance OFF-state.

The device is fully specified for partial power-down applications using I_{OFF} . The I_{OFF} circuitry disables the output, preventing any damaging backflow current through the device when it is powered down. In suspend mode when either $V_{CC(A)}$ or $V_{CC(B)}$ are at GND level, all output ports will assume a high impedance OFF-state. The bus hold circuitry on the powered-up side always stays active.

The 74AVCH20T245 has active bus hold circuitry which is provided to hold unused or floating data inputs at a valid logic level. This feature eliminates the need for external pull-up or pull-down resistors.

2. Features and benefits

- Wide supply voltage range:
 - V_{CC(A)}: 0.8 V to 3.6 V
 - V_{CC(B)}: 0.8 V to 3.6 V
- Complies with JEDEC standards:
 - JESD8-12 (0.8 V to 1.3 V)
 - JESD8-11 (0.9 V to 1.65 V)
 - JESD8-7 (1.2 V to 1.95 V)
 - JESD8-5 (1.8 V to 2.7 V)
 - JESD8-B (2.7 V to 3.6 V)
- ESD protection:
 - HBM JESD22-A114E Class 3B exceeds 8000 V
 - MM JESD22-A115-A exceeds 200 V
 - CDM JESD22-C101C exceeds 1000 V

ne<mark>x</mark>peria

- Maximum data rates:
 - 380 Mbit/s (≥ 1.8 V to 3.3 V translation)
 - 260 Mbit/s (≥ 1.1 V to 3.3 V translation)
 - 260 Mbit/s (≥ 1.1 V to 2.5 V translation)
 - 210 Mbit/s (≥ 1.1 V to 1.8 V translation)
 - 120 Mbit/s (≥ 1.1 V to 1.5 V translation)
 - 100 Mbit/s (≥ 1.1 V to 1.2 V translation)
 - Suspend mode
- Bus hold on data inputs
- Latch-up performance exceeds 100 mA per JESD 78 Class II
- Inputs accept voltages up to 3.6 V
- IOFF circuitry provides partial Power-down mode operation
- Multiple package options
- Specified from -40 °C to +85 °C and -40 °C to +125 °C

3. Ordering information

•

Table 1. Ordering information

| Type number | Package | kage | | | | | | | |
|-----------------|-------------------|---------|---|----------|--|--|--|--|--|
| | Temperature range | Name | Description | Version | | | | | |
| 74AVCH20T245DGG | -40 °C to +125 °C | TSSOP56 | plastic thin shrink small outline package; 56 leads; body width 6.1 mm | SOT364-1 | | | | | |

4. Functional diagram





5. Pinning information



5.1. Pinning

5.2. Pin description

Table 2. Pin description

| Symbol | Pin | Description |
|--------------------|---------------------------------------|---|
| 1DIR, 2DIR | 1, 28 | direction control |
| 1B1 to 1B10 | 2, 3, 5, 6, 8, 9, 10, 12, 13, 14 | data input or output |
| 2B1 to 2B10 | 15, 16, 17, 19, 20, 21, 23, 24,26, 27 | data input or output |
| GND[1] | 4, 11, 18, 25, 32, 39, 46, 53 | ground (0 V) |
| V _{CC(B)} | 7, 22 | supply voltage B (nBn inputs are referenced to $V_{CC(B)}$) |
| 10E, 20E | 56, 29 | output enable input (active LOW) |
| 1A1 to 1A10 | 55, 54, 52, 51, 49, 48, 47, 45,44, 43 | data input or output |
| 2A1 to 2A10 | 42, 41, 40, 38, 37, 36, 34, 33,31, 30 | data input or output |
| V _{CC(A)} | 35, 50 | supply voltage A (nAn, n $\overline{\text{OE}}$ and nDIR inputs are referenced to $V_{\text{CC}(A)})$ |

[1] All GND pins must be connected to ground (0 V).

6. Functional description

Table 3. Function table

| | | - | |
|---|---|---|--|
| | ~ | | |
| | | | |
| | | | |
| | | | |
| _ | | | |

| Supply voltage | Input | | Input/output [2] | | |
|---|-----------------------|----------|------------------|-----------|--|
| V _{CC(A)} , V _{CC(B)} | n <mark>OE [3]</mark> | nDIR [3] | nAn [3] | nBn [3] | |
| 0.8 V to 3.6 V | L | L | nAn = nBn | input | |
| 0.8 V to 3.6 V | L | Н | input | nBn = nAn | |
| 0.8 V to 3.6 V | Н | Х | Z | Z | |
| GND [2] | Х | Х | Z | Z | |

[1] H = HIGH voltage level; L = LOW voltage level; X = don't care; Z = high-impedance OFF-state.

[2] If at least one of V_{CC(A)} or V_{CC(B)} is at GND level, the device goes into suspend mode.
 [3] The nAn, nDIR and nOE input circuit is referenced to V_{CC(A)}; The nBn input circuit is referenced to V_{CC(B)}.

7. Limiting values

Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

| Symbol | Parameter | Conditions | | Min | Max | Unit |
|--------------------|-------------------------|--|-------|------|------------------------|------|
| V _{CC(A)} | supply voltage A | | | -0.5 | +4.6 | V |
| V _{CC(B)} | supply voltage B | | | -0.5 | +4.6 | V |
| I _{IK} | input clamping current | V ₁ < 0 V | | -50 | - | mA |
| VI | input voltage | | [1] | -0.5 | +4.6 | V |
| I _{ОК} | output clamping current | V _O < 0 V | | -50 | - | mA |
| Vo | output voltage | Active mode [1][2 | 2][3] | -0.5 | V _{CCO} + 0.5 | V |
| | | Suspend or 3-state mode | [1] | -0.5 | +4.6 | V |
| I _O | output current | $V_{O} = 0 V$ to V_{CCO} | [2] | - | ±50 | mA |
| I _{CC} | supply current | I _{CC(A)} or I _{CC(B)} | | - | 100 | mA |
| I _{GND} | ground current | | | -100 | - | mA |
| T _{stg} | storage temperature | | | -65 | +150 | °C |
| P _{tot} | total power dissipation | T _{amb} = -40 °C to +125 °C | [4] | - | 600 | mW |

[1] The minimum input and minimum output voltage ratings may be exceeded if the input and output clamping current ratings are observed.

[2] V_{CCO} is the supply voltage associated with the output port.

[3] V_{CCO} + 0.5 V should not exceed 4.6 V.

[4] Above 55 °C the value of P_{tot} derates linearly with 8.0 mW/K.

8. Recommended operating conditions

Table 5. Recommended operating conditions

| Symbol | Parameter | Conditions | Min | Max | Unit |
|--------------------|-------------------------------------|---------------------------------------|-----|------------------|------|
| V _{CC(A)} | supply voltage A | | 0.8 | 3.6 | V |
| V _{CC(B)} | supply voltage B | | 0.8 | 3.6 | V |
| VI | input voltage | | 0 | 3.6 | V |
| Vo | output voltage | Active mode [1] | 0 | V _{CCO} | V |
| | | Suspend or 3-state mode | 0 | 3.6 | V |
| T _{amb} | ambient temperature | | -40 | +125 | °C |
| Δt/ΔV | input transition rise and fall rate | V _{CCI} = 0.8 V to 3.6 V [2] | - | 5 | ns/V |

[1] V_{CCO} is the supply voltage associated with the output port.

[2] V_{CCI} is the supply voltage associated with the input port.

9. Static characteristics

Table 6. Typical static characteristics at T_{amb} = 25 °C

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).[1] [2]

| Symbol | Parameter | Conditions | | Min | Тур | Max | Unit |
|-------------------|------------------------------------|---|-----|-----|--------|-------|------|
| V _{OH} | HIGH-level output voltage | $V_{I} = V_{IH} \text{ or } V_{IL}$ | | | | | |
| | | I_{O} = -1.5 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 0.8 V | | - | 0.69 | - | V |
| V _{OL} | LOW-level output voltage | $V_{I} = V_{IH} \text{ or } V_{IL}$ | | | | | |
| | | I _O = 1.5 mA; V _{CC(A)} = V _{CC(B)} = 0.8 V | | - | 0.07 | - | V |
| l _l | input leakage current | nDIR, n \overline{OE} input; V _I = 0 V or 3.6 V; V _{CC(A)} = V _{CC(B)} = 0.8 V to 3.6 V | | - | ±0.025 | ±0.25 | μA |
| I _{BHL} | bus hold LOW current | A or B port; V_I = 0.42 V; $V_{CC(A)}$ = $V_{CC(B)}$ = 1.2 V | [3] | - | 26 | - | μA |
| I _{BHH} | bus hold HIGH current | A or B port; $V_1 = 0.78 V$; $V_{CC(A)} = V_{CC(B)} = 1.2 V$ | [4] | - | -24 | - | μA |
| I _{BHLO} | bus hold LOW overdrive current | A or B port; $V_{CC(A)} = V_{CC(B)} = 1.2 V$ | [5] | - | 27 | - | μA |
| I _{BHHO} | bus hold HIGH overdrive current | A or B port; $V_{CC(A)} = V_{CC(B)} = 1.2 V$ | [6] | - | -26 | - | μA |
| I _{OZ} | OFF-state output current | A or B port; $V_O = 0 V$ or V_{CCO} ; $V_{CC(A)} = V_{CC(B)} = 3.6 V$ | [7] | - | ±0.5 | ±2.5 | μA |
| | | suspend mode A port; $V_O = 0 V$ or V_{CCO} ; $V_{CC(A)} = 3.6 V$; $V_{CC(B)} = 0 V$ | [7] | - | ±0.5 | ±2.5 | μA |
| | | suspend mode B port; $V_O = 0 V \text{ or } V_{CCO}$; $V_{CC(A)} = 0 V$; $V_{CC(B)} = 3.6 V$ | [7] | - | ±0.5 | ±2.5 | μA |
| I _{OFF} | power-off leakage current | A port; V ₁ or V _O = 0 V to 3.6 V; V _{CC(A)} = 0 V; V _{CC(B)} = 0.8 V to 3.6 V | | - | ±0.1 | ±1 | μA |
| | | B port; V ₁ or V _O = 0 V to 3.6 V; V _{CC(B)} = 0 V; V _{CC(A)} = 0.8 V to 3.6 V | | - | ±0.1 | ±1 | μA |
| CI | input capacitance | nDIR, n \overline{OE} input; V _I = 0 V or 3.3 V; V _{CC(A)} = V _{CC(B)} = 3.3 V | | - | 2.0 | - | pF |
| C _{I/O} | input/output capacitance | A and B port; $V_0 = 3.3 V \text{ or } 0 V$; $V_{CC(A)} = V_{CC(B)} = 3.3 V$ | | - | 4.0 | - | pF |

[1] V_{CCO} is the supply voltage associated with the output port.

[2] V_{CCI} is the supply voltage associated with the data input port.

[3] The bus hold circuit can sink at least the minimum low sustaining current at V_{IL} max. I_{BHL} should be measured after lowering V_I to GND and then raising it to V_{IL} max.

[4] The bus hold circuit can source at least the minimum high sustaining current at V_{IH} min. I_{BHH} should be measured after raising V_I to V_{CC} and then lowering it to V_{IH} min.

[5] An external driver must source at least I_{BHLO} to switch this node from LOW to HIGH.

[6] An external driver must sink at least I_{BHHO} to switch this node from HIGH to LOW.

[7] For I/O ports, the parameter I_{OZ} includes the input leakage current.

Table 7. Static characteristics

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).[1] [2]

| Symbol | Parameter | Conditions | -40 °C t | o +85 °C | -40 °C to | Unit | |
|-----------------|--------------------------|---|------------------------|------------------------|------------------------|------------------------|----|
| | | | Min | Max | Min | Max | |
| V _{IH} | HIGH-level | data input | | | | | |
| | input voltage | V _{CCI} = 0.8 V | 0.70V _{CCI} | - | 0.70V _{CCI} | - | V |
| | | V _{CCI} = 1.1 V to 1.95 V | 0.65V _{CCI} | - | 0.65V _{CCI} | - | V |
| | | V _{CCI} = 2.3 V to 2.7 V | 1.6 | - | 1.6 | - | V |
| | | V _{CCI} = 3.0 V to 3.6 V | 2 | - | 2 | - | V |
| | | nDIR, nOE input | | | | | |
| | | V _{CC(A)} = 0.8 V | 0.70V _{CC(A)} | - | 0.70V _{CC(A)} | - | V |
| | | V _{CC(A)} = 1.1 V to 1.95 V | 0.65V _{CC(A)} | - | 0.65V _{CC(A)} | - | V |
| | | V _{CC(A)} = 2.3 V to 2.7 V | 1.6 | - | 1.6 | - | V |
| | | V _{CC(A)} = 3.0 V to 3.6 V | 2 | - | 2 | - | V |
| V _{IL} | LOW-level | data input | | | | | |
| | input voltage | V _{CCI} = 0.8 V | - | 0.30V _{CCI} | - | 0.30V _{CCI} | V |
| | | V _{CCI} = 1.1 V to 1.95 V | - | 0.35V _{CCI} | - | 0.35V _{CCI} | V |
| | | V _{CCI} = 2.3 V to 2.7 V | - | 0.7 | - | 0.7 | V |
| | | V _{CCI} = 3.0 V to 3.6 V | - | 0.8 | - | 0.8 | V |
| | | nDIR, nOE input | | | | | |
| | | V _{CC(A)} = 0.8 V | - | 0.30V _{CC(A)} | - | 0.30V _{CC(A)} | V |
| | | V _{CC(A)} = 1.1 V to 1.95 V | - | 0.35V _{CC(A)} | - | 0.35V _{CC(A)} | V |
| | | V _{CC(A)} = 2.3 V to 2.7 V | - | 0.7 | - | 0.7 | V |
| | | V _{CC(A)} = 3.0 V to 3.6 V | - | 0.8 | - | 0.8 | V |
| V _{OH} | HIGH-level | $V_{I} = V_{IH} \text{ or } V_{IL}$ | | | | | |
| | output voltage | I _O = -100 μA; V _{CC(A)} = V _{CC(B)} = 0.8 V to 3.6 V | V _{CCO} - 0.1 | - | V _{CCO} - 0.1 | - | V |
| | | I_{O} = -3 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 1.1 V | 0.85 | - | 0.85 | - | V |
| | | I_{O} = -6 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 1.4 V | 1.05 | - | 1.05 | - | V |
| | | I _O = -8 mA; V _{CC(A)} = V _{CC(B)} = 1.65 V | 1.2 | - | 1.2 | - | V |
| | | I_{O} = -9 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 2.3 V | 1.75 | - | 1.75 | - | V |
| | | I_{O} = -12 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 3.0 V | 2.3 | - | 2.3 | - | V |
| V _{OL} | LOW-level | $V_{I} = V_{IH} \text{ or } V_{IL}$ | | | | | |
| | output voltage | I _O = 100 μA; V _{CC(A)} = V _{CC(B)} = 0.8 V to 3.6 V | - | 0.1 | - | 0.1 | V |
| | | $I_{O} = 3 \text{ mA}; V_{CC(A)} = V_{CC(B)} = 1.1 \text{ V}$ | - | 0.25 | - | 0.25 | V |
| | | $I_0 = 6 \text{ mA}; V_{CC(A)} = V_{CC(B)} = 1.4 \text{ V}$ | | 0.35 | - | 0.35 | V |
| | | I _O = 8 mA; V _{CC(A)} = V _{CC(B)} = 1.65 V | - | 0.45 | - | 0.45 | V |
| | | $I_{O} = 9 \text{ mA}; V_{CC(A)} = V_{CC(B)} = 2.3 \text{ V}$ | - | 0.55 | - | 0.55 | V |
| | | I_{O} = 12 mA; $V_{CC(A)}$ = $V_{CC(B)}$ = 3.0 V | - | 0.7 | - | 0.7 | V |
| lı | input leakage current | nDIR, n \overline{OE} input; V _I = 0 V or 3.6 V; V _{CC(A)} = V _{CC(B)} = 0.8 V to 3.6 V | - | ±1 | - | ±5 | μA |

74AVCH20T245

| Symbol Parameter | | Conditions | -40 °C t | o +85 °C | -40 °C to +125 °C | | Unit |
|-------------------|--------------------------------------|---|----------|----------|-------------------|-----|------|
| | | | Min | Max | Min | Max | |
| I _{BHL} | bus hold LOW | A or B port [3] | | | | | |
| | current | V _I = 0.49 V; V _{CC(A)} = V _{CC(B)} = 1.4 V | 15 | - | 15 | - | μA |
| | | V _I = 0.58 V; V _{CC(A)} = V _{CC(B)} = 1.65 V | 25 | - | 25 | - | μA |
| | | $V_{I} = 0.70 \text{ V}; V_{CC(A)} = V_{CC(B)} = 2.3 \text{ V}$ | 45 | - | 45 | - | μA |
| | | V _I = 0.80 V; V _{CC(A)} = V _{CC(B)} = 3.0 V | 100 | - | 90 | - | μA |
| I _{BHH} | bus hold | A or B port [4] | | | | | |
| | HIGH current | V _I = 0.91 V; V _{CC(A)} = V _{CC(B)} = 1.4 V | -15 | - | -15 | - | μA |
| | | V _I = 1.07 V; V _{CC(A)} = V _{CC(B)} = 1.65 V | -25 | - | -25 | - | μA |
| | | V _I = 1.60 V; V _{CC(A)} = V _{CC(B)} = 2.3 V | -45 | - | -45 | - | μA |
| | | $V_{I} = 2.00 \text{ V}; V_{CC(A)} = V_{CC(B)} = 3.0 \text{ V}$ | -100 | - | -100 | - | μA |
| I _{BHLO} | bus hold LOW overdrive current | A or B port [5] | | | | | |
| | | $V_{CC(A)} = V_{CC(B)} = 1.6 V$ | 125 | - | 125 | - | μA |
| | | V _{CC(A)} = V _{CC(B)} = 1.95 V | 200 | - | 200 | - | μA |
| | | $V_{CC(A)} = V_{CC(B)} = 2.7 V$ | 300 | - | 300 | - | μA |
| | | $V_{CC(A)} = V_{CC(B)} = 3.6 V$ | 500 | - | 500 | - | μA |
| I _{внно} | bus hold | A or B port [6] | | | | | |
| | HIGH | $V_{CC(A)} = V_{CC(B)} = 1.6 V$ | -125 | - | -125 | - | μA |
| | current | V _{CC(A)} = V _{CC(B)} = 1.95 V | -200 | - | -200 | - | μA |
| | | $V_{CC(A)} = V_{CC(B)} = 2.7 V$ | -300 | - | -300 | - | μA |
| | | $V_{CC(A)} = V_{CC(B)} = 3.6 V$ | -500 | - | -500 | - | μA |
| I _{OZ} | OFF-state output current | A or B port; $V_O = 0$ V or V_{CCO} ; [7] $V_{CC(A)} = V_{CC(B)} = 3.6$ V | - | ±5 | - | ±30 | μA |
| | | suspend mode A port; [7] $V_O = 0 V \text{ or } V_{CCO}; V_{CC(A)} = 3.6 V;$ $V_{CC(B)} = 0 V$ | - | ±5 | - | ±30 | μA |
| | | suspend mode B port; [7] $V_O = 0 V \text{ or } V_{CCO}; V_{CC(A)} = 0 V;$ $V_{CC(B)} = 3.6 V$ | - | ±5 | - | ±30 | μA |
| I _{OFF} | power-off leakage | A port; V_1 or $V_0 = 0$ V to 3.6 V; $V_{CC(A)} = 0$ V; $V_{CC(B)} = 0.8$ V to 3.6 V | - | ±5 | - | ±30 | μA |
| | current | B port; V ₁ or V _O = 0 V to 3.6 V; V _{CC(B)} = 0 V; V _{CC(A)} = 0.8 V to 3.6 V | - | ±5 | - | ±30 | μA |

20-bit dual supply translating transceiver with configurable voltage translation; 3-state

| Symbol | Parameter | Conditions | -40 °C t | o +85 °C | -40 °C to | Unit | |
|-----------------|--|---|----------|----------|-----------|------|----|
| | | | Min | Max | Min | Max | |
| I _{CC} | supply current | A port; $V_I = 0 V$ or V_{CCI} ; $I_O = 0 A$ | | | | | |
| | | V _{CC(A)} = 0.8 V to 3.6 V; V _{CC(B)} = 0.8 V to 3.6 V | - | 45 | - | 190 | μA |
| | | V _{CC(A)} = 1.1 V to 3.6 V; V _{CC(B)} = 1.1 V to 3.6 V | - | 35 | - | 140 | μA |
| | | V _{CC(A)} = 3.6 V; V _{CC(B)} = 0 V | - | 35 | - | 140 | μA |
| | | V _{CC(A)} = 0 V; V _{CC(B)} = 3.6 V | -5 | - | -20 | - | μA |
| | B port; $V_I = 0$ V or V_{CCI} ; $I_O = 0$ A | | | | | | |
| | | $V_{CC(A)} = 0.8 V \text{ to } 3.6 V;$ $V_{CC(B)} = 0.8 V \text{ to } 3.6 V$ | - | 45 | - | 190 | μA |
| | | V _{CC(A)} = 1.1 V to 3.6 V; V _{CC(B)} = 1.1 V to 3.6 V | - | 35 | - | 140 | μA |
| | | V _{CC(A)} = 3.6 V; V _{CC(B)} = 0 V | -5 | - | -20 | - | μA |
| | | V _{CC(A)} = 0 V; V _{CC(B)} = 3.6 V | - | 35 | - | 140 | μA |
| | | A plus B port ($I_{CC(A)} + I_{CC(B)}$); $I_O = 0 A$; $V_I = 0 V \text{ or } V_{CCI}$; $V_{CC(A)} = 0.8 V \text{ to } 3.6 V$; $V_{CC(B)} = 0.8 V \text{ to } 3.6 V$ | - | 80 | - | 270 | μA |
| | | A plus B port ($I_{CC(A)} + I_{CC(B)}$); $I_O = 0 A$; $V_I = 0 V \text{ or } V_{CCI}$; $V_{CC(A)} = 1.1 V \text{ to } 3.6 V$; $V_{CC(B)} = 1.1 V \text{ to } 3.6 V$ | - | 65 | - | 220 | μA |

[1] V_{CCO} is the supply voltage associated with the output port.

[2] V_{CCI} is the supply voltage associated with the data input port.

[3] The bus hold circuit can sink at least the minimum low sustaining current at V_{IL} max. I_{BHL} should be measured after lowering V_I to GND and then raising it to V_{IL} max.

[4] The bus hold circuit can source at least the minimum high sustaining current at V_{IH} min. I_{BHH} should be measured after raising V_I to V_{CC} and then lowering it to V_{IH} min.

[5] An external driver must source at least I_{BHLO} to switch this node from LOW to HIGH.

[6] An external driver must sink at least I_{BHHO} to switch this node from HIGH to LOW.

[7] For I/O ports, the parameter I_{OZ} includes the input leakage current.

Table 8. Typicaltotal supply current (I_{CC(A)} + I_{CC(B)})

| V _{CC(A)} | V _{CC(B)} | | | | | | | |
|--------------------|--------------------|-------|-------|-------|-------|-------|-------|----|
| | 0 V | 0.8 V | 1.2 V | 1.5 V | 1.8 V | 2.5 V | 3.3 V | |
| 0 V | 0 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | μA |
| 0.8 V | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.3 | 1.6 | μA |
| 1.2 V | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.8 | μA |
| 1.5 V | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.4 | μA |
| 1.8 V | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | 0.2 | μA |
| 2.5 V | 0.1 | 0.3 | 0.1 | 0.1 | 0.1 | 0.1 | 0.1 | μA |
| 3.3 V | 0.1 | 1.6 | 0.8 | 0.4 | 0.2 | 0.1 | 0.1 | μA |

10. Dynamic characteristics

Table 9. Typical power dissipation capacitance at $V_{CC(A)} = V_{CC(B)}$ and $T_{amb} = 25 \text{ °C}$ Voltages are referenced to GND (ground = 0 V).[1][2]

| Symbol | Parameter | Conditions | | $V_{CC(A)} = V_{CC(B)}$ | | | | | |
|-----------------|-------------------|---|-------|-------------------------|-------|-------|-------|-------|----|
| | | | 0.8 V | 1.2 V | 1.5 V | 1.8 V | 2.5 V | 3.3 V | |
| C _{PD} | power dissipation | A port: (direction A to B); output enabled | 0.2 | 0.2 | 0.2 | 0.2 | 0.3 | 0.4 | pF |
| capacitance | capacitance | A port: (direction A to B); output disabled | 0.2 | 0.2 | 0.2 | 0.2 | 0.3 | 0.4 | pF |
| | | A port: (direction B to A); output enabled | 9.5 | 9.7 | 9.8 | 9.9 | 10.7 | 11.9 | pF |
| | | A port: (direction B to A); output disabled | 0.6 | 0.6 | 0.6 | 0.6 | 0.7 | 0.7 | pF |
| | | B port: (direction A to B); output enabled | 9.5 | 9.7 | 9.8 | 9.9 | 10.7 | 11.9 | pF |
| | | B port: (direction A to B); output disabled | 0.6 | 0.6 | 0.6 | 0.6 | 0.7 | 0.7 | pF |
| | | B port: (direction B to A); output enabled | 0.2 | 0.2 | 0.2 | 0.2 | 0.3 | 0.4 | pF |
| | | B port: (direction B to A); output disabled | 0.2 | 0.2 | 0.2 | 0.2 | 0.3 | 0.4 | pF |

[1] C_{PD} is used to determine the dynamic power dissipation (P_D in μW).

 $P_{D} = C_{PD} \times V_{CC}^{2} \times f_{i} \times N + \Sigma (C_{L} \times V_{CC}^{2} \times f_{o}) \text{ where:}$

 f_i = input frequency in MHz;

 f_o = output frequency in MHz;

 C_L = load capacitance in pF;

V_{CC} = supply voltage in V;

N = number of inputs switching;

 $\Sigma(C_L \times V_{CC}^2 \times f_0)$ = sum of the outputs.

[2] $f_i = 10 \text{ MHz}$; $V_I = \text{GND}$ to V_{CC} ; $t_r = t_f = 1 \text{ ns}$; $C_L = 0 \text{ pF}$; $R_L = \infty \Omega$.

Table 10. Typical dynamic characteristics at $V_{CC(A)}$ = 0.8 V and T_{amb} = 25 °C

Voltages are referenced to GND (ground = 0 V); for test circuit see Fig. 6; for wave forms see Fig. 4 and Fig. 5.[1]

| Symbol | Parameter | Conditions V _{CC(B)} | | | | | | | Unit |
|------------------|-------------------|-------------------------------|-------|-------|-------|-------|-------|-------|------|
| | | | 0.8 V | 1.2 V | 1.5 V | 1.8 V | 2.5 V | 3.3 V | |
| t _{pd} | propagation delay | nAn to nBn | 14.4 | 7.0 | 6.2 | 6.0 | 5.9 | 6.0 | ns |
| | | nBn to nAn | 14.4 | 12.4 | 12.1 | 11.9 | 11.8 | 11.8 | ns |
| t _{dis} | disable time | n OE to nAn | 16.2 | 16.2 | 16.2 | 16.2 | 16.2 | 16.2 | ns |
| | | n OE to nBn | 17.6 | 10.0 | 9.0 | 9.1 | 8.7 | 9.3 | ns |
| t _{en} | enable time | nOE to nAn | 21.9 | 21.9 | 21.9 | 21.9 | 21.9 | 21.9 | ns |
| | | nOE to nBn | 22.2 | 11.1 | 9.8 | 9.4 | 9.4 | 9.6 | ns |

[1] t_{pd} is the same as t_{PLH} and t_{PHL} ; t_{dis} is the same as t_{PLZ} and t_{PHZ} ; t_{en} is the same as t_{PZL} and t_{PZH} .

Table 11. Typical dynamic characteristics at $V_{CC(B)}$ = 0.8 V and T_{amb} = 25 °C

Voltages are referenced to GND (ground = 0 V); for test circuit see Fig. 6; for wave forms see Fig. 4 and Fig. 5. [1]

| Symbol | Parameter | Conditions | V _{CC(A)} | | | | | | |
|-----------------------------------|--------------|------------|--------------------|-------|-------|-------|-------|-------|----|
| | | | 0.8 V | 1.2 V | 1.5 V | 1.8 V | 2.5 V | 3.3 V | |
| t _{pd} propagation delay | nAn to nBn | 14.4 | 12.4 | 12.1 | 11.9 | 11.8 | 11.8 | ns | |
| | | nBn to nAn | 14.4 | 7.0 | 6.2 | 6.0 | 5.9 | 6.0 | ns |
| t _{dis} | disable time | nOE to nAn | 16.2 | 5.9 | 4.4 | 4.2 | 3.1 | 3.5 | ns |
| | | nOE to nBn | 17.6 | 14.2 | 13.7 | 13.6 | 13.3 | 13.1 | ns |
| t _{en} | enable time | nOE to nAn | 21.9 | 6.4 | 4.4 | 3.5 | 2.6 | 2.3 | ns |
| | | nOE to nBn | 22.2 | 17.7 | 17.2 | 17.0 | 16.8 | 16.7 | ns |

[1] t_{pd} is the same as t_{PLH} and t_{PHL} ; t_{dis} is the same as t_{PLZ} and t_{PHZ} ; t_{en} is the same as t_{PZL} and t_{PZH} .

74AVCH20T245

Table 12. Dynamic characteristics for temperature range -40 °C to +85 °C

Voltages are referenced to GND (ground = 0 V); for test circuit see Fig. 6; for wave forms see Fig. 4 and Fig. 5. [1]

| Symbol | Parameter | Conditions | | | | | Vc | C(B) | | | | | Unit |
|----------------------|-----------------------------|------------------------|---------|---------|---------|---------|---------|----------|---------|---------|---------|---------|------|
| - | | | 1.2 V : | ± 0.1 V | 1.5 V : | ± 0.1 V | 1.8 V ± | : 0.15 V | 2.5 V : | ± 0.2 V | 3.3 V : | ± 0.3 V | - |
| | | | Min | Мах | Min | Max | Min | Мах | Min | Мах | Min | Max | - |
| $V_{CC(A)} =$ | 1.1 V to 1.3 V | | | | | | | | | | | | |
| t _{nd} | propagation | nAn to nBn | 0.5 | 9.4 | 0.5 | 7.1 | 0.5 | 6.2 | 0.5 | 5.2 | 0.5 | 5.1 | ns |
| pa | delay | nBn to nAn | 0.5 | 9.4 | 0.5 | 8.9 | 0.5 | 8.7 | 0.5 | 8.4 | 0.5 | 8.2 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 11.9 | 2.0 | 11.9 | 2.0 | 11.9 | 2.0 | 11.9 | 2.0 | 11.9 | ns |
| ulo | | nOE to nBn | 1.5 | 12.7 | 1.5 | 9.8 | 1.5 | 9.6 | 1.0 | 8.1 | 1.0 | 9.0 | ns |
| t _{en} | enable time | nOE to nAn | 1.5 | 15.3 | 1.5 | 15.3 | 1.5 | 15.3 | 1.5 | 15.3 | 1.5 | 15.3 | ns |
| on | | nOE to nBn | 1.0 | 15.6 | 1.0 | 11.5 | 1.0 | 10.0 | 0.5 | 8.4 | 0.5 | 8.0 | ns |
| $V_{CC(A)} =$ | 1.4 V to 1.6 V | | | | | | | | | | | | |
| t _{nd} | propagation | nAn to nBn | 0.5 | 8.9 | 0.5 | 6.4 | 0.5 | 5.4 | 0.5 | 4.3 | 0.5 | 3.9 | ns |
| pa | delay | nBn to nAn | 0.5 | 7.1 | 0.5 | 6.4 | 0.5 | 6.1 | 0.5 | 5.8 | 0.5 | 5.7 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 9.0 | 2.0 | 9.0 | 2.0 | 9.0 | 2.0 | 9.0 | 2.0 | 9.0 | ns |
| | | nOE to nBn | 1.5 | 11.7 | 1.5 | 9.0 | 1.5 | 7.8 | 1.0 | 6.4 | 1.0 | 6.0 | ns |
| t _{en} | enable time | nOE to nAn | 1.5 | 10.3 | 1.5 | 10.3 | 1.5 | 10.3 | 1.5 | 10.2 | 1.5 | 10.2 | ns |
| 0.1 | | nOE to nBn | 1.0 | 14.3 | 1.0 | 10.3 | 1.0 | 8.4 | 0.5 | 6.1 | 0.5 | 5.3 | ns |
| $V_{CC(A)} =$ | 1.65 V to 1.95 | V | | | | | | | | | | | |
| t _{pd} | t _{nd} propagation | nAn to nBn | 0.5 | 8.7 | 0.5 | 6.1 | 0.5 | 5.0 | 0.5 | 3.9 | 0.5 | 3.5 | ns |
| P- | delay | nBn to nAn | 0.5 | 6.2 | 0.5 | 5.4 | 0.5 | 5.0 | 0.5 | 4.7 | 0.5 | 4.6 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 7.4 | 2.0 | 7.4 | 2.0 | 7.4 | 2.0 | 7.4 | 2.0 | 7.4 | ns |
| | | nOE to nBn | 1.5 | 11.3 | 1.5 | 8.7 | 1.5 | 7.4 | 1.0 | 5.8 | 1.0 | 5.6 | ns |
| t _{en} | enable time | nOE to nAn | 1.0 | 8.1 | 1.0 | 8.1 | 1.0 | 7.9 | 1.0 | 7.9 | 1.0 | 7.9 | ns |
| | | nOE to nBn | 0.5 | 13.8 | 0.5 | 10.0 | 0.5 | 7.9 | 0.5 | 5.7 | 0.5 | 4.8 | ns |
| $V_{CC(A)} =$ | 2.3 V to 2.7 V | | 1 | | | | 1 | 1 | | 1 | | 1 | 1 |
| t _{pd} | propagation | nAn to nBn | 0.5 | 8.4 | 0.5 | 5.8 | 0.5 | 4.7 | 0.5 | 3.5 | 0.5 | 3.0 | ns |
| | delay | nBn to nAn | 0.5 | 5.2 | 0.5 | 4.3 | 0.5 | 3.9 | 0.5 | 3.5 | 0.5 | 3.4 | ns |
| t _{dis} | disable time | nOE to nAn | 1.1 | 5.2 | 1.1 | 5.2 | 1.1 | 5.2 | 1.1 | 5.2 | 1.1 | 5.2 | ns |
| | | nOE to nBn | 1.2 | 10.8 | 1.2 | 8.2 | 1.2 | 6.9 | 1.0 | 5.3 | 1.0 | 5.2 | ns |
| t _{en} | enable time | nOE to nAn | 0.5 | 5.4 | 0.5 | 5.4 | 0.5 | 5.3 | 0.5 | 5.2 | 0.5 | 5.2 | ns |
| | | nOE to nBn | 0.5 | 13.3 | 0.5 | 9.6 | 0.5 | 7.6 | 0.5 | 5.3 | 0.5 | 4.3 | ns |
| V _{CC(A)} = | 3.0 V to 3.6 V | | | | | | | | | | | | |
| t _{pd} | propagation | nAn to nBn | 0.5 | 8.2 | 0.5 | 5.7 | 0.5 | 4.6 | 0.5 | 3.4 | 0.5 | 2.9 | ns |
| | delay | nBn to nAn | 0.5 | 5.1 | 0.5 | 3.9 | 0.5 | 3.5 | 0.5 | 3.0 | 0.5 | 2.9 | ns |
| t _{dis} | disable time | nOE to nAn | 0.8 | 5.0 | 0.8 | 5.0 | 0.8 | 5.0 | 0.8 | 5.0 | 0.8 | 5.0 | ns |
| | | nOE to nBn | 1.2 | 10.5 | 1.2 | 8.1 | 1.2 | 6.7 | 1.0 | 5.1 | 0.8 | 5.0 | ns |
| t _{en} | enable time | n OE to nAn | 0.5 | 4.4 | 0.5 | 4.4 | 0.5 | 4.3 | 0.5 | 4.2 | 0.5 | 4.1 | ns |
| | | nOE to nBn | 1.0 | 13.1 | 1.0 | 9.6 | 0.5 | 7.5 | 0.5 | 5.1 | 0.5 | 4.1 | ns |

 $[1] \quad t_{pd} \text{ is the same as } t_{PLH} \text{ and } t_{PHL}; \ t_{dis} \text{ is the same as } t_{PLZ} \text{ and } t_{PHZ}; \ t_{en} \text{ is the same as } t_{PZL} \text{ and } t_{PZH}.$

Table 13. Dynamic characteristics for temperature range -40 °C to +125 °C

Voltages are referenced to GND (ground = 0 V); for test circuit see Fig. 6; for wave forms see Fig. 4 and Fig. 5. [1]

| Symbol | Parameter | Conditions | V _{CC(B)} | | | | | | | | | Unit | |
|----------------------|-----------------------------|------------------------|--------------------|----------------------------------|-----|------|---------|--|-----|------|-----|------|----|
| - | | | 1.2 V : | .2 V ± 0.1 V 1.5 V ± 0.1 V 1.8 V | | | 1.8 V ± | 8 V ± 0.15 V 2.5 V ± 0.2 V 3.3 V ± 0.3 V | | | | - | |
| | | | Min | Мах | Min | Max | Min | Max | Min | Max | Min | Max | |
| $V_{CC(A)} =$ | 1.1 V to 1.3 V | | | | | | | | | | | | |
| t _{nd} | propagation | nAn to nBn | 0.5 | 10.4 | 0.5 | 7.9 | 0.5 | 6.9 | 0.5 | 5.8 | 0.5 | 5.7 | ns |
| pa | delay | nBn to nAn | 0.5 | 10.4 | 0.5 | 9.8 | 0.5 | 9.6 | 0.5 | 9.3 | 0.5 | 9.1 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 13.1 | 2.0 | 13.1 | 2.0 | 13.1 | 2.0 | 13.1 | 2.0 | 13.1 | ns |
| | | nOE to nBn | 1.5 | 14.0 | 1.5 | 10.8 | 1.5 | 10.6 | 1.0 | 9.0 | 1.0 | 9.9 | ns |
| t _{en} | enable time | nOE to nAn | 1.5 | 16.9 | 1.5 | 16.9 | 1.5 | 16.9 | 1.5 | 16.9 | 1.5 | 16.9 | ns |
| | | nOE to nBn | 1.0 | 17.2 | 1.0 | 12.7 | 1.0 | 11.0 | 0.5 | 9.3 | 0.5 | 8.8 | ns |
| $V_{CC(A)} =$ | 1.4 V to 1.6 V | | 1 | 1 | | | | | | 1 | | | |
| t _{pd} | propagation | nAn to nBn | 0.5 | 9.8 | 0.5 | 7.1 | 0.5 | 6.0 | 0.5 | 4.8 | 0.5 | 4.3 | ns |
| | delay | nBn to nAn | 0.5 | 7.9 | 0.5 | 7.1 | 0.5 | 6.8 | 0.5 | 6.4 | 0.5 | 6.3 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 9.9 | 2.0 | 9.9 | 2.0 | 9.9 | 2.0 | 9.9 | 2.0 | 9.9 | ns |
| | | nOE to nBn | 1.5 | 12.9 | 1.5 | 9.9 | 1.5 | 8.6 | 1.0 | 7.1 | 1.0 | 6.6 | ns |
| t _{en} | enable time | nOE to nAn | 1.5 | 11.4 | 1.5 | 11.4 | 1.5 | 11.4 | 1.5 | 11.3 | 1.5 | 11.3 | ns |
| | | nOE to nBn | 1.0 | 15.8 | 1.0 | 11.4 | 1.0 | 9.3 | 0.5 | 6.8 | 0.5 | 5.9 | ns |
| V _{CC(A)} = | 1.65 V to 1.95 | V | 1 | 1 | 1 | | 1 | 1 | | 1 | | 1 | |
| t _{pd} | t _{pd} propagation | nAn to nBn | 0.5 | 9.6 | 0.5 | 6.8 | 0.5 | 5.5 | 0.5 | 4.3 | 0.5 | 3.9 | ns |
| | delay | nBn to nAn | 0.5 | 6.9 | 0.5 | 6.0 | 0.5 | 5.5 | 0.5 | 5.2 | 0.5 | 5.1 | ns |
| t _{dis} | disable time | nOE to nAn | 2.0 | 8.2 | 2.0 | 8.2 | 2.0 | 8.2 | 2.0 | 8.2 | 2.0 | 8.2 | ns |
| | | n OE to nBn | 1.5 | 12.5 | 1.5 | 9.6 | 1.5 | 8.2 | 1.0 | 6.4 | 1.0 | 6.2 | ns |
| t _{en} | enable time | nOE to nAn | 1.0 | 9.0 | 1.0 | 9.0 | 1.0 | 8.7 | 1.0 | 8.7 | 1.0 | 8.7 | ns |
| | | n OE to nBn | 0.5 | 15.2 | 0.5 | 11.0 | 0.5 | 8.7 | 0.5 | 6.3 | 0.5 | 5.3 | ns |
| V _{CC(A)} = | 2.3 V to 2.7 V | 1 | | | | | | | | | | | |
| t _{pd} | propagation | nAn to nBn | 0.5 | 9.3 | 0.5 | 6.4 | 0.5 | 5.2 | 0.5 | 3.9 | 0.5 | 3.3 | ns |
| | delay | nBn to nAn | 0.5 | 5.8 | 0.5 | 4.8 | 0.5 | 4.3 | 0.5 | 3.9 | 0.5 | 3.8 | ns |
| t _{dis} | disable time | nOE to nAn | 1.1 | 5.8 | 1.1 | 5.8 | 1.1 | 5.8 | 1.1 | 5.8 | 1.1 | 5.8 | ns |
| | | nOE to nBn | 1.2 | 11.9 | 1.2 | 9.1 | 1.2 | 7.6 | 1.0 | 5.9 | 1.0 | 5.8 | ns |
| t _{en} | enable time | nOE to nAn | 0.5 | 6.0 | 0.5 | 6.0 | 0.5 | 5.9 | 0.5 | 5.8 | 0.5 | 5.8 | ns |
| | | nOE to nBn | 0.5 | 14.7 | 0.5 | 10.6 | 0.5 | 8.4 | 0.5 | 5.9 | 0.5 | 4.8 | ns |
| $V_{CC(A)} =$ | 3.0 V to 3.6 V | | | | | | | 1 | | | | | |
| t _{pd} | propagation | nAn to nBn | 0.5 | 9.1 | 0.5 | 6.3 | 0.5 | 5.1 | 0.5 | 3.8 | 0.5 | 3.2 | ns |
| | delay | nBn to nAn | 0.5 | 5.7 | 0.5 | 4.3 | 0.5 | 3.9 | 0.5 | 3.3 | 0.5 | 3.2 | ns |
| t _{dis} | disable time | nOE to nAn | 0.8 | 5.5 | 0.8 | 5.5 | 0.8 | 5.5 | 0.8 | 5.5 | 0.8 | 5.5 | ns |
| | | nOE to nBn | 1.2 | 11.6 | 1.2 | 9.0 | 1.2 | 7.4 | 1.0 | 5.7 | 0.8 | 5.5 | ns |
| t _{en} | enable time | nOE to nAn | 0.5 | 4.9 | 0.5 | 4.9 | 0.5 | 4.8 | 0.5 | 4.7 | 0.5 | 4.6 | ns |
| | | n OE to nBn | 1.0 | 14.5 | 1.0 | 10.6 | 0.5 | 8.3 | 0.5 | 5.7 | 0.5 | 4.6 | ns |

 $[1] \quad t_{pd} \text{ is the same as } t_{PLH} \text{ and } t_{PHL}; \ t_{dis} \text{ is the same as } t_{PLZ} \text{ and } t_{PHZ}; \ t_{en} \text{ is the same as } t_{PZL} \text{ and } t_{PZH}.$

10.1. Waveforms and test circuit



| Table | 14. | Measurement | points |
|-------|-----|-------------|--------|
|-------|-----|-------------|--------|

| Supply voltage | Input [1] | Output [2] | | | | | | |
|---|---------------------|---------------------|--------------------------|--------------------------|--|--|--|--|
| V _{CC(A)} , V _{CC(B)} | V _M | V _M | V _X | V _Y | | | | |
| 0.8 V to 1.6 V | 0.5V _{CCI} | 0.5V _{CCO} | V _{OL} + 0.1 V | V _{OH} - 0.1 V | | | | |
| 1.65 V to 2.7 V | 0.5V _{CCI} | 0.5V _{CCO} | V _{OL} + 0.15 V | V _{OH} - 0.15 V | | | | |
| 3.0 V to 3.6 V | 0.5V _{CCI} | 0.5V _{CCO} | V _{OL} + 0.3 V | V _{OH} - 0.3 V | | | | |

[1] V_{CCI} is the supply voltage associated with the data input port.

[2] V_{CCO} is the supply voltage associated with the output port.

74AVCH20T245

20-bit dual supply translating transceiver with configurable voltage translation; 3-state



Table 15. Test data

| Supply voltage Input | | Load | | V _{EXT} | | | |
|------------------------|--------------------|------------|-------|------------------|-------------------------------------|-------------------------------------|---|
| $V_{CC(A)}, V_{CC(B)}$ | V _I [1] | Δt/ΔV [2] | CL | R _L | t _{PLH} , t _{PHL} | t _{PZH} , t _{PHZ} | t _{PZL} , t _{PLZ} [3] |
| 0.8 V to 1.6 V | V _{CCI} | ≤ 1.0 ns/V | 15 pF | 2 kΩ | open | GND | 2V _{CCO} |
| 1.65 V to 2.7 V | V _{CCI} | ≤ 1.0 ns/V | 15 pF | 2 kΩ | open | GND | 2V _{CCO} |
| 3.0 V to 3.6 V | V _{CCI} | ≤ 1.0 ns/V | 15 pF | 2 kΩ | open | GND | 2V _{CCO} |

[1] V_{CCI} is the supply voltage associated with the data input port.

[2] dV/dt ≥ 1.0 V/ns

[3] V_{CCO} is the supply voltage associated with the output port.



11. Typical propagation delay characteristics

74AVCH20T245







c. LOW to HIGH propagation delay (nAn to nBn); $V_{CC(A)} = 1.5 V$

 $(1) V_{CC(B)} = 1.2 V$ $(2) V_{CC(B)} = 1.5 V$ $(3) V_{CC(B)} = 1.8 V$ $(4) V_{CC(B)} = 2.5 V$

(5) $V_{CC(B)} = 3.3 V$

Fig. 8. Typical propagation delay versus load capacitance; T_{amb} = 25 °C



b. HIGH to LOW propagation delay (nAn to nBn); V_{CC(A)} = 1.2 V



d. HIGH to LOW propagation delay (nAn to nBn); $V_{CC(A)} = 1.5 V$







c. LOW to HIGH propagation delay (nAn to nBn); $V_{CC(A)} = 2.5 V$

 $(1) V_{CC(B)} = 1.2 V$ $(2) V_{CC(B)} = 1.5 V$ $(3) V_{CC(B)} = 1.8 V$ $(4) V_{CC(B)} = 2.5 V$

- (5) $V_{CC(B)} = 3.3 V$





b. HIGH to LOW propagation delay (nAn to nBn); V_{CC(A)} = 1.8 V



d. HIGH to LOW propagation delay (nAn to nBn); $V_{CC(A)} = 2.5 V$



a. LOW to HIGH propagation delay (nAn to nBn); $V_{CC(A)} = 3.3 V$

(1) $V_{CC(B)}$ = 1.2 V (2) $V_{CC(B)} = 1.5 V$ (3) $V_{CC(B)} = 1.8 V$

(4) $V_{CC(B)} = 2.5 V$ (5) $V_{CC(B)} = 3.3 V$

Fig. 10. Typical propagation delay versus load capacitance; T_{amb} = 25 °C



b. HIGH to LOW propagation delay (nAn to nBn); $V_{CC(A)} = 3.3 V$

12. Package outline



13. Abbreviations

| Acronym | Description |
|---------|---|
| CDM | Charged Device Model |
| CMOS | Complementary Metal Oxide Semiconductor |
| DUT | Device Under Test |
| ESD | ElectroStatic Discharge |
| HBM | Human Body Model |
| MM | Machine Model |

14. Revision history

| Table 17. Revision histor | у | | | | | |
|---------------------------|--|--------------------|---------------|------------------|--|--|
| Document ID | Release date | Data sheet status | Change notice | Supersedes | | |
| 74AVCH20T245 v.6 | 20190114 | Product data sheet | - | 74AVCH20T245 v.5 | | |
| Modifications: | The format of this data sheet has been redesigned to comply with the identity guidelin Nexperia. Legal texts have been adapted to the new company name where appropriate. Type numbers 74AVCH20T245DGV and 74AVCH20T245BX removed. | | | | | |
| 74AVCH20T245 v.5 | 20160223 | Product data sheet | - | 74AVCH20T245 v.4 | | |
| Modifications: | General descri | ption updated. | · | | | |
| 74AVCH20T245 v.4 | 20111214 | Product data sheet | - | 74AVCH20T245 v.3 | | |
| Modifications: | Legal pages up | odated. | | | | |
| 74AVCH20T245 v.3 | 20110623 | Product data sheet | - | 74AVCH20T245 v.2 | | |
| 74AVCH20T245 v.2 | 20100315 | Product data sheet | - | 74AVCH20T245 v.1 | | |
| 74AVCH20T245 v.1 | 20100113 | Product data sheet | - | - | | |

15. Legal information

Data sheet status

| Document status [1][2] | Product status [3] | Definition |
|-----------------------------------|-----------------------|---|
| Objective [short] data sheet | Development | This document contains data from the objective specification for product development. |
| Preliminary [short] data sheet | Qualification | This document contains data from the preliminary specification. |
| Product [short] data sheet | Production | This document contains the product specification. |

 Please consult the most recently issued document before initiating or completing a design.

- [2] The term 'short data sheet' is explained in section "Definitions".
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the internet at <u>https://www.nexperia.com</u>.

Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. Nexperia does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local Nexperia sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between Nexperia and its customer, unless Nexperia and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the Nexperia product is deemed to offer functions and qualities beyond those described in the Product data sheet.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, Nexperia does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Nexperia takes no responsibility for the content in this document if provided by an information source outside of Nexperia.

In no event shall Nexperia be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Nexperia's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of Nexperia.

Right to make changes — Nexperia reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — Nexperia products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an Nexperia product can reasonably be expected to result in personal

injury, death or severe property or environmental damage. Nexperia and its suppliers accept no liability for inclusion and/or use of Nexperia products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. Nexperia makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Nexperia products, and Nexperia accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Nexperia product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Nexperia does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Nexperia products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). Nexperia does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — Nexperia products are sold subject to the general terms and conditions of commercial sale, as published at <u>http://www.nexperia.com/profile/terms</u>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Nexperia hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of Nexperia products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

Non-automotive qualified products — Unless this data sheet expressly states that this specific Nexperia product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. Nexperia accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without Nexperia's warranty of the product for such automotive applications, use and specifications, and (b) whenever customer uses the product for automotive applications beyond Nexperia's specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies Nexperia for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond Nexperia's standard warranty and Nexperia's product specifications.

Translations — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

Contents

| 1. General description | 1 |
|---|----|
| 2. Features and benefits | 1 |
| 3. Ordering information | 2 |
| 4. Functional diagram | 2 |
| 5. Pinning information | 4 |
| 5.1. Pinning | 4 |
| 5.2. Pin description | 5 |
| 6. Functional description | 5 |
| 7. Limiting values | 6 |
| 8. Recommended operating conditions | 6 |
| 9. Static characteristics | 7 |
| 10. Dynamic characteristics | 11 |
| 10.1. Waveforms and test circuit | 14 |
| 11. Typical propagation delay characteristics | |
| 12. Package outline | 20 |
| 13. Abbreviations | 21 |
| 14. Revision history | 21 |
| 15. Legal information | 22 |
| | |

© Nexperia B.V. 2019. All rights reserved

For more information, please visit: http://www.nexperia.com For sales office addresses, please send an email to: salesaddresses@nexperia.com Date of release: 14 January 2019





Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.З, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж: moschip.ru moschip.ru_4

moschip.ru_6 moschip.ru_9