

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

## General Description

The MAX6633/MAX6634/MAX6635 combine a temperature sensor, a programmable overtemperature alarm, and an SMBus™/I<sup>2</sup>C™-compatible serial interface into a single package. They convert their die temperatures into digital values using internal analog-to-digital converters (ADCs). The result of the conversion is then held in a temperature register as a 12-bit + sign value, allowing 0.0625°C resolution, readable at any time through the serial interface. The devices are capable of reading temperatures up to +150°C.

The MAX6633/MAX6634/MAX6635 feature a shutdown mode that saves power by turning off everything except the power-on reset (POR) and the serial interface. The devices can be configured to separate addresses, allowing multiple devices to be used on the same bus.

The MAX6633 has four address pins, allowing up to 16 devices to be connected to a single bus. The MAX6634 has three address pins, allowing up to eight devices to be connected to a single bus. The MAX6635 has two address pins, allowing up to four devices to be connected to a single bus.

The MAX6633/MAX6634/MAX6635 make temperature data available for transfer over the serial interface. The MAX6634 incorporates a dual-mode  $\overline{\text{ALERT}}$  output (open drain) and can serve as an upgraded alternative to the LM75. The MAX6635 includes an  $\overline{\text{ALERT}}$  output and an  $\overline{\text{OVERT}}$  output (both open drain) and can function as an upgraded replacement for the LM76 in most applications. The MAX6634/MAX6635 feature user-programmable temperature thresholds. All three devices come in an 8-pin SO package.

## Applications

Battery Temperature Alarms  
PC Temperature Control  
Automotive Equipment

*Pin Configurations appear at end of data sheet.*

SMBus is a trademark of Intel Corp.

I<sup>2</sup>C is a trademark of Philips Corp.


## Features

- ◆ **+3V to +5.5V Supply Range**
- ◆ **Accuracy**
  - ±1°C max (0°C to +50°C)
  - ±1.5°C max (-20°C to +85°C)
  - ±2.5°C max (-40°C to +125°C)
  - ±2.5°C typ (+150°C)
- ◆ **User-Programmable Temperature Thresholds (MAX6634/MAX6635)**
- ◆ **User-Configurable Alarm Output(s) (MAX6634/MAX6635)**
- ◆ **Ability to Respond to SMBus/I<sup>2</sup>C-Compatible Alert Response Address (MAX6634/MAX6635)**
- ◆  **$\overline{\text{OVERT}}$  Output for System Shutdown (MAX6635)**
- ◆ **Multiple Devices per Bus**
  - 16 devices (MAX6633)
  - 8 devices (MAX6634)
  - 4 devices (MAX6635)

## Ordering Information

| PART       | TEMP. RANGE     | PIN-PACKAGE |
|------------|-----------------|-------------|
| MAX6633MSA | -55°C to +150°C | 8 SO        |
| MAX6634MSA | -55°C to +150°C | 8 SO        |
| MAX6635MSA | -55°C to +150°C | 8 SO        |

## Typical Operating Circuit



# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

## ABSOLUTE MAXIMUM RATINGS

V<sub>CC</sub>, SDA, SCL ..... -0.3V to +6.0V  
 All Other Pins ..... -0.3V to V<sub>CC</sub> +0.3V  
 SDA, ALERT, OVERT Current ..... -1mA to +50mA  
 ESD Protection (Human Body Model) ..... 2000V  
 Continuous Power Dissipation (T<sub>A</sub> = +70°C)  
   8-Pin SO (derate 5.88mW/°C above +70°C) ..... 471mW

Junction Temperature ..... +150°C  
 Operating Temperature Range ..... -55°C to +150°C  
 Storage Temperature Range ..... -65°C to +150°C  
 Lead Temperature (soldering, 10s) ..... +300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

## ELECTRICAL CHARACTERISTICS

(V<sub>CC</sub> = +3.0V to +5.5V, T<sub>A</sub> = -55°C to +125°C, unless otherwise noted. Typical values are V<sub>CC</sub> = +3.3V, T<sub>A</sub> = +25°C, unless otherwise noted.)

| PARAMETER                                               | SYMBOL              | CONDITIONS                                               | MIN  | TYP  | MAX  | UNITS |
|---------------------------------------------------------|---------------------|----------------------------------------------------------|------|------|------|-------|
| <b>TEMPERATURE-TO-DIGITAL CONVERTER CHARACTERISTICS</b> |                     |                                                          |      |      |      |       |
| Supply Range                                            | V <sub>CC</sub>     |                                                          | 3.0  |      | 5.5  | V     |
| Accuracy (Note 1)                                       |                     | 0°C ≤ T <sub>A</sub> ≤ +50°C, V <sub>CC</sub> = +3.3V    | -1.0 | ±0.4 | +1.0 | °C    |
|                                                         |                     | -20°C ≤ T <sub>A</sub> ≤ +85°C, V <sub>CC</sub> = +3.3V  | -1.5 | ±0.6 | +1.5 |       |
|                                                         |                     | -40°C ≤ T <sub>A</sub> ≤ +125°C, V <sub>CC</sub> = +3.3V | -2.5 | ±1.0 | +2.5 |       |
|                                                         |                     | T <sub>A</sub> = -55°C, V <sub>CC</sub> = +3.3V          |      | ±1.5 | +2.8 |       |
|                                                         |                     | T <sub>A</sub> = +150°C, V <sub>CC</sub> = +3.3V         |      | ±2.5 |      |       |
| Power-Supply Rejection Ratio                            | PSRR                |                                                          |      | 0.2  | 0.5  | °C/V  |
| POR Threshold Hysteresis                                |                     |                                                          |      | 90   |      | mV    |
| Supply Current in Shutdown                              |                     | V <sub>CC</sub> = +3.0V, SMBus inactive                  |      | 12   | 20   | μA    |
|                                                         |                     | V <sub>CC</sub> = +5.5V, SMBus inactive                  |      | 20   | 30   |       |
| Average Operating Current                               |                     | V <sub>CC</sub> = +3.0V, SMBus inactive                  |      | 150  |      | μA    |
|                                                         |                     | V <sub>CC</sub> = +5.5V, SMBus inactive                  |      | 200  |      |       |
| Peak Operating Current (Note 2)                         |                     | V <sub>CC</sub> = +3.0V, SMBus inactive                  |      | 270  | 350  | μA    |
|                                                         |                     | V <sub>CC</sub> = +5.5V, SMBus inactive                  |      | 350  | 700  |       |
| Conversion Rate                                         |                     |                                                          | 1.4  | 2    | 2.4  | Hz    |
| <b>DIGITAL INTERFACE</b>                                |                     |                                                          |      |      |      |       |
| Logic Input Low Voltage                                 | V <sub>IL</sub>     | V <sub>CC</sub> = +3.0V to +5.5V                         |      |      | 0.65 | V     |
| Logic Input High Voltage                                | V <sub>IH</sub>     | V <sub>CC</sub> = +3V                                    | 2.2  |      |      | V     |
|                                                         |                     | V <sub>CC</sub> = +5.5V                                  | 2.4  |      |      |       |
| Input Leakage Current                                   | I <sub>I_LEAK</sub> | V <sub>IN</sub> = GND or V <sub>CC</sub>                 |      |      | ±1   | μA    |
| Output Low Sink Current                                 | I <sub>OL</sub>     | V <sub>OL</sub> = 0.6V (SMBDATA, ALERT, OVERT)           | 6    |      |      | mA    |
| Output Leakage Current                                  | I <sub>O_LEAK</sub> | ALERT, OVERT at V <sub>CC</sub>                          |      |      | ±1   | μA    |
| Input Capacitance                                       | C <sub>IN</sub>     |                                                          |      | 5    |      | pF    |

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

## ELECTRICAL CHARACTERISTICS (continued)

(V<sub>CC</sub> = +3.0V to +5.5V, T<sub>A</sub> = -55°C to +125°C, unless otherwise noted. Typical values are V<sub>CC</sub> = +3.3V, T<sub>A</sub> = +25°C, unless otherwise noted.)

| PARAMETER                                         | SYMBOL               | CONDITIONS                      | MIN | TYP | MAX | UNITS |
|---------------------------------------------------|----------------------|---------------------------------|-----|-----|-----|-------|
| <b>SMBus TIMING</b> (Note 3, Figures 1, 2, and 3) |                      |                                 |     |     |     |       |
| Serial Clock Frequency                            | f <sub>SCL</sub>     |                                 | 10  |     | 100 | kHz   |
| Bus Free Time Between STOP and START Condition    | t <sub>BUF</sub>     |                                 | 4.7 |     |     | μs    |
| START Condition Setup Time                        |                      |                                 | 4.7 |     |     | μs    |
| Repeat START Condition Setup Time                 | t <sub>SU:STA</sub>  | 90% to 90%                      | 4.7 |     |     | μs    |
| START Condition Hold Time                         | t <sub>HD:STA</sub>  | 10% of SMBDATA to 90% of SMBCLK | 4   |     |     | μs    |
| STOP Condition Setup Time                         | t <sub>SU:STO</sub>  | 90% of SMBCLK to 10% of SMBDATA | 4   |     |     | μs    |
| Data Setup Time                                   | t <sub>SU: DAT</sub> | 90% of SMBDATA to 10% of SMBCLK | 250 |     |     | ns    |
| Data Hold Time (Note 4)                           | t <sub>HD: DAT</sub> |                                 | 300 |     |     | ns    |
| Receive SCL/SDA Rise Time                         | t <sub>R</sub>       |                                 |     |     | 1   | μs    |
| SCL/SDA Fall Time (Note 4)                        | t <sub>F</sub>       |                                 |     |     | 300 | ns    |
| Clock Low Period                                  | t <sub>LOW</sub>     | 10% to 10%                      | 4.7 |     |     | μs    |
| Clock High Period                                 | t <sub>HIGH</sub>    | 90% to 90%                      | 4   |     |     | μs    |
| SMBus Timeout                                     |                      |                                 | 25  |     | 48  | ms    |

**Note 1:** Guaranteed by design and characterization.

**Note 2:** Peak operating current measured during conversion. See Figure 4.

**Note 3:** Guaranteed by design, not production tested.

**Note 4:** A master device must provide a hold time of at least 300ns for the SDA signal in order to bridge the undefined region of SCL's falling edge.


MAX6633/MAX6634/MAX6635

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface


## Typical Operating Characteristics

( $V_{CC} = +3.3V$ ,  $T_A = +25^{\circ}C$ , unless otherwise noted.)


**SHUTDOWN SUPPLY CURRENT  
vs. TEMPERATURE**




**AVERAGE SUPPLY CURRENT  
vs. TEMPERATURE**




**TEMPERATURE ERROR  
vs. SUPPLY NOISE FREQUENCY**



**RESPONSE TO THERMAL SHOCK**



**TEMPERATURE ERROR  
vs. TEMPERATURE**



# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

## Pin Description

| PIN     |         |         | NAME                      | FUNCTION                                                                                    |
|---------|---------|---------|---------------------------|---------------------------------------------------------------------------------------------|
| MAX6633 | MAX6634 | MAX6635 |                           |                                                                                             |
| 1       | 1       | 1       | SDA                       | Serial Data Input/Output. Open drain.                                                       |
| 2       | 2       | 2       | SCL                       | Serial Clock Input                                                                          |
| 3       | —       | —       | A3                        | Address Pin                                                                                 |
| 4       | 4       | 4       | GND                       | Ground                                                                                      |
| 5       | 5       | —       | A2                        | Address Pin                                                                                 |
| 6       | 6       | 6       | A1                        | Address Pin                                                                                 |
| 7       | 7       | 7       | A0                        | Address Pin                                                                                 |
| 8       | 8       | 8       | V <sub>CC</sub>           | Supply Voltage Input. +3.0V to +5.5V. Bypass V <sub>CC</sub> to GND with a 0.1μF capacitor. |
| —       | 3       | 5       | $\overline{\text{ALERT}}$ | $\overline{\text{ALERT}}$ Output. Open drain.                                               |
| —       | —       | 3       | $\overline{\text{OVERT}}$ | $\overline{\text{OVERT}}$ Output. Open drain.                                               |

## Detailed Description

The MAX6633/MAX6634/MAX6635 continuously convert their die temperatures into digital values using their integrated ADCs. The resulting data is readable at any time through the SMBus/I<sup>2</sup>C-compatible serial interface. The device functions as a slave on the SMBus interface, supporting Write Byte, Write Word, Read Byte, and Read Word commands. Separate addresses can be configured using the individual address pins. Figures 5, 6, and 7 show the functional diagrams of the MAX6633/MAX6634/MAX6635, respectively.

### SMBus/I<sup>2</sup>C-Compatible Operation

The MAX6633/MAX6634/MAX6635 are readable and programmable through their SMBus/I<sup>2</sup>C-compatible serial interface. Figures 1, 2, and 3 show the timing details of the clock (SCL) and data (SDA) signals. The devices function as slaves on the SMBus and support Write Byte, Write Word, Read Byte, and Read Word commands. Figure 8 is the MAX6633/MAX6634/MAX6635 programmer's model.

### Addressing

Separate addresses can be configured using the individual address pins. The address of each device is selected by connecting the address (A<sub>n</sub>) pins to one of two potentials: GND or V<sub>CC</sub>. The MAX6635 makes two address pins available (A0, A1), allowing up to four devices to be connected to a single bus line. The MAX6634 makes three address pins available (A0, A1, A2), allowing up to eight devices to be connected to a single bus line. The MAX6633 makes four address pins available (A0, A1, A2, A3), allowing as many as 16

devices to be connected to a single bus line. Table 1 shows the full SMBus/I<sup>2</sup>C address for each device type.

### Control Registers (MAX6633)

Three registers control the operation of the MAX6633 (Figure 5 and Tables 2 through 6). The Pointer register is the first addressed and determines which of the other two registers is acted upon. The other two are the Temperature and Configuration registers. The temperature value is stored as 12 bits plus a sign bit, read only, and contains the latest temperature data. The true register length is 16 bits, with the lower 3 unused in this part. The digital temperature data contained in the temperature register is in °C, using a two's-complement format with 1LSB corresponding to 0.0625°C.

The Configuration register is 8 bits, read/write, and contains the SMBus timeout disable bit, fault queue enable bit, and the shutdown bit.

### Control Registers (MAX6634)

Six registers control the operation of the MAX6634 (Figure 6 and Tables 2 through 7). The pointer register is the first addressed and determines which of the other five registers is acted upon. The other five are the Temperature, Configuration, High-Temperature (THIGH), Low-Temperature (TLOW), and Hysteresis (THYST) registers. The temperature value is stored as 12 bits plus a sign bit, read only, and contains the latest temperature data. The true register length is 16 bits, with the lowest 2 used as status bits, and the third bit (D2) is unused. The digital temperature data contained in the temperature register is in °C, using a two's-complement format with 1LSB corresponding to 0.0625°C.

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

## Write Byte Format

| S | ADDRESS                                                             | WR | ACK | COMMAND                                           | ACK | DATA                                                           | ACK | P |
|---|---------------------------------------------------------------------|----|-----|---------------------------------------------------|-----|----------------------------------------------------------------|-----|---|
|   | 7 bits                                                              |    |     | 8 bits                                            |     | 8 bits                                                         |     |   |
|   | Slave Address: equivalent to chip-select line of a 3-wire interface |    |     | Command Byte: selects register you are writing to |     | Data Byte: data goes into the register set by the command byte |     |   |

## Write Word Format

| S | ADDRESS                                                             | WR | ACK | COMMAND                                           | ACK | DATA                                                            | ACK | DATA         | ACK | P |
|---|---------------------------------------------------------------------|----|-----|---------------------------------------------------|-----|-----------------------------------------------------------------|-----|--------------|-----|---|
|   | 7 bits                                                              |    |     | 8 bits                                            |     | 8 bits (MSB)                                                    |     | 8 bits (LSB) |     |   |
|   | Slave Address: equivalent to chip-select line of a 3-wire interface |    |     | Command Byte: selects register you are writing to |     | Data Bytes: data goes into the register set by the command byte |     |              |     |   |

## Read Byte Format

| S | ADDRESS                                       | WR | ACK | COMMAND                                             | ACK | S | ADDRESS                                                      | RD | ACK | DATA                                                       | /// | P |
|---|-----------------------------------------------|----|-----|-----------------------------------------------------|-----|---|--------------------------------------------------------------|----|-----|------------------------------------------------------------|-----|---|
|   | 7 bits                                        |    |     | 8 bits                                              |     |   | 7 bits                                                       |    |     | 8 bits                                                     |     |   |
|   | Slave Address: equivalent to chip-select line |    |     | Command Byte: selects register you are reading from |     |   | Slave Address: repeated due to change in data-flow direction |    |     | Data Byte: reads from the register set by the command byte |     |   |

## Read Word Format

| S | ADDRESS                                       | WR | ACK | COMMAND                                             | ACK | S | ADDRESS                                                      | RD | ACK | DATA                                                        | ACK | DATA         | /// | P |
|---|-----------------------------------------------|----|-----|-----------------------------------------------------|-----|---|--------------------------------------------------------------|----|-----|-------------------------------------------------------------|-----|--------------|-----|---|
|   | 7 bits                                        |    |     | 8 bits                                              |     |   | 7 bits                                                       |    |     | 8 bits (MSB)                                                |     | 8 bits (LSB) |     |   |
|   | Slave Address: equivalent to chip-select line |    |     | Command Byte: selects register you are reading from |     |   | Slave Address: repeated due to change in data-flow direction |    |     | Data Bytes: reads from the register set by the command byte |     |              |     |   |

S = Start condition      Shaded = Slave transmission  
P = Stop condition      /// = Not acknowledged

Figure 1. SMBus Protocols




Figure 2. SMBus Write Timing Diagram

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface




Figure 3. SMBus Read Timing Diagram




Figure 4. ADC Conversion Timing Diagram

The Configuration register is 8 bits, read/write, and contains the SMBus timeout disable bit, fault queue enable bit, the temperature alarm output polarity select bits, the interrupt mode select bit, and the shutdown bit. Registers  $T_{HIGH}$  and  $T_{LOW}$  are 16 bits, read/write, and contain the values that trigger ALERT. Register  $T_{HYST}$  is 16 bits, read/write, and contains the values by which the temperature must rise or fall beyond  $T_{HIGH}$  or  $T_{LOW}$ , before ALERT deasserts.

## Control Registers (MAX6635)

Seven registers control the operation of the MAX6635 (Figure 7 and Tables 2 through 7). The Pointer register is the first addressed and determines which of the other six registers is acted upon. The other six are the Temperature, Configuration, High-Temperature ( $T_{HIGH}$ ), Low-Temperature ( $T_{LOW}$ ), Maximum Temperature ( $T_{MAX}$ ), and Hysteresis ( $T_{HYST}$ ) registers. The temperature value is stored as 12 bits plus a sign bit, read only, and contains the latest temperature data. The true register length is 16 bits, with the lower three used as status bits. The digital temperature data contained in the temperature register is in  $^{\circ}\text{C}$ , using a two's-complement format with 1LSB corresponding to  $0.0625^{\circ}\text{C}$ .

The Configuration register is 8 bits, read/write, and contains the SMBus timeout disable bit, fault queue enable bit, the temperature alarm output polarity select bits, the interrupt mode select bit, and the shutdown




Figure 5. MAX6633 Functional Diagram

# 12-Bit Plus Sign Temperature Sensors with SMBus/I2C-Compatible Serial Interface




Figure 6. MAX6634 Functional Diagram




Figure 7. MAX6635 Functional Diagram

# 12-Bit Plus Sign Temperature Sensors with SMBus/I2C-Compatible Serial Interface

MAX6633/MAX6634/MAX6635




Figure 8. MAX6633/MAX6634/MAX6635 Programmer's Model

# 12-Bit Plus Sign Temperature Sensors with SMBus/I2C-Compatible Serial Interface




Figure 9. Alarm Output and Reset Diagram

bit. Registers  $T_{\text{HIGH}}$  and  $T_{\text{LOW}}$  are 16 bits, read/write, and contain values that trigger  $\overline{\text{ALERT}}$  and  $\overline{\text{OVERT}}$ . Register  $T_{\text{HYST}}$  is 16 bits, read/write, and contains the values by which the temperature must rise or fall beyond  $T_{\text{HIGH}}$ ,  $T_{\text{LOW}}$ , or  $T_{\text{MAX}}$ , before  $\overline{\text{ALERT}}$  or  $\overline{\text{OVERT}}$  deassert.

## Temperature Conversion

An on-chip bandgap reference produces a signal proportional to absolute temperature (PTAT), as well as the temperature-stable reference voltage necessary for the analog-to-digital conversion. The PTAT signal is digitized by the on-board ADC to a resolution of  $0.0625^{\circ}\text{C}$ . The resulting digital value is placed in the Temperature register. The temperature conversion runs continuously and asynchronously from the serial interface at a rate of 500ms per conversion. When the Temperature register is read, the conversion in progress is aborted. The bus transaction is completed by a stop condition.

## Fault Queue (MAX6634/MAX6635)

A programmable fault queue on the MAX6634/MAX6635 eliminates spurious alarm activity in noisy environments. The queue sets the number of consecutive out-of-tolerance temperature readings that must occur before the  $\overline{\text{ALERT}}$  or  $\overline{\text{OVERT}}$  alarm outputs are toggled. An out-of-tolerance reading is above  $T_{\text{HIGH}}$  or  $T_{\text{MAX}}$  or below  $T_{\text{LOW}}$ . The fault queue depth defaults to 1 at power-up and may be programmed—through the Configuration register—to four consecutive conversions. Any time the conversion result is in tolerance, and the particular alarm output is not asserted, the queue is cleared, even if it contains some out-of-tolerance counts. Additionally, the fault queue automatically clears at power-up and in shutdown. Whenever the fault queue is cleared, the alarm outputs are deasserted. Figure 9 is the alarm output and reset diagram.

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface




Figure 10. Simple Thermostat

## Temperature Alert (MAX6634/MAX6635)

$\overline{\text{ALERT}}$  has programmable polarity and two modes: comparator and interrupt. Polarity and mode are selected through the Configuration register (Table 4). The  $\overline{\text{ALERT}}$  output is open drain.

### Interrupt Mode

With  $\overline{\text{ALERT}}$  in interrupt mode, the MAX6634/MAX6635 look for a  $T_{\text{HIGH}}$  or a  $T_{\text{LOW}}$  fault. The  $\overline{\text{ALERT}}$  pin asserts an alarm for an undertemperature fault, as well as for an overtemperature fault. Once either fault has occurred, it remains active until deasserted by a read of any register. The device then begins to look for a temperature change crossing the hysteresis level. The activation of  $\overline{\text{ALERT}}$  is subject to the depth of the fault queue.

For example: If  $T_{\text{HIGH}}$  is set to 100°C,  $T_{\text{HYST}}$  is set to 20°C, and the fault queue depth is set to 4,  $\overline{\text{ALERT}}$  does not assert until four consecutive conversions exceed 100°C. If the temperature is then read through the I<sup>2</sup>C-compatible interface,  $\overline{\text{ALERT}}$  deasserts.  $\overline{\text{ALERT}}$  asserts again when four consecutive conversions are less than 80°C.

### Comparator Mode

In comparator mode,  $\overline{\text{ALERT}}$  is asserted when the number of consecutive conversions exceeding the value in the  $T_{\text{HIGH}}$  register, or lower than the value in the  $T_{\text{LOW}}$  register, is equal to the depth of the fault queue.  $\overline{\text{ALERT}}$  deasserts when the number of consecutive conversions




Figure 11. Fan Controller

less than  $T_{\text{HIGH}} - T_{\text{HYST}}$  or greater than  $T_{\text{LOW}} + T_{\text{HYST}}$  is equal to the depth of the fault queue.

For example: If  $T_{\text{HIGH}}$  is set to 100°C,  $T_{\text{LOW}}$  is set to 80°C, and the fault queue depth is set to four,  $\overline{\text{ALERT}}$  does not assert until four consecutive conversions exceed 100°C, or are below 80°C.  $\overline{\text{ALERT}}$  only deasserts if four consecutive conversions are less than  $T_{\text{HIGH}} - T_{\text{HYST}}$  or greater than  $T_{\text{LOW}} + T_{\text{HYST}}$ .

Comparator mode allows autonomous clearing of an  $\overline{\text{ALERT}}$  fault without the intervention of a master and is ideal to use for driving a thermostat (Figure 10).

## Overtemperature Alarm (MAX6635)

The MAX6635 also includes an overtemperature output that is always in comparator mode. Whenever the temperature exceeds a value in the programmable  $T_{\text{MAX}}$  register,  $\overline{\text{OVERT}}$  is asserted.  $\overline{\text{OVERT}}$  only deasserts after the temperature drops below  $T_{\text{MAX}} - T_{\text{HYST}}$ . When the fault queue is activated,  $\overline{\text{OVERT}}$  is subject to that queue, which sets the number of faults that must occur before  $\overline{\text{OVERT}}$  asserts or deasserts. This helps prevent spurious alarms in noisy environments.

Comparator mode also allows autonomous clearing of an  $\overline{\text{OVERT}}$  fault without the intervention of a master and thus is ideal to use for driving a cooling fan (Figure 11). In this application, the polarity of  $\overline{\text{OVERT}}$  is active high.

## Shutdown

The MAX6633/MAX6634/MAX6635 feature a shutdown mode, accessible through the serial interface that saves power by turning off everything except the POR

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

and the serial interface. Enter shutdown by programming the shutdown bit of the Configuration register high. While in shutdown, the Temperature register retains the last conversion result and can be read at any time. The ADC is turned off, reducing the device current draw to 30 $\mu$ A (max). The outputs of  $\overline{\text{ALERT}}$  and  $\overline{\text{OVERT}}$  are latched upon entering shutdown, and the fault queue is held in reset. After coming out of shutdown, the Temperature register continues to read the last converted temperature, until the next conversion result is available.

## Thermal Considerations

The MAX6633/MAX6634/MAX6635 supply current is typically 200 $\mu$ A when the serial interface is inactive. When used to drive high-impedance loads, the devices dissipate negligible power; therefore, the die temperature is essentially the same as the package temperature. The key to accurate temperature monitoring is good thermal contact between the MAX6633/MAX6634/MAX6635 package and the monitored device or circuit. Heat flows in and out of plastic packages primarily through the leads. Short, wide copper traces leading to the temperature monitor ensure that heat transfers quickly and reliably. The rise in die temperature due to self-heating is given by the following formula:

$$\Delta T_J = P_{\text{DISSIPATION}} \times \theta_{JA}$$

where  $P_{\text{DISSIPATION}}$  is the power dissipated by the MAX6633/MAX6634/MAX6635, and  $\theta_{JA}$  is the package's thermal resistance.

The typical thermal resistance is 170°C/W for the 8-pin SO package. To limit the effects of self-heating, minimize the output currents. For example, if the MAX6634/MAX6635 sink 4mA with the maximum  $\overline{\text{ALERT}}$   $V_L$  specification of 0.8V, an additional 3.2mW of power is dissipated within the IC. This corresponds to a 0.54°C rise in the die temperature.

## Applications Information

Figure 10 shows the MAX6634 used as a simple thermostat to control a heating element. Figure 11 shows the MAX6635 used as a temperature-triggered fan controller.

## Chip Information

TRANSISTOR COUNT: 12,085

PROCESS: BiCMOS

Table 1. Address Selection

| MAX6633         |                 |                 |                 |          |
|-----------------|-----------------|-----------------|-----------------|----------|
| A3              | A2              | A1              | A0              | ADDRESS  |
| GND             | GND             | GND             | GND             | 1000 000 |
| GND             | GND             | GND             | V <sub>CC</sub> | 1000 001 |
| GND             | GND             | V <sub>CC</sub> | GND             | 1000 010 |
| GND             | GND             | V <sub>CC</sub> | V <sub>CC</sub> | 1000 011 |
| GND             | V <sub>CC</sub> | GND             | GND             | 1000 100 |
| GND             | V <sub>CC</sub> | GND             | V <sub>CC</sub> | 1000 101 |
| GND             | V <sub>CC</sub> | V <sub>CC</sub> | GND             | 1000 110 |
| GND             | V <sub>CC</sub> | V <sub>CC</sub> | V <sub>CC</sub> | 1000 111 |
| V <sub>CC</sub> | GND             | GND             | GND             | 1001 000 |
| V <sub>CC</sub> | GND             | GND             | V <sub>CC</sub> | 1001 001 |
| V <sub>CC</sub> | GND             | V <sub>CC</sub> | GND             | 1001 010 |
| V <sub>CC</sub> | GND             | V <sub>CC</sub> | V <sub>CC</sub> | 1001 011 |
| V <sub>CC</sub> | V <sub>CC</sub> | GND             | GND             | 1001 100 |
| V <sub>CC</sub> | V <sub>CC</sub> | GND             | V <sub>CC</sub> | 1001 101 |
| V <sub>CC</sub> | V <sub>CC</sub> | V <sub>CC</sub> | GND             | 1001 110 |
| V <sub>CC</sub> | V <sub>CC</sub> | V <sub>CC</sub> | V <sub>CC</sub> | 1001 111 |
| MAX6634         |                 |                 |                 |          |
|                 | A2              | A1              | A0              | ADDRESS  |
|                 | GND             | GND             | GND             | 1001 000 |
|                 | GND             | GND             | V <sub>CC</sub> | 1001 001 |
|                 | GND             | V <sub>CC</sub> | GND             | 1001 010 |
|                 | GND             | V <sub>CC</sub> | V <sub>CC</sub> | 1001 011 |
|                 | V <sub>CC</sub> | GND             | GND             | 1001 100 |
|                 | V <sub>CC</sub> | GND             | V <sub>CC</sub> | 1001 101 |
|                 | V <sub>CC</sub> | V <sub>CC</sub> | GND             | 1001 110 |
|                 | V <sub>CC</sub> | V <sub>CC</sub> | V <sub>CC</sub> | 1001 111 |
| MAX6635         |                 |                 |                 |          |
|                 |                 | A1              | A0              | ADDRESS  |
|                 |                 | GND             | GND             | 1001 000 |
|                 |                 | GND             | V <sub>CC</sub> | 1001 001 |
|                 |                 | V <sub>CC</sub> | GND             | 1001 010 |
|                 |                 | V <sub>CC</sub> | V <sub>CC</sub> | 1001 011 |

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

**Table 2. Pointer Register Bit Assignments**

| ADDRESS | DESCRIPTION                      | POR STATE |
|---------|----------------------------------|-----------|
| 00h     | Temperature register (READ only) | 0000h     |
| 01h     | Configuration-Byte register      | 00h       |
| 02h     | T <sub>HYST</sub> register       | 0100h     |
| 03h     | T <sub>MAX</sub> register        | 2800h     |
| 04h     | T <sub>LOW</sub> register        | 0500h     |
| 05h     | T <sub>HIGH</sub> register       | 2000h     |

**Table 3. Temperature Register**

| D15        | D14    | D13    | D12    | D11   | D10   | D9    | D8    | D7    | D6    | D5    | D4    | D3    | D2               | D1                | D0               |
|------------|--------|--------|--------|-------|-------|-------|-------|-------|-------|-------|-------|-------|------------------|-------------------|------------------|
| MSB (Sign) | Bit 12 | Bit 11 | Bit 10 | Bit 9 | Bit 8 | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | T <sub>MAX</sub> | T <sub>HIGH</sub> | T <sub>LOW</sub> |

D15: MSB is the first sign bit.

D2, D1, D0: Flag bits for T<sub>MAX</sub>, T<sub>HIGH</sub>, T<sub>LOW</sub>.

1LSB = 0.0625°C.

Temperature is stored in two's complement format.

**Table 4. Configuration Register**

| D7 | D6 | D5                  | D4                 | D3                                 | D2                                 | D1                      | D0       |
|----|----|---------------------|--------------------|------------------------------------|------------------------------------|-------------------------|----------|
| 0  | 0  | SMB Timeout Disable | Fault Queue Enable | $\overline{\text{ALERT}}$ Polarity | $\overline{\text{OVERT}}$ Polarity | Comparator or Interrupt | Shutdown |

Power-on default = 0h.

D0: 0 = normal operation; 1 = shutdown.

D1: 0 = comparator mode; 1 = interrupt mode.

D2 to D3: 0 = active low; 1 = active high.

D5: 0 = normal SMBus operation; 1 = full I<sup>2</sup>C compatibility.

D7 to D6: Reserved locations, always write zeros.

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface

Table 5. Fault Queue Depth

| D4 | NO. OF FAULTS |
|----|---------------|
| 0  | 1 (DEFAULT)   |
| 1  | 4             |

Table 6. Output Code vs. Temperature

| TEMP. (°C) | DIGITAL OUTPUT CODE |     |      |
|------------|---------------------|-----|------|
|            | BINARY              |     | HEX  |
|            | MSB                 | LSB |      |
| +150.0000  | 0100 1011 0000 0XXX |     | 4B00 |
| +125.0000  | 0011 1110 1000 0XXX |     | 3E80 |
| +25.0000   | 0000 1100 1000 0XXX |     | 0C80 |
| +0.0625    | 0000 0000 0000 1XXX |     | 0008 |
| 0.0000     | 0000 0000 0000 0XXX |     | 0000 |
| -0.0625    | 1111 1111 1111 1XXX |     | FFF8 |
| -25.0000   | 1111 0011 0111 0XXX |     | F370 |
| -55.0000   | 1110 0100 0111 0XXX |     | E470 |

Table 7. THIGH, TLOW, TMAX, and THYST Registers

| D15        | D14   | D13   | D12   | D11   | D10   | D9    | D8    | D7  | D6 | D5 | D4 | D3 | D2 | D1 | D0 |
|------------|-------|-------|-------|-------|-------|-------|-------|-----|----|----|----|----|----|----|----|
| MSB (Sign) | Bit 7 | Bit 6 | Bit 5 | Bit 4 | Bit 3 | Bit 2 | Bit 1 | LSB | 0  | 0  | 0  | 0  | 0  | 0  | 0  |


D6 to D0: Reads all zeros, cannot be written.

1LSB = 1°C.

Power-On Default: T<sub>HIGH</sub> = +64°C (2000h), T<sub>LOW</sub> = +10°C (0500h), T<sub>MAX</sub> = +80°C (2008h), T<sub>HYST</sub> = 2°C (0100h).

# 12-Bit Plus Sign Temperature Sensors with SMBus/I<sup>2</sup>C-Compatible Serial Interface


## Pin Configurations




MAX6633/MAX6634/MAX6635

# 12-Bit Plus Sign Temperature Sensors with SMBus/I2C-Compatible Serial Interface


## Package Information



TOP VIEW



FRONT VIEW



SIDE VIEW

- NOTES:
1. D&E DO NOT INCLUDE MOLD FLASH.
  2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED 0.15mm (.006").
  3. LEADS TO BE COPLANAR WITHIN 0.10mm (.004").
  4. CONTROLLING DIMENSION: MILLIMETERS.
  5. MEETS JEDEC MS012.
  6. N = NUMBER OF PINS.

| DIM | INCHES    |       | MILLIMETERS |      |
|-----|-----------|-------|-------------|------|
|     | MIN       | MAX   | MIN         | MAX  |
| A   | 0.053     | 0.069 | 1.35        | 1.75 |
| A1  | 0.004     | 0.010 | 0.10        | 0.25 |
| B   | 0.014     | 0.019 | 0.35        | 0.49 |
| C   | 0.007     | 0.010 | 0.19        | 0.25 |
| e   | 0.050 BSC |       | 1.27 BSC    |      |
| E   | 0.150     | 0.157 | 3.80        | 4.00 |
| H   | 0.228     | 0.244 | 5.80        | 6.20 |
| L   | 0.016     | 0.050 | 0.40        | 1.27 |

VARIATIONS:

| DIM | INCHES |       | MILLIMETERS |       | N  | MS012 |
|-----|--------|-------|-------------|-------|----|-------|
|     | MIN    | MAX   | MIN         | MAX   |    |       |
| D   | 0.189  | 0.197 | 4.80        | 5.00  | 8  | AA    |
| D   | 0.337  | 0.344 | 8.55        | 8.75  | 14 | AB    |
| D   | 0.386  | 0.394 | 9.80        | 10.00 | 16 | AC    |

**DALLAS**  
SEMICONDUCTOR



PROPRIETARY INFORMATION

TITLE:  
PACKAGE OUTLINE, .150" SOIC

APPROVAL

DOCUMENT CONTROL NO.  
21-0041

REV.  
B

1/1

SOICN .EPS

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9