

# S8JX-G Switch Mode Power Supply

Offers Flexible Selection, High Reliability  
and Ease of Operation

More Variations for More Applications



15W / 35W / 50W / 100W / 150W / 300W / 600W

**10 Years**    **4.5 G**  
Life Expectancy    Vibration Resistance

- » Smoothly handle even more applications
- » Output voltage models for 5 V and 48 V expand lineup
- » Simple installation and maintenance free operation
  - » Slim design for smaller, more compact control panels

# Simple

## Two Mounting Methods for Simple Installation

### Use Screw or DIN Rail Mounting Even with 300-W Models

In addition to front mounting and top mounting, you can mount models up to 300-W to DIN Rail for simple installation that reduces installation work.

\*Only screw mounting is possible for 600-W models  
 \*Use a steel DIN Rail for 300-W Power Supplies.



Front Mounting



Compact right-angle mounting bracket enclosed for easy mounting.

Screw Mounting from Top



Easy mounting from the top with screws.

## Fan-free Design for Maintenance-free Operation

### The 300-W models need no fan

The thermal design and circuit design of the 300-W models were improved to achieve a fan-free structure. This eliminates the need to replace fans every few years and greatly reduces the risk of lowering the insulation resistance due to dust drawn in by the fan.

\*The 600-W models have fans.

Standard Power Supply with Fan



Fan replacement every 2 to 3 years  
 Dust drawn in by fan

S8JX(300-W Models)



Fan-free means maintenance-free  
 No fan for reduced risk from dust



# Slim

## Contributes to Thinner Panels

### The Shortest Body Class in the Industry

The S8JX Power Supplies have a shorter body than OMRON's S82J Power Supplies. This allows them to fit into tighter spots to contribute to smaller, thinner control panels and devices in this age where functionality and mounting density continue to increase.

(Comparison to Previous OMRON Models)

Length Reduced  
 by **30%**



145 mm


110 mm

\*For 50-W model with front mounting.

# Selectable

## More Output Voltage Specifications for an Expanded Lineup

### Voltage Specifications from 5 V to 48 V



| Power rating Voltage | 15w | 35w | 50w | 100w | 150w | 300w | 600w |
|----------------------|-----|-----|-----|------|------|------|------|
| 5v                   | ●   | ●   | ●   | ●    | ●    | ●    | ●    |
| 12v                  | ●   | ●   | ●   | ●    | ●    | ●    | ●    |
| 15v                  | ●   | ●   |     |      |      |      |      |
| 24v                  | ●   | ●   | ●   | ●    | ●    | ●    | ●    |
| 48v                  | ●   | ●   | ●   | ●    | ●    | ●    | ●    |

# Smooth

## More Applications

### Application is now possible with 48-V equipment.

You can handle more applications smoothly, including motor drive and power supply systems.



Robots



Conveyors



Ships



Elevators



Vehicle manufacturing equipment



Wind power generation

# Ordering Information

## List of Models

**Note:** For details on normal stock models, contact your nearest OMRON representative.

● Open-frame Power Supplies from 15 W to 150 W

| Configuration       | Input voltage  | Power ratings | Output voltage (VDC) | Output current | Model        |
|---------------------|--|---------------|----------------------|----------------|--------------|
| Front-mounting*1    | 100 to 240 VAC (wide-range) (80 to 370 VDC*3)                                    | 15W           | 5V                   | 3A             | S8JX-G01505  |
|                     |  |               | 12V                  | 1.3A           | S8JX-G01512  |
|                     |  |               | 15V                  | 1A             | S8JX-G01515  |
|                     |  |               | 24V                  | 0.65A          | S8JX-G01524  |
|                     |  |               | 48V                  | 0.35A          | S8JX-G01548  |
|                     |  | 35W           | 5V                   | 7A             | S8JX-G03005  |
|                     |  |               | 12V                  | 3A             | S8JX-G03012  |
|                     |  |               | 15V                  | 2.4A           | S8JX-G03015  |
|                     |  |               | 24V                  | 1.5A           | S8JX-G03024  |
|                     |  |               | 48V                  | 0.75A          | S8JX-G03048  |
|                     |  | 50W           | 5V                   | 10A            | S8JX-G05005  |
|                     |  |               | 12V                  | 4.2A           | S8JX-G05012  |
|                     |  |               | 24V                  | 2.1A           | S8JX-G05024  |
|                     |  |               | 48V                  | 1.1A           | S8JX-G05048  |
|                     |  | 100W          | 5V                   | 20A            | S8JX-G10005  |
|                     |  |               | 12V                  | 8.5A           | S8JX-G10012  |
|                     |  |               | 24V                  | 4.5A           | S8JX-G10024  |
|                     |  |               | 48V                  | 2.1A           | S8JX-G10048  |
|                     |  | 150W          | 5V                   | 30A            | S8JX-G15005  |
|                     |  |               | 12V                  | 13A            | S8JX-G15012  |
| 24V                 | 6.5A   |               | S8JX-G15024          |                |              |
| 48V                 | 3.3A   |               | S8JX-G15048          |                |              |
| DIN Rail-mounting*2 | S8JXN 15005□□□ only 100 to 120 VAC or 200 to 240 VAC (DC input is not supported) | 15W           | 5V                   | 3A             | S8JX-G01505D |
|                     |  |               | 12V                  | 1.3A           | S8JX-G01512D |
|                     |  |               | 15V                  | 1A             | S8JX-G01515D |
|                     |  |               | 24V                  | 0.65A          | S8JX-G01524D |
|                     |  | 35W           | 5V                   | 7A             | S8JX-G03005D |
|                     |  |               | 12V                  | 3A             | S8JX-G03012D |
|                     |  |               | 15V                  | 2.4A           | S8JX-G03015D |
|                     |  |               | 24V                  | 1.5A           | S8JX-G03024D |
|                     |  | 48V           | 0.75A                | S8JX-G03048D   |              |
|                     |  |               | 5V                   | 10A            | S8JX-G05005D |
|                     |  |               | 12V                  | 4.2A           | S8JX-G05012D |
|                     |  |               | 24V                  | 2.1A           | S8JX-G05024D |
|                     |  | 50W           | 48V                  | 1.1A           | S8JX-G05048D |
|                     |  |               | 5V                   | 20A            | S8JX-G10005D |
|                     |  |               | 12V                  | 8.5A           | S8JX-G10012D |
|                     |  |               | 24V                  | 4.5A           | S8JX-G10024D |
|                     |  | 100W          | 48V                  | 2.1A           | S8JX-G10048D |
|                     |  |               | 5V                   | 30A            | S8JX-G15005D |
|                     |  |               | 12V                  | 13A            | S8JX-G15012D |
|                     |  |               | 24V                  | 6.5A           | S8JX-G15024D |
| 150W                | 48V  | 3.3A          | S8JX-G15048D         |                |              |

\*1. The Front-mounting Bracket is included with the product as a standard feature.  
 \*2. The Front-mounting Bracket is not included with the product.  
 \*3. The applicable range for EC Directives and safety standards (UL, EN, etc.) is 100 to 240 VAC (85 to 264 VAC).

### ■ Safety-standard and RoHS Compliant



● Power Supplies with Covers for 15 W to 150 W

| Configuration       | Input voltage  | Power ratings | Output voltage (VDC) | Output current | Model         |
|---------------------|--|---------------|----------------------|----------------|---------------|
| Front-mounting*1    | 100 to 240 VAC (wide-range) (80 to 370 VDC*3)                                    | 15W           | 5V                   | 3A             | S8JX-G01505C  |
|                     |  |               | 12V                  | 1.3A           | S8JX-G01512C  |
|                     |  |               | 15V                  | 1A             | S8JX-G01515C  |
|                     |  |               | 24V                  | 0.65A          | S8JX-G01524C  |
|                     |  |               | 48V                  | 0.35A          | S8JX-G01548C  |
|                     |  | 35W           | 5V                   | 7A             | S8JX-G03005C  |
|                     |  |               | 12V                  | 3A             | S8JX-G03012C  |
|                     |  |               | 15V                  | 2.4A           | S8JX-G03015C  |
|                     |  |               | 24V                  | 1.5A           | S8JX-G03024C  |
|                     |  |               | 48V                  | 0.75A          | S8JX-G03048C  |
|                     |  | 50W           | 5V                   | 10A            | S8JX-G05005C  |
|                     |  |               | 12V                  | 4.2A           | S8JX-G05012C  |
|                     |  |               | 24V                  | 2.1A           | S8JX-G05024C  |
|                     |  |               | 48V                  | 1.1A           | S8JX-G05048C  |
|                     |  | 100W          | 5V                   | 20A            | S8JX-G10005C  |
|                     |  |               | 12V                  | 8.5A           | S8JX-G10012C  |
|                     |  |               | 24V                  | 4.5A           | S8JX-G10024C  |
|                     |  |               | 48V                  | 2.1A           | S8JX-G10048C  |
|                     |  | 150W          | 5V                   | 30A            | S8JX-G15005C  |
|                     |  |               | 12V                  | 13A            | S8JX-G15012C  |
| 24V                 | 6.5A   |               | S8JX-G15024C         |                |               |
| 48V                 | 3.3A   |               | S8JX-G15048C         |                |               |
| DIN Rail-mounting*2 | S8JXN 15005□□□ only 100 to 120 VAC or 200 to 240 VAC (DC input is not supported) | 15W           | 5V                   | 3A             | S8JX-G01505CD |
|                     |  |               | 12V                  | 1.3A           | S8JX-G01512CD |
|                     |  |               | 15V                  | 1A             | S8JX-G01515CD |
|                     |  |               | 24V                  | 0.65A          | S8JX-G01524CD |
|                     |  | 35W           | 5V                   | 7A             | S8JX-G03005CD |
|                     |  |               | 12V                  | 3A             | S8JX-G03012CD |
|                     |  |               | 15V                  | 2.4A           | S8JX-G03015CD |
|                     |  |               | 24V                  | 1.5A           | S8JX-G03024CD |
|                     |  | 48V           | 0.75A                | S8JX-G03048CD  |               |
|                     |  |               | 5V                   | 10A            | S8JX-G05005CD |
|                     |  |               | 12V                  | 4.2A           | S8JX-G05012CD |
|                     |  |               | 24V                  | 2.1A           | S8JX-G05024CD |
|                     |  | 50W           | 48V                  | 1.1A           | S8JX-G05048CD |
|                     |  |               | 5V                   | 20A            | S8JX-G10005CD |
|                     |  |               | 12V                  | 8.5A           | S8JX-G10012CD |
|                     |  |               | 24V                  | 4.5A           | S8JX-G10024CD |
|                     |  | 100W          | 48V                  | 2.1A           | S8JX-G10048CD |
|                     |  |               | 5V                   | 30A            | S8JX-G15005CD |
|                     |  |               | 12V                  | 13A            | S8JX-G15012CD |
|                     |  |               | 24V                  | 6.5A           | S8JX-G15024CD |
| 150W                | 48V  | 3.3A          | S8JX-G15048CD        |                |               |

● Power Supplies with Covers for 300 W and 600 W

| Configuration       | Input voltage                                 | Power ratings | Output voltage (VDC) | Output current | Model        |
|---------------------|---|---------------|----------------------|----------------|--------------|
| Front-mounting*1    | 100 to 120 VAC or 200 to 240 VAC (switchable) | 300W          | 24V                  | 14A            | S8JX-G30024C |
|                     |   | 600W          |                      | 27A            | S8JX-G60024C |
| DIN Rail-mounting*2 | 300W  | 14A           |                      | S8JX-G30024CD  |              |

OMRON AUTOMATION AND SAFETY • THE AMERICAS HEADQUARTERS • Schaumburg, IL USA • 847.843.7900 • 800.556.6766 • www.omron247.com

OMRON CANADA, INC. • HEAD OFFICE  
 Toronto, ON, Canada • 416.286.6465 • 866.986.6766 • www.omron247.com

OMRON ARGENTINA • SALES OFFICE  
 Cono Sur • 54.11.4783.5300

OMRON ELECTRONICS DE MEXICO • HEAD OFFICE  
 México DF • 52.55.59.01.43.00 • 001.800.556.6766 • mela@omron.com

OMRON CHILE • SALES OFFICE  
 Santiago • 56.9.9917.3920

OMRON ELECTRONICS DE MEXICO • SALES OFFICE  
 Apodaca, N.L. • 52.81.11.56.99.20 • 001.800.556.6766 • mela@omron.com

OTHER OMRON LATIN AMERICA SALES  
 54.11.4783.5300

OMRON ELETRÔNICA DO BRASIL LTDA • HEAD OFFICE  
 São Paulo, SP, Brasil • 55.11.2101.6300 • www.omron.com.br

OMRON EUROPE B.V. • Wegalaan 67-69, NL-2132 JD, Hoofddorp, The Netherlands. • Tel: +31 (0) 23 568 13 00 • Fax: +31 (0) 23 568 13 88 • www.industrial.omron.eu

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Omron:

[S8JX-G01512](#) [S8JX-G10005CD](#) [S8JX-G05024D](#) [S8JX-G03512D](#) [S8JX-G05005D](#) [S8JX-G01512D](#) [S8JX-G15024D](#)  
[S8JX-G03505D](#) [S8JX-G03524D](#) [S8JX-G01524D](#) [S8JX-G01505D](#) [S8JX-G05012D](#) [S8JX-G10012C](#) [S8JX-G15024](#)  
[S8JX-G05005C](#) [S8JX-G01505](#) [S8JX-G01512C](#) [S8JX-G03515](#) [S8JX-G01515C](#) [S8JX-G05012C](#) [S8JX-G03505C](#)  
[S8JX-G10005C](#) [S8JX-G10005](#) [S8JX-G03505](#) [S8JX-G01524](#) [S8JX-G03512](#) [S8JX-G01515D](#) [S8JX-G10024C](#) [S8JX-](#)  
[G01515](#) [S8JX-G05005](#) [S8JX-G10012](#) [S8JX-G03515D](#) [S8JX-G01505C](#) [S8JX-G01524C](#) [S8JX-G03515CD](#) [S8JX-](#)  
[G10012CD](#)

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9