


# Terminal Relay

## G6B-4□□ND

### Compact Terminal Relay with 4 Independent Outputs

- Equipped with four G6B Mini-relays that are compact, highly sensitive, and highly resistant to dielectric surges, and that can switch 5 amps of power.
- Sealed plastic construction used for relays.
- Easy wiring with separated input/output terminals.
- Special P6B Mounting Socket used to facilitate maintenance (except for high-reliability models).
- Standard models meet UL508 and CSA requirements.
- DIN Track mounting, and screw mounting models are available.



## Model Number Structure

### Model Number Legend

G6B-□□□ND  
1 2 3

**Note:** UL508 and CSA requirements met by standard models.

#### 1. Number of Poles

- 4: 4 poles (4PST-NO standard circuit)
- 47: 4 poles (4PST-NO long-life circuit)
- 48: 4 poles (4PST-NO high-reliability circuit)

#### 2. Mounting

- None: DIN Track or screw mounting
- F: Screw mounting

#### 3. Input Terminal

- B: Phillips screw (3.5 mm) terminals (4 independent points)
- B1: Flat-bladed screw terminals (4 points with same common)
- P: Connector terminals (4 independent points)

## Ordering Information

### List of Models

| Classification                                                   | Contact form            | Mounting method             | Terminals                  | Rated voltage             | Model      |
|------------------------------------------------------------------|-------------------------|-----------------------------|----------------------------|---------------------------|------------|
| Equipped with operation indicator and diode to absorb coil surge | 4PST (standard)         | DIN Track or screw mounting | Phillips screw terminal    | 5 VDC<br>12 VDC<br>24 VDC | G6B-4BND   |
|                                                                  | 4PST (long-life)        | DIN Track or screw mounting | Phillips screw terminal    | 5 VDC<br>12 VDC<br>24 VDC | G6B-47BND  |
|                                                                  | 4PST (high reliability) | DIN Track or screw mounting | Phillips screw terminal    | 5 VDC<br>12 VDC<br>24 VDC | G6B-48BND  |
|                                                                  | 4PST (standard)         | Screw mounting              | Flat-bladed screw terminal | 5 VDC<br>12 VDC<br>24 VDC | G6B-4FB1ND |
|                                                                  | 4PST (standard)         | Screw mounting              | Connector                  | 5 VDC<br>12 VDC<br>24 VDC | G6B-4FPND  |

**Note:** 1. For replacement relays, use relays with the same voltage specifications as the relays provided with the Terminal when it was purchased. Longer operating life can be achieved by replacing the G6B-4□□ND with the G6B-1147P-FD-US.

2. Standard models are also available without relays mounted to the sockets. To obtain such terminals, replace the "G6B" portion of the model number with "P6BF." For example, to order G6B-4BND with empty sockets, use model number P6BF-4BND. Also specify voltage specifications for models with operation indicators.

# Specifications

## ■ Ratings

### Coil Ratings (per G6B Relay)

|                      |                           |              |                |
|----------------------|---------------------------|--------------|----------------|
| Rated voltage        | 5 VDC                     | 12 VDC       | 24 VDC         |
| Rated current        | 35.5 mA                   | 19.1 mA      | 10.7 mA        |
| Coil resistance      | 125 $\Omega$              | 720 $\Omega$ | 2,880 $\Omega$ |
| Must operate voltage | 80% max. of rated voltage |              |                |
| Must release voltage | 10% min. of rated voltage |              |                |
| Max. voltage         | 130% of rated voltage     |              |                |
| Power consumption    | Approx. 200 mW            |              |                |

- Note:** 1. Rated current and coil resistance were measured at a coil temperature of 23°C with a tolerance of  $\pm 20\%$ .  
 2. Operating characteristics were measured at a coil temperature of 23°C.  
 3. The maximum allowable voltage is the maximum value of the allowable voltage range for the relay coil operating power supply. There is no continuous allowance.  
 4. Diodes to absorb coil surge are equivalent to S5688J (reverse voltage resistance: 600 V; forward current: 1 A).

### Contact Ratings

| Classification                          | G6B-4BND (standard), G6B-47BND (long-life) |                                            | G6B-48BND (high-reliability)     |                                            |
|-----------------------------------------|--------------------------------------------|--------------------------------------------|----------------------------------|--------------------------------------------|
| Load                                    | Resistive load<br>(cosφ = 1)               | Inductive load<br>(cosφ = 0.4, L/R = 7 ms) | Resistive load<br>(cosφ = 1)     | Inductive load<br>(cosφ = 0.4, L/R = 7 ms) |
| Rated load                              | 5 A at 250 VAC,<br>5 A at 30 VDC           | 2 A at 250 VAC,<br>2 A at 30 VDC           | 2 A at 250 VAC,<br>2 A at 30 VDC | 0.5 A at 250 VAC,<br>0.5 A at 30 VDC       |
| Rated carry current                     | 5 A                                        |                                            | 2 A                              |                                            |
| Max. switching voltage                  | 380 VAC, 125 VDC                           |                                            |                                  |                                            |
| Max. switching current                  | 5 A                                        |                                            | 2 A                              |                                            |
| Max. switching power                    | 1,250 VA, 150 W                            | 500 VA, 60 W                               | 500 VA, 60 W                     | 125 VA, 15 W                               |
| Error rate (reference value) (see note) | 10 mA at 5 VDC                             |                                            | 1 mA at 1 VDC                    |                                            |

**Note:** This value fulfills the P reference value of opening/closing at a rate of 120 times per min (ambient operating environment and determination criteria according to JIS C5442).


## ■ Characteristics

|                                 |                                                                                                                                                                                                                                                                       |
|---------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Contact resistance (see note 2) | 100 m $\Omega$ max.                                                                                                                                                                                                                                                   |
| Operate time                    | 10 ms max. (approx. 3 ms)                                                                                                                                                                                                                                             |
| Release time                    | 15 ms max. (approx. 4 ms)                                                                                                                                                                                                                                             |
| Switching power                 | Mechanical: 18,000 operations/hr<br>Rated load: 1,800 operations/hr                                                                                                                                                                                                   |
| Insulation resistance           | 1,000 M $\Omega$ min. (at 500 VDC)                                                                                                                                                                                                                                    |
| Dielectric strength             | 2,000 VAC, 50/60 Hz for 1 min between coil and contacts<br>2,000 VAC, 50/60 Hz for 1 min between contacts of different polarity<br>1,000 VAC, 50/60 Hz for 1 min between contacts of same polarity<br>250 VAC, 50/60 Hz for 1 min between coils of different polarity |
| Vibration resistance            | Destruction: 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude)<br>Malfunction: 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude)                                                                                              |
| Shock resistance                | Destruction: 1,000 m/s <sup>2</sup> (approx. 100G)<br>Malfunction: 100 m/s <sup>2</sup> (approx. 10G)                                                                                                                                                                 |
| Endurance                       | Mechanical: 50,000,000 operations min. (at 18,000 operations/hr)<br>Electrical: 100,000 operations min. (at 1,800 operations/hr, rated load)<br>500,000 operations min. for long-life at 2 A<br>100,000 operations min for long-life at 5 A                           |
| Ambient temperature             | Operating: -25°C to 55°C (with no icing or condensation)<br>Storage: -25°C to 55°C (with no icing or condensation)                                                                                                                                                    |
| Ambient humidity                | Operating: 35% to 85%                                                                                                                                                                                                                                                 |
| Weight                          | Approx. 75 g                                                                                                                                                                                                                                                          |


- Note:** 1. The above values are initial values.  
 2. Measurement condition: 1 A at 5 VDC

# Engineering Data


## Maximum Switching Power



## Endurance



## Contact Reliability (High-reliability Models)



# Dimensions

**Note:** All units are in millimeters unless otherwise indicated.


## Philip Screw Terminals

G6B-4BND


G6B-47BND

G6B-48BND


**Note:** G6B-4BND is shown in illustration (terminal numbers are incised).



### Mounting Holes




### Terminal Arrangement/ Internal Connections (Top View)




**Note:** Do not reverse the coil polarity.

## Flat Screw Terminal


G6B-4FB1ND



### Mounting Holes




### Terminal Arrangement/ Internal Connections (Top View)




**Note:** Do not reverse the coil polarity.

## Connector Terminal


G6B-4FPND



### Mounting Holes



### Terminal Arrangement/ Internal Connections (Top View)



**Note:** Do not reverse the coil polarity.

## ■ Accessories (Order Separately)

### Replacement Relays


| Applicable terminal relay | Rated voltage             | Model           |
|---------------------------|---------------------------|-----------------|
| G6B-4BND                  | 5 VDC<br>12 VDC<br>24 VDC | G6B-1114P-FD-US |
| G6B-47BND                 | 5 VDC<br>12 VDC<br>24 VDC | G6B-1174P-FD-US |

**Note:** Relays cannot be replaced for G6B-48BND, which is mounted directly to boards.

### Relay Mounting Products


| Name               | Model     |
|--------------------|-----------|
| Relay Removal Tool | P6B-Y1    |
| Short Bars         | G6B-4-SB  |
| Mounting Track     | PFP-100N  |
|                    | PFP-50N   |
|                    | PFP-100N2 |
| End Plate          | PFP-M     |
| Spacer             | PFP-S     |

#### P6B-Y1 Relay Removal Tool





#### G6B-4-SB Short Bars

Short Bars are used to wire crossovers for common terminals for coils or contacts.



#### G6B-4-C Terminal Covers (Two per set)



# Precautions

## Wiring

Be sure to turn OFF the power when wiring the Unit and do not touch the charged terminals of the Unit. Otherwise, an electric shock may result.

Do not apply overvoltage to the input terminals. Otherwise, the Unit may malfunction or burn.

## Relay Models

Do not connect the Unit to loads exceeding the rated switching power (switching voltage or current). Otherwise, faulty insulation, contact weld, or faulty contact of Relays, or damage to Relays may result, or the Relays may malfunction or burn.

The life of Relays varies with the switching condition. Test the Relays under the actual operating conditions before using the Relays within the permissible switching frequency. The use of deteriorated Relays may result in the faulty insulation of the Relays or cause the Relays to burn.

Do not use the Unit in locations with inflammable gas. Otherwise, a fire or explosion due to the heat of the Relays or sparks from the Relays may result when they are switched.

## Correct Use


## Mounting

Heat generated by the relays must be considered when gang-mounting. Space must be provided between the relays or other methods must be taken to maintain the relays' ambient temperature at 55 °C or lower.

## Replacement of Relays

### G6B-4□□ND

Use the P6B-Y1 Removal Tool as shown in the following diagram.



Be sure to turn OFF the power to the Unit before replacing a Relay. Relays must be inserted straight onto the socket connector pins to ensure proper connection.

G6B-48BND models (high reliability) are connected directly to boards to increase reliability and the relays are thus not replaceable. If relay replacement is necessary, use the P6BF-4BND Terminal Sockets together with the G6B-1184P Mini Relays. P6BF-4BND Terminal Sockets are equipped with relay replacement sockets.

Do not mount Relays that are different to one another in voltage.

## Relays Mounted

G6B-4□□ND standard: G6B-1114P-FD-US  
 G6B-4□□ND long life: G6B-1174P-FD  
 G6B-4□□ND high reliability: G6B-1184P-US  
 Replacement is not possible for G6B-48BND.

## Wiring


Be sure to connect the input terminals with the correct polarity.

## Coil Voltage

Be sure not to impose voltage exceeding the permissible voltage on the coil continuously.

Do not use the relays when other inductive loads are connected in parallel with the coil input or when there are surges during power supply because the built-in diodes used to absorb surge may be destroyed.

## Do Not Use the Following Circuit



## Handling

Do not drop, shock, or vibrate the Unit excessively. Otherwise, damage to the Unit may result or the Unit may malfunction.

Make sure that all the Relays are properly mounted before use.

## Screw Tightening Torque

Tighten each terminal screw to a torque of 0.78 to 1.18N·m.

Tighten each mounting screw to a torque of 0.59 to 0.98 N·m.

## Installation Environment

Do not install the Unit in the following locations. Otherwise, damage to the Unit may result or the Unit may malfunction.

Locations with direct sunlight.

Locations with an ambient temperature range not within 0°C to 55°C.

Locations with rapid temperature changes resulting in condensation or locations with relative humidity ranges not within 10% to 90%.

Locations with corrosive or inflammable gas.

Locations with excessive dust, salinity, or metal powder.

Locations with vibration or shock affecting the Unit.

Locations with water, oil, or chemical sprayed on the Unit.

## Disassembly, Repair, and Modification

Do not disassemble, repair, or modify the Unit. Otherwise, an electric shock may result or the Unit may malfunction.

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.

To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9