

# Ethernet PICtail™ Daughter Board

## Overview

The Ethernet PICtail™ Daughter Board is an Ethernet demonstration board for evaluating Microchip Technology's ENC28J60 stand-alone 10 Base-T Ethernet controller. It is an expansion board compatible with a number of PICDEM™ demonstration boards. A complete list of compatible PICDEM demonstration boards is available on Microchip's web site.

## Getting Started

To get started, a compatible PICDEM demonstration board is required. In general, a board is compatible if it has a PICtail™ board interface expansion port, which is a 14x2 connector. Most PICDEM demonstration boards do not have the female header installed. Thus, a 14x2 female connector is included with this kit for the user to install onto the PICDEM demonstration board if necessary. When connecting the two boards together, pay close attention to the orientation of the connector and pin alignment. The AC/DC power adapter should be plugged into the PICtail board's power socket. Only one AC/DC power adapter is required because the Ethernet PICtail board is capable of supplying power to the PICDEM demonstration board.

## Features

- ENC28J60 Ethernet Controller with 25 MHz oscillator and integrated magnetic RJ-45 connector (see device data sheet DS39662 for additional information)
- 256 Kbits SPI EEPROM (25LC256) for storing web pages and configurations
- Dedicated power supply
- PICtail™ Daughter Board connection interface

## Board Configurations

As shipped from the factory, some of the jumper locations are bridged by circuit traces forming a default setup. To change this, the user will need to cut the traces and install pins and a block jumper. Afterward, the features can be enabled or disabled easily by installing or removing the jumper.

Jumper	Position	Function
J4	Pin 1-2 (Default)	Clock out path from ENC28J60 to PICDEM™ board is disabled
	Pin 2-3	Clock out path from ENC28J60 to PICDEM board is enabled
J5	Pin 1-2 (Default)	RC5 is connected to ENC28J60/25LC256's SI pin
	Pin 2-3	RC7 is connected to ENC28J60/25LC256's SI pin (1)
J6	Pin 1-2 (Default)	RC4 is connected to ENC28J60/25LC256's SO pin
	Pin 2-3	RB0 is connected to ENC28J60/25LC256's SO pin (1)
J7	Pin 1-2 (Default)	RC3 is connected to ENC28J60/25LC256's SCK pin
	Pin 2-3	RB1 is connected to ENC28J60/25LC256's SCK pin (1)
J8	Disabled (Default)	Reserved – Do Not Use
J9	Pin 1-2	3.3V power supply to PICDEM demonstration board
	Pin 2-3 (Default)	5V power supply to PICDEM demonstration board
	Not connected	No power supply to PICDEM demonstration board

**Note 1:** This option is available to support the PICDEM™ FS USB Demo Board.

## Firmware

Firmware examples can be downloaded from <http://www.microchip.com/Ethernet>. Make sure to download the firmware version that has been designated for the particular PICDEM demonstration board that you have.

## Signal Interface

Function	I/O	Pin	Description
$\overline{CS}$ for ENC28J60	I	RB3	SPI Chip Select for ENC28J60
$\overline{CS}$ for 25LC256	I	RB4	SPI Chip Select for 25LC256
SCK	I	RC3 or RB1	SPI Clock
SO	O	RC4 or RB0	SPI Data Out from ENC28J60/25LC256
SI	I	RC5 or RC7	SPI Data In to ENC28J60/25LC256
$\overline{RESET}$	I	RB5	Reset Signal
$\overline{INT}$	O	RB2	$\overline{INT}$ Interrupt Signal
CLKOUT	O	OSC1	Programmable Clock Output

## Media Access Control (MAC) Address

For evaluation purposes, each Ethernet PICtail board comes with a board number which can be used to form a unique MAC address. This number can be found on the sticker label on the back of each board. To form a MAC address, replace the last 3 bytes of the following MAC address, 00-04-A3-XX-XX-XX, with the number from the sticker. The number on the sticker is in decimal format and conversion to a hex number is required. For example, if the sticker has the value of "12345", then the MAC address would be 00-04-A3-00-30-39.

## Other Information

To obtain the most recent and complete documentation for this demonstration board, including:

- User's Guide
- Board Description
- Board Schematics
- Source Code
- Application Examples
- Links to Web Seminars

please refer to the web site: <http://www.microchip.com/Ethernet>

### Americas

Atlanta (770) 640-0034  
 Boston (774) 760-0087  
 Chicago (630) 285-0071  
 Dallas (972) 818-7423  
 Detroit (248) 538-2250  
 Kokomo (765) 864-8360  
 Los Angeles (949) 462-9523  
 Phoenix (480) 792-7200  
 San Jose (650) 215-1444  
 Toronto (905) 673-0699

### Asia/Pacific

Australia - Sydney 61-2-9868-6733  
 China - Beijing 86-10-8528-2100  
 China - Chengdu 86-28-8676-6200  
 China - Fuzhou 86-591-8750-3506  
 China - Hong Kong SAR 852-2401-1200  
 China - Qingdao 86-532-8502-7355  
 China - Shanghai 86-21-5407-5533  
 China - Shenyang 86-24-2334-2829  
 China - Shenzhen 86-755-8203-2660  
 China - Shunde 86-757-2839-5507  
 China - Wuhan 86-27-5980-5300  
 China - Xian 86-29-8833-7250  
 India - Bangalore 91-80-2229-0061  
 India - New Delhi 91-11-5160-8631  
 India - Pune 91-20-2566-1512  
 Japan - Yokohama 81-45-471-6166  
 Korea - Gumi 82-54-473-4301  
 Korea - Seoul 82-2-554-7200

### Asia/Pacific

Malaysia - Penang 60-4-646-8870  
 Philippines - Manila 63-2-634-9065  
 Singapore 65-6334-8870  
 Taiwan - Hsin Chu 886-3-572-9526  
 Taiwan - Kaohsiung 886-7-536-4818  
 Taiwan - Taipei 886-2-2500-6610  
 Thailand - Bangkok 66-2-694-1351

### Europe

Austria - Wels 43-7242-2244-399  
 Denmark - Copenhagen 45-4450-2828  
 France - Paris 33-1-69-53-63-20  
 Germany - Munich 49-89-627-144-0  
 Italy - Milan 39-0331-742611  
 Netherlands - Drunen 31-416-690399  
 Spain - Madrid 34-91-708-08-90  
 UK - Wokingham 44-118-921-5869

As of 10/31/05



Microchip Technology Inc. • 2355 West Chandler Blvd. • Chandler, AZ 85224-6199  
[www.microchip.com](http://www.microchip.com)

The Microchip name and logo, the Microchip logo, PIC and PICmicro are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. In-Circuit Serial Programming, ICSP, PICDEM and PICtail are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companies. © 2006, Microchip Technology Incorporated, Printed in the U.S.A. All Rights Reserved. 1/06



DS51569B

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Microchip:](#)

[AC164121](#)

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9