

### Data Sheet

The model 1672 is a quad display triple output regulated DC power supply that provides one fixed output (5V/3A) and two variable outputs (0-32V/ 0-3A) ratings. The variable outputs can work independently, or in series tracking, or parallel mode.

- Independent control of Voltage and Current controls for variable output.
- CV/CC operation.
- Separate 3 digit displays for voltage (Green) and current (Red) for both variable outputs.
- LED indication for CV (Green)/ CC (Red) mode.
- Overload indication LED for Fixed output.
- Series tracking and parallel mode operation for Triple output unit.



Model 1672, a Quad 3-Digit, Triple Output Regulated DC Power Supply has been added to B&K expanding new line of power supplies. Utilizing a standard 115VAC outlet as the power source, the new bench top unit provides the accuracy of quad 3-digit LED resolution, two variable voltage outputs of 0 to 32VDC/0 to 3A and one fixed 5VDC/3A output.

Model 1672 offers exceptional performance and is an ideal supply for Educational, Service and Maintenance, Hobbyist and Manufacturing applications.

Model 1672 provides the user with many unique and useful features not normally found in a triple output power at this low price.

Model 1672 features four large, easy-to-read front-panel-mounted 3-digit LED displays – one set reading volts and amps of the "B" supply, the other set reads volts and amps of the "A" supply. The unit has a unique variable tracking, B track A at 5% to 100% capability. The voltage meter resolution is 0.00 to 99.9, the amperage meter resolution is 0.00 to 9.99, and all meters offer an accuracy of  $\pm(0.1\% \text{ rdg} + 3 \text{ digit})$ .

Other front panel indicators and controls include an OFF/ON power switch, a Power LED, Overload Indicator Light, Voltage Adjustment Knob, and adjustable current limit controls.

### Specifications

	model <b>1672</b>
Output Voltage	0-32VDC
	0-32VDC
	Fixed 5VDC
Output Current	0-3A
	0-3A
	Fixed 0-3A
Constant Voltage Operation	
Voltage Regulation	
Line (120VAC $\pm 10\%$ )	$<0.01\% + 3\text{mV}$
Load	$<0.2\% + 10\text{mV}$
Ripple & Noise	$\leq 1\text{mV rms}$

### B&K Precision Corporation

22820 Savi Ranch Parkway, Yorba Linda, CA 92887  
Tel: 714-921-9095, Fax: 714-921-6422  
www.bkprecision.com

Specifications subject to change without notice

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9