


SMD Power Inductor 0630CDMCC/DS



RoHS


Halogen
Free




Description

- Metal compound molding type construction.
- Magnetically shielded.
- Low audible core noise.
- Suitable for large current.
- L × W × H: 7.3 × 6.8 × 3.0mm Max.
- Product weight: 0.73g (Ref.)
- Moisture Sensitivity Level: 1
- RoHS compliance.
- Halogen Free available.

Dimension - [mm]



Land pattern and Schematics - [mm]



Environmental Data

- Operating temperature range: -55°C ~ +125°C (including coil's self temperature rise)
- Storage temperature range: -55°C ~ +125°C
- Solder reflow temperature: 260 °C peak.

Packaging

- Carrier tape and reel packaging.
- 1500pcs/Reel.

Applications

- Ideally used in notebook, ultrabook, tablet PC, LCD display, Server application.
- High current, POL converters.
- Low profile, high current power supplies.
- Battery powered devices.
- DC/DC converters in distributed power systems.

SMD Power Inductor 0630CDMCC/DS



Electrical Characteristics

Part No.	Stamp	Inductance [Within] (μ H) ※1	D.C.R (m Ω) Max.(Typ.) at 25°C	Saturation Current (A) Max.(Typ.) (at 25°C) ※2	Temperature rise current (A) (Typ.) ※3
0630CDMCCDS-R22MC	R22	0.22 $\pm$ 20%	3.0(2.5)	32.3(38.0)	24.0
0630CDMCCDS-R24MC	R24	0.24 $\pm$ 20%	3.1(2.6)	31.0(36.6)	23.0
0630CDMCCDS-R33MC	R33	0.33 $\pm$ 20%	3.5(3.0)	27.5(32.3)	21.0
0630CDMCCDS-R47MC	R47	0.47 $\pm$ 20%	4.1(3.5)	20.6(24.2)	20.0
0630CDMCCDS-R56MC	R56	0.56 $\pm$ 20%	4.5(3.9)	17.5(20.5)	18.8
0630CDMCCDS-R68MC	R68	0.68 $\pm$ 20%	5.3(4.8)	17.0(20.0)	16.5
0630CDMCCDS-R82MC	R82	0.82 $\pm$ 20%	6.0(5.4)	16.5(19.5)	14.8
0630CDMCCDS-1R0MC	1R0	1.0 $\pm$ 20%	7.4(6.7)	14.0(16.5)	14.4
0630CDMCCDS-1R5MC	1R5	1.5 $\pm$ 20%	12.1(10.6)	12.9(15.2)	10.2
0630CDMCCDS-2R2MC	2R2	2.2 $\pm$ 20%	15.0(13.5)	10.5(12.3)	9.3
0630CDMCCDS-3R3MC	3R3	3.3 $\pm$ 20%	22.0(18.0)	9.7(11.4)	8.4
0630CDMCCDS-4R7MC	4R7	4.7 $\pm$ 20%	33.0(28.0)	5.8(6.8)	6.3
0630CDMCCDS-6R8MC	6R8	6.8 $\pm$ 20%	48.0(42.5)	5.3(6.3)	5.0
0630CDMCCDS-8R2MC	8R2	8.2 $\pm$ 20%	60.0(54.0)	4.9(5.8)	4.3
0630CDMCCDS-100MC	100	10.0 $\pm$ 20%	67.0(62.0)	4.6(5.5)	4.0
0630CDMCCDS-150MC	150	15.0 $\pm$ 20%	115.0(104.0)	3.6(4.3)	3.3
0630CDMCCDS-220MC	220	22.0 $\pm$ 20%	200.0(180.0)	3.4(4.0)	2.3

※1 Measuring frequency Inductance at 100kHz, 1.0V

※2 Saturation current: The value of DC current when the inductance is over 70% of its initial value.

※3 Temperature rise current: The actual value of DC current when temperature of coil rise is













$\Delta T=40^{\circ}\text{C}$ ($T_a=25^{\circ}\text{C}$) Board conditions: FR4, Copper=70 μm , four-layer PWB, $t=1.6\text{mm}$.

SMD Power Inductor 0630CDMCC/DS



Saturation Current & Temperature Rise Graph

— L (20°C) — ΔT








SMD Power Inductor 0630CDMCC/DS



Saturation Current & Temperature Rise Graph



— L (20°C) — ΔT



SMD Power Inductor 0630CDMCC/DS



Solder Reflow Condition



Please refer to the sales offices on our website - <http://www.sumida.com>

Hong Kong

Tel. +852-2880-6781
FAX. +852-2565-9600
sales@hk.sumida.com

Saitama(Japan)

Tel. +81-48-691-7300
FAX. +81-48-691-7340
sales@jp.sumida.com

Chicago

Tel. +1-847-545-6700
FAX. +1-847-545-6720
sales@us.sumida.com

Shanghai

Tel. +86-21-5836-3299
FAX. +86-21-5836-3266
shanghai.sales@cn.sumida.com

Seoul

Tel. +82-2-6237-0777
FAX. +82-2-6237-0778
sales@kr.sumida.com

Obernzell

Tel. +49-8591-937-0
FAX. +49-8591-937-103
contact@eu.sumida.com

Shenzhen

Tel. +86-755-8291-0228
FAX. +86-755-8291-0338
shenzhen.sales@cn.sumida.com

Singapore

Tel. +65-6296-3388
FAX. +65-6841-4426
sales@sg.sumida.com

Neumarkt

Tel. +49-9181-4509-110
FAX. +49-9181-4509-310
infocomp@eu.sumida.com

Taipei

Tel. +886-2-8751-2737
FAX. +886-2-8751-2738
sales@tw.sumida.com

San Jose

Tel. +1-408-321-9660
FAX. +1-408-321-9308
sales@us.sumida.com

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9