




## FineAdjust Applicator Specification Sheet Part No. 63867-7000



### FEATURES

- Quick punch removal with the push of a button for fast and easy tooling change
- Applicator designed to industry standard mounting and shut height 135.80mm (5.346")
- Quick set-up time; plus the crimp height, track and feed adjustments can be set without removing the applicator from the press
- Fine adjustment allows users to achieve target with little effort by adjusting in increments of 0.15mm (.0006") for conductor crimp height and .063mm (.0025") for insulation height
- Independent adjustment rings allow users to quickly adjust the conductor or insulation crimp height without affecting each other
- Directly adapts to most automatic wire processing machines


### SCOPE

Products: 3.33mm (.131") Pitch MOX Power Crimp Terminal, 1.50mm (.059"), Female, 14-16 AWG

| Terminal Part No. | Terminal Order No. | *Wire Type | Wire Size |                        | Insulation Diameter |           | Strip Length |           |
|-------------------|--------------------|------------|-----------|------------------------|---------------------|-----------|--------------|-----------|
|                   |                    |            | AWG       | Actual mm <sup>2</sup> | mm                  | In.       | mm           | In.       |
| 98195             | 98195-1213         | TXL - 16   | 16        | 1.226                  | 2.18-2.34           | .086-.092 | 4.60-5.00    | .181-.197 |
|                   |                    | TXL - 14   | 14        | 1.941                  | 2.54-2.69           | .100-.106 | 4.60-5.00    | .181-.197 |

\* Only tested on listed wire types, any other types must be tested

### DEFINITION OF TERMS



The above terminal drawing is a generic terminal representation. It is not an image of a terminal listed in the scope.

**CRIMP SPECIFICATION**

| Terminal Series No. | Bell mouth |           | Cut-off Tab Maximum |      | Conductor Brush |           |
|---------------------|------------|-----------|---------------------|------|-----------------|-----------|
|                     | mm         | In.       | mm                  | In.  | mm              | In.       |
| 98195               | 0.25-1.00  | .010-.039 | 0.30                | .012 | 0.20-0.60       | .008-.024 |

| Terminal Series No. | Bend up   Bend down |   | Twist   Roll |   | Punch Width mm (Ref) |      |            |      | Seam<br>Seam shall not be open<br>and no wire allowed out<br>of the crimping area |
|---------------------|---------------------|---|--------------|---|----------------------|------|------------|------|-----------------------------------------------------------------------------------|
|                     | Degree              |   | Degree       |   | Conductor            |      | Insulation |      |                                                                                   |
|                     |                     |   |              |   | mm                   | In   | mm         | In   |                                                                                   |
| 98195               | 2                   | 2 | 4            | 4 | 2.45                 | .096 | 2.90       | .114 |                                                                                   |

After crimping, the conductor profile should measure the following.

| Terminal Series No. | Wire Type | Wire Size |                        | Conductor Crimp |           |       |      |
|---------------------|-----------|-----------|------------------------|-----------------|-----------|-------|------|
|                     |           |           |                        | Height          |           | Width |      |
|                     |           | AWG       | Actual mm <sup>2</sup> | mm              | In.       | mm    | In.  |
| 98195               | TXL - 16  | 16        | 1.226                  | 1.32-1.38       | .052-.054 | 2.50  | .098 |
|                     | TXL - 14  | 14        | 1.941                  | 1.40-1.45       | .055-.057 | 2.50  | .098 |

| Terminal Series No. | Wire Type | Wire Size |            | Insulation Crimp |           |       |      | Pull Force Minimum |      |
|---------------------|-----------|-----------|------------|------------------|-----------|-------|------|--------------------|------|
|                     |           |           |            | Height           |           | Width |      |                    |      |
|                     |           | AWG       | Actual mm² | mm               | In.       | mm    | In.  | N                  | Lb.  |
| 98195               | TXL - 16  | 16        | 1.226      | 2.55-2.65        | .100-.104 | 3.00  | .118 | 180                | 40.5 |
|                     | TXL - 14  | 14        | 1.941      | 2.95-3.05        | .116-.120 | 3.00  | .118 | 220                | 49.5 |

Pull Force should be measured with no influence from the insulation crimp.

The above specifications are guidelines to an optimum crimp.

**PARTS LIST**

| <b>FineAdjust Applicator 63867-7000</b>                                      |                 |                        |                                    |                 |
|------------------------------------------------------------------------------|-----------------|------------------------|------------------------------------|-----------------|
| <b>Item</b>                                                                  | <b>Order No</b> | <b>Engineering No.</b> | <b>Description</b>                 | <b>Quantity</b> |
| <b>Perishable Tooling</b>                                                    |                 |                        |                                    |                 |
|                                                                              | 63867-7070      | 63867-7070             | Tool Kit (All "Y" Items)           | REF             |
| 1                                                                            | 63457-0016      | 63457-0016             | Conductor Punch                    | 1 Y             |
| 2                                                                            | 63455-0016      | 63455-0016             | Conductor Anvil                    | 1 Y             |
| 3                                                                            | 63454-0027      | 63454-0027             | Insulation Punch                   | 1 Y             |
| 4                                                                            | 63445-2971      | 63445-2971             | Insulation Anvil                   | 1 Y             |
| 5                                                                            | 63443-0002      | 63443-0002             | Cut-Off Plunger                    | 1 Y             |
| 6                                                                            | 63443-0012      | 63443-0012             | Front Plunger Retainer             | 1 Y             |
| <b>Other Components</b>                                                      |                 |                        |                                    |                 |
| 7                                                                            | 11-18-4080      | 60707-5                | Wire Stop                          | 1               |
| 8                                                                            | 11-18-4083      | 60707-8                | Front Cover                        | 1               |
| 9                                                                            | 11-24-1067      | 4996-4                 | Cut-Off Plunger Spring             | 1               |
| 10                                                                           | 63443-0009      | 63443-0009             | Scrap Chute                        | 1               |
| 11                                                                           | 63443-0021      | 63443-0021             | Lower Tooling Key                  | 1               |
| 12                                                                           | 63443-2801      | 63443-2801             | Front Plunger Striker              | 1               |
| 13                                                                           | 63443-0067      | 63443-0067             | Wire Hold-Down Plunger             | 1               |
| 14                                                                           | 63443-2509      | 63443-2509             | Anvil Mount                        | 1               |
| 15                                                                           | 63443-6015      | 63443-6015             | Rear Cover                         | 1               |
| 16                                                                           | 63600-1057      | 63600-1057             | Compression Spring                 | 1               |
| <b>Frame</b>                                                                 |                 |                        |                                    |                 |
| 17                                                                           | 63800-4901      | 63800-4901             | Top                                | 1               |
| 18                                                                           | 63801-3281      | 63801-3281             | Base                               | 1               |
| 19                                                                           | 63801-4650      | 63801-4650             | Track                              | 1               |
| <b>Hardware</b>                                                              |                 |                        |                                    |                 |
| 20                                                                           | N/A             | N/A                    | M3 by 6Lg. SHCS                    | 2**             |
| 21                                                                           | N/A             | N/A                    | M4 by 6Lg. SHCS                    | 1**             |
| 22                                                                           | N/A             | N/A                    | M4 by 12Lg. BHCS                   | 2**             |
| 23                                                                           | N/A             | N/A                    | M4 by 50Lg. SHCS                   | 2**             |
| 24                                                                           | N/A             | N/A                    | M5 by 12Lg SHCS                    | 1**             |
| 25                                                                           | N/A             | N/A                    | 3MM by 6Lg. Roll Pin               | 1**             |
| 26                                                                           | N/A             | N/A                    | #10-32 by 3/8" Long Flat Point SSS | 1**             |
| 27                                                                           | N/A             | N/A                    | #10-32 Hex Jam Nut                 | 1**             |
| ** Available from an industrial supply company such as MSC (1-800-645-7270). |                 |                        |                                    |                 |

# Assembly Drawing




Figure 1

## NOTES

1. Molex recommends an extra perishable tooling kit be maintained at your facility.
2. Verify tooling alignment by manually cycling the press and Applicator before crimping under power. Check that all screws are tight.
3. Slugs, Terminals, Dirt and Oil should be kept clear of work area.
4. Wear safety glasses at all times.
5. For recommended maintenance refer to the FineAdjust Manual.

**CAUTION:** This applicator should only be used in a press with a shut height of 135.8 mm (5.346"). Tooling damage could result at a lower setting.

**CAUTION:** To prevent injury never operate this Applicator without the guards supplied with the press or wire-processing machine in place. Reference the press or wire processing manufacturer's instruction manual.

**CAUTION:** Molex crimp specifications are valid only when used with Molex terminals, applicators and tooling.

**Americas Headquarters**  
Lisle, Illinois 60532 U.S.A.  
1-800-78MOLEX  
amerinfo@molex.com

**Far East North Headquarters**  
Yamato, Kanagawa, Japan  
81-462-65-2324  
feninfo@molex.com

**Far East South Headquarters**  
Jurong, Singapore  
65-6-268-6868  
fesinfo@molex.com

**European Headquarters**  
Munich, Germany  
49-89-413092-0  
eurinfo@molex.com

**Corporate Headquarters**  
2222 Wellington Ct.  
Lisle, IL 60532 U.S.A.  
630-969-4550  
Fax: 630-969-1352

Visit our Web site at <http://www.molex.com>

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9