To all our customers

Regarding the change of names mentioned in the document, such as Mitsubishi Electric and Mitsubishi XX, to Renesas Technology Corp.

The semiconductor operations of Hitachi and Mitsubishi Electric were transferred to Renesas Technology Corporation on April 1st 2003. These operations include microcomputer, logic, analog and discrete devices, and memory chips other than DRAMs (flash memory, SRAMs etc.) Accordingly, although Mitsubishi Electric, Mitsubishi Electric Corporation, Mitsubishi Semiconductors, and other Mitsubishi brand names are mentioned in the document, these names have in fact all been changed to Renesas Technology Corp. Thank you for your understanding. Except for our corporate trademark, logo and corporate statement, no changes whatsoever have been made to the contents of the document, and these changes do not constitute any alteration to the contents of the document itself.

Note : Mitsubishi Electric will continue the business operations of high frequency & optical devices and power devices.

Renesas Technology Corp.
Customer Support Dept.
April 1, 2003

MITSUBISHI Nch POWER MOSFET

FK20UM-6


HIGH-SPEED SWITCHING USE

FK20UM-6



- V_{DSS} 300V
- $r_{DS\ (ON)\ (MAX)}$ 0.33Ω
- I_D 20A
- Integrated Fast Recovery Diode (MAX.) 150ns

OUTLINE DRAWING Dimensions in mm



TO-220

APPLICATION

Servo motor drive, Robot, UPS, Inverter Fluorecent lamp, etc.

MAXIMUM RATINGS (T_C = 25°C)

Symbol	Parameter	Conditions	Ratings	Unit
V_{DSS}	Drain-source voltage	V_{GS} = 0V	300	V
V_{GSS}	Gate-source voltage	V_{DS} = 0V	±30	V
I_D	Drain current		20	A
I_{DM}	Drain current (Pulsed)		60	A
I_S	Source current		20	A
I_{SM}	Source current (Pulsed)		60	A
P_D	Maximum power dissipation		150	W
T_{ch}	Channel temperature		–55 ~ +150	°C
T_{stg}	Storage temperature		–55 ~ +150	°C
—	Weight	Typical value	2.0	g


RENESAS
Renesas Technology Corp.

ELECTRICAL CHARACTERISTICS (Tch = 25°C)


Symbol	Parameter	Test conditions	Limits			Unit
			Min.	Typ.	Max.	
$V_{(BR)\ DSS}$	Drain-source breakdown voltage	I_D = 1mA, V_{GS} = 0V	300	—	—	V
$V_{(BR)\ GSS}$	Gate-source breakdown voltage	I_G = ±100µA, V_{DS} = 0V	±30	—	—	V
I_{GSS}	Gate-source leakage current	V_{GS} = ±25V, V_{DS} = 0V	—	—	±10	µA
I_{DSS}	Drain-source leakage current	V_{DS} = 300V, V_{GS} = 0V	—	—	1	mA
$V_{GS\ (th)}$	Gate-source threshold voltage	I_D = 1mA, V_{DS} = 10V	2	3	4	V
$r_{DS\ (ON)}$	Drain-source on-state resistance	I_D = 10A, V_{GS} = 10V	—	0.25	0.33	Ω
$V_{DS\ (ON)}$	Drain-source on-state voltage	I_D = 10A, V_{GS} = 10V	—	2.5	3.3	V
$\lvert y_{fs} \rvert$	Forward transfer admittance	I_D = 10A, V_{DS} = 10V	8.5	13.0	—	S
C_{iss}	Input capacitance	V_{DS} = 25V, V_{GS} = 0V, f = 1MHz	—	1400	—	pF
C_{oss}	Output capacitance		—	280	—	pF
C_{rss}	Reverse transfer capacitance		—	55	—	pF
$t_{d\ (on)}$	Turn-on delay time	V_{DD} = 150V, I_D = 10A, V_{GS} = 10V, R_{GEN} = R_{GS} = 50Ω	—	25	—	ns
t_r	Rise time		—	50	—	ns
$t_{d\ (off)}$	Turn-off delay time		—	150	—	ns
t_f	Fall time		—	65	—	ns
V_{SD}	Source-drain voltage	I_S = 10A, V_{GS} = 0V	—	1.5	2.0	V
$R_{th\ (ch-c)}$	Thermal resistance	Channel to case	—	—	0.83	°C/W
t_{rr}	Reverse recovery time	I_S = 20A, di_S/dt = –100A/µs	—	—	150	ns

PERFORMANCE CURVES

POWER DISSIPATION DERATING CURVE




MAXIMUM SAFE OPERATING AREA




RENESAS
Renesas Technology Corp.


OUTPUT CHARACTERISTICS (TYPICAL)




OUTPUT CHARACTERISTICS (TYPICAL)




ON-STATE VOLTAGE VS. GATE-SOURCE VOLTAGE (TYPICAL)




ON-STATE RESISTANCE VS. DRAIN CURRENT (TYPICAL)



TRANSFER CHARACTERISTICS (TYPICAL)




FORWARD TRANSFER ADMITTANCE VS.DRAIN CURRENT (TYPICAL)




RENESAS
Renesas Technology Corp.


CAPACITANCE VS. DRAIN-SOURCE VOLTAGE (TYPICAL)




SWITCHING CHARACTERISTICS (TYPICAL)




GATE-SOURCE VOLTAGE VS.GATE CHARGE (TYPICAL)




SOURCE-DRAIN DIODE FORWARD CHARACTERISTICS (TYPICAL)



ON-STATE RESISTANCE VS. CHANNEL TEMPERATURE (TYPICAL)




THRESHOLD VOLTAGE VS. CHANNEL TEMPERATURE (TYPICAL)




RENESAS
Renesas Technology Corp.


BREAKDOWN VOLTAGE VS. CHANNEL TEMPERATURE (TYPICAL)




DIODE REVERSE VS. SOURCE CURRENT CHARACTERISTIC (TYPICAL)



DIODE REVERSE VS. SOURCE CURRENT dis/dt CHARACTERISTIC (TYPICAL)



TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS



RENESAS
Renesas Technology Corp.

Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001
Адрес: 105318, г.Москва, ул.Щербаковская д.3, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:
moschip.ru
moschip.ru_4
moschip.ru_6
moschip.ru_9