



Neon Indicator Lamps

Configuration	Part Number	Old Ref. Number	Design Current mA	Maximum Breakdown Voltage	
				VAC	VDC
Wire Terminal-Standard Brightness					
	2ML	NE -38S	0.3	65	90
	A1A	NE -2	0.6	65	90
	A1A-T	NE -2T	0.6	65	90
	A1B		0.3	65	90
	A1D		0.3	65	90
	A1D-T		0.3	65	90
	K4A	AR -9	0.3	80	115
	A2B	NE -2V	0.7	65	90
	A2B-T	NE -2VT	0.7	65	90
	A9A	NE -2E	0.7	65	90
	A9A-T	NE -2E T	0.7	65	90
	A9A-C	NE -2E 1	0.7	65	90
A9A-C T	NE -2E 1T	0.7	65	90	
Wire Terminal-High Brightness					
	1MH	NE -38	1.2	95	135
	A1C		1.2	95	135
	A1C -T		1.2	95	135
	G2B -1		1.2	95	135
	G2B -2		1.4	95	135
	A3C	NE -2U	1.9	95	135
	A3C -T	NE -2UT	1.9	95	135
	C2A	NE -2H	1.9	95	135
	C2A-T	NE -2HT	1.9	95	135
	C2A-C	NE -2H1	1.9	95	135
	D2A		2.6	95	135

Footnotes

1. Life value is to approximately 50% of initial light output. Values shown apply to use on AC unless otherwise shown. Life on DC is approximately 60% of AC values when DC current is equal to RMS AC value. When equal DC and RMS AC voltages and equal resistances are utilized, life will be approximately the same.
2. For DC operation of high brightness lamps use a minimum of 150 circuit volts. Maximum initial breakdown voltage 95 VAC, 135 VDC in light.
3. Tinned leads.
4. High brightness.
5. Formed tip.
6. Dark effect reduced.
7. Lamp drops through a \varnothing .310" cylinder of .500" minimum length.

Neon Indicator Lamps

Series Resistor				Average Useful Life	Dimensions inches			Footnotes
100-125V		220-250V			A(Max.)	B(Max.)	C(Min.)	
Ohms	W	Ohms	W					
Wire Terminal-Standard Brightness								
100K	1/4	220K	1/3	12,000	.156	.395	1.00	1,5
100K	1/4	540K	1/3	25,000	.244	1.00	1.00	1,5
100K	1/4	540K	1/3	25,000	.244	1.00	1.00	1,3,5
220K	1/4	540K	1/3	25,000	.244	.500	1.00	1,5
220K	1/4	540K	1/3	25,000	.244	.500	1.00	1,5,6
220K	1/4	540K	1/3	25,000	.244	.500	1.00	1,3,5,6
220K	1/4	540K	1/3	50	.244	.980	1.00	14
100K	1/4	220K	1/3	25,000	.244	.750	2.00	1,5,6
100K	1/4	220K	1/3	25,000	.244	.750	2.00	1,3,5,6
100K	1/4	220K	1/3	25,000	.244	.750	2.00	1,5
100K	1/4	220K	1/3	25,000	.244	.750	2.00	1,3,5
100K	1/4	220K	1/3	25,000	.244	.750	1.00	1,5
100K	1/4	220K	1/3	25,000	.244	.750	1.00	1,3,5
Wire Terminal-High Brightness								
47K	1/4	150K	1/3	12,000	.156	.395	1.00	1,4,5
47K	1/4	150K	1/3	25,000	.244	.500	1.00	2,4,5,6,8
47K	1/4	150K	1/3	25,000	.244	.500	1.00	2,3,4,5,6,8
47K	1/4	150K	1/3	15,000	.244	.500	1.00	1,4,5,13
39K	1/4	120K	1/3	15,000	.244	.750	1.00	1,4,5,13
30K	1/4	100K	1/3	25,000	.244	.750	2.00	2,4,5,6,8,9
30K	1/4	100K	1/3	25,000	.244	.750	2.00	2,3,4,5,6,8,9
30K	1/4	100K	1/3	25,000	.244	.750	2.00	2,4,5,6,8
30K	1/4	100K	1/3	25,000	.244	.750	2.00	2,3,4,5,6,8
30K	1/4	100K	1/3	25,000	.244	.750	1.00	2,4,5,6,8
22K	1/4	68K	1/3	25,000	.244	.980	1.00	2,4,5,6,8,10

8. Life values shown apply to use on AC unless otherwise shown. End of life occurs when breakdown voltage increases to line voltage and lamp will no longer start. With equal DC and RMS AC current, life will be somewhat lower than the 60% value quoted for standard brightness lamp.
9. Maximum breakdown voltage in total darkness 100VAC.
10. Minimum current for stable operation 1.5mA.
11. Resistor included in Base.
12. Caution: Bulb may shatter and/or circuit may be damaged without external series resistance.
13. Green fluorescent.
14. Argon gas filled.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9