

G3VM-41PR□/51PR

MOS FET Relays USOP, Low-output-capacitance and Low-ON-resistance Type (with Low C × R)

USOP Package with Low Output Capacitance and ON Resistance

- Load voltage: 40 V or 50 V
- G3VM-41PR12: Low $C \times R = 4.5 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 0.3 pF, R_{ON} (standard) = 15 Ω
- G3VM-41PR6: Low $C \times R = 10 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 1 pF, R_{ON} (standard) = 10 Ω
- G3VM-41PR10: Low $C \times R = 5.4 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 0.45 pF, R_{ON} (standard) = 12 Ω
- G3VM-41PR11: Low $C \times R = 4.9 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 0.7 pF, R_{ON} (standard) = 7 Ω
- G3VM-41PR5: Low $C \times R = 10 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 10 pF, R_{ON} (standard) = 1 Ω
- G3VM-51PR: Low $C \times R = 12 \text{ pF}\cdot\Omega$, C_{OFF} (standard) = 12 pF, R_{ON} (standard) = 1 Ω



NEW

Note: The actual product is marked differently from the image shown here.


RoHS Compliant

Application Examples

- | | |
|--------------------------------|---------------------------|
| • Semiconductor test equipment | • Communication equipment |
| • Test & measurement equipment | • Data loggers |

■ Package (Unit : mm, Average)

USOP 4-pin



Note: The actual product is marked differently from the image shown here.

■ Model Number Legend

G3VM-□ □ □ □ □
1 2 3 4 5

1. Load Voltage

- 4: 40 V
5: 50 V

2. Contact form

- 1: 1a (SPST-NO)

3. Package

- P: USOP 4-pin

4. Additional functions

- R: Low On-resistance

5. Other informations

When specifications overlap, serial code is added in the recorded order.

■ Ordering Information

Package	Contact form	Terminals	Load voltage (peak value) *	Continuous load current (peak value) *	Tape cut packaging		Tape packaging	
					Model	Minimum package quantity	Model	Minimum package quantity
USOP4	1a (SPST-NO)	Surface-mounting Terminals	40 V	100 mA	G3VM-41PR12	1 pc.	G3VM-41PR12(TR05)	500 pcs.
				120 mA	G3VM-41PR6		G3VM-41PR6(TR05)	
				140 mA	G3VM-41PR10		G3VM-41PR10(TR05)	
				300 mA	G3VM-41PR11		G3VM-41PR11(TR05)	
				300 mA	G3VM-41PR5		G3VM-41PR5(TR05)	
			50 V	300 mA	G3VM-51PR		G3VM-51PR(TR05)	

Note: To order tape packaging for Relays with surface-mounting terminals, add "(TR05)" to the end of the model number.

Tape-cut USOPs are packaged without humidity resistance. Use manual soldering to mount them.

Refer to common precautions.

* The AC peak and DC value are given for the load voltage and continuous load current.

Absolute Maximum Ratings ($T_a = 25^\circ\text{C}$)


Item	Symbol	G3VM-41PR12	G3VM-41PR6	G3VM-41PR10	G3VM-41PR11	G3VM-41PR5	G3VM-51PR	Unit	Measurement conditions
Input/Output	LED forward current	I _F		50				mA	
	LED forward current reduction rate	$\Delta I_F/\text{°C}$		-0.5				mA/°C	$T_a \geq 25^\circ\text{C}$
	LED reverse voltage	V _R		5				V	
	Connection temperature	T _J		125				°C	
	Load voltage (AC peak/DC)	V _{OFF}		40		50		V	
	Continuous load current (AC peak/DC)	I _O	100	120	140	300		mA	
	ON current reduction rate	$\Delta I_O/\text{°C}$	-1.0	-1.2	-1.4	-3		mA/°C	$T_a \geq 25^\circ\text{C}$
	Pulse ON current	I _{OP}	300	360	420	900		mA	t=100 ms, Duty=1/10
	Connection temperature	T _J		125				°C	
	Dielectric strength between I/O (See note 1.)	V _{i-o}		500				Vrms	AC for 1 min
	Ambient operating temperature	T _a		-40 to +85				°C	
	Ambient storage temperature	T _{STG}		-40 to +125				°C	With no icing or condensation
	Soldering temperature	-		260				°C	10 s

Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.


Electrical Characteristics ($T_a = 25^\circ\text{C}$)

Item	Symbol	G3VM-41PR12	G3VM-41PR6	G3VM-41PR10	G3VM-41PR11	G3VM-41PR5	G3VM-51PR	Unit	Measurement conditions	
Input	LED forward voltage	V _F	Minimum	1.0				V	I _F =10 mA	
			Typical	1.15						
			Maximum	1.3						
	Reverse current	I _R	Maximum		10			μA	V _R =5 V	
	Capacitance between terminals	C _T	Typical		15			pF	V=0, f=1 MHz	
	Trigger LED forward current	I _{FT}	Typical	1.0	0.6	0.5	1.0	0.6	0.5	
			Maximum			3			mA	
	Release LED forward current	I _{FR}	Minimum		0.1		0.2	mA	I _{OFF} =10 μA	
	Maximum resistance with output ON	R _{ON}	Typical	15	10	12	7	1	Ω	
			Maximum	20	15	14	10	1.5		
Output	Current leakage when the relay is open	I _{LEAK}	Maximum	1	0.2		1	nA	V _{OFF} =Load voltage ratings	
	Capacitance between terminals	C _{OFF}	Typical	0.3	1	0.45	0.7	10	pF	
			Maximum	0.6	2	0.8	1.3	14	V=0, f=100 MHz, t<1 s	
	Capacitance between I/O terminals	C _{i-o}	Typical		0.4			pF	f=1 MHz, Vs=0 V	
	Insulation resistance between I/O terminals	R _{i-o}	Minimum		1000			MΩ	V _{i-o} =500 VDC, RoHs=60%	
			Typical		10 ⁸					
	Turn-ON time	t _{ON}	Typical	0.04	0.05	0.03	0.04	0.2	ms	I _F =5 mA, R _L =200 Ω, V _D =20 V (See note 2.)
			Maximum			0.2		0.5		
	Turn-OFF time	t _{OFF}	Typical	0.12	0.16	0.2	0.14	0.2		
			Maximum	0.2		0.3	0.2	0.3		
	Equivalent rise time	ERT	Typical			—		40	ps	I _F =5 mA, V _D =0.25 V, Tr(10%)=25 ps (See Note 3)
			Maximum			—		90		

Note: 2. Turn-ON and Turn-OFF Times






Note: 3. Equivalent Rise Time




For usage with high reliability, Recommended Operation Conditions is a measure that takes into account the derating of Absolute Maximum Ratings and Electrical Characteristics.

Each item on this list is an independent condition, so it is not simultaneously satisfy several conditions.



Item	Symbol	G3VM-41PR12	G3VM-41PR6	G3VM-41PR10	G3VM-41PR11	G3VM-41PR5	G3VM-51PR	Unit
Load voltage (AC peak/DC)	V _D	Maximum		32			40	V
Operating LED forward current	I _F	Minimum		5				mA
		Typical		7.5				
		Maximum		20				
Continuous load current (AC peak/DC)	I _O	Maximum	100	120	140	300		
Ambient operating temperature	T _a	Minimum		—				°C
		Maximum		65				

■Engineering Data**● LED forward current vs.
Ambient temperature****● Continuous load current vs.
Ambient temperature****● LED forward current vs.
LED forward voltage****● Continuous load current vs.
On-state voltage**


G3VM-41PR6/41PR5




G3VM-41PR12/41PR10/41PR11/51PR

**● On-state resistance vs.
Ambient temperature****● Trigger LED forward current vs.
Ambient temperature**

G3VM-41PR6/41PR5




G3VM-41PR12/41PR10/41PR11/51PR


**● Turn ON, Turn OFF time vs.**

LED forward current


G3VM-41PR6/41PR5



G3VM-41PR12/41PR10/41PR11



G3VM-51PR




G3VM-41PR□/51PR

MOS FET Relays


Engineering Data

● Turn ON, Turn OFF time vs.


Ambient temperature




G3VM-41PR12/41PR10/41PR11



G3VM-51PR




● Output terminal capacitance vs. Load voltage




● Current leakage vs. Load voltage

G3VM-41PR6/41PR5




G3VM-41PR12/41PR10/41PR11/51PR



■Appearance / Terminal Arrangement / Internal Connections**●Appearance****USOP (Ultra Small Outline Package)**

USOP 4-pin




* Actual model name marking for each model


Model	Marking
G3VM-41PR12	4PC
G3VM-41PR6	4P6
G3VM-41PR10	4PA
G3VM-41PR11	4PB
G3VM-41PR5	4P5
G3VM-51PR	5P0

Note: 1. The actual product is marked differently from the image shown here.

Note: 2. "G3VM" does not appear in the model number on the Relay.

**●Terminal Arrangement/Internal Connections
(Top View)****■Dimensions (Unit: mm)****Surface-mounting Terminals**


Weight: 0.03 g



Unless otherwise specified, the dimensional tolerance is ± 0.2 mm.

Actual Mounting Pad Dimensions

(Recommended Value, Top View)



Unless otherwise specified, the dimensional tolerance is ± 0.2 mm.

Note: The actual product is marked differently from the image shown here.

■Approved Standards

UL recognized

Approved Standards	Contact form	File No.
UL recognized	1a (SPST-NO)	E80555

■Safety Precautions

- Refer to the *Common Precautions for All MOS FET Relays* for precautions that apply to all MOS FET Relays.

Данный компонент на территории Российской Федерации**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибуторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ Р В 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru
moschip.ru_4

moschip.ru_6
moschip.ru_9