

### Features


- Operating voltage: 4.4V~5.25V
- Complete Universal Serial Bus specs V1.1 compatibility
- Serial Bus Interface Engine (SIE)
- USB transceiver
- Microsoft 3D Intelli mouse and IBM PS/2 mouse compatible
- Supports three buttons (R, M, L) and three axes (X, Y, Z) input
- Z axis can only support encoder which divided by 2
- Single chip solution especially for USB mouse function
- HALT function and wake-up feature reduce power consumption
- Plug and Play functions
- Minimal external components
- 6MHz crystal oscillator for system clock
- 18/20-pin DIP package

### General Description


HT82M98A is a 3D mouse controller especially designed for USB and PS/2 applications. The HT82M98A can support the USB Standard Request as well as HID Class Request version 1.1. It is compatible with Microsoft Intelli 3D PS/2 mouse. The X/Y axis photo input with built-in Holtek's special dynamic photo-input resistor and Z axis can support two kinds of scroller input,

namely; optomechanical and mechanical. It requires minimal external components to implement 3D USB plus PS/2 mouse. It can be briefly described as a Holtek 8-bit MCU with an on-chip USB interface logic. The USB is specified by the *Universal Serial Bus Specification V1.1*.

### Block Diagram



## Pin Assignment



## Pin Description

| Pin Name                      | I/O | Description                                                                                                |
|-------------------------------|-----|------------------------------------------------------------------------------------------------------------|
| USB Interface (2 pins)        |     |                                                                                                            |
| USB+/CLK                      | I/O | USB data plus or PS2 Clock, F/W auto-detect USB+ for USB, CLK for PS2                                      |
| USB-/DATA                     | I/O | USB data minus or PS2 Data, F/W auto-detect USB- for USB, DATA for PS2                                     |
| General purpose I/O (11 pins) |     |                                                                                                            |
| X1, X2                        | I   | X-axis photo input with built-in Holtek's special dynamic photo input resistor                             |
| Y1, Y2                        | I   | Y-axis photo input with built-in Holtek's special dynamic photo input resistor                             |
| Z1, Z2                        | I   | Z-axis input supports two kinds of scroller input; optomechanical and mechanical                           |
| L, R, M                       | I   | Input ports with pull-high resistor. These pads can function as Left, Right and Middle button input lines. |
| SEL0*                         | I   | SEL0=1: 400DPI (default)                                                                                   |
| SEL1*                         | I   | SEL0=0: 800DIP                                                                                             |
|                               |     | SEL1=1: USB and PS2 combo (default)                                                                        |
|                               |     | SEL1=0: USB only                                                                                           |
| Miscellaneous (7 pins)        |     |                                                                                                            |
| VSS                           | —   | Negative power supply, ground                                                                              |
| V33O                          | O   | 3.3V voltage output                                                                                        |
| RESET                         | I   | Chip reset input, low active                                                                               |
| LED                           | I/O | Drives LED output                                                                                          |
| VDD                           | —   | 5V positive power supply                                                                                   |
| OSC2                          | O   | 6MHz OSC output                                                                                            |
| OSC1                          | I   | 6MHz OSC input                                                                                             |

Note: "\*" These functions are only available on date code '-4' version

## Absolute Maximum Ratings

|                         |                                 |                            |                                  |
|-------------------------|---------------------------------|----------------------------|----------------------------------|
| Supply Voltage .....    | $V_{SS}-0.3V$ to $V_{SS}+6V$    | Storage Temperature .....  | $-50^{\circ}C$ to $125^{\circ}C$ |
| MCU Input Voltage.....  | $V_{SS}-0.3V$ to $V_{DD}+0.3V$  | Operating Temperature..... | $-25^{\circ}C$ to $70^{\circ}C$  |
| USB Input Voltage ..... | $V_{SS}-0.3V$ to $V_{33O}+0.3V$ |                            |                                  |

Note: These are stress ratings only. Stresses exceeding the range specified under "Absolute Maximum Ratings" may cause substantial damage to the device. Functional operation of this device at other conditions beyond those listed in the specification is not implied and prolonged exposure to extreme conditions may affect device reliability.

**D.C. Characteristics**


Ta=25°C

| Symbol           | Parameter                                        | Test Conditions |                                 | Min. | Typ. | Max. | Unit |
|------------------|--------------------------------------------------|-----------------|---------------------------------|------|------|------|------|
|                  |                                                  | V <sub>DD</sub> | Conditions                      |      |      |      |      |
| V <sub>DD</sub>  | Operating Voltage                                | —               | —                               | 4.4  | —    | 5.25 | V    |
| I <sub>DD</sub>  | Operating Current (Crystal OSC)                  | 5V              | No load, f <sub>SYS</sub> =6MHz | —    | 10   | —    | mA   |
|                  |                                                  |                 | USB mode                        | —    | 3    | —    | mA   |
|                  |                                                  |                 | PS/2 mode                       | —    | 3    | —    | mA   |
| I <sub>STB</sub> | Standby Current                                  | 5V              | No load, system HALT            | —    | —    | 250  | μA   |
| V <sub>IL1</sub> | Input Low Voltage for I/O Ports                  | 5V              | —                               | 0    | —    | 1.0  | V    |
| V <sub>IH1</sub> | Input High Voltage for MCU I/O Ports             | 5V              | —                               | 3.5  | —    | 5    | V    |
| V <sub>IL2</sub> | Input Low Voltage (RESET)                        | 5V              | —                               | 0    | —    | 1.5  | V    |
| V <sub>IH2</sub> | Input High Voltage (RESET)                       | 5V              | —                               | 3.5  | —    | 5    | V    |
| V <sub>IH3</sub> | Input High Voltage for USB I/O Ports             | 3.3V            | —                               | 2.8  | —    | 3.6  | V    |
| V <sub>POR</sub> | Power on Reset V <sub>DD</sub> Detection Voltage | 5V              | —                               | 3.5  | —    | 3.9  | V    |
| I <sub>OL1</sub> | Output Port Sink Current                         | 5V              | V <sub>OL</sub> =0.5V           | —    | 4    | —    | mA   |
| I <sub>OH1</sub> | Output Port Source Current                       | 5V              | V <sub>OL</sub> =4.5V           | —    | -4   | —    | mA   |
| I <sub>OL2</sub> | Output Port Sink Current (LED)                   | 5V              | V <sub>OL</sub> =4.5V           | —    | 50   | —    | mA   |
| R <sub>PH</sub>  | Pull-high Resistance for RESET                   | 5V              | —                               | 50   | 100  | 150  | kΩ   |


**A.C. Characteristics**

Ta=25°C

| Symbol           | Parameter                         | Test Conditions |                               | Min. | Typ. | Max. | Unit             |
|------------------|-----------------------------------|-----------------|-------------------------------|------|------|------|------------------|
|                  |                                   | V <sub>DD</sub> | Conditions                    |      |      |      |                  |
| f <sub>SYS</sub> | System Clock (Crystal OSC)        | 5V              | —                             | 0    | 6000 | —    | kHz              |
| t <sub>OST</sub> | Oscillation Start-up Timer Period | —               | Power-up or wake-up form HALT | —    | 1024 | —    | t <sub>SYS</sub> |



Note: t<sub>SYS</sub>=1/f<sub>SYS</sub>
**Timing Diagram**
**X, Y Axis Photo-Coupler Crossed Width**


Note: For X, Y-axis tr, tp, tr > 30μs  
For Z-axis tr, tp, tr > 2.5ms

**X, Y, Z Axis Counting**


## Application Circuits

This Application Circuit is for Reference Only




Note: Layout 0.1μF capacitor, 22Ω resistor and 0.01μF capacitor as close to VDD pin as possible.

Layout power plane and ground plane as large as possible.


Place 0.1μF capacitor as close to RESET pin as possible.

Place 6MHz crystal as close to OSC1 and OSC2 pins as possible.

Components with \* are used for EMC issue.

**Package Information**
**18-pin DIP (300mil) Outline Dimensions**


| Symbol   | Dimensions in mil |      |      |
|----------|-------------------|------|------|
|          | Min.              | Nom. | Max. |
| A        | 895               | —    | 915  |
| B        | 240               | —    | 260  |
| C        | 125               | —    | 135  |
| D        | 125               | —    | 145  |
| E        | 16                | —    | 20   |
| F        | 50                | —    | 70   |
| G        | —                 | 100  | —    |
| H        | 295               | —    | 315  |
| I        | 335               | —    | 375  |
| $\alpha$ | 0°                | —    | 15°  |

**20-pin DIP (300mil) Outline Dimensions**


| Symbol   | Dimensions in mil |      |      |
|----------|-------------------|------|------|
|          | Min.              | Nom. | Max. |
| A        | 1020              | —    | 1045 |
| B        | 240               | —    | 260  |
| C        | 125               | —    | 135  |
| D        | 125               | —    | 145  |
| E        | 16                | —    | 20   |
| F        | 50                | —    | 70   |
| G        | —                 | 100  | —    |
| H        | 295               | —    | 315  |
| I        | 335               | —    | 375  |
| $\alpha$ | 0°                | —    | 15°  |

**Holtek Semiconductor Inc. (Headquarters)**

No.3, Creation Rd. II, Science Park, Hsinchu, Taiwan  
Tel: 886-3-563-1999  
Fax: 886-3-563-1189  
<http://www.holtek.com.tw>

**Holtek Semiconductor Inc. (Taipei Sales Office)**

4F-2, No. 3-2, YuanQu St., Nankang Software Park, Taipei 115, Taiwan  
Tel: 886-2-2655-7070  
Fax: 886-2-2655-7373  
Fax: 886-2-2655-7383 (International sales hotline)

**Holtek Semiconductor Inc. (Shanghai Sales Office)**

7th Floor, Building 2, No.889, Yi Shan Rd., Shanghai, China 200233  
Tel: 021-6485-5560  
Fax: 021-6485-0313  
<http://www.holtek.com.cn>

**Holtek Semiconductor Inc. (Shenzhen Sales Office)**

5/F, Unit A, Productivity Building, Cross of Science M 3rd Road and Gaoxin M 2nd Road, Science Park, Nanshan District, Shenzhen, China 518057  
Tel: 0755-8616-9908, 8616-9308  
Fax: 0755-8616-9533

**Holtek Semiconductor Inc. (Beijing Sales Office)**

Suite 1721, Jinyu Tower, A129 West Xuan Wu Men Street, Xicheng District, Beijing, China 100031  
Tel: 010-6641-0030, 6641-7751, 6641-7752  
Fax: 010-6641-0125

**Holtek Semiconductor Inc. (Chengdu Sales Office)**

709, Building 3, Champagne Plaza, No.97 Dongda Street, Chengdu, Sichuan, China 610016  
Tel: 028-6653-6590  
Fax: 028-6653-6591

**Holmate Semiconductor, Inc. (North America Sales Office)**

46729 Fremont Blvd., Fremont, CA 94538  
Tel: 510-252-9880  
Fax: 510-252-9885  
<http://www.holmate.com>

Copyright © 2006 by HOLTEK SEMICONDUCTOR INC.

The information appearing in this Data Sheet is believed to be accurate at the time of publication. However, Holtek assumes no responsibility arising from the use of the specifications described. The applications mentioned herein are used solely for the purpose of illustration and Holtek makes no warranty or representation that such applications will be suitable without further modification, nor recommends the use of its products for application that may present a risk to human life due to malfunction or otherwise. Holtek's products are not authorized for use as critical components in life support devices or systems. Holtek reserves the right to alter its products without prior notification. For the most up-to-date information, please visit our web site at <http://www.holtek.com.tw>.

## Данный компонент на территории Российской Федерации

**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9