



Main

Range	TeSys
Device short name	LUF
Product or component type	Function module
Product compatibility	LUCB LUCC LUCD

Complementary

Mounting mode	Plug-in
Mounting location	Front side
Function available	Thermal overload signalling and automatic or remote reset
Auxiliary contact composition	1 NO
Communication of faults	LED front panel
[Us] rated supply voltage	24...240 V AC 24...240 V DC
Current consumption	7 mA at 24 V DC 1.1 mA at 240 V AC
Discrete output function	1 NO (AC-15) at 230 V - power: 400 VA - electrical service life: 100000 cycles 1 NO (DC-13) at 24 V - power: 50 W - electrical service life: 100000 cycles
[Ith] conventional free air thermal current	2 A at ≤ 158 °F (70 °C)
Short-circuit protection	2 A fuse gG conforming to IEC 60947-5-1
Input type	Remote reset - cable cross section: 0.2...1.5 mm ² 500 m - relative impedance: 50 Ohm 52.8 mH - cable capacitance: 0.093 nF
Connection pitch	0.2 in (5.08 mm)
Connections - terminals	Screw clamp terminals 2 cable 0...0 in ² (0.2...1 mm ²) - cable stiffness: rigid - without cable end Screw clamp terminals 2 cable 0...0 in ² (0.25...1 mm ²) - cable stiffness: flexible - with cable end Screw clamp terminals 2 cable 0...0 in ² (0.5...1 mm ²) - cable stiffness: flexible - with cable end 2 cable 0...0 in ² (0.2...1 mm ²) - cable stiffness: flexible - without cable end
Associated cable type	
Tightening torque	4.42...5.31 lbf.in (0.5...0.6 N.m) - with screwdriver 0.14 in (3.5 mm) flat
Product weight	0.12 lb(US) (0.055 kg)

Environment

Offer Sustainability

WARNING: This product can expose you to chemicals including:	WARNING: This product can expose you to chemicals including:
Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.	Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm.
For more information go to www.p65warnings.ca.gov	For more information go to www.p65warnings.ca.gov

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9