

# Slide Potentiometer

Model PSxxM / PSxxL



## Features:

- Molded element
- 100,000 cycle life
- Metal or plastic shaft options
- With/without LED illumination
- With/without dust cover
- RoHS compliant

## Model Styles Available

|                       |       |
|-----------------------|-------|
| Dual Gang Without LED | PSxxM |
| Single Gang With LED  | PSxxL |

## Electrical

|   |   |
|---|---|
| Resistance Range, Ohms                        | 500 -1M   |
| Standard Resistance Tolerance                 | ± 20%   |
| Resistance Tapers                             | A,B,C   |
| Residual Resistance                           | Terminals 1 to 2: Less than 10 ohms<br>Terminals 2 to 3: Less than 30 ohms  |
| Input Voltage, Maximum                        | Linear B taper: 200 Vac    Other tapers: 150 Vac  |
| Power rating, Watts (Single Unit / Dual Unit) | <b>Linear B taper:</b> 20mm: 0.1W / 0.05W, 30mm: 0.2W / 0.1W<br>45mm: 0.25W / 0.125W, 60mm: 0.2W / 0.2W<br><b>Other tapers:</b> 20mm: 0.05W / 0.025W, 30mm: 0.1W / 0.05W<br>45mm: 0.125W / 0.06W, 60mm: 0.1W / 0.1W |
| Dielectric Strength                           | 300Vac, 1 minute  |
| Insulation Resistance, Minimum                | 10M ohms at 250Vdc/ 1 minute  |
| Sliding Noise                                 | Less than 100mV   |
| Gang Error                                    | ±3dB (-40dB to 0dB)   |

## Mechanical

|                               |               |
|-------------------------------|---------------|
| Static Stop Strength, Minimum | 5.0 Kg/cm     |
| Operating Force               | 10gf to 100gf |
| Detent Slip-out force         | 30gf to 200gf |

## Durability

|              |                |
|--------------|----------------|
| Sliding Life | 100,000 cycles |
|--------------|----------------|

### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
www.ttelectronics.com | sensors@ttelectronics.com

# Slide Potentiometer

Model PSxxM / PSxxL



## Ordering

### Model PSxxM (Without LED)



### Model PSxxL (With LED)



### Standard Resistance Values, ohms

|     |    |    |    |     |     |     |      |      |      |       |
|-----|----|----|----|-----|-----|-----|------|------|------|-------|
| 500 | 1K | 2K | 5K | 10K | 20K | 50K | 100K | 200K | 500K | 1 MEG |
|-----|----|----|----|-----|-----|-----|------|------|------|-------|

**General Note**

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
www.ttelectronics.com | sensors@ttelectronics.com

# Slide Potentiometer

Model PSxxM / PSxxL



## Tapers

For Dual Gang units ONLY, the Standard Taper is a 3B taper  
If Linear Taper is desired, use "L" taper option



### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
www.ttelectronics.com | sensors@ttelectronics.com

# Slide Potentiometer

Model PSxxM / PSxxL



## Outline Drawings

### Plastic Lever Types (For PSxxM Only)

| E-Type |     | B-Type |    | C-Type |       | D-Type |          |  |
|--------|-----|--------|----|--------|-------|--------|----------|--|
|        |     |        |    |        |       |        |          |  |
| L      | 5.0 | L      | 15 | L      | 10 15 | L      | 10 15 20 |  |
| CODE   | 1   | CODE   | 1  | CODE   | 1 2   | CODE   | 1 2 3    |  |

**Dust Cover option not offered for levers less than 10 mm in length**

### Metal Lever Types (For PSxxM Only)

| D-Type |    |    |    | C-Type |   |    |    | E-Type |      |   |
|--------|----|----|----|--------|---|----|----|--------|------|---|
|        |    |    |    |        |   |    |    |        |      |   |
| L      | 15 | 20 | 25 | F      | 5 | 10 | 10 | L      | 7.6  |   |
| CODE   | 1  | 2  | 3  | CODE   | 1 | 2  | 3  | 4      | CODE | 1 |

**\* Dust Cover option not offered for levers less than 10 mm in length**

#### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
www.ttelectronics.com | sensors@ttelectronics.com

# Slide Potentiometer

Model PSxxM / PSxxL



## Outline Drawings

### Model PSxxM (Without LED)



### For PSxxM and PSxxL

| MODEL       | A  | B  | C  | D  | F    | G    |
|-------------|----|----|----|----|------|------|
| PS20M PS20L | 35 | 31 | 20 | 30 | 5    | 12.5 |
| PS30M PS30L | 45 | 41 | 30 | 40 | 10   | 22.5 |
| PS45M PS45L | 60 | 56 | 45 | 55 | 15   | 32.5 |
| PS60M PS60L | 75 | 71 | 60 | 70 | 22.5 | 47.5 |

#### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
 4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
 www.ttelectronics.com | sensors@ttelectronics.com

# Slide Potentiometer

Model PSxxM / PSxxL



## Outline Drawings

### Model PSxxL (With LED)

#### With Dust Cover



#### Without Dust Cover



|      |    |    |
|------|----|----|
| L    | 15 | 19 |
| CODE | 1  | 2  |



FRAME OPTION (F)



### PSxxL (Single gang with LED)



### PSxxM (Dual gang)



#### General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | BI Technologies  
4200 Bonita Place, Fullerton, CA USA 92835 | Ph: +1 714 447 2345  
www.ttelectronics.com | sensors@ttelectronics.com

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9