

## 101/102/105/107/109/121/125/127/129 Series Rivet/Eyelet Mount Fuse Clips for 1/4" - 13/16" Dia. Fuses RoHS



### Product Dimensions

**Earless Clip Type**  
(without fuse stops)



**Ear Clip Type**  
(with fuse stops)



**Straight Solder Lug Type**



**45° Angle Solder Lug Type**



| Catalog No.                          | Fuse Diameter | A      | B     | C    | D    | H Diameter |
|--------------------------------------|---------------|--------|-------|------|------|------------|
| 101001<br>101002<br>121001<br>121002 | 1/4"          | .48"   | .31"  | .30" | .16" | .131"      |
| 101003<br>121004                     |               |        |       |      |      |            |
| 102064                               |               | .47"   | NA    | .31" | .15" |            |
| 105001<br>105002<br>125001<br>125002 |               | 13/32" | .75"  | .44" | .52" |            |
| 107002<br>127001<br>127002           | 9/16"         |        |       |      |      | .94"       |
| 109001<br>109002<br>129001<br>129002 |               | 13/16" | 1.31" | .75" | .88" |            |

### Product Characteristics

|                      | 101/102/121 Series | 105/125 Series   | 107/127 Series  | 109/129 Series   |
|----------------------|--------------------|------------------|-----------------|------------------|
| Compatible Fuse Size | 1/4" Dia Fuses     | 13/32" Dia Fuses | 9/16" Dia Fuses | 13/16" Dia Fuses |

### Additional Information



**Datasheet**  
101 Series



**Resources**  
101 Series



**Samples**  
101 Series



**Datasheet**  
102 Series



**Resources**  
102 Series



**Samples**  
102 Series



**Datasheet**  
121 Series



**Resources**  
121 Series



**Samples**  
121 Series



**Datasheet**  
105 Series



**Resources**  
105 Series



**Samples**  
105 Series



**Datasheet**  
125 Series



**Resources**  
125 Series



**Samples**  
125 Series



**Datasheet**  
107 Series



**Resources**  
107 Series



**Samples**  
107 Series



**Datasheet**  
127 Series



**Resources**  
127 Series



**Samples**  
127 Series



**Datasheet**  
109 Series



**Resources**  
109 Series



**Samples**  
109 Series



**Datasheet**  
129 Series



**Resources**  
129 Series



**Samples**  
129 Series

## Ordering Information

| Ordering PN* | Catalog PN | Material         | Plating       | Style                   | Current Level | Packaging |
|--------------|------------|------------------|---------------|-------------------------|---------------|-----------|
| 0101 0001    | 101 001    | Spring Brass     | Nickel-plated | Ear                     | 15A max       | Z         |
| 0121 0001    | 121 001    | Beryllium Copper | Silver-plated | Ear                     | 30A max       | Z         |
| 0105 0001    | 105 001    | Spring Brass     | Nickel-plated | Ear                     | 15A max       | Z         |
| 0125 0001    | 125 001    | Beryllium Copper | Silver-plated | Ear                     | 30A max       | Z         |
| 0127 0001    | 127 001    | Beryllium Copper | Silver-plated | Ear                     | 30A max       | Z         |
| 0109 0001    | 109 001    | Phos. Bronze     | Nickel-plated | Ear                     | 60A max       | H or Z    |
| 0129 0001    | 129 001    | Beryllium Copper | Silver-plated | Ear                     | 30A max       | H or Z    |
| 0101 0002    | 101 002    | Spring Brass     | Nickel-plated | Earless                 | 15A max       | Z         |
| 0121 0002    | 121 002    | Beryllium Copper | Silver-plated | Earless                 | 30A max       | Z         |
| 0105 0002    | 105 002    | Spring Brass     | Nickel-plated | Earless                 | 15A max       | Z         |
| 0125 0002    | 125 002    | Beryllium Copper | Silver-plated | Earless                 | 30A max       | Z         |
| 0107 0002    | 107 002    | Spring Brass     | Nickel-plated | Earless                 | 30A max       | Z         |
| 0127 0002    | 127 002    | Beryllium Copper | Silver-plated | Earless                 | 30A max       | H or Z    |
| 0109 0002    | 109 002    | Phos. Bronze     | Nickel-plated | Earless                 | 60A max       | H or Z    |
| 0129 0002    | 129 002    | Beryllium Copper | Silver-plated | Earless                 | 30A max       | H or Z    |
| 0101 0003    | 101 003    | Spring Brass     | Tin-plated    | Ear- Solder Lug 45*     | 15A max       | Z         |
| 0121 0004    | 121 004    | Beryllium Copper | Silver-plated | Ear- Solder Lug 45*     | 30A max       | H or Z    |
| 0102 0064    | 102 064    | Spring Brass     | Tin-plated    | Ear-Solder Lug Straight | 15A max       | H or Z    |

### Add Suffix to the Ordering PN for Packaging

"H" =std. package 100 pcs per pack

"Z" =for bulk package

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9