

# E6A2-C

## Compact Encoder (External Diameter: 25 mm)

- Models with origin output (phase Z) for positioning applications.
- Resolution of 500 ppr in an Encoder with an external diameter of only 25 mm.



 Be sure to read *Safety Precautions* on page 3.

### Ordering Information

**Encoders** [Refer to *Dimensions* on page 4.]

| Output phases         | Power supply voltage  | Output configuration  | Resolution (pulses/rotation)   | Model   |
|-----------------------|-----------------------|-----------------------|--|---|
| Phase A               | 5 to 12 VDC           | Voltage output        | 10, 20, 60, 100, 200, 300, 360<br>500                                  | <b>E6A2-CS3E (resolution) 0.5M</b><br>Example: E6A2-CS3E 10P/R 0.5M |
|                       |                       | Open-collector output | 10, 20, 60, 100, 200, 300, 360<br>500                                  | <b>E6A2-CS3C (resolution) 0.5M</b><br>Example: E6A2-CS3C 10P/R 0.5M |
|                       | 12 to 24 VDC          |                       | Open-collector output  | 10, 20, 60, 100, 200, 300, 360<br>500                               |
|                       |                       | Phases A and B        |  | 5 to 12 VDC   |
| Open-collector output | 100, 200, 360<br>500  |                       | <b>E6A2-CW3C (resolution) 0.5M</b><br>Example: E6A2-CW3C 100P/R 0.5M   |   |
|                       | 12 to 24 VDC          |                       | Open-collector output  | 100, 200, 360<br>500  |
| Phases A, B, and Z    |                       |                       |  | 5 to 12 VDC   |
|                       | Open-collector output | 100, 200, 360<br>500  | <b>E6A2-CWZ3C (resolution) 0.5M</b><br>Example: E6A2-CWZ3C 100P/R 0.5M |   |
|                       |                       | 12 to 24 VDC          | Open-collector output  | 100, 200, 360<br>500  |
|                       |                       |                       |  |   |

**Accessories (Order Separately)** [Refer to *Dimensions* on *Rotary Encoder Accessories*.]

| Name                   | Model           | Remarks                      |
|------------------------|-----------------|------------------------------|
| Coupling               | <b>E69-C04B</b> | Provided with the product.   |
| Servo Mounting Bracket | <b>E69-1</b>    | Provided with the E6A2-CWZ□. |

Refer to *Accessories* for details.

## Ratings and Specifications

| Item                             | Model  | E6A2-CS3E   | E6A2-CS3C  | E6A2-CS5C   | E6A2-CW3E   | E6A2-CW3C  | E6A2-CW5C   | E6A2-CWZ3E  | E6A2-CWZ3C   | E6A2-CWZ5C  |
|----------------------------------|--------|---|--|---|---|--|---|---|--|---|
| Power supply voltage             |        | 5 VDC -5% to 12 V +10%, ripple (p-p): 5% max.   |  | 12 VDC -10% to 24 VDC +15%, ripple (p-p): 5% max. | 5 VDC -5% to 12 V +10%, ripple (p-p): 5% max.   |  | 12 VDC -10% to 24 VDC +15%, ripple (p-p): 5% max. | 5 VDC -5% to 12 V +10% ripple (p-p): 5% max.  |  | 12 VDC -10% to 24 VDC +15%, ripple (p-p): 5% max. |
| Current consumption*1            |        | 30 mA max.  | 20 mA max.   |   | 30 mA max.  | 20 mA max.   |   | 50 mA max.  | 30 mA max.   |   |
| Resolution (pulses/rotation)     |        | 10, 20, 60, 100, 200, 300, 360, 500   |  |   | 100, 200, 360, 500  |  |   |   |  |   |
| Output phases                    |        | Phase A   |  |   | Phases A and B  |  |   | Phases A, B, and Z  |  |   |
| Output configuration             |        | Voltage output  | Open-collector output  |   | Voltage output  | Open-collector output  |   | Voltage output  | Open-collector output  |   |
| Output capacity                  |        | Output resistance: 2 kΩ<br>Output current: 20 mA max.<br>Residual voltage: 0.4 V max.<br>(Output current: 20 mA max.) | Applied voltage: 30 VDC max.<br>Sink current: 30 mA max.<br>Residual voltage: 0.4 V max.<br>(at sink current of 30 mA) |   | Output resistance: 2 kΩ<br>Output current: 20 mA max.<br>Residual voltage: 0.4 V max.<br>(Output current: 20 mA max.) | Applied voltage: 30 VDC max.<br>Sink current: 30 mA max.<br>Residual voltage: 0.4 V max.<br>(at sink current of 30 mA) |   | Output resistance: 2 kΩ<br>Output current: 20 mA max.<br>Residual voltage: 0.4 V max.<br>(Output current: 20 mA max.) | Applied voltage: 30 VDC max.<br>Sink current: 30 mA max.<br>Residual voltage: 0.4 V max.<br>(at sink current of 30 mA) |   |
| Maximum response frequency*2     |        | 30 kHz  |  |   |   |  |   |   |  |   |
| Phase difference between outputs |        | ---   |  |   | Phase difference between phases A and B: 90°±45°  |  |   |   |  |   |
| Output duty factor               |        | 50±25%  |  |   | ---   |  |   |   |  |   |
| Rise and fall times of output    |        | 1.0 μs max.<br>(Cable length: 500 mm, Sink current: 10 mA)  | 1.0 μs max. (Cable length: 500 mm, Control output voltage: 5 V, Load resistance: 1 kΩ)                                 |   | 1.0 μs max.<br>(Cable length: 500 mm, Sink current: 10 mA)  | 1.0 μs max. (Cable length: 500 mm, Control output voltage: 5 V, Load resistance: 1 kΩ)                                 |   | 1.0 μs max.<br>(Cable length: 500 mm, Sink current: 10 mA)  | 1.0 μs max. (Cable length: 500 mm, Control output voltage: 5 V, Load resistance: 1 kΩ)                                 |   |
| Starting torque                  |        | 1 mN·m max.   |  |   |   |  |   |   |  |   |
| Moment of inertia                |        | 1 × 10 <sup>-7</sup> kg·m <sup>2</sup> max.   |  |   |   |  |   |   |  |   |
| Shaft loading                    | Radial | 10 N  |  |   |   |  |   |   |  |   |
|                                  | Thrust | 50 N  |  |   |   |  |   |   |  |   |
| Maximum permissible speed        |        | 5,000 r/min   |  |   |   |  |   |   |  |   |
| Ambient temperature range        |        | Operating: -10 to 55°C (with no icing), Storage: -25 to 80°C (with no icing)  |  |   |   |  |   |   |  |   |
| Ambient humidity range           |        | Operating/storage: 35% to 85% (with no condensation)  |  |   |   |  |   |   |  |   |
| Insulation resistance            |        | 20 MΩ min. (at 500 VDC) between current-carrying parts and case   |  |   |   |  |   |   |  |   |
| Dielectric strength              |        | 500 VAC, 50/60 Hz for 1 min between current-carrying parts and case   |  |   |   |  |   |   |  |   |
| Vibration resistance             |        | Destruction: 10 to 55 Hz, 1.5-mm double amplitude for 2 hours each in X, Y, and Z directions                          |  |   |   |  |   |   |  |   |
| Shock resistance                 |        | Destruction: 500m/s <sup>2</sup> 3 times each in X, Y, and Z directions   |  |   |   |  |   |   |  |   |
| Degree of protection*3           |        | IEC 60529 IP50  |  |   |   |  |   |   |  |   |
| Connection method                |        | Pre-wired Models (Standard cable length: 500 mm)  |  |   |   |  |   |   |  |   |
| Material                         |        | Case: Aluminum alloy, Main unit: Aluminum, Shaft: SUS420J2, Mounting Bracket: Galvanized iron                         |  |   |   |  |   |   |  |   |
| Weight (packed state)            |        | Approx. 35 g  |  |   |   |  |   |   |  |   |
| Accessories                      |        | Coupling, Servo Mounting Bracket (provided with the E6A2-CWZ□), Hexagonal wrench, Instruction manual                  |  |   |   |  |   |   |  |   |

\*1. An inrush current of approximately 9 A will flow for approximately 0.3 ms when the power is turned ON.

\*2. The maximum electrical response speed is determined by the resolution and maximum response frequency as follows:

$$\text{Maximum electrical response speed (rpm)} = \frac{\text{Maximum response frequency}}{\text{Resolution}} \times 60$$

This means that the E6A2-C Rotary Encoder will not operate electrically if its speed exceeds the maximum electrical response speed.

\*3. No protection is provided against water or oil.

## I/O Circuit Diagrams

| Model                    | Output circuits  | Output mode  | Connection   |       |        |       |     |       |         |       |         |        |         |      |              |
|--------------------------|--|--|--|-------|--------|-------|-----|-------|---------|-------|---------|--------|---------|------|--------------|
| E6A2-CS3C<br>E6A2-CS5C   |  | <p>Output transistor</p>   | <table border="1"> <thead> <tr> <th>Color</th> <th>Signal</th> </tr> </thead> <tbody> <tr> <td>Brown</td> <td>Vcc</td> </tr> <tr> <td>Black</td> <td>Phase A</td> </tr> <tr> <td>White</td> <td>Phase B</td> </tr> <tr> <td>Orange</td> <td>Phase Z</td> </tr> <tr> <td>Blue</td> <td>0 V (common)</td> </tr> </tbody> </table> <p>Note: 1. The white and orange wires of Single Models (E6A2-CS□□) do not output signals (no connection).<br/>2. The white and orange wires of Single Models (E6A2-CS□□) do not output signals (no connection).<br/>3. Voltage Output Models are capable of sinking a maximum current of 20 mA.</p> | Color | Signal | Brown | Vcc | Black | Phase A | White | Phase B | Orange | Phase Z | Blue | 0 V (common) |
| Color                    |  | Signal   |  |       |        |       |     |       |         |       |         |        |         |      |              |
| Brown                    |  | Vcc  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| Black                    | Phase A  |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| White                    | Phase B  |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| Orange                   | Phase Z  |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| Blue                     | 0 V (common)   |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| E6A2-CW3C<br>E6A2-CW5C   | <p>Direction of rotation: CW<br/>(as viewed from end of shaft)</p> <p>Output transistor</p>  |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| E6A2-CWZ3C<br>E6A2-CWZ5C | <p>Direction of rotation: CCW<br/>(as viewed from end of shaft)</p> <p>Output transistor</p> |  |  |       |        |       |     |       |         |       |         |        |         |      |              |
| E6A2-CW3E                |  | <p>Direction of rotation: CCW<br/>(as viewed from end of shaft)</p> <p>Output transistor</p> | <p>Note: 1. *(H) and (L) indicate the output levels of Voltage Output Models.</p> <p>2. Output A leads B by 1/4 T ± 1/8 T when the shaft revolves clockwise, while A lags behind B by 1/4 T ± 1/8 T when the shaft revolves counterclockwise.</p>  |       |        |       |     |       |         |       |         |        |         |      |              |
| E6A2-CWZ3E               |  | <p>Output transistor</p>   |  |       |        |       |     |       |         |       |         |        |         |      |              |
| E6A2-CS3E                |  | <p>Output transistor</p>   |  |       |        |       |     |       |         |       |         |        |         |      |              |

## Safety Precautions

Refer to *Warranty and Limitations of Liability*.

### ⚠ WARNING

This product is not designed or rated for ensuring safety of persons either directly or indirectly. Do not use it for such purposes.



### Precautions for Correct Use

Do not use the Encoder under ambient conditions that exceed the ratings.

#### ● Wiring

Spurious pulses may be generated when power is turned ON and OFF. Wait at least 0.1 s after turning ON the power to the Encoder before using the connected device, and stop using the connected device at least 0.1 s before turning OFF the power to the Encoder. Also, turn ON the power to the load only after turning ON the power to the Encoder.

(Unit: mm)

## Dimensions

Tolerance class IT16 applies to dimensions in this datasheet unless otherwise specified.

## Encoder

### E6A2-C



## Accessories (Order Separately)

**Coupling**

**Servo Mounting Bracket**

**E69-C04B**

**E69-1**

Refer to *Accessories* for details.

## Read and Understand This Catalog

Please read and understand this catalog before purchasing the products. Please consult your OMRON representative if you have any questions or comments.

## Warranty and Limitations of Liability

### WARRANTY

OMRON's exclusive warranty is that the products are free from defects in materials and workmanship for a period of one year (or other period if specified) from date of sale by OMRON.

OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, REGARDING NON-INFRINGEMENT, MERCHANTABILITY, OR FITNESS FOR PARTICULAR PURPOSE OF THE PRODUCTS. ANY BUYER OR USER ACKNOWLEDGES THAT THE BUYER OR USER ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE. OMRON DISCLAIMS ALL OTHER WARRANTIES, EXPRESS OR IMPLIED.

### LIMITATIONS OF LIABILITY

OMRON SHALL NOT BE RESPONSIBLE FOR SPECIAL, INDIRECT, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED ON CONTRACT, WARRANTY, NEGLIGENCE, OR STRICT LIABILITY.

In no event shall the responsibility of OMRON for any act exceed the individual price of the product on which liability is asserted.

IN NO EVENT SHALL OMRON BE RESPONSIBLE FOR WARRANTY, REPAIR, OR OTHER CLAIMS REGARDING THE PRODUCTS UNLESS OMRON'S ANALYSIS CONFIRMS THAT THE PRODUCTS WERE PROPERLY HANDLED, STORED, INSTALLED, AND MAINTAINED AND NOT SUBJECT TO CONTAMINATION, ABUSE, MISUSE, OR INAPPROPRIATE MODIFICATION OR REPAIR.

## Application Considerations

### SUITABILITY FOR USE

OMRON shall not be responsible for conformity with any standards, codes, or regulations that apply to the combination of products in the customer's application or use of the products.

At the customer's request, OMRON will provide applicable third party certification documents identifying ratings and limitations of use that apply to the products. This information by itself is not sufficient for a complete determination of the suitability of the products in combination with the end product, machine, system, or other application or use.

The following are some examples of applications for which particular attention must be given. This is not intended to be an exhaustive list of all possible uses of the products, nor is it intended to imply that the uses listed may be suitable for the products:

- Outdoor use, uses involving potential chemical contamination or electrical interference, or conditions or uses not described in this catalog.
- Nuclear energy control systems, combustion systems, railroad systems, aviation systems, medical equipment, amusement machines, vehicles, safety equipment, and installations subject to separate industry or government regulations.
- Systems, machines, and equipment that could present a risk to life or property.

Please know and observe all prohibitions of use applicable to the products.

NEVER USE THE PRODUCTS FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCTS ARE PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

### PROGRAMMABLE PRODUCTS

OMRON shall not be responsible for the user's programming of a programmable product, or any consequence thereof.

## Disclaimers

### CHANGE IN SPECIFICATIONS

Product specifications and accessories may be changed at any time based on improvements and other reasons.

It is our practice to change model numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the products may be changed without any notice. When in doubt, special model numbers may be assigned to fix or establish key specifications for your application on your request. Please consult with your OMRON representative at any time to confirm actual specifications of purchased products.

### DIMENSIONS AND WEIGHTS

Dimensions and weights are nominal and are not to be used for manufacturing purposes, even when tolerances are shown.

### PERFORMANCE DATA

Performance data given in this catalog is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of OMRON's test conditions, and the users must correlate it to actual application requirements. Actual performance is subject to the OMRON Warranty and Limitations of Liability.

### ERRORS AND OMISSIONS

The information in this document has been carefully checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical, or proofreading errors, or omissions.

2008.11

In the interest of product improvement, specifications are subject to change without notice.

**OMRON Corporation**  
Industrial Automation Company

<http://www.ia.omron.com/>

(c)Copyright OMRON Corporation 2008 All Right Reserved.

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9