



UNIDIRECTIONAL P-GATE THYRISTOR OVERVOLTAGE AND OVERCURRENT PROTECTOR

TISP8250D Overvoltage and Overcurrent Protector

Telecommunication System 30 A 10/1000 Protector

Ion-Implanted Breakdown Region
- Precise and Stable Voltage

Device Name	V_{DRM} V	$V_{(BO)}$ V
TISP8250D	250	340

Rated for International Surge Wave Shapes


Wave Shape	Standard	I_{PPSM} A
2/10	GR-1089-CORE	75
0.5/700	CNET I 31-24	40
10/700	ITU-T K.20/21	40
10/1000	GR-1089-CORE	30

Functional Replacement for TPP25011




..... UL Recognized Component

8-SOIC Package (Top View)



Device Symbol



Description

The TISP8250D is a P-gate reverse-blocking thyristor (SCR) designed for the protection of telecommunications equipment against overvoltages and overcurrents on the telephone line caused by lightning, a.c. power contact and induction. The fixed voltage and current triggered modes make the TISP8250D particularly suitable for the protection of ungrounded customer premise equipment. Connected across the d.c. side of a telephone set polarity bridge, in fixed voltage mode these devices can protect the ringer in the on-hook condition. In an off-hook condition, either the fixed voltage or current triggered modes can protect the following telephone electronics.

Without external gate activation, the TISP8250D is a fixed voltage protector. The maximum working voltage without clipping is 250 V and the protection voltage is 340 V. Lower values of protection voltage may be set by connecting an avalanche breakdown diode of less than 250 V between the TISP8250D gate and anode (see Figure 2.)

By connecting a small value resistor in series with the line conductor and connecting the TISP8250D gate cathode terminals in parallel with the resistor, conductor overcurrents can gate trigger the TISP8250D into conduction.

Overvoltages are initially clipped by breakdown clamping until the voltage rises to the breakover level, which causes the device to crowbar into a low-voltage on state. Overcurrents develop sufficient voltage across the external gate-cathode resistor to trigger the device into a low-voltage on state. This low-voltage on state causes the current resulting from the overstress to be safely diverted through the device. The high crowbar holding current prevents d.c. latchup as the diverted current subsides.

How To Order

Device	Package	Carrier	For Standard Termination Finish Order As	For Lead Free Termination Finish Order As	Marking Code	Standard Quantity
TISP8250D	8-SOIC	Embossed Tape Reeled	TISP8250DR	TISP8250DR-S	8250	2500
		Tube	TISP8250D	TISP8250D-S		1500

TISP8250D Overvoltage and Overcurrent Protector

BOURNS®

Absolute Maximum Ratings, $T_A = 25\text{ }^{\circ}\text{C}$ (Unless Otherwise Noted)

Rating	Symbol	Value	Unit
Repetitive peak off-state voltage (see Note 1)	V_{DRM}	250	V
Non-repetitive peak impulse current (see Notes 2, 3 and 4) 2/10 μs (Telcordia GR-1089-CORE, 2/10 μs waveshape) 0.2/310 (CNET I 31-24, 0.5/700 μs waveshape) 5/310 μs (ITU-T K.20/21, 10/700 μs voltage waveshape) 5/310 μs (FTZ R12, 10/700 μs voltage waveshape) 10/1000 μs (Telcordia GR-1089-CORE, 10/1000 μs voltage waveshape)	I_{PPSM}	75 40 40 40 30	A
Non-repetitive peak on-state current, 50 Hz (see Notes 2, 3 and 4) 10 ms half sine wave 1 s rectified sine wave 1000 s rectified sine wave	I_{TSM}	5 3.5 0.7	A
Junction temperature	T_J	-40 to +150	$^{\circ}\text{C}$
Storage temperature range	T_{stg}	-65 to +150	$^{\circ}\text{C}$

- NOTES: 1. For voltage values at lower temperatures, derate at 0.13 %/ $^{\circ}\text{C}$.
2. Initially the device must be in thermal equilibrium, with $T_J = 25\text{ }^{\circ}\text{C}$.
3. The surge may be repeated after the device returns to its initial conditions.
4. EIA/JESD51-2 environment and EIA/JESD51-3 PCB with standard footprint dimensions connected with 5 A printed wiring track widths. Derate current values at -0.61 %/ $^{\circ}\text{C}$ for ambient temperatures above $25\text{ }^{\circ}\text{C}$.

Electrical Characteristics, $T_A = 25\text{ }^{\circ}\text{C}$ (Unless Otherwise Noted)

Parameter	Test Conditions	Min	Typ	Max	Unit
I_{DRM} Repetitive peak off-state current	$V_D = V_{\text{DRM}}$ $T_A = 25\text{ }^{\circ}\text{C}$ $T_A = 85\text{ }^{\circ}\text{C}$			5 10	μA
$V_{\text{(BO)}}$ Breakover voltage	$dv/dt = 250\text{ V/ms}$, $R_{\text{SOURCE}} = 300\text{ }\Omega$			340	V
$I_{\text{(BO)}}$ Breakover current	$dv/dt = 250\text{ V/ms}$, $R_{\text{SOURCE}} = 300\text{ }\Omega$	15		200	mA
I_H Holding current	$I_T = 5\text{ A}$, $di/dt = -30\text{ mA/ms}$	180			mA
V_{GK} Gate-cathode voltage	$I_G = 30\text{ mA}$	0.6		1.2	V
I_{GT} Gate trigger current	$V_{\text{AK}} = 100\text{ V}$			40	mA
I_D Off-state current	$V_D = 60\text{ V}$			5	μA
C_O Off-state capacitance	$f = 1\text{ MHz}$, $V_d = 1\text{ V rms}$, $V_D = 5\text{ V}$			100	pF

Thermal Characteristics, $T_A = 25\text{ }^{\circ}\text{C}$ (Unless Otherwise Noted)

Parameter	Test Conditions	Min	Typ	Max	Unit
R_{JA} Junction to ambient thermal resistance	EIA/JESD51-3 PCB, $I_T = I_{\text{TSM}(1000)}$ (see Note 5)			170	$^{\circ}\text{C/W}$

- NOTE 5. EIA/JESD51-2 environment and PCB has standard footprint dimensions connected with 5A rated printed wiring track widths.

TISP8250D Overvoltage and Overcurrent Protector

BOURNS®

Parameter Measurement Information




Figure 1. Voltage-Current Characteristic for A and K Terminals
All Measurements are Referenced to the K Terminal




Figure 2. Overvoltage Protection Circuit

Bourns Sales Offices

Region	Phone	Fax
The Americas:	+1-951-781-5500	+1-951-781-5700
Europe:	+41-41-7685555	+41-41-7685510
Asia-Pacific:	+886-2-25624117	+886-2-25624116

Technical Assistance

Region	Phone	Fax
The Americas:	+1-951-781-5500	+1-951-781-5700
Europe:	+41-41-7685555	+41-41-7685510
Asia-Pacific:	+886-2-25624117	+886-2-25624116

www.bourns.com

Bourns® products are available through an extensive network of manufacturer's representatives, agents and distributors. To obtain technical applications assistance, a quotation, or to place an order, contact a Bourns representative in your area.



Reliable Electronic Solutions

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9