

DATA SHEET

For a complete data sheet, please also download:

- The IC04 LOCMOS HE4000B Logic Family Specifications HEF, HEC
- The IC04 LOCMOS HE4000B Logic Package Outlines/Information HEF, HEC

HEF4060B

MSI

14-stage ripple-carry binary counter/divider and oscillator

Product specification
File under Integrated Circuits, IC04



January 1995

14-stage ripple-carry binary counter/divider and oscillator

HEF4060B
MSI

DESCRIPTION

The HEF4060B is a 14-stage ripple-carry binary counter/divider and oscillator with three oscillator terminals (RS, R_{TC} and C_{TC}), ten buffered outputs (O₃ to O₉ and O₁₁ to O₁₃) and an overriding asynchronous master reset input (MR). The oscillator configuration allows design of either RC or crystal oscillator circuits. The oscillator may be replaced by an external clock signal at input RS. The counter advances on the negative-going transition of RS. A HIGH level on MR resets the counter (O₃ to O₉ and O₁₁ to O₁₃ = LOW), independent of other input conditions. Schmitt-trigger action in the clock input makes the circuit highly tolerant to slower clock rise and fall times.



- PINNING
- MR

RS

R_{TC}

C_{TC}

O₃ to O₉

O₁₁ to O₁₃

master reset

clock input/oscillator pin

oscillator pin

external capacitor connection

counter outputs
- HEF4060BP(N): 16-lead DIL; plastic (SOT38-1)
- HEF4060BD(F): 16-lead DIL; ceramic (cerdip) (SOT74)
- HEF4060BT(D): 16-lead SO; plastic (SOT109-1)
- (): Package Designator North America

FAMILY DATA, I_{DD} LIMITS category MSI

See Family Specifications

14-stage ripple-carry binary counter/divider and oscillator


HEF4060B
MSI

Fig.3 Logic diagram.

14-stage ripple-carry binary counter/divider and oscillator

HEF4060B MSI

AC CHARACTERISTICS

$V_{SS} = 0$ V; $T_{amb} = 25$ °C; $C_L = 50$ pF; input transition times ≤ 20 ns

	V _{DD} V	SYMBOL	MIN.	TYP.	MAX.	TYPICAL EXTRAPOLATION FORMULA
Propagation delays RS → O ₃ HIGH to LOW LOW to HIGH O _n → O _{n+1} HIGH to LOW LOW to HIGH MR → O _n HIGH to LOW	5	t _{PHL}	210	420	ns	183 ns + (0,55 ns/pF) C _L
	10		80	160	ns	69 ns + (0,23 ns/pF) C _L
	15		50	100	ns	42 ns + (0,16 ns/pF) C _L
	5	t _{PLH}	210	420	ns	183 ns + (0,55 ns/pF) C _L
	10		80	160	ns	69 ns + (0,23 ns/pF) C _L
	15		50	100	ns	42 ns + (0,16 ns/pF) C _L
	5	t _{PHL}	25	50	ns	
	10		10	20	ns	
	15		6	12	ns	
	5	t _{PLH}	25	50	ns	
	10		10	20	ns	
	15		6	12	ns	
5	t _{PHL}	100	200	ns	73 ns + (0,55 ns/pF) C _L	
10		40	80	ns	29 ns + (0,23 ns/pF) C _L	
15		30	60	ns	22 ns + (0,16 ns/pF) C _L	
Output transition times HIGH to LOW LOW to HIGH	5	t _{THL}	60	120	ns	10 ns + (1,0 ns/pF) C _L
	10		30	60	ns	9 ns + (0,42 ns/pF) C _L
	15		20	40	ns	6 ns + (0,28 ns/pF) C _L
	5	t _{TLH}	60	120	ns	10 ns + (1,0 ns/pF) C _L
	10		30	60	ns	9 ns + (0,42 ns/pF) C _L
	15		20	40	ns	6 ns + (0,28 ns/pF) C _L
Minimum clock pulse width input RS HIGH	5	t _{WRSH}	120	60	ns	
	10		50	25	ns	
	15		30	15	ns	
Minimum MR pulse width; HIGH	5	t _{WMRH}	50	25	ns	
	10		30	15	ns	
	15		20	10	ns	
Recovery time for MR	5	t _{RMR}	160	80	ns	
	10		80	40	ns	
	15		60	30	ns	
Maximum clock pulse frequency input RS	5	f _{max}	4	8	MHz	
	10		10	20	MHz	
	15		15	30	MHz	

14-stage ripple-carry binary counter/divider
and oscillator

HEF4060B
MSI

AC CHARACTERISTICS

V_{SS} = 0 V; T_{amb} = 25 °C; input transition times ≤ 20 ns

	V _{DD} V	TYPICAL FORMULA FOR P (μW) ⁽¹⁾
Dynamic power dissipation per package (P)	5	700 f _i + f _o C _L V _{DD} ²
	10	3 300 f _i + f _o C _L V _{DD} ²
	15	8 900 f _i + f _o C _L V _{DD} ²
Total power dissipation when using the on-chip oscillator (P)	5	700 f _{osc} + f _o C _L V _{DD} ² + 2C _t V _{DD} ² f _{osc} + 690 V _{DD}
	10	3 300 f _{osc} + f _o C _L V _{DD} ² + 2C _t V _{DD} ² f _{osc} + 6 900 V _{DD}
	15	8 900 f _{osc} + f _o C _L V _{DD} ² + 2C _t V _{DD} ² f _{osc} + 22 000 V _{DD}

Notes

1. where:
- f_i = input frequency (MHz)

f_o = output frequency (MHz)


C_L = load capacitance (pF)

V_{DD} = supply voltage (V)

C_t = timing capacitance (pF)

f_{osc} = oscillator frequency (MHz)

RC oscillator



14-stage ripple-carry binary counter/divider and oscillator

HEF4060B
MSI

Timing component limitations

The oscillator frequency is mainly determined by $R_t C_t$, provided $R_t \ll R_2$ and $R_2 C_2 \ll R_t C_t$. The function of R_2 is to minimize the influence of the forward voltage across the input protection diodes on the frequency. The stray capacitance C_2 should be kept as small as possible. In consideration of accuracy, C_t must be larger than the inherent stray capacitance. R_t must be larger than the LOCMOS 'ON' resistance in series with it, which typically is $500\ \Omega$ at $V_{DD} = 5\text{ V}$, $300\ \Omega$ at $V_{DD} = 10\text{ V}$ and $200\ \Omega$ at $V_{DD} = 15\text{ V}$.

The recommended values for these components to maintain agreement with the typical oscillation formula are:

$C_t \geq 100\text{ pF}$, up to any practical value,
 $10\text{ k}\Omega \leq R_t \leq 1\text{ M}\Omega$.

Typical crystal oscillator circuit

In Fig.5, R_2 is the power limiting resistor. For starting and maintaining oscillation a minimum transconductance is necessary.




Fig.5 External component connection for crystal oscillator.







Fig.6 Test set-up for measuring forward transconductance $g_{fs} = di_o/dv_i$ at v_o is constant (see also graph Fig.7); $MR = LOW$.

14-stage ripple-carry binary counter/divider
and oscillator

HEF4060B
MSI



Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9