

QUICK START GUIDE FOR DEMONSTRATION CIRCUIT DC963B

LOW POWER ACTIVE UP-CONVERTING MIXER

LT5560

DESCRIPTION

Demonstration circuit DC963B is optimized for an up-converting mixer test & measurement for input frequency range of 45MHz to 190MHz, output frequency range of 850MHz to 935MHz, (12dB return loss BW). The LO port frequency range is 520MHz to 920MHz (10dB return loss BW).

The LT®5560 is a 0.01MHz to 4000MHz low power, high performance broadband Up/Down-converting active mixer. This double-balanced mixer can be driven by a single-ended LO source and requires minus 2dBm of LO power. The signal ports can be impedance matched to a broad range of frequencies, which allow the LT®5560 to be used as an up- or

down-conversion mixer in a wide variety of applications.

The LT®5560 is characterized with a supply current of 10mA; however, the DC current is adjustable, which allows the performance to be optimized for each application by changing the value of resistor R1. For $I_{CC}=10\text{mA}$ the value of $R1 = 3 \text{ Ohm}$. Operation at a lower supply current will, however, degrade linearity.

Design files for this circuit board are available. Call the LTC factory.

LT is a registered trademark of Linear Technology Corporation.

Table 1. Typical Performance Summary ($T_A = 25^\circ\text{C}$)

PARAMETER	CONDITION ($f_{\text{INPUT}} = 140\text{MHz}$, $f_{\text{LO}}=760\text{MHz}$)	VALUE
Supply Voltage		2.7V to 5.0V
Supply Current	$V_{CC} = 3\text{V}$, EN = High, $R1=3$	10mA
Maximum Shutdown Current	$V_{CC} = 3\text{V}$, EN = 0.3V	10 μA
Signal Input Frequency Range	Requires External Matching	< 4000MHz
LO Signal Frequency Range	Requires External Matching	< 4000MHz
Signal Output Frequency Range	Requires External Matching	< 4000MHz
IF Input Return Loss	$Z_0 = 50 \Omega$, with External Matching	15dB
LO Input Return Loss	$Z_0 = 50 \Omega$, with External Matching	15dB
RF Output Return Loss	$Z_0 = 50 \Omega$, with External Matching	15dB
LO Input Power		-6dBm to 1dBm
Conversion Gain	$P_{\text{INPUT}} = -20\text{dBm}$, $P_{\text{LO}} = -2\text{dBm}$	2.4dB
SSB Noise Figure	$P_{\text{LO}} = -2\text{dBm}$	9.3dB
Input 3 rd Order Intercept	2-Tone, -20dBm/Tone, $\Delta f = 1\text{MHz}$, $P_{\text{LO}} = -2\text{dBm}$	+9.0dBm
Input 2 nd Order Intercept	2-Tone, -20dBm/Tone, $\Delta f = 1\text{MHz}$, $P_{\text{LO}} = -2\text{dBm}$	+47dBm
Input 1dB Compression	$P_{\text{LO}} = -2\text{dBm}$	-2.8dBm
LO to IN leakage	$P_{\text{LO}} = -2\text{dBm}$	-54dBm
LO to OUT leakage	$P_{\text{LO}} = -2\text{dBm}$	-41dBm

QUICK START GUIDE FOR DEMONSTRATION CIRCUIT DC963B

LOW POWER ACTIVE UP-CONVERTING MIXER

QUICK START PROCEDURE

Demonstration circuit DC963B is easy to set up to evaluate the performance of the LT®5560. Refer to Figure 1 for proper measurement equipment setup and follow the procedure below:

NOTE:

- a. Use high performance signal generators with low harmonic output for 2nd & 3rd order distortion measurements. Otherwise, low-pass filters at the signal generator outputs should be used to suppress harmonics, particularly the 2nd harmonic.
 - b. High quality combiners that provide a 50 Ohm termination on all ports and have good port-to-port isolation should be used. Attenuators on the outputs of the signal generators are recommended to further improve source isolation and to reduce reflection into the sources.
1. Connect all test equipment as shown in Figure 1.
 2. Set the DC power supply's current limit to 15mA, and adjust output voltage to 3V.
 3. Connect Vcc to the 3V DC supply, and then connect EN to 3V; the Mixer is enabled (on).
 4. Set Signal Generator #1 to provide a 760MHz, -2dBm, CW signal to the demo board LO input port.
 5. Set the Signal Generators #2 and #3 to provide two -20dBm CW signals to the demo board RF

input port, one at 140MHz, and the other at 141MHz.

6. To measure 3rd order distortion and conversion gain, set the Spectrum Analyzer start and stop frequencies to 898MHz and 903MHz, respectively. Sufficient spectrum analyzer input attenuation should be used to avoid distortion in the instrument.
7. The 3rd order intercept point is equal to $(P_1 - P_3) / 2 + P_{in}$, where P_1 is the power level of the two fundamental output tones at 900MHz and 901MHz, P_3 is the 3rd order product at 899MHz and 902MHz, and P_{in} is the input power (in this case, -20dBm). All units are in dBm.
8. Output 2nd order distortion product (OIM2) can be measured at 1041MHz, $(140\text{MHz}+141\text{MHz}) + 760\text{MHz} = 1041\text{MHz}$. To measure 2nd order distortion, set the Spectrum Analyzer start and stop frequencies to 1040MHz and 1042MHz, respectively. Sufficient spectrum analyzer input attenuation should be used to avoid distortion in the instrument.
9. The input referred 2nd order intercept point (IIP2) is equal to $P_1 - P_2 + P_{in}$, where P_1 is the power level of the fundamental output tone at 900MHz or 901MHz, P_2 is the 2nd order distortion product at 1041MHz, and P_{in} is the input power (in this case -20dBm).

QUICK START GUIDE FOR DEMONSTRATION CIRCUIT DC963B

LOW POWER ACTIVE UP-CONVERTING MIXER






Figure 1. Proper Measurement Equipment Setup

QUICK START GUIDE FOR DEMONSTRATION CIRCUIT DC963B

LOW POWER ACTIVE UP-CONVERTING MIXER



T1 Circuit Diagram
TOP VIEW



CUSTOMER NOTICE		CONTRACT NO.	
APPROVALS	DATE		
DRAWN A. Karpova	7/14/05	TITLE	LT5560EDD UPCONVERTING MIXER APPLICATION
CHECKED			
APPROVED			
ENGINEER V. Dvorkin	7/14/05	SIZE	CAGE CODE
DESIGNER			DWG NO.
			DC963B
		REV	
		SHEET	1 OF 1
		FILENAME:	
		SCALE:	
		2	
		3	
		4	
		5	

1630 McCarthy Blvd.
Milpitas, CA 95035
Phone: (408)422-9000
Fax: (408)424-2657

Данный компонент на территории Российской Федерации**Вы можете приобрести в компании MosChip.**

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибуторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ Р В 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru
moschip.ru_4

moschip.ru_6
moschip.ru_9