

DESCRIPTION

Demonstration Circuit 565 is a constant-frequency synchronous boost converter using the LTC3421. Guaranteed to start-up at 1V input voltage, this converter provides up to 95% efficiency. For 1.8V minimum input voltage, this converter can provide up to 1A load current.

This converter has true output disconnect by eliminating body diode conduction of the internal PMOS rectifier. This feature reduces the inrush current during start-up and isolates the load from input source in shutdown to eliminate any leakage current. With the V_{REF} output and low-battery comparator disabled, the IC only draws less than 1 μ A in shutdown.

The output voltage is set at 3.3V. A different output voltage in the range of 2.4V to 5.25V can be obtained by changing one of the feedback resistors. The switching frequency is set at 1MHz, which is a good trade-off between efficiency and size. The frequency can be adjusted by selecting R13 at R_T pin. It can also be synchronized to an external clock for noise-sensitive applications.

Long wires from input sources (such as wall adaptors) can cause large voltage spikes during initial plug-in. C12 is installed on DC565 to damp the possible voltage spikes. C12 is not required for applications where input source is close to the regulator. Please refer to Application Note 88 for details.

For $V_{OUT} > 4.3V$ applications, D1, Q1, R18 and C10 have to be installed to limit the peak switch voltage below the absolute maximum rating. Instead of using a schottky diode connected directly from SW pin to the output, this active snubber keeps the LTC3421 true output disconnect feature. R18 can be used to limit the current going through Q1 in short-circuit conditions.

The optional circuit at ILIM pin can be added to provide current limit foldback for extended short-circuit conditions. Refer to Short Circuit section in the datasheet for details.

Design files for this circuit board are available. Call the LTC factory.

Table 1. Performance Summary ($T_A = 25^\circ C$ unless otherwise noted)

PARAMETER	CONDITION	VALUE
Minimum Input Voltage		1V
Output Voltage V_{OUT}	$V_{IN} = 1.8V$ to $3.2V$, $I_{OUT} = 0A$ to $1A$	$3.3V \pm 3\%$
Maximum Output Current	$V_{IN} = 1.8V$ to $3.2V$	1A
Typical Output Ripple V_{OUT}	$V_{IN} = 2.4V$, $I_{OUT} = 1A$ (20MHz BW)	30mV _{P-P}
Typical Switching Frequency		1MHz
Efficiency	$V_{IN} = 2.4V$, $I_{OUT} = 0.2A$	95% Typical
	$V_{IN} = 2.4V$, $I_{OUT} = 1A$	88% Typical
On/Off Control	Logic Low Voltage-Off	0.25V MAX
	Logic High Voltage-On $V_{OUT} = 0V$	1V MIN
	$V_{OUT} > 2.4V$	0.6V MIN

QUICK START PROCEDURE

Demonstration circuit 565 is easy to set up to evaluate the performance of the LTC3421. Refer to Figure 1 for proper measurement equipment setup and follow the procedure below:

NOTE: When measuring the input or output voltage ripple, care must be taken to avoid a long ground lead on the oscilloscope probe. Measure the input or output voltage ripple by touching the probe tip directly across the Vin or Vout and GND terminals. See Figure 2 for proper scope probe technique.

1. Place jumpers in the following positions:

JP1 ON or OFF
JP2 RUN
JP3 AUTO ON

2. With power off, connect the input power supply to Vin and GND.

3. Turn on the power at the input.

NOTE: Make sure that the input voltage does not exceed 3.3V.

4. Check for the proper output voltage. $V_{out} = 3.2V$ to $3.4V$.

NOTE: If there is no output, temporarily disconnect the load to make sure that the load is not set too high.

5. Once the proper output voltage is established, adjust the load within the operating range and observe the output voltage regulation, ripple voltage, efficiency and other parameters.

GRAPHICS




Figure 1. Proper Measurement Equipment Setup




Figure 2. Measuring Input or Output Ripple





Figure 3. Load Transient Response ($V_{in}=3V$; Channel 1: V_{out} ; Channel 2: I_{out} : load step from 100mA to 1A)



Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9