KAI-0330 Imager Board User's Manual

Description

The KAI-0330 Imager Evaluation Board, referred to in this document as the Imager Board, is designed to be used as part of a two-board set, used in conjunction with a Timing Generator Board. ON Semiconductor offers an Imager Board / Timing Generator Board package that has been designed and configured to operate with the KAI-0330 Image Sensors.

The Timing Generator Board generates the timing signals necessary to operate the CCD, and provides the power required by the Imager Board. The timing signals, in LVDS format, and the power, are provided to the Imager Board via the interface connector (J3). In addition, the Timing Generator Board performs the processing and digitization of the analog video output of the Imager Board.



ON Semiconductor®

http://onsemi.com

EVAL BOARD USER'S MANUAL

The KAI-0330 Imager Board has been designed to operate the KAI-0330 with the specified performance at up to 30 MHz pixel clocking rate and nominal operating conditions. (See the KAI-0330 performance specifications for details).

IMAGER BOARD INPUT REQUIREMENTS

Table 1. POWER REQUIREMENTS

| Power Supplies | Minimum | Typical | Maximum | Units |
|-----------------|---------|---------|---------|-------|
| +5 V_MTR Supply | 4.9 | 5 | 5.1 | V |
| | | 100 | | mA |
| -5 V_MTR Supply | -5.1 | -5 | -4.9 | V |
| | | 50 | | mA |
| VPLUS Supply | 18 | 20 | 21 | V |
| | | 250 | | mA |
| VMINUS Supply | -21 | -20 | -18 | V |
| | | 250 | | mA |

Table 2. SIGNAL LEVEL REQUIREMENTS

| Input Signals (LVDS) | V _{min} | V _{threshold} | V _{max} | Units | Comments |
|----------------------|------------------|------------------------|------------------|-------|--|
| H1A (±) | 0 | ±0.1 | 2.4 | V | H1A clock |
| H1B (±) | 0 | ±0.1 | 2.4 | V | H1B clock |
| H2A (±) | 0 | ±0.1 | 2.4 | V | H2 clock |
| H2B (±) | 0 | ±0.1 | 2.4 | V | (Not Used) |
| R (±) | 0 | ±0.1 | 2.4 | V | Reset clock |
| V1 (±) | 0 | ±0.1 | 2.4 | V | V1 clock |
| V2 (±) | 0 | ±0.1 | 2.4 | V | V2 clock |
| V3RD (±) | 0 | ±0.1 | 2.4 | V | Vertical clock 3 rd -level signal |
| VES (±) | 0 | ±0.1 | 2.4 | V | Electronic Shutter signal |
| FDG (±) | 0 | ±0.1 | 2.4 | V | Fast Dump Gate signal |
| V2B (±) | 0 | ±0.1 | 2.4 | V | (Not Used) |

1

KAI-0330 IMAGER BOARD ARCHITECTURE OVERVIEW

The following sections describe the functional blocks of the KAI–0330 Imager Board (See Figure 1).

Power Filtering and Regulation

Power is supplied to the Imager Board via the J3 interface connector. The power supplies are de-coupled and filtered with ferrite beads and capacitors to suppress noise. Voltage regulators are used to create the +15 V and -15 V supplies from the VPLUS and VMINUS supplies.

LVDS Receivers / TTL Buffers

LVDS timing signals are input to the Imager Board via the J3 interface connector. These signals are shifted to TTL levels before being sent to the CCD clock drivers.

Reset Clock One-Shot

The pulse width of the RESET_CCD clock is set by a programmable One–Shot. The One–Shot can be configured to provide a RESET_CCD clock signal with a pulse width from 5 ns to 15 ns (See section Reset Clock Pulse Width).

CCD Pixel-Rate Clock Drivers (H1, H2 & Reset Clocks)

The pixel rate CCD clock drivers utilize two fast switching transistors that are designed to translate TTL-level input clock signals to the voltage levels required by the CCD. The high and low voltage levels of the CCD clocks are set by voltage dividers feeding into operational amplifiers configured as voltage followers. The current source is a high current (up to 600 mA) transistor.

CCD VCLK Drivers

The vertical clock (VCLK) drivers consist of MOSFET driver IC's. These drivers are designed to translate the TTL-level clock signals to the voltage levels required by the CCD. The high and low voltage rails of the vertical clocks are generated from the output of the positive and negative voltage regulators. The voltage level is set by a voltage divider and an operational amplifier configured as a voltage follower. The current source is a high current (up to 600 mA) transistor. The mid-level voltage is set by a voltage regulator and a diode to be several tenths of a volt above AGND. The

third level of the V1_CCD clock (V3RD) is AC-coupled onto the mid-level voltage once per frame to transfer the charge from the photodiodes to the vertical CCDs.

CCD FDG Driver

The Fast Dump Gate (FDG) driver is a transistor that will switch the voltage on the FDG pin of the CCD from -5 V to +5 V during Fast Dump Gate operation. When not in operation, or when the Fast Dump Gate feature is not being utilized, the FDG pin of the CCD is held at -5 V.

VES Circuit

The quiescent CCD substrate voltage (VSUB) is set via a potentiometer. For electronic shutter operation, the VES signal drives a transistor amplifier which AC-couples the voltage difference between the VPLUS and VMINUS supplies onto the Substrate voltage. This creates the necessary potential to clear all charge from the photodiodes, thereby acting as an electronic shutter to control exposure.

CCD Bias Voltages

The bias voltages are set by voltage dividers. The bias voltages are de-coupled at the CCD pin.

CCD Image Sensor

This evaluation board supports the KAI-0330 Image Sensor.

Emitter-Follower

The VOUT_CCD signals are buffered using a bipolar junction transistor in the emitter–follower configuration. This circuit also provides the necessary current sink for the CCD output circuit.

Line Drivers

The buffered VOUT_CCD signals are AC-coupled and driven from the Imager Board by operational amplifiers in a non-inverting configuration. The operational amplifiers are configured to have a gain of 2, to correctly drive 75 Ω video coaxial cabling from the SMB connectors (see SMB Connectors J1 AND J2).

KAI-0330 OPERATIONAL SETTINGS

The Imager board is configured to operate the KAI-0330 under the following operating conditions:

Table 3. BIAS VOLTAGES

| Description | Symbol | Setting | Units | Notes |
|-------------------------|--------|---------|-------|---|
| Output Amplifier Supply | VDD | 15 | V | |
| Reset Drain | VRD | 9 | V | |
| Output Amplifier Return | VSS | 0 | V | |
| Ground, P-Well | GND | 0 | V | |
| Substrate | VSUB | 10 | V | VSUB is adjustable via R56 |
| Fast Dump Gate | FDG | -5 | V | Held at -5 V when the FDG Option disabled |
| P-WELL | WELL | 0 | V | |

Table 4. CLOCK VOLTAGES

| Description | Symbol | Low | Mid | High | Units | Notes |
|--------------------------|-----------|------|-----|------|-------|--------------------------|
| Phase 1 Horizontal Clock | H1A_CCD | -7 | | 3 | V | |
| Phase 1 Horizontal Clock | H1B_CCD | -7 | | 3 | V | |
| Phase 2 Horizontal Clock | H2_CCD | -7 | | 3 | V | |
| Phase 1 Vertical Clock | V1_CCD | -9.5 | 0.2 | 9 | V | |
| Phase 2 Vertical Clock | V2_CCD | -9.5 | 0.2 | 9 | V | |
| Reset Clock | RESET_CCD | -6 | | 0 | V | R- is adjustable via R28 |
| Fast Dump Gate Clock | FDG_CCD | -5 | | 5 | V | |

Reset Clock Pulse Width

The pulse width of RESET_CCD is set by configuring P[2..0], the inputs to the programmable one-shot. P[2..0]

can be tied high or low to achieve the desired pulse width by populating the resistors R33–38 accordingly.

| Pulse Width | P0 | P1 | P2 | R33 | R34 | R35 | R36 | R37 | R38 | Notes |
|-------------|----|----|----|-----|-----|-----|-----|-----|-----|-----------------|
| 15 ns | 0 | 0 | 0 | OUT | OUT | OUT | IN | IN | IN | |
| 5 ns | 1 | 0 | 0 | OUT | OUT | IN | IN | IN | OUT | Default Setting |
| 7.5 ns | 0 | 1 | 0 | OUT | IN | OUT | IN | OUT | IN | |
| 10 ns | 1 | 1 | 0 | OUT | IN | IN | IN | OUT | OUT | |
| 12.5 ns | 0 | 0 | 1 | IN | OUT | OUT | OUT | IN | IN | |
| 15 ns | 1 | 0 | 1 | IN | OUT | IN | OUT | IN | OUT | |
| 15 ns | 0 | 1 | 1 | IN | IN | OUT | OUT | OUT | IN | |
| 15 ns | 1 | 1 | 1 | IN | IN | IN | OUT | OUT | OUT | |

Table 5. RESET CLOCK PULSE WIDTH

BLOCK DIAGRAM AND PERFORMANCE DATA



Figure 1. KAI-0330 Imager Board Block Diagram



Figure 2. Measured Performance at 20 MHz – Linearity

Photon Transfer



Figure 3. Measured Performance at 20 MHz – Dynamic Range and Noise Floor



MULTI-FRAME INTEGRATION LINEARITY



Photon Transfer



Figure 5. Measured Performance at 30 MHz – Dynamic Range and Noise Floor

CONNECTOR ASSIGNMENTS AND PINOUTS

SMB Connectors J1 and J2

The emitter–follower buffered CCD_VOUT signals are driven from the Imager Board via the SMB connector J1 and J2. Coaxial cable with a characteristic impedance of 75 Ω

should be used to connect the imager board to the Timing Generator Board to match the series and terminating resistors used on these boards.

Table 6. J3 INTERFACE CONNECTOR PIN ASSIGNMENTS

| Pin | Signal | Pin | Signal |
|-----|------------|-----|------------|
| 1 | N.C. | 2 | N.C. |
| 3 | AGND | 4 | AGND |
| 5 | VES+ | 6 | VES- |
| 7 | AGND | 8 | AGND |
| 9 | FDG+ | 10 | FDG- |
| 11 | AGND | 12 | AGND |
| 13 | V3RD+ | 14 | V3RD- |
| 15 | AGND | 16 | AGND |
| 17 | V2B+ | 18 | V2B- |
| 19 | AGND | 20 | AGND |
| 21 | V2+ | 22 | V2- |
| 23 | AGND | 24 | AGND |
| 25 | V1+ | 26 | V1- |
| 27 | AGND | 28 | AGND |
| 29 | R+ | 30 | R- |
| 31 | AGND | 32 | AGND |
| 33 | H2B+ | 34 | H2B- |
| 35 | AGND | 36 | AGND |
| 37 | H2A+ | 38 | H2A- |
| 39 | AGND | 40 | AGND |
| 41 | H1B+ | 42 | H1B- |
| 43 | AGND | 44 | AGND |
| 45 | H1A+ | 46 | H1A– |
| 47 | N.C. | 48 | N.C. |
| 49 | AGND | 50 | AGND |
| 51 | N.C. | 52 | N.C. |
| 53 | VMINUS_MTR | 54 | VMINUS_MTR |
| 55 | N.C. | 56 | N.C. |
| 57 | AGND | 58 | AGND |
| 59 | N.C. | 60 | N.C. |
| 61 | _5 V_MTR | 62 | -5 V_MTR |
| 63 | N.C. | 64 | N.C. |
| 65 | AGND | 66 | AGND |
| 67 | N.C. | 68 | N.C. |
| 69 | +5 V_MTR | 70 | +5 V_MTR |
| 71 | N.C. | 72 | N.C. |
| 73 | AGND | 74 | AGND |
| 75 | N.C. | 76 | N.C. |
| 77 | VPLUS_MTR | 78 | VPLUS_MTR |
| 79 | N.C. | 80 | N.C. |

Warnings and Advisories

ON Semiconductor is not responsible for customer damage to the Imager Board or Imager Board electronics. The customer assumes responsibility and care must be taken when probing, modifying, or integrating the ON Semiconductor Evaluation Board Kits.

When programming the Timing Board, the Imager Board must be disconnected from the Timing Board before power is applied. If the Imager Board is connected to the Timing Board during the reprogramming of the Altera PLD, damage to the Imager Board will occur.

Purchasers of an Evaluation Board Kit may, at their discretion, make changes to the Timing Generator Board firmware. ON Semiconductor can only support firmware developed by, and supplied by, ON Semiconductor. Changes to the firmware are at the risk of the customer.

Ordering Information

Please address all inquiries and purchase orders to:

Truesense Imaging, Inc. 1964 Lake Avenue Rochester, New York 14615 Phone: (585) 784–5500 E-mail: info@truesenseimaging.com

ON Semiconductor reserves the right to change any information contained herein without notice. All information furnished by ON Semiconductor is believed to be accurate.

ON Semiconductor and the initial are registered trademarks of Semiconductor Components Industries, LLC (SCILLC) or its subsidiaries in the United States and/or other countries. SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product for any such unintended or unauthorized application. Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable atorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This l

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Depage 421 22 700 2010

Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative





Общество с ограниченной ответственностью «МосЧип» ИНН 7719860671 / КПП 771901001 Адрес: 105318, г.Москва, ул.Щербаковская д.З, офис 1107

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

http://moschip.ru/get-element

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.З, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж: moschip.ru moschip.ru_4

moschip.ru_6 moschip.ru_9