

Inspired LED **Flexible Strip Lights** are a simple, customizable solution for all of your LED lighting needs. These unique strips can be cut to length and terminated with solderless end connectors for easy DIY installation. Energy efficient, with a wide range of options for brightness and color, LED Flex Strips are the perfect option for any lighting application.



Warm White 3000K    Pure White 4200K    Cool White 6000K



Red    Green    Blue  
Available in NB & SB Only    NB, SB & UB Only



**NB – Normal Bright** 9 LEDs per foot, >60 lumens per foot, ~0.65 watt per foot



**SB – Super Bright** 18 LEDs per foot, >125 lumens per foot, ~1.5 watts per foot




**UB – Ultra Bright** 30 LEDs per foot, >210 lumens per foot, ~2.35 watts per foot



**MB – Mega Bright** 36 LEDs per foot, >235 lumens per foot, ~2.55 watts per foot

## Product Features

- Minimal Heat Production- No IR or UV
- Available in various colors and brightness levels
- Custom pre-cut lengths or full 12m reels
- Adhesive mounts to almost any clean flat surface
- Class 2 DC plug in connectors (3.5 x 1.3 mm) or screw terminal end-connectors available
- Dimmable with compatible components
- Rated to last up to 100,000 hours
- **To be installed in accordance with NEC, using Class 2 12V DC power supply only**



## Installation Instructions

1. Clean desired mounting surface(s) and test all products prior to installation
2. Temporarily mount LED flex strips in desired location using scotch or painter's tape
3. Connect LED strips using compatible interconnect cables, or tiger paw screw terminals with bulk 18-22 AWG wire
4. If using class 2 plug-in power supply connect first string of lights to controller, then connect to power
5. If using hardwire transformer connect first string of lights directly to transformer, then connect to high voltage wall switch (see transformer spec for more detail)
6. When satisfied with placement, peel adhesive backing from strips and press firmly to secure LEDs in place



Power Source	Maximum Length of LED Flex Strip Lighting			
	Normal Bright*	Super Bright**	Ultra Bright***	Mega Bright****
1 Amp / 1 Amp Mini (12 Watt)	154.5" (10.8 Watts)	70" (10.8 Watts)	40.5" (10.8 Watts)	38.5" (10.8 Watts)
1.5 Amp Skinny (18 Watt)	205.5" (16.1 Watts)	101.5" (15.5 Watts)	59.5" (16.1 Watts)	50" (16.1 Watts)
2 Amp (24 Watt)	274.5" (21.6 Watts)	135" (21.6 Watts)	81" (21.6 Watts)	76" (21.6 Watts)
40 Watt Dimmable Transformer	456" (36 Watts)	227.5" (36 Watts)	133.5" (36 Watts)	129" (36 Watts)
3.8 Amp (45.6 Watt)	520" (41 Watts)	259" (41 Watts)	153" (41 Watts)	146.5" (41 Watts)
5 Amp (60 Watt)	684" (54 Watts)	339.5" (54 Watts)	200" (54 Watts)	192" (54 Watts)
60 Watt Dimmable Transformer	684" (54 Watts)	339.5" (54 Watts)	200" (54 Watts)	192" (54 Watts)
100 Watt Dimmable Transformer	1140" (90 Watts)	568" (90 Watts)	335" (90 Watts)	320" (90 Watts)

\*Individual strips over 200" should be powered from the center of the strip, individual strips should not exceed 400" in length.  
 \*\*Individual strips over 150" should be powered from the center of the strip, individual strips should not exceed 300" in length.  
 \*\*\* Individual strips over 105" should be powered from the center of the strip, individual strips should not exceed 210" in length.  
 \*\*\*\* Individual strips over 100" should be powered from the center of the strip, individual strips should not exceed 200" in length.



## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9