



| JKL PART NUMBER | LENGTH A +/- 2mm | COLOR | STARTING CIRCUIT VOLTAGE VS (Vrms) | OPERATING LAMP VOLTAGE VL (Vrms) | OPERATING LAMP CURRENT IL (mAmps) | BRIGHTNESS (CANDELA/m ²) | *RATED LIFE (HRS) |
|-----------------|------------------|---|------------------------------------|----------------------------------|-----------------------------------|--------------------------------------|-------------------|
| BF350-20B | 50mm | RGB HIGH OUTPUT WHITE 5400° KELVIN (REF.) | 500 | 195 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF375-20B | 75mm | | 525 | 210 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF386-20B | 86mm | | 540 | 220 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3100-20B | 100mm | | 665 | 270 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3115-20B | 115mm | | 685 | 287 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3130-20B | 130mm | | 705 | 305 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3160-20B | 160mm | | 850 | 345 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3180-20B | 180mm | | 940 | 380 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3216-20B | 216mm | | 1100 | 440 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3240-20B | 240mm | | 1150 | 480 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3250-20B | 250mm | | 1200 | 520 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3275-20B | 275mm | | 1275 | 593 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3300-20B | 300mm | | 1350 | 665 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3360-20B | 360mm | | 1500 | 785 | 5 ± 1 | 28000 ± 2800 | 20,000 |
| BF3380-20B | 380mm | | 1590 | 825 | 5 ± 1 | 28000 ± 2800 | 20,000 |

*NOTE: RATED LIFE IS DEFINED AS THE POINT AT WHICH THE INTENSITY BECOMES 50% OF THE INITIAL RATING.

| | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|---|---|--------------------------------|--------------------------|----------------------------|----------|---|---|----------|---|----------------------------|---------|---|----------------------------|---------|---|---------------------------|---------|---|-----------------|---------|--|--------------------------------------|---------|----------|-----------------------|-------------|--|--|---------------|-------------------------------|--|--------------------------------------|--|--------------|--|---------------|--|-------------|---|--|--|--|-----------------------------------|--|--|--|---|--|--|--|--------------------------|-------------------|------------------|---------------|------------------|--------------------------|--------------------------------|--------------------------|---|--|---------------------------|-------------------|--|--|-----------------|--|
| <table border="1"> <tr> <td>F</td> <td>ADD PART NUMBER BF3115-20B</td> <td>12/19/02</td> </tr> <tr> <td>E</td> <td>ADD PART NUMBER BF3180-20B & BF3380-20B</td> <td>11/30/01</td> </tr> <tr> <td>D</td> <td>ADD PART NUMBER BF3240-20B</td> <td>4/28/01</td> </tr> <tr> <td>C</td> <td>ADD PART NUMBER BF3130-20B</td> <td>9/11/00</td> </tr> <tr> <td>B</td> <td>ADD PART NUMBER BF375-20B</td> <td>4/21/00</td> </tr> <tr> <td>A</td> <td>LENGTH ±5 TO ±2</td> <td>2/25/00</td> </tr> <tr> <td></td> <td>RELEASED - CANCEL BF-3mm DIA DRAWING</td> <td>2/21/00</td> </tr> <tr> <td>REV. NO.</td> <td>DESCRIPTION/ECONUMBER</td> <td>APPV'D DATE</td> </tr> </table> | | | F | ADD PART NUMBER BF3115-20B | 12/19/02 | E | ADD PART NUMBER BF3180-20B & BF3380-20B | 11/30/01 | D | ADD PART NUMBER BF3240-20B | 4/28/01 | C | ADD PART NUMBER BF3130-20B | 9/11/00 | B | ADD PART NUMBER BF375-20B | 4/21/00 | A | LENGTH ±5 TO ±2 | 2/25/00 | | RELEASED - CANCEL BF-3mm DIA DRAWING | 2/21/00 | REV. NO. | DESCRIPTION/ECONUMBER | APPV'D DATE | <table border="1"> <tr> <td>METRIC</td> <td>DIMENSIONS ARE IN MILLIMETERS</td> </tr> <tr> <td></td> <td>TOLERANCE UNLESS OTHERWISE SPECIFIED</td> </tr> <tr> <td></td> <td>1 PL +/- 0.2</td> </tr> <tr> <td></td> <td>2 PL +/- 0.20</td> </tr> <tr> <td></td> <td>ANGLE +/- 0</td> </tr> </table> | | METRIC | DIMENSIONS ARE IN MILLIMETERS | | TOLERANCE UNLESS OTHERWISE SPECIFIED | | 1 PL +/- 0.2 | | 2 PL +/- 0.20 | | ANGLE +/- 0 | <table border="1"> <tr> <td colspan="4" style="text-align: center;">JKL COMPONENTS CORPORATION</td> </tr> <tr> <td colspan="4" style="text-align: center;">TITLE MINIATURE COLD CATHODE FLUORESCENT LAMP</td> </tr> <tr> <td>DRAWN BY L. WENGSTROM</td> <td>APPV'D BY F.D.</td> <td>DATE 12/19/02</td> <td>SCALE NONE</td> </tr> <tr> <td>SIZE A</td> <td>FSCM NO. 55335</td> <td>DRAWING NO. BF 3-20B</td> <td>RELEASED DATE 2/21/00</td> </tr> <tr> <td colspan="2" style="text-align: center;">- CAD DRAWING - MANUAL REVISIONS NOT PERMITTED</td> <td>REVISION DATE 12/19/02</td> <td>REV. NO. F</td> </tr> <tr> <td colspan="2"></td> <td>SHEET 1 OF 1</td> <td></td> </tr> </table> | | | | JKL COMPONENTS CORPORATION | | | | TITLE MINIATURE COLD CATHODE FLUORESCENT LAMP | | | | DRAWN BY L. WENGSTROM | APPV'D BY F.D. | DATE 12/19/02 | SCALE NONE | SIZE A | FSCM NO. 55335 | DRAWING NO. BF 3-20B | RELEASED DATE 2/21/00 | - CAD DRAWING - MANUAL REVISIONS NOT PERMITTED | | REVISION DATE 12/19/02 | REV. NO. F | | | SHEET 1 OF 1 | |
| F | ADD PART NUMBER BF3115-20B | 12/19/02 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| E | ADD PART NUMBER BF3180-20B & BF3380-20B | 11/30/01 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| D | ADD PART NUMBER BF3240-20B | 4/28/01 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| C | ADD PART NUMBER BF3130-20B | 9/11/00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| B | ADD PART NUMBER BF375-20B | 4/21/00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| A | LENGTH ±5 TO ±2 | 2/25/00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | RELEASED - CANCEL BF-3mm DIA DRAWING | 2/21/00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| REV. NO. | DESCRIPTION/ECONUMBER | APPV'D DATE | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| METRIC | DIMENSIONS ARE IN MILLIMETERS | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | TOLERANCE UNLESS OTHERWISE SPECIFIED | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | 1 PL +/- 0.2 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | 2 PL +/- 0.20 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | ANGLE +/- 0 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| JKL COMPONENTS CORPORATION | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| TITLE MINIATURE COLD CATHODE FLUORESCENT LAMP | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| DRAWN BY L. WENGSTROM | APPV'D BY F.D. | DATE 12/19/02 | SCALE NONE | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| SIZE A | FSCM NO. 55335 | DRAWING NO. BF 3-20B | RELEASED DATE 2/21/00 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| - CAD DRAWING - MANUAL REVISIONS NOT PERMITTED | | REVISION DATE 12/19/02 | REV. NO. F | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| | | SHEET 1 OF 1 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9