


DX-350/355 Accessory and I/O Configuration Reference Guide (Website)


STANDARD ACCESSORIES/SPARE PARTS (Include with the unit)




SH-300
Syringe Holder




7045-0120
Air Line Holder



7045-9020
Foot Switch




7045-0080
Wire Bracket Holder




1700-0014
Power Adapter



FTKIT
Air Hose Fitting



910-3RHB
10cc Receiver head Assembly




DXSAMPLENEEDLE
TE/TT Sample Needles


OPTIONAL ACCESSORIES (Not include with the unit)



881-000-000
Inline Filter (Optional)



TSD800-6
Air Filter (Optional)



700KIT
Receiver Head Assembly
And Needle Kit (Optional)

Spare Parts/Repair Parts


Part Number	Description
TSD500-48	Air Regulator, 0 - 15 psi (DX-355)
TSD500-30	Air Regulator, 0 - 100 psi (DX-350)
2900-0015	LCD
7066-9010	PCBA
TSD650-21	Solenoid Valve
INTFKIT	Internal Fitting/Tubing Kit
TSD210-3	Valve, Needle
TSD201-22	Check valve
7044-0120	Vacuum Venturi
535	Coupler, Panel Mt. Quick Disc. Assy. Black
TSD1121-22	Knob, Small
TSD1121-23	Knob, Large

I/O Configuration and End of Cycle Switch


During a dispense cycle, an open collector circuit closes and remains closed while the valve is dispensing. This circuit can be used to signal back to a host computer, start another device in sequence, or drive any other operations that need to be tied to the dispense cycle. Power from an external source is allowed to pass through the circuit to operate a 5 to 24 VDC load. Power consumption must not exceed 250 mA. The load could be a relay, solenoid, counter, LED, or any device that will operate within a 5 to 24 VDC range and a maximum of 250 mA.

Note:


During the dispense cycle, pin 3 will be grounded. Please make sure the external device (your machine that controls the dispenser/controller) has the same ground as the DX-350/355.



ELECTRICAL SCHEMATIC



PNEUMATIC DIAGRAM



Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9