

CONNECTOR P1 DESCRIPTION/ PART NO	CONNECTOR P2 DESCRIPTION/ PART NO	CABLE GROUPS; WRENCH CRIMP, (TODL CRIMP)									CKT CODE
		1(011)	2(013A)	2(013/013B)	3(012)	1(011)	2(013)	1(012)	2(011)		
		TCC-50-2	TCC-75-2	RG62	M17/167-00001 (RG623)	RG58 BLACK	RG59 BLACK	RG142	RG303		
11-01 DASH NUMBERS											
(PL1C-) 1-0453-	(PL1C-) 1-0453-	-1	-3	-4	-2	-88	-189	-203	-228	K1	
(PL1WC-) 1-0453-W	(PL1WC-) 1-0453-W	-5	-7	-8	-6	-89	-204	-205	-206	K1	
(PL1C-) 1-0453-	(PL71-1 FIS) 305-0562-1	-9	_____	_____	_____	-90	_____	-207	_____	E2	
(PL1C-) 1-0453-	(PL71-2 FIS) 305-0562-3	_____	-10	-11	_____	_____	-208	_____	_____	E2	
(PL1WC-) 1-0453-W	(PL71-1 FIS) 305-0562-1	-12	_____	_____	_____	-91	_____	-209	_____	E2	
(PL1WC-) 1-0453-W	(PL71-2 FIS) 305-0562-3	_____	-13	-14	_____	_____	-236	_____	_____	E2	
(PL20-) 1-0369-	(PL1C-) 1-0453-	-15	-17	-18	-16	-92	-238	-239	-240	K1	
(PL20-) 1-0369-	(PL1WC-) 1-0453-W	-19	-22	-23	-20	-93	-241	-242	-243	K1	
(PL3C-) 1-0045-	(PL3C-) 1-0045-	-244	-245	-246	-21	-247	-248	-249	-250	K1	
(PL20-) 1-0369-	(PL20-) 1-0369-	-24	-26	-27	-25	-251	-190	-252	-253	K1	
(PL20-) 1-0369-	(PL40-) 1-0014-	-28	-254	-255	-29	-94	-256	-257	-258	K1	
(CJ20-) 1-0134-	(CJ40-) 1-0135-	-30	-259	-260	-31	-95	-261	-262	-263	K1	
(PL40-) 1-0014-	(CJ40-) 1-0135-	-32	-33	-34	-264	-96	-265	-266	-267	K1	
(PL95-) 1-0370-	(PL95-) 1-0370-	-35	-77	-268	-195	-97	-269	-270	-271	K1	
(PL95-) 1-0370-	(PL1C-) 1-0453-	-36	-272	-273	-274	-98	-275	-276	-277	K1	
(PL1WC-) 1-0453-W	(J3WE) 1-0378-W	-278	-37	-279	-280	-281	-282	-283	_____	K1	
UG111/U	UG111/U	_____	-38	_____	_____	_____	_____	_____	_____	K1	
(PL20-) 1-0369-	(CJ20-) 1-0134-	-62	-63	-64	-39	-106	-284	-285	-286	K1	
(BJ26-) 1-0341-	(PL40-) 1-0014-	-40	-287	-288	-289	-99	-290	-291	-292	K1	
(PL11C-) 1-0326-	(PL11C-) 1-0326-	-293	-82	-41	-294	-295	-296	-297	-298	K1	
(PL94-) 1-0029-	(PL20-) 1-0369-	-42	-299	-300	-301	-100	-302	-303	-304	K1	
(PL123-) 1-0390-	(PL1C-) 1-0453-	-43	-44	-45	-305	-101	-306	-307	-308	K1	
(UPL123-) 1-0390-U	(PL1WC-) 1-0453-W	-46	-47	-48	-309	-102	-310	-311	-312	K1	
(MP2W) 1-0398	(PL1WC-) 1-0453-W	_____	-49	-313	_____	_____	-314	_____	_____	K1	
(CJ40-) 1-0135-	(PL60-) 1-0353-	-50	_____	_____	-315	-103	_____	-316	-317	K1	
(PL20-) 1-0369-	(PL50-) 1-0016-	-170	-172	-51	-231	-318	-319	-320	_____	K1	
(PL20-) 1-0369-	(BANANA PLUG) 210-103	-52	_____	_____	_____	-104	_____	_____	_____	X1	
(PL20-) 1-0369-	(BANANA PLUG) 210-102	_____	-53	_____	_____	_____	_____	_____	_____	X1	
(J12-) 1-0258-	(PL1WC-) 1-0453-W	-321	-54	-322	-323	-324	-325	-326	_____	K1	
(PL11C-) 1-0326-	(J3WE) 1-0378-W	-327	-55	-328	-329	-330	-340	-350	_____	K1	
(UPL20-) 1-0369-U	(UPL20-) 1-0369-U	-351	-66	-56	-352	-353	-354	-355	-356	K1	
(PL94-) 1-0029-	(PL1C-) 1-0326-	-357	-358	-359	-57	-360	-361	-362	-363	K1	
(PL11C-) 1-0326-	(UPL20-) 1-0369-U	-364	-58	-365	-366	-367	-368	-369	-370	K1	
(PL40-) 1-0014-	(PL40-) 1-0014-	-84	-371	-372	-59	-112	-373	-192	-374	K1	
(PL20-) 1-0369-	(RT ANG SMA) DSM531-2	-60	_____	_____	_____	-105	_____	-382	_____	K1	
(PL1WC-) 1-0453-W	(PL11C-) 1-0326-	-375	-61	-376	-377	-378	-379	-380	-381	K1	
(PL20-) 1-0369-	(RT ANG BNC(M)) 31-335	-65	_____	_____	_____	-107	_____	-383	_____	K1	
(MP3W-) 1-0410-W	(MP3W-) 1-0410-W	-67	-68	-384	_____	-108	-385	-386	_____	K1	
(J3WE-) 1-0378-W	_____	-387	-69	-388	-389	-390	-391	-392	_____	K2	
(PL20-) 1-0369-	(F59A) 1-0353-	_____	-70	-393	_____	_____	_____	_____	_____	K1	
(PL40-) 1-0014-	(PL60-) 1-0353-	-71	_____	_____	-394	-109	_____	-396	-397	K1	
(PL123-) 1-0390-	(PL123-) 1-0390-	-72	-73	-75	-212	-110	-398	-399	-400	K1	
(UPL123-) 1-0390-U	(UPL123-) 1-0390-U	-401	-74	-76	-402	-403	-404	-405	-406	K1	
(PL95-) 1-0370-	(PL20-) 1-0369-	-120	-78	-407	-201	-408	-409	-410	-411	K1	
(PL95-) 1-0370-	(PL1WC-) 1-0453-W	-412	-79	-413	-414	-415	-416	-417	-418	K1	
(PL60-) 1-0353-	(BJ69-) 1-0355-	-80	_____	_____	-395	-111	_____	-419	-420	K1	
(PL11C-) 1-0326-	(PL50-) 1-0016-	-421	-81	-422	-423	-424	-425	-426	_____	K1	
(PL20-) 1-0369-	_____	-214	-427	-83	-233	-428	-429	-430	-431	K2	
(PL95-) 1-0370-	(PL130-) 105-0181-	-432	-85	-433	-434	-435	-436	-437	_____	K1	

CONNECTOR P1 DESCRIPTION/ PART NO	CONNECTOR P2 DESCRIPTION/ PART NO	CABLE GROUPS; WRENCH CRIMP, (TODL CRIMP)								CKT CODE
		1(011)	2(013A)	2(013/013B)	3(012)	1(011)	2(013)	1(012)	2(011)	
		TCC-50-2	TCC-75-2	RG62	M17/167-00001 (RG623)	RG58 BLACK	RG59 BLACK	RG142	RG303	
11-01 DASH NUMBERS										
⟨PL1C-⟩ 1-0453-	⟨UG536 B/U⟩ 1-0453-	-86	—	—	—	-113	—	—	—	K1
⟨BJ29-⟩ 1-0126-	⟨PL20-⟩ 1-0369-	-128	-438	-439	-440	-87	-441	-442	-443	K1
⟨UPL20-⟩ 1-0369-U	⟨PL1C-⟩ 1-0453-	-444	-114	-115	-445	-446	-447	-448	-449	K1
⟨UPL20-⟩ 1-0369-U	⟨PL1WC-⟩ 1-0453-W	-450	-116	-117	-451	-452	-453	-454	-455	K1
⟨UPL123-⟩ 1-0390-U	⟨PL1C-⟩ 1-0453-	-456	-118	-119	-457	-458	-459	-460	-461	K1
⟨PL20-⟩ 1-0369-	⟨BJ95-⟩ 1-0175-	-121	-462	-463	-464	-465	-466	-467	-468	K1
⟨PL20-⟩ 1-0369-	⟨PL11C-⟩ 1-0326-	-469	-122	-470	-471	-472	-473	-474	-475	K1
⟨UPL40-⟩ 1-0014-U	⟨PL11C-⟩ 1-0326-	-476	-123	-477	-478	-479	-480	-481	-482	K1
⟨UPL40-⟩ 1-0014-U	⟨PL1WC-⟩ 1-0453-W	-483	-124	-484	-485	-486	-487	-488	-489	K1
⟨J12NMF-⟩ 105-0910-	⟨PL1WC-⟩ 1-0453-W	-490	-125	-491	-492	-493	-494	-495	—	K1
⟨J3E-⟩ 1-0378-	⟨PL20-⟩ 1-0369-	-496	-497	-126	-498	-499	-500	-501	—	K1
⟨PL20-⟩ 1-0369-	⟨PL75-1 FDS⟩ 305-0111-1	-127	—	—	—	-502	—	-503	—	E1
⟨UPL95-⟩ 1-0370-U	⟨PL11C-⟩ 1-0326-	-504	-129	-505	-506	-507	-508	-509	-510	K1
⟨UPL95-⟩ 1-0370-U	⟨PL1WC-⟩ 1-0453-W	-511	-130	-512	-513	-514	-515	-516	-517	K1
⟨PL220-⟩ 1-0442-	⟨PL1C-⟩ 1-0453-	-131	-132	-133	-518	-159	-519	-520	-521	K1
⟨PL220-⟩ 1-0442-	⟨PL1WC-⟩ 1-0453-W	-134	-135	-136	-522	-160	-523	-524	-525	K1
⟨PL220-⟩ 1-0442-	⟨PL220-⟩ 1-0442-	-137	-138	-139	-197	-161	-526	-527	-528	K1
⟨PL223-⟩ 1-0009-	⟨PL1C-⟩ 1-0453-	-140	-141	-142	-529	-162	-530	-531	-532	K1
⟨UPL223-⟩ 1-0050-	⟨PL1WC-⟩ 1-0453-W	-143	-144	-145	-533	-163	-534	-535	-536	K1
⟨UPL220-⟩ 1-0468-	⟨UPL220-⟩ 1-0468-	-537	-147	-146	-538	-539	-540	-541	-542	K1
⟨PL223-⟩ 1-0009-	⟨PL223-⟩ 1-0009-	-148	-149	-151	-543	-164	-544	-545	-546	K1
⟨UPL223-⟩ 1-0050-	⟨UPL223-⟩ 1-0050-	-547	-150	-152	-548	-549	-550	-551	-552	K1
⟨UPL220-⟩ 1-0468-	⟨PL1C-⟩ 1-0453-	-553	-153	-154	-554	-555	-556	-557	-558	K1
⟨UPL220-⟩ 1-0468-	⟨PL1WC-⟩ 1-0453-W	-559	-155	-156	-560	-561	-562	-563	-564	K1

IF PLASTIC STRAIN RELIEF IS REQUIRED, SUFFIX PART NO WITH BT, ADD 1 STRAIN RELIEF EACH CONNECTOR AS FOLLOWS:

- ACA1
- ACA2
- ACB013-7 FOR VIOLET CABLE
ALL OTHERS USE -0 BLACK
- ACC011
- ACC013

WHEN ASSEMBLY IS ORDERED BY MODEL NO ADD ACB013-7 PLASTIC STRAIN RELIEF 2 PER EACH CABLE ASSY

9. EXAMPLE OF COMPLETE PART NO:

11-01- X - 1 YEL
DASH NO

SEE 11-08 FOR CABLE ASSEMBLIES WITH BEND RELIEF SPRING(S)

- JERROLD
- BELL IND
- H.H SMITH
- AMPHENOL

IDENTIFY PER MARKING TABLE CENTER ONLY ON CABLES 60 INCHES OR LESS; AT BOTH ENDS ON CABLES OVER 60 INCHES LONG

2. SEE CONN DWG FOR CABLE STRIPPING & ASSY INSTRUCTIONS

1 LENGTH IN INCHES
TOL PER TT-03

INSTALL ACA1 -0 BOOT OVER CONNECTOR CRIMP.

PIGTAIL UN-TERMINATED END USING 3' EACH 700-0094 + 700-0095 HOOK-UP WIRE.

SWITCHCRAFT

MALE 'F' CONN (PL210HB-AUGAT LRC)

CUSTOMER FURNISHED CONNECTORS (ALLIED SIGNAL)

SMB CONNECTOR, ITT CANNON RF PRODUCTS OR EQUIV

EF JOHNSON

IF ALTERNATIVE COLOR IS REQUIRED, SUFFIX P/N WITH COLOR DESIGNATION AND REPLACE TCC-75-2 WITH APPROPRIATE CABLE AS FOLLOWS:

BLK FOR TCC-75-2 BLACK
BLU FOR TCC-75-2 BLUE
GRN FOR TCC-75-2 GREEN
RED FOR TCC-75-2 RED
YEL FOR TCC-75-2 YELLOW

IF COLORED 50 OHM CABLE IS REQUIRED, REPLACE TCC-50-2 WITH THE FOLLOWING:

RED: RG58/RED
BLUE: RG58/BLU

MAY SUBSTITUTE (UPLR220-) (1-0504-)

SEE CONNECTOR TOP ASSEMBLY FOR CORRECT CABLE GROUP DASH NUMBER

'BT' SUFFIX WILL NOT BE UTILIZED ON ASSEMBLIES LISTED IN NOTES 10 AND 2

WHEN ASSEMBLY IS ORDERED BY MODEL NO, ADD ACB013-7 PLASTIC STRAIN RELIEF 1 PER EACH PATCH CORD END

DATA CONTAINED IN THIS DOCUMENT IS PROPRIETARY TO TROMPETER ELECTRONICS INC. AND SHALL NOT BE DISCLOSED, COPIED OR USED FOR PROCUREMENT OR MANUFACTURE WITHOUT EXPRESS WRITTEN PERMISSION.

REVISIONS			11-01		SH 1
REV	EO	DESCRIPTION	DWN	APPROVED	DATE
CB	12871	ADDED -1164	DAR	NAVARETTE	1/03/03

MARKING TABLE 3	
MARK MODEL NO ONLY ON CABLES LISTED-MARK PART NO. ON ALL OTHERS	
DASH NO	MODEL NO
-1	PC-50
-3	PC-75
-4	PC-93
-5	PCW-50
-7	PCW-75
-8	PCW-93
-9	PCV-50
-10	PCV-75
-11	PCV-93
-12	PCWV-50
-13	PCWV-75
-14	PCWV-93
-15	PCX-50
-17	PCX-75
-18	PCX-93
-19	PCWX-50
-22	PCWX-75
-23	PCWX-93
-24	PCY-50
-26	PCY-75
-27	PCY-93
-43	PCPX-50
-44	PCPX-75
-45	PCPX-93
-46	UPCPWX-50
-47	UPCPWX-75
-48	UPCPWX-93
-49	MPCW-75
-56	UPCY-93
-66	UPCY-75

MARKING TABLE 3	
MARK MODEL NO ONLY ON CABLES LISTED-MARK PART NO. ON ALL OTHERS	
DASH NO	MODEL NO
-67	PPCW-1-50
-68	PPCW-1-75
-72	PCP-1-50
-73	PCP-1-75
-74	UPCP-1-75
-75	PCP-1-93
-76	UPCP-1-93
-114	UPCX-1-75
-115	UPCX-1-93
-116	UPCWX-1-75
-117	UPCWX-1-93
-118	UPCPX-1-75
-119	UPCPX-1-93
-131	PCXC-1-50
-132	PCXC-1-75
-133	PCXC-1-93
-134	PCWXC-1-50
-135	PCWXC-1-75
-136	PCWXC-1-93
-137	PCYC-1-50
-138	PCYC-1-75
-139	PCYC-1-93
-140	PCPXC-1-50
-141	PCPXC-1-75
-142	PCPXC-1-93
-143	PCPWXC-1-50
-144	PCPWXC-1-75
-145	PCPWXC-1-93
-146	UPPYC-1-93
-147	UPPYC-1-75

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9